

# TABLE 1 : NPN GENERAL PURPOSE

The devices shown in this table are general purpose transistors designed for small and medium signal applications from d.c. to radio frequencies. Typical application areas include: AUDIO FREQUENCY AMPLIFIERS, DRIVERS and OUTPUT STAGES, OSCILLATORS, AND GENERAL PURPOSE SWITCHES.

Type	V <sub>CBO</sub> V	V <sub>CEO</sub> V	Max I <sub>c</sub> mA	Max V <sub>CE(sat)</sub> at			h <sub>FE</sub> at			Min f <sub>T</sub> at		P <sub>tot</sub> at T <sub>amb</sub> = 25°C mW	Complement
				V	I <sub>c</sub> mA	I <sub>B</sub> mA	Min	Max	I <sub>c</sub> mA	MHz	I <sub>c</sub> mA		
ZTX453	120	100	1000	0.7	150	15	40	200	150	150	50	1000	—
ZTX452	100	80	1000	0.7	150	15	40	150	150	150	50	1000	ZTX552
MPSA06	80	80	500	0.25	100	10	50	—	100	100	10	750	MPSA56
BC546P	80	65	200	0.25	10	0.5	75	200	2	300*	10	500	BC556P
ZTX451	80	60	1000	0.35	150	15	50	150	150	150	50	1000	ZTX551
BFS61	80	60	1000	0.35	150	15	40	160	150	150	50	500	BFS98
MPS2222A	75	45	800	1.0	500	50	100	300	150	300	20	500	MPS2907A
ZTX304	70	70	500	0.35	50	5	50	300	10	150	10	300	ZTX504
MPSA05	60	60	500	0.25	100	10	50	—	100	100	10	750	—
BCY65EP	60	60	100	0.35	10	0.25	120	460	2	125	10	1000†	BCY77P
BC182P	60	50	200	0.25	10	0.5	100	480	2	150	10	300	BC212P
ZTX107	60	50	100	0.1*	10	1	125	500	2	350*	10	300	ZTX212
ZTX450	60	45	1000	0.25	150	15	100	300	150	150	50	1000	ZTX550
BFS60	60	40	1000	0.25	150	15	100	300	150	150	50	500	BFS97
2N4401	60	40	600	0.4	150	15	100	300	150	250	20	500	2N4403
2N4400	60	40	600	0.4	150	15	50	150	150	200	20	500	2N4402
2N3904	60	40	200	0.2	10	1	100	300	10	300	10	500	2N3906
2N3903	60	40	200	0.2	10	1	50	150	10	250	10	500	2N3905
BFS59	60	30	1000	0.35	150	15	40	300	150	150	50	500	BFS96
MPS2222	60	30	800	1.6	500	50	100	300	150	250	20	500	MPS2907
BC547P	50	45	200	0.25	10	0.5	75	450	2	300*	10	500	BC557P
ZTX382	50	45	200	0.25	10	0.5	100	850	2	150	10	350	—
BC107P	50	45	200	0.2	10	0.5	120	460	2	150	10	300	BC177P
BC237P	50	45	200	0.2	10	0.5	120	460	2	150	10	300	BC307P
ZTX237	50	45	200	0.25	10	0.5	120	460	2	150	10	300	ZTX212
ZTX223	50	30	800	0.3	100	10	100	450	50	100	50	500	—
ZTX303	45	45	500	0.35	50	5	50	300	10	150	10	300	ZTX503
BCY59P	45	45	200	0.35	10	0.25	120	630	2	125	10	1000†	BCY79P
ZTX238	45	30	200	0.25	10	0.5	120	800	2	150	10	350	ZTX213
ZTX383	45	30	200	0.25	10	0.5	100	850	2	150	10	350	—
ZTX384	45	30	200	0.25	10	0.5	250	—	2	150	10	350	—
BC183P	45	30	200	0.25	10	0.5	100	850	2	150	10	300	BC213P
ZTX108	45	30	100	0.1*	10	1	125	900	2	350*	10	300	ZTX213
2N4123	40	30	200	0.3	50	5	50	150	2	250	10	500	2N4125
ZTX302	35	35	500	0.25	50	5	100	300	10	150	10	300	ZTX502
ZTX301	35	35	500	0.25	50	5	50	300	10	150	10	300	ZTX501
BCY58P	32	32	200	0.35	10	0.25	120	630	2	125	10	1000†	BCY78P
BC548P	30	30	200	0.25	10	0.5	75	800	2	300*	10	500	BC558P
2N4124	30	25	200	0.3	50	5	120	360	2	300	10	500	2N4126
BC108P	30	20	200	0.2	10	0.5	120	800	2	150	10	300	BC178P
BC238P	30	20	200	0.2	10	0.5	120	800	2	150	10	300	BC308P
ZTX300	25	25	500	0.35	10	1	50	300	10	150	10	300	ZTX500
MPSA20	—	40	100	0.25	10	1	40	400	5	125	5	500	—

\*Typical †T<sub>case</sub> = 45°C

# TABLE 7 : NPN/PNP MEDIUM POWER

The transistors shown in this table have been designed to operate and provide useful gain at current levels up to 2 amps with power dissipation capabilities in excess of 1000mW at 25°C ambient temperature.

Typical application areas include: Audio Frequency Drivers and Output Stages, Relay Switching, etc.

Type	V <sub>CB0</sub> V	V <sub>CEO</sub> V	Max Cont. I <sub>C</sub> mA	Max V <sub>CE(sat)</sub> at			h <sub>FE</sub> at			Min f <sub>T</sub> at		P <sub>tot</sub> at T <sub>amb</sub> = 25°C mW	Complement
				V	I <sub>C</sub> mA	I <sub>B</sub> mA	Min	Max	I <sub>C</sub> mA	MHz	I <sub>C</sub> mA		
<b>NPN</b>													
ZTX455	160	140	1000	0.7	150	15	100	300	150	100	50	1000	—
ZTX454	140	120	1000	0.7	150	15	100	300	150	100	50	1000	—
ZTX653	120	100	2000	0.3	1000	100	100	300	500	100	100	1000	ZTX753
ZTX453	120	100	1000	0.7	150	15	40	200	150	150	50	1000	—
ZTX652	100	80	2000	0.3	1000	100	100	300	500	100	100	1000	ZTX752
ZTX452	100	80	1000	0.7	150	15	40	150	150	150	50	1000	—
MPSA06	80	80	500	0.25	100	10	50	—	100	100	10	750	MPSA56
ZTX651	80	60	2000	0.3	1000	100	100	300	500	100	100	1000	ZTX751
ZTX451	80	60	1000	0.35	150	15	50	150	150	150	50	1000	ZTX551
MPSA05	60	60	500	0.25	100	10	50	—	100	100	10	750	MPSA55
ZTX650	60	45	2000	0.3	1000	100	100	300	500	100	100	1000	ZTX750
ZTX450	60	45	1000	0.25	150	15	100	300	150	50	50	1000	ZTX550
ZTX337	50	45	800	0.7	500	50	100	630	100	200*	10	750	ZTX537
BC337P	50	45	800	0.7	500	50	100	630	100	100	10	625	BC327P
ZTX449	50	30	1000	0.5	1000	100	100	300	500	150	50	1000	ZTX549
ZTX338	30	25	800	0.7	500	50	100	630	100	200*	10	750	ZTX538
BC338P	30	25	800	0.7	500	50	100	630	100	100	10	625	BC328P
<b>PNP</b>													
ZTX753	120	100	2000	0.3	1000	100	100	100	500	75	100	1000	ZTX653
ZTX752	100	80	2000	0.3	1000	100	100	300	500	75	100	1000	ZTX652
ZTX552	100	80	1000	0.7	150	15	40	150	150	150	50	1000	ZTX452
MPSA56	80	80	500	0.25	100	10	50	—	100	100	10	750	MPSA06
ZTX751	80	60	2000	0.3	1000	100	100	300	500	75	100	1000	ZTX651
ZTX551	80	60	1000	0.35	150	15	50	150	150	150	50	1000	ZTX451
MPSA55	60	60	500	0.25	100	10	50	—	100	100	10	750	MPSA05
ZTX750	60	45	2000	0.3	1000	100	100	300	500	75	100	1000	ZTX650
ZTX550	60	45	1000	0.25	150	15	100	300	150	150	50	1000	ZTX450
ZTX537	50	45	800	0.7	500	50	100	630	100	200*	10	750	ZTX337
BC327P	50	45	800	0.7	500	50	100	630	100	100	10	625	BC337P
ZTX549	35	25	1000	0.5	1000	100	100	300	1000	100	100	1000	ZTX449
ZTX538	30	25	800	0.7	500	50	100	630	100	200*	10	750	ZTX338
BC328P	30	25	800	0.7	500	50	100	630	100	100	10	625	BC338P

\*Typical

# ELECTRICAL CHARACTERISTICS

## N.P.N. MEDIUM POWER

Dice Type	V <sub>CB0</sub> Min.	V <sub>CE0</sub> Min.	I <sub>CB0</sub> Max. at V <sub>CB</sub>		h <sub>FE</sub> @ I <sub>C</sub>			V <sub>CE</sub>	V <sub>CE(sat)</sub> I <sub>C</sub> I <sub>B</sub>			f <sub>T</sub> Min.	C <sub>obo</sub> Max.	Geometry
	V	V	nA	V	Min.	Max.	mA	V	Max.	mA	mA	MHz	pF	
ZTX653	120	100	100	100	100	300	500	2	0.5	2000	200	140	—	G17
ZTX453	120	100	100	100	40	200	150	10	0.7	150	15	150	15	G4
ZTX652	100	80	100	80	100	300	500	2	0.5	2000	200	140	—	G17
ZTX452	100	80	100	80	40	150	150	10	0.7	150	15	150	15	G4
MPSA06	80	80	100	80	50	—	100	1	0.25	100	10	100	—	G4
ZTX651	80	60	100	60	100	300	500	2	0.5	2000	200	140	—	G17
ZTX451	80	60	100	60	50	150	150	10	0.35	150	15	150	15	G4
BFY50	80	35	500	80	30	—	150	10	0.1	10	1	60	12	G4
MPSA05	60	60	100	60	50	—	100	1	0.25	100	10	100	—	G4
ZTX650	60	45	100	45	100	300	500	2	0.5	2000	200	140	—	G17
ZTX450	60	45	100	45	100	300	150	10	0.25	150	15	150	15	G4
BFY51	60	30	500	60	40	—	150	10	0.15	10	1	50	12	G4
BC337A	50	45	100*	45	100	250	100	1	0.7	500	50	100	12	G4
BC337B	50	45	100*	45	160	400	100	1	0.7	500	50	100	12	G4
BC337C	50	45	100*	45	250	630	100	1	0.7	500	50	100	12	G4
BFY52	40	20	500	40	60	—	150	10	0.15	10	1	50	12	G4
BC338A	30	25	100*	25	100	250	100	1	0.7	500	50	100§	12§	G4
BC338B	30	25	100*	25	160	400	100	1	0.7	500	50	100§	12§	G4
BC338C	30	25	100*	25	250	630	100	1	0.7	500	50	100§	12§	G4

## P.N.P. MEDIUM POWER

Dice Type	V <sub>CB0</sub> Min.	V <sub>CE0</sub> Min.	I <sub>CB0</sub> Max. at V <sub>CB</sub>		h <sub>FE</sub> @ I <sub>C</sub>			V <sub>CE</sub>	V <sub>CE(sat)</sub> I <sub>C</sub> I <sub>B</sub>			f <sub>T</sub> Min.	C <sub>obo</sub> Max.	Geometry
	V	V	nA	V	Min.	Max.	mA	V	Max.	mA	mA	MHz	pF	
ZTX753	120	100	100	100	100	300	500	2	0.5	2000	200	100	—	G16
ZTX752	100	80	100	80	100	300	500	2	0.5	2000	200	100	—	G16
ZTX552	100	80	100	80	40	150	150	10	0.7	150	15	150	25	G6
MPSA56	80	80	100	80	50	—	100	1	0.25	100	10	100	—	G6
ZTX751	80	60	100	60	100	300	500	2	0.5	2000	200	100	—	G16
ZTX551	80	60	100	60	50	150	150	10	0.35	150	15	150	25	G6
MPSA55	60	60	100	60	50	—	100	1	0.25	100	10	100	—	G6
ZTX750	60	45	100	45	100	300	500	2	0.5	2000	200	100	—	G16
ZTX550	60	45	100	45	100	300	150	10	0.25	150	15	150	25	G6
BC327A	50	45	100*	45	100	250	100	1	0.7	500	50	100§	12§	G6
BC327B	50	45	100*	45	160	400	100	1	0.7	500	50	100§	12§	G6
BC327C	50	45	100*	45	250	630	100	1	0.7	500	50	100§	12§	G6
BC328A	30	25	100*	25	100	250	100	1	0.7	500	50	100§	12§	G6
BC328B	30	25	100*	25	160	400	100	1	0.7	500	50	100§	12§	G6
BC328C	30	25	100*	25	250	630	100	1	0.7	500	50	100§	12§	G6

V<sub>CE(sat)</sub>, f<sub>T</sub> and C<sub>obo</sub> are parameters which are assembly dependent and figures quoted are those typically achieved on Ferranti assembly lines.

\*I<sub>CES</sub> at V<sub>CES</sub> §Typical