

TYPE NUMBER	MFR	APP	COMP	GBP MIN	SLEW RATE MIN	V <sub>S</sub> <sup>+</sup> MAX	V <sub>S</sub> <sup>-</sup> MAX	T <sub>OP</sub> MAX	A <sub>VOL</sub> MIN	V <sub>IO</sub> MAX	I <sub>B</sub> MAX	I <sub>IO</sub> MAX	P <sub>TOT</sub> MAX	I <sub>OUT</sub> MIN	V <sub>OUT</sub> MIN	V <sub>ICM</sub> MAX	V <sub>IDF</sub> MAX	dV <sub>IO</sub> /dT MAX	P <sub>O</sub> MAX	I <sub>O</sub> MAX	CM RR MIN	PS RR MIN	R <sub>IN</sub> MIN
TSC1711E	TRU	DCP	EXT	.	.	+14V	-7V	125C	54dB	3.5MV	75uA	10uA	670MWF	.5MA	1.2V	7V	5V	25uV/C	200MW	9MA	.	.	.
TSC1711F	TRU	DCP	EXT	.	.	+14V	-7V	125C	54dB	3.5MV	75uA	10uA	300MWF	.5MA	1.2V	7V	5V	25uV/C	200MW	9MA	.	.	.
TSC1711J	TRU	DCP	EXT	.	.	+14V	-7V	125C	54dB	3.5MV	75uA	10uA	300MWF	.5MA	1.2V	7V	5V	25uV/C	200MW	9MA	.	.	.
TSC1711V	TRU	DCP	EXT	.	.	+14V	-7V	125C	54dB	3.5MV	75uA	10uA	300MWF	.5MA	1.2V	7V	5V	25uV/C	200MW	9MA	.	.	.
TSC2225E	TRU	DCP	EXT	.	.	+14V	-7V	70C		3.5MV	30uA	10uA	300MWF	.	1.3V	7V	5V			20MA	.	.	.
TSC2225F	TRU	DCP	EXT	.	.	+14V	-7V	70C		3.5MV	30uA	10uA	300MWF	.	1.3V	7V	5V			20MA	.	.	.
TSC2225J	TRU	DCP	EXT	.	.	+14V	-7V	70C		3.5MV	30uA	10uA	300MWF	.	1.3V	7V	5V			20MA	.	.	.
TSC2225V	TRU	DCP	EXT	.	.	+14V	-7V	70C		3.5MV	30uA	10uA	300MWF	.	1.3V	7V	5V			20MA	.	.	.
TSC2711E	TRU	DCP	EXT	.	.	+14V	-7V	70C	54dB	5MV	100uA	15uA	300MWF	.5MA	1.2V	7V	5V	25uV/C	230MW	9MA	.	.	.
TSC2711F	TRU	DCP	EXT	.	.	+14V	-7V	70C	54dB	5MV	100uA	15uA	300MWF	.5MA	1.2V	7V	5V	25uV/C	230MW	9MA	.	.	.
TSC2711J	TRU	DCP	EXT	.	.	+14V	-7V	70C	54dB	5MV	100uA	15uA	300MWF	.5MA	1.2V	7V	5V	25uV/C	230MW	9MA	.	.	.
TSC2711V	TRU	DCP	EXT	.	.	+14V	-7V	70C	54dB	5MV	100uA	15uA	300MWF	.5MA	1.2V	7V	5V	25uV/C	230MW	9MA	.	.	.
TSC3225E	TRU	DCP	EXT	.	.	+14V	-7V	70C	80dB	5MV	50uA	15uA	300MWF	.	1.3V	7V	5V			20MA	.	.	.
TSC3225F	TRU	DCP	EXT	.	.	+14V	-7V	70C	80dB	5MV	50uA	15uA	300MWF	.	1.3V	7V	5V			20MA	.	.	.
TSC3225J	TRU	DCP	EXT	.	.	+14V	-7V	70C	80dB	5MV	50uA	15uA	300MWF	.	1.3V	7V	5V			20MA	.	.	.
TSC3225V	TRU	DCP	EXT	.	.	+14V	-7V	70C	80dB	5MV	50uA	15uA	300MWF	.	1.3V	7V	5V			20MA	.	.	.
TSC4711E	TRU	DCP	EXT	.	.	+14V	-7V	125C	54dB	3.5MV	75uA	10uA	300MWF	.5MA	1.2V	7V	5V	25uV/C	300MW	11MA	.	.	.
TSC4711F	TRU	DCP	EXT	.	.	+14V	-7V	125C	54dB	3.5MV	75uA	10uA	300MWF	.5MA	1.2V	7V	5V	25uV/C	300MW	11MA	.	.	.
TSC4711J	TRU	DCP	EXT	.	.	+14V	-7V	125C	54dB	3.5MV	75uA	10uA	300MWF	.5MA	1.2V	7V	5V	25uV/C	300MW	11MA	.	.	.
TSC4711V	TRU	DCP	EXT	.	.	+14V	-7V	125C	54dB	3.5MV	75uA	10uA	300MWF	.5MA	1.2V	7V	5V	25uV/C	300MW	11MA	.	.	.
TSC5711E	TRU	DCP	EXT	.	.	+14V	-7V	70C	54dB	5MV	100uA	15uA	300MWF	.5MA	1.2V	7V	5V	25uV/C	300MW	11MA	.	.	.
TSC5711F	TRU	DCP	EXT	.	.	+14V	-7V	70C	54dB	5MV	100uA	15uA	300MWF	.5MA	1.2V	7V	5V	25uV/C	300MW	11MA	.	.	.
TSC5711J	TRU	DCP	EXT	.	.	+14V	-7V	70C	54dB	5MV	100uA	15uA	300MWF	.5MA	1.2V	7V	5V	25uV/C	300MW	11MA	.	.	.
TSC5711V	TRU	DCP	EXT	.	.	+14V	-7V	70C	54dB	5MV	100uA	15uA	300MWF	.5MA	1.2V	7V	5V	25uV/C	300MW	11MA	.	.	.
uA101AD	FAU	GPU	EXT	.	.	+22V	-22V	125C	94dB	2MV	75NA	10NA	670MWF	.5MA	12V	15V	30V	15uV/C		3MA	80dB	80dB	1.5M
uA101AF	FAU	GPU	EXT	.	.	+22V	-22V	125C	94dB	2MV	75NA	10NA	670MWF	.5MA	12V	15V	30V	15uV/C		3MA	80dB	80dB	1.5M
uA101AH	FAU	GPU	EXT	.	.	+22V	-22V	125C	94dB	2MV	75NA	10NA	500MWF	.5MA	12V	15V	30V	15uV/C		3MA	80dB	80dB	1.5M
uA101D	FAU	GPU	EXT	.	.	+22V	-22V	125C	94dB	5MV	500NA	200NA	670MWF	.5MA	12V	15V	30V	15uV/C		3MA	70dB	70dB	300K
uA101H	FAU	GPU	EXT	.	.	+22V	-22V	125C	94dB	5MV	500NA	200NA	500MWF	.5MA	12V	15V	30V	15uV/C		3MA	70dB	70dB	300K
uA102M	FAU	VFA	INT	.	.	+18V	-18V	125C	0dB	5MV	10NA		500MWF	1MA	10V	15V		20uV/C		6MA		60dB	10G
uA107H	FAU	GPK	INT	.	.	+22V	-22V	125C	94dB	2MV	75NA	10NA	500MWF	.5MA	12V	15V	30V	15uV/C		3MA	80dB	80dB	1.5M
uA108AD	FAU	SBA	EXT	.	.	+20V	-20V	125C	98dB	0.5MV	2NA	0.2NA	500MWF	1MA	13V	15V	0.5V	5uV/C		1MA	96dB	96dB	30M
uA108AF	FAU	SBA	EXT	.	.	+20V	-20V	125C	98dB	0.5MV	2NA	0.2NA	500MWF	1MA	13V	15V	1V	5uV/C		1MA	96dB	96dB	30M
uA108AH	FAU	SBA	EXT	.	.	+20V	-20V	125C	98dB	0.5MV	2NA	0.2NA	500MWF	1MA	13V	15V	1V	5uV/C		1MA	96dB	96dB	30M
uA108D	FAU	SBA	EXT	.	.	+20V	-20V	125C	94dB	2MV	2NA	0.2NA	500MWF	1MA	13V	15V	1V	15uV/C		1MA	80dB	80dB	30M
uA108F	FAU	SBA	EXT	.	.	+20V	-20V	125C	94dB	2MV	2NA	0.2NA	500MWF	1MA	13V	15V	1V	15uV/C		1MA	80dB	80dB	30M
uA108H	FAU	SBA	EXT	.	.	+20V	-20V	125C	94dB	2MV	2NA	0.2NA	500MWF	1MA	13V	15V	1V	15uV/C		1MA	80dB	80dB	30M
uA110M	FAU	VFA	INT	.	.	+18V	-18V	125C	0dB	4MV	3NA		500MWF	1MA	10V	15V		20uV/C		6MA		70dB	10G
uA111H	FAU	CPR	EXT	.	.	+18V	-18V	125C	100dB	3MV	100NA	10NA	500MWF	8MA		15V	30V			6MA			
uA111R	FAU	CPR	EXT	.	.	+18V	-18V	125C	100dB	3MV	100NA	10NA	500MWF	8MA		15V	30V			6MA			
uA201AD	FAU	GPU	EXT	.	.	+22V	-22V	85C	94dB	2MV	75NA	10NA	670MWF	.5MA	12V	15V	30V	15uV/C		3MA	80dB	80dB	1.5M
uA201AF	FAU	GPU	EXT	.	.	+22V	-22V	85C	94dB	2MV	75NA	10NA	670MWF	.5MA	12V	15V	30V	15uV/C		3MA	80dB	80dB	1.5M
uA201AH	FAU	GPU	EXT	.	.	+22V	-22V	85C	94dB	2MV	75NA	10NA	500MWF	.5MA	12V	15V	30V	15uV/C		3MA	80dB	80dB	1.5M
uA201D	FAU	GPU	EXT	.	.	+22V	-22V	70C	86dB	7.5MV	1.5uA	500NA	670MWF	.5MA	12V	15V	30V	30uV/C		3MA	65dB	70dB	100K
uA201H	FAU	GPU	EXT	.	.	+22V	-22V	70C	86dB	7.5MV	1.5uA	500NA	500MWF	.5MA	12V	15V	30V	30uV/C		3MA	65dB	70dB	100K
uA207H	FAU	GPK	INT	.	.	+22V	-22V	85C	94dB	2MV	75NA	10NA	500MWF	.5MA	12V	15V	30V	15uV/C		3MA	80dB	80dB	1.5M
uA208AD	FAU	SBA	EXT	.	.	+20V	-20V	85C	98dB	0.5MV	2NA	0.2NA	500MWF	1MA	13V	15V	1V	5uV/C		1MA	96dB	96dB	30M
uA208AF	FAU	SBA	EXT	.	.	+20V	-20V	85C	98dB	0.5MV	2NA	0.2NA	500MWF	1MA	13V	15V	1V	5uV/C		1MA	96dB	96dB	30M
uA208AH	FAU	SBA	EXT	.	.	+20V	-20V	85C	98dB	0.5MV	2NA	0.2NA	500MWF	1MA	13V	15V	1V	5uV/C		1MA	96dB	96dB	30M
uA208D	FAU	SBA	EXT	.	.	+20V	-20V	85C	94dB	2MV	2NA	0.2NA	500MWF	1MA	13V	15V	1V	15uV/C		1MA	80dB	80dB	30M
uA208F	FAU	SBA	EXT	.	.	+20V	-20V	85C	94dB	2MV	2NA	0.2NA	500MWF	1MA	13V	15V	1V	15uV/C		1MA	80dB	80dB	30M
uA208H	FAU	SBA	EXT	.	.	+20V	-20V	85C	94dB	2MV	2NA	0.2NA	500MWF	1MA	13V	15V	1V	15uV/C		1MA	80dB	80dB	30M
uA301AD	FAU	GPU	EXT	.	.	+18V	-18V	70C	88dB	7.5MV	250NA	50NA	670MWF	.5MA	12V	15V	30V	30uV/C		3MA	70dB	70dB	0.5M
uA301AH	FAU	GPU	EXT	.	.	+18V	-18V	70C	88dB	7.5MV	250NA	50NA	500MWF	.5MA	12V	15V	30V	30uV/C		3MA	70dB	70dB	0.5M
uA301AT	FAU	GPU	EXT	.	.	+18V	-18V	70C	88dB	7.5MV	250NA	50NA	310MWF	.5MA	12V	15V	30V	30uV/C		3MA	70dB	70dB	0.5M
uA302C	FAU	VFA	INT	.	.	+18V	-18V	70C	0dB	15MV	30NA		500MWF	1MA	10V	15V		50uV/C		6MA		60dB	10G
uA307H	FAU	GPK	INT	.	.	+18V	-18V	70C	88dB	7.5MV	250NA	50NA	500MWF	.5MA	12V	15V	30V	30uV/C		3MA	70dB	70dB	0.5M
uA307T	FAU	GPK	INT	.	.	+18V	-18V	70C	88dB	7.5MV	250NA	50NA	310MWF	.5MA	12V	15V	30V	30uV/C		3MA	70dB	70dB	0.5M
uA308AD	FAU	SBA	EXT	.	.	+18V	-18V	70C	98dB	0.5MV	7NA	1NA	500MWF	1MA	13V	15V	1V	5uV/C		1MA	96dB	96dB	10M
uA308AH	FAU	SBA	EXT	.	.	+18V	-18V	70C	98dB	0.5MV	7NA	1NA	500MWF	1MA	13V	15V	1V	5uV/C		1MA	96dB	96dB	10M

For detailed explanations of column heading notations, see App. A.

Also for ready references the more important abbreviations used in the column headings are listed below:

LEFT HAND PAGE

APP = application

(codes at APP.E.)

CMRR = common mode rejection ratio

CMP = compensation (frequency)

$dV_{io}/dT$  = input offset voltage temperature drift

GBP = gain bandwidth product

$I_B$  = input bias current

$I_{io}$  = input bias offset current

$I_Q$  = quiescent supply current

MFR = manufacturer (codes at App.C.)

$P_D$  = quiescent power consumer

PSRR = power supply rejection ratio

$V_{icm}$  = common mode input voltage rating

$V_{id}$  = differential input voltage rating

$V_{io}$  = input offset voltage

$V_S$  = dc supply voltage

RIGHT HAND PAGE

Lead out coding summary (details at APP.G.) for different cases (APP.F.)

A = gain adjust

B = bias adjust

C = case

E- = inverting input

E+ = non-inverting input

F,F\* = input frequency compensation

G = ground

J = high level input

K = output, open collector

L = output, open emitter

M = metal case

N = not connected

Q = special terminal

R,R\* = outputs

S = strobe

T,T\* = offset balance

V+ = +ve dc supply

V- = -ve dc supply

W = guard ring

X = blank position, no lead

+ + = +ve supplementary dc supply

- - = -ve supplementary dc supply

$\phi, \phi^*$  = output frequency compensation

CASE (APP.F.)	LD 1	LD 2	LD 3	LD 4	LD 5	LD 6	LD 7	LD 8	LD 9	LD 10	LD 11	LD 12	LD 13	LD 14	LD 15	LD 16	EUROPE SUBSTI-TUTE	USA SUBSTI-TUTE	S	T	S	TYPE NUMBER
DIL-14/1P	N	E-1	E+1	V-	E+2	E-2	N	N	S2	R	V+	G	S1	N	.	.	SFC2711KM	UA711DM	0	TSC1711E		
FLP-10/1C	E-1	E+1	V-	E+2	E-2	S2	R	V+	G	S1	.	.	.	.	.	.	SFC2711PM	UA711FM	0	TSC1711F		
DIL-14/1C	N	E-1	E+1	V-	E+2	E-2	N	N	S2	R	V+	G	S1	N	.	.	SFC2711KM	UA711DM	0	TSC1711J		
T05-10/1M	G	S1	E-1	E+1	V-	E+2	E-2	S2	R	V+	.	.	.	.	.	.	SFC2711M	UA711HM	0	TSC1711M		
DIL-14/1P	N	E-1	E+1	V-	E+2	E-2	N	N	S2	R	V+	G	S1	N	.	.	.	.	0	TSC2225E		
FLP-10/3C	E-1	E+1	V-	E+2	E-2	S2	R	V+	G	S1	.	.	.	.	.	.	.	.	0	TSC2225F		
DIL-14/1C	N	E-1	E+1	V-	E+2	E-2	N	N	S2	R	V+	G	S1	N	.	.	.	.	0	TSC2225J		
T05-10/1M	G	S1	E-1	E+1	V-M	E+2	E-2	S2	R	V+	.	.	.	.	.	.	.	.	0	TSC2225V		
DIL-14/1P	N	E-1	E+1	V-	E+2	E-2	N	N	S2	R	V+	G	S1	N	.	.	SFC2711EC	UA711DC	0	TSC2711E		
FLP-10/3C	E-1	E+1	V-	E+2	E-2	S2	R	V+	G	S1	.	.	.	.	.	.	SFC2711PM	UA711FM	0	TSC2711F		
DIL-14/1C	N	E-1	E+1	V-	E+2	E-2	N	N	S2	R	V+	G	S1	N	.	.	SFC2711EC	UA711DC	0	TSC2711J		
T05-10/1M	G	S1	E-1	E+1	V-	E+2	E-2	S2	R	V+	.	.	.	.	.	.	SFC2711C	UA711HC	0	TSC2711V		
DIL-14/1P	N	E-1	E+1	V-	E+2	E-2	N	N	S2	R	V+	G	S1	N	.	.	.	.	0	TSC3225E		
FLP-10/3C	E-1	E+1	V-	E+2	E-2	S2	R	V+	G	S1	.	.	.	.	.	.	.	.	0	TSC3225F		
DIL-14/1C	N	E-1	E+1	V-	E+2	E-2	N	N	S2	R	V+	G	S1	N	.	.	.	.	0	TSC3225J		
T05-10/1M	G	S1	E-1	E+1	V-M	E+2	E-2	S2	R	V+	.	.	.	.	.	.	.	.	0	TSC3225V		
DIL-14/1P	N	E-1	E+1	V-	E+2	E-2	N	N	S2	R	V+	G	S1	N	.	.	SFC2711KM	UA711DM	0	TSC4711E		
FLP-10/3C	E-1	E+1	V-	E+2	E-2	S2	R	V+	G	S1	.	.	.	.	.	.	SFC2711PM	UA711FM	0	TSC4711F		
DIL-14/1C	N	E-1	E+1	V-	E+2	E-2	N	N	S2	R	V+	G	S1	N	.	.	SFC2711KM	UA711DM	0	TSC4711J		
T05-10/1M	G	S1	E-1	E+1	V-	E+2	E-2	S2	R	V+	.	.	.	.	.	.	SFC2711M	UA711HM	0	TSC4711M		
DIL-14/1P	N	E-1	E+1	V-	E+2	E-2	N	N	S2	R	V+	G	S1	N	.	.	SFC2711EC	UA711DC	0	TSC5711E		
FLP-10/3C	E-1	E+1	V-	E+2	E-2	S2	R	V+	G	S1	.	.	.	.	.	.	SFC2711PM	UA711FM	0	TSC5711F		
DIL-14/1C	N	E-1	E+1	V-	E+2	E-2	N	N	S2	R	V+	G	S1	N	.	.	SFC2711EC	UA711DC	0	TSC5711J		
T05-10/1M	G	S1	E-1	E+1	V-	E+2	E-2	S2	R	V+	.	.	.	.	.	.	SFC2711C	UA711HC	0	TSC5711V		
DIL-14/1C	N	N	TF	E-	E+	V-	N	N	T*	R	V+	F*	N	N	.	.	.	.	0	UA101AD		
FLP-10/3C	N	TF	E-	E+	V-	T*	R	V+	F*	N	.	.	.	.	.	.	SFC2101APM	LM101AF	0	UA101AF		
T05-8/1M	TF	E-	E+	V-M	T*	R	V+	F*	.	.	.	.	.	.	.	.	SFC2101A	LM101AH	0	UA101AH		
DIL-14/1C	N	N	TF	E-	E+	V-	N	N	T*	R	V+	F*	N	N	.	.	.	.	0	UA101D		
T05-8/1M	TF	E-	E+	V-M	T*	R	V+	F*	.	.	.	.	.	.	.	.	SFC2101APM	LM101AH	0	UA101H		
T05-8/1M	T	N	E+	V-	B	R	V+	T*	.	.	.	.	.	.	.	.	.	.	0	UA102M		
T05-8/1M	N	E-	E+	V-M	N	R	V+	N	.	.	.	.	.	.	.	.	SFC2107M	LM107H	0	UA107H		
DIL-14/1C	N	F	W	E-	E+	W	V-	N	N	R	V+	F*	N	N	.	.	.	.	0	UA108AD		
FLP-10/3C	N	W	E-	E+	W	V-	R	V+	F*	F	.	.	.	.	.	.	SFC2108PM	LM108AF	0	UA108AF		
T05-8/1M	F	E-	E+	V-	N	R	V+	F*	.	.	.	.	.	.	.	.	SFC2108A	LM108AH	0	UA108AH		
DIL-14/1C	N	F	W	E-	E+	W	V	N	N	R	V+	F*	N	N	.	.	.	.	0	UA108D		
FLP-10/3C	N	W	E-	E+	W	V-	R	V+	F*	F	.	.	.	.	.	.	SFC2108PM	LM108AF	0	UA108F		
T05-8/1M	F	E-	E+	V-	N	R	V+	F*	.	.	.	.	.	.	.	.	SFC2108A	LM108AH	0	UA108H		
T05-8/1M	T	N	E+	V-	B	R	V+	T*	.	.	.	.	.	.	.	.	SFC2110M	LM110H	0	UA110M		
T05-8/1M	G	E+	E-	V-	T	T*S	R	V+	.	.	.	.	.	.	.	.	SFC2111M	LM111H	0	UA111H		
DIL-8/1P	G	E+	E-	V-	T	T*S	R	V+	.	.	.	.	.	.	.	.	.	.	0	UA111R		
DIL-14/1C	N	N	TF	E-	E+	V-	N	N	T*	R	V+	F*	N	N	.	.	.	.	0	UA201AD		
FLP-10/3C	N	TF	E-	E+	V-	T*	R	V+	F*	N	.	.	.	.	.	.	SFC2201APT	LM201AF	0	UA201AF		
T05-8/1M	TF	E-	E+	V-M	T*	R	V+	F*	.	.	.	.	.	.	.	.	SFC2101A	LM201AH	0	UA201AH		
DIL-14/1C	N	N	TF	E-	E+	V-	N	N	T*	R	V+	F*	N	N	.	.	.	.	0	UA201D		
T05-8/1M	TF	E-	E+	V-M	T*	R	V+	F*	.	.	.	.	.	.	.	.	SFC2201A	LM201AH	0	UA201H		
T05-8/1M	N	E-	E+	V-M	N	R	V+	N	.	.	.	.	.	.	.	.	SFC2207M	LM207H	0	UA207H		
DIL-14/1C	N	F	W	E-	E+	W	V-	N	N	R	V+	F*	N	N	.	.	.	.	0	UA208AD		
FLP-10/3C	N	W	E-	E+	W	V-	R	V+	F*	F	.	.	.	.	.	.	SFC2208PT	LM208AF	0	UA208AF		
T05-8/1M	F	E-	E+	V-	N	R	V+	F*	.	.	.	.	.	.	.	.	SFC2208A	LM208AH	0	UA208AH		
DIL-14/1C	N	F	W	E-	E+	W	V-	N	N	R	V+	F*	N	N	.	.	.	.	0	UA208D		
FLP-10/3C	N	W	E-	E+	W	V-	R	V+	F*	F	.	.	.	.	.	.	SFC2208PT	LM208F	0	UA208F		
T05-8/1M	F	E-	E+	V-	N	R	V+	F*	.	.	.	.	.	.	.	.	SFC2208	LM208H	0	UA208H		
DIL-14/1C	N	N	TF	E-	E+	V-	N	N	T*	R	V+	F*	N	N	.	.	.	.	0	UA301AD		
T05-8/1M	TF	E-	E+	V-M	T*	R	V+	F*	.	.	.	.	.	.	.	.	SFC2301A	LM301AH	0	UA301AH		
DIL-8/1P	TF	E-	E+	V-	T*	R	V+	F*	.	.	.	.	.	.	.	.	SFC301ADC	LM301AJ	0	UA301AT		
T05-8/1M	T	N	E+	V-	B	R	V+	T*	.	.	.	.	.	.	.	.	.	.	0	UA302C		
T05-8/1M	N	E-	E+	V-M	N	R	V+	N	.	.	.	.	.	.	.	.	SFC2307	LM307H	0	UA307H		
DIL-8/1P	N	E-	E+	V-	N	R	V+	N	.	.	.	.	.	.	.	.	SFC2307DC	LM307J	0	UA307T		
DIL-14/1C	N	F	W	E-	E+	W	V-	N	N	R	V+	F*	N	N	.	.	.	.	0	UA308AD		
T05-8/1M	F	E-	E+	V-	N	R	V+	F*	.	.	.	.	.	.	.	.	SFC2308A	LM308AH	0	UA308AH		

# Appendix A

# Explanatory notes to tabulations

The general layout plan of the information in the tables of this compendium should be immediately evident from the data tabulation explanatory chart set out overleaf.

Supporting Appendices with additional information are:

- App. B Glossary of *Opamp Terms*
- App. C Tabulation *Codes for Manufacturers*
- App. D IC Manufacturers' *House Numbers*
- App. E Tabulation *Codes for Applications*
- App. F *Case Outline and Leadout Diagrams*
- App. G Codes for *Leadout Connections*

Unit symbols used in the tables are:

- A = amperes
- C = °centigrade
- dB = decibels
- G = gigaohms (megohms  $\times 10^3$ )
- GHZ = gigahertz (megahertz  $\times 10^3$ )
- K = kilohms
- KHZ = kilohertz
- M = megohms
- MA = milliamperes, mA
- MAX = maximum
- MHZ = megahertz
- MIN = minimum
- MV = millivolts
- MWC = milliwatts, case at 25C
- MWF = milliwatts, free air at 25C
- MWH = milliwatts, heat sink, 25C
- NA = nanoamps (microamps  $\times 10^{-3}$ )
- NV = nanovolts (microvolts  $\times 10^{-3}$ )
- PA = picoamps (microamps  $\times 10^{-12}$ )
- R = ohms
- T = teraohms (megohms  $\times 10^6$ )
- V = volts
- WC = watts, case at 25C
- WF = watts, free air at 25C
- WH = watts, heatsink, 25C
- $\mu$ A = microamps
- $\mu$ S = microseconds
- $\mu$ V = microvolts
- $\mu$ W = microwatts
- $\mu$ WF = microwatts, free air at 25C

Where a unit symbol appears in the middle of a value, it indicates the position of the decimal point, e.g. 3K3 = 3.3K.



## Appendix A

### LEFT HAND PAGE

For detailed explanations of column heading notations, see App. A.

Also for ready references the more important abbreviations used in the column headings are listed below:

- APP = application  
(codes at APP.E.)
- CMRR = common mode rejection ratio
- CMP = compensation  
(frequency)
- $dV_{io}/dT$  = input offset voltage temperature drift
- GBP = gain bandwidth product
- $I_B$  = input bias current
- $I_{IO}$  = input bias offset current
- $I_Q$  = quiescent supply current
- MFR = manufacturer  
(codes at App.C.)
- $P_Q$  = quiescent power consumer
- PSRR = power supply rejection ratio
- $V_{icm}$  = common mode input voltage rating
- $V_{idc}$  = differential input voltage rating
- $V_{io}$  = input offset voltage
- $V_S$  = dc supply voltage

### RIGHT HAND PAGE

Lead out coding summary (details at APP.G.) for different cases (APP.F.)

- A = gain adjust
- B = bias adjust
- C = case
- E- = inverting input
- E+ = non-inverting input
- F,F\* = input frequency compensation
- G = ground
- J = high level input
- K = output, open collector
- L = output, open emitter
- M = metal case
- N = not connected
- Q = special terminal
- R,R\* = outputs
- S = strobe
- T,T\* = offset balance
- V+ = +ve dc supply
- V- = -ve dc supply
- W = guard ring
- X = blank position, no lead
- + + = +ve supplementary dc supply
- - = -ve supplementary dc supply
- $\phi, \phi^*$  = output frequency compensation

CASE (APP. F.)	LD 1	LD 2	LD 3	LD 4	LD 5	LD 6	LD 7	LD 8	LD 9	LD 10	LD 11	LD 12	LD 13	LD 14	LD 15	LD 16	EUROPE SUBSTITUTION	USA SUBSTITUTION	ISS	TYPE NUMBER	
T05-8/1M	T	E-	E+	V-	T*	R	V+	N	.	.	.	.	.	.	.	.	.	.	LH0022H	0	LH0022CH

CASE = PACKAGE OF DIFFERENT TYPES CODED ACCORDING TO APP. F - FIRST NUMBER INDICATES NUMBER OF LEAD POSITIONS EG DIL-14 = 14 LEAD DUAL-IN-LINE PACKAGE

LD1, LD2, ETC = LEAD NUMBERS WITH CONNECTIONS ACCORDING TO PAGE FOOTNOTE OR APP. G.

EURO SUBSTITUTION = PROELECTRON STANDARD OR OTHER TYPE AVAILABLE IN EUROPE

USA SUBSTITUTION = SUGGESTED ALTERNATIVE AVAILABLE IN USA.

ISS = ISSUE NUMBER OF DATA ENTRY

TYPE No. REPEATED ON R.H. MARGIN

# Appendix C

## Tabulation Codes for Manufacturers

<b>ADU</b>	<b>Advanced Micro Devices Inc.,</b> 901 Thompson Pl., Sunnyvale, CA 94086, USA	<b>ITU</b>	DA14 5HT, UK <b>ITT Semiconductors</b> 74 Commerce Way, Woburn, MA, 01801, USA
<b>ANG</b>	<b>Analog Devices Ltd,</b> Central Ave., East Molesey, KT8 9BR, Surrey, UK	<b>MNG</b>	<b>Mitsubishi Shoji Kaisha Ltd,</b> Bow Bells House, Bread St., London, EC4, UK
<b>ANU</b>	<b>Analog Devices Inc.,</b> P.O. Box 280, Norwood, Mass., 02062	<b>MNJ</b>	<b>Mitsubishi Electric Corp.,</b> 2-12 Marunouchi, Chiyoda-ku, Tokyo, Japan
<b>BLG</b>	<b>Bell &amp; Howell Ltd,</b> Lennox Road, Basingstoke, Hants, UK	<b>MTG</b>	<b>Motorola Ltd</b> (Semiconductor Products Div.), York House, Empire Way, Wembley, Middlesex, HA9 0PR, UK
<b>BLU</b>	<b>Bell &amp; Howell</b> (Control Products Divison), 706 Bostwick Ave, Bridgeport, Conn. 06605, USA	<b>MTU</b>	<b>Motorola Semiconductor Products Inc.,</b> 5005 E. McDowell Road, Phoenix, AZ, 85008, USA
<b>BUG</b>	<b>Burr-Brown International Ltd,</b> 17 Exchange Rd, Watford, WQD1 7EB, Herts., UK	<b>MUG</b>	<b>Mullard Ltd,</b> Mullard House, Torrington Place, London, WC1E 7HD, UK
<b>BUU</b>	<b>Burr-Brown Research Corp.,</b> P.O. Box 11400, Tucson, AZ, 85734, USA	<b>NAG</b>	<b>National Semiconductor (UK) Ltd,</b> Harpur Centre, Bedford, MK40 3LF, UK
<b>CMG</b>	<b>Computing Techniques Ltd,</b> Brookers Rd, Billingshurst, Sussex, RH14 9RZ, UK	<b>NAU</b>	<b>National Semiconductor Corp.,</b> 2900 Semiconductor Drive, Santa Clara, CA, 95051, USA
<b>DAG</b>	<b>Datel UK Ltd,</b> Stephenson Close, Portway Ind. Estate, Andover, Hants, UK	<b>NIJ</b>	<b>Nippon Electric Co. Ltd,</b> 1753 Shimonumabe, Nakahara-ku, Kawasaki, Japan
<b>DAU</b>	<b>Datel Systems Inc.,</b> 1020 Turnpike St., Canton, MA 02021, USA	<b>OAU</b>	<b>Opamp Labs Inc.,</b> 1033 N. Sycamore Ave., Los Angeles, CA 90038, USA
<b>FAG</b>	<b>Fairchild Camera &amp; Instrument (UK) Ltd,</b> 230 High St., Potters Bar, Herts., UK	<b>OBS</b>	Obsolete – no longer commercially available.
<b>FAU</b>	<b>Fairchild Semiconductor</b> 464 Ellis St., Mountain View, CA 94042, USA	<b>OTU</b>	<b>Optical Electronics Inc.,</b> P.O. Box 11140, Tucson, AZ, 85734, USA
<b>FEG</b>	<b>Ferranti Ltd,</b> (Electronic Department), Gem Mill, Chadderton, Oldham, Lancs., OL9 8NP, UK	<b>PLG</b>	<b>Plessey Semiconductors,</b> Cheney Manor, Swindon, Wilts., SN2 2QW, UK
<b>FUJ</b>	<b>Fujitsu Ltd,</b> 1015 Kamikodanaka, Kawasaki, Japan	<b>PRG</b>	<b>Precision Monolithics</b> (Bourns Trimpot Ltd) 17/27 High St., Hounslow, Middlesex, UK
<b>HAG</b>	<b>Harris Semiconductor (Memec) Ltd,</b> The Firs, Whitchurch, Nr. Aylesbury, Bucks., HP22 4JU, UK	<b>PRU</b>	<b>Precision Monolithics (Bourns) Inc.,</b> 1500 Space Park Drive, Santa Clara, CA, 95050, USA
<b>HAU</b>	<b>Harris Semiconductor</b> P.O. Box 883, Melbourne, FL, 32901, USA	<b>RAG</b>	<b>Raytheon Semiconductor</b> The Pinnacles, Harlow, Essex, CM19 5BB, UK
<b>HIJ</b>	<b>Hitachi Ltd</b> (Semiconductor and IC Div.), 1450 Josuihonimachi, Kodaira City, Tokyo, Japan	<b>RAU</b>	<b>Raytheon Semiconductor,</b> 350 Ellis Street, Mountain View, CA, 94042, USA
<b>ING</b>	<b>Intersil Inc.,</b> 8 Tessa Rd, Richfield Trading Estate, Reading, Berks., UK	<b>RCG</b>	<b>RCA (Great Britain) Ltd,</b> Lincoln Way, Windmill Road, Sunbury-on- Thames, Middlesex, UK
<b>INU</b>	<b>Intersil Inc.,</b> 10900 N. Tantau Ave, Cupertino, CA, 95014, USA	<b>RCU</b>	<b>RCA Solid State Division</b> Route 202, Somerville, NJ, 08876, USA
<b>ITG</b>	<b>ITT Semiconductors</b> Maidstone Rd, Fooks Cray, Sidcup, Kent,	<b>SAJ</b>	<b>Sanken Electric Co. Ltd,</b> 1-22-8 Nishi-Ikebukuro, Toshima-Ku, Tokyo, Japan

Appendix C

<b>SGG</b>	<b>SGS-ATES (UK) Ltd,</b> Planar House, Walton Street, Aylesbury, Bucks., UK	<b>SPU</b>	<b>Sprague Electric Company</b> (Semiconductor Div.), 115 Northeast Cutoff, Worcester, MA, 01606, USA
<b>SGI</b>	<b>SGS-ATES Componenti Spa,</b> Via Olivetti, 2 Agrate Brianza, 20041, Milan, Italy	<b>TDG</b>	<b>Teledyne Semiconductor,</b> Heathrow House, Bath Road, Cranford, Hounslow, Middlesex, TW5 9QP, UK
<b>SHG</b>	<b>Shindengen Hyokuto Boeki Haisha Ltd,</b> St. Alphage House, Fore St., London, EC2Y 5DA, UK	<b>TDU</b>	<b>Teledyne (Amelco) Semiconductor,</b> 1300 Terra Bella Ave, Mountain View, CA, 94032, USA
<b>SHJ</b>	<b>Shindengen Electric Mfg Co., Ltd,</b> New Ohtemachi Bldng, 2-1, 2-chome, Ohtemachi, Chiyoda-ku, Tokyo, Japan	<b>TEB</b>	<b>Teledyne-Philbrick,</b> Heathrow House, Bath Road, Cranford, Hounslow, Middlesex, TW5 9QP, UK
<b>SIG</b>	<b>Siemens Ltd,</b> Great West Road, Brentford, Middlesex, TW8 9DG, UK	<b>TEU</b>	<b>Teledyne-Philbrick,</b> Allied Drive at Route 128, Dedham, MA, 02026, USA
<b>SIW</b>	<b>Siemens Aktiengesellschaft,</b> Richard-Strauss-Strasse 76, D-8000 Munchen 2, Postfach 202109, W. Germany	<b>TGG</b>	<b>Texas Instruments Ltd,</b> Manton Lane, Bedford, UK
<b>SJG</b>	<b>Signetics International Corporation</b> Yeoman House, 63 Croydon Rd, London, SE20, UK	<b>TGU</b>	<b>Texas Instruments Inc.</b> (Components Group), P.O. Box 5012, Dallas, Texas, 75222, USA
<b>SJU</b>	<b>Signetics Corp.,</b> 811 East Arques Ave, Sunnydale, CA. 94086, USA	<b>THF</b>	<b>Thomson-CSF (Sescosem),</b> 50 Rue Jean Pierre Timbaud, BP 120, 92403, Courbevoie, France
<b>SKU</b>	<b>Silicon General Inc.,</b> 7382 Bolsa Avenue, Westminster, CA, 92683, USA	<b>THG</b>	<b>Thomson-CSF (UK) Ltd,</b> Ringway House, Bell Rd, Daneshill, Basingstoke, Hants., RG24 0QG, UK.
<b>SLG</b>	<b>Siliconix Ltd,</b> 30A High St., Thatcham, Newbury, Berks., RG13 4JG, UK	<b>TKJ</b>	<b>Tokyo Sanyo Electric Co. Ltd</b> (Semiconductor Div.), Oizumachi, Oragun, Gumma, Japan
<b>SLU</b>	<b>Siliconix Incorporated,</b> 2201 Laurelwood Road, Santa Clara, CA, 95054, USA	<b>TOG</b>	<b>Toshiba (UK) Ltd,</b> Toshiba House, Great South West Rd, Feltham, Middlesex, UK
<b>SOJ</b>	<b>Sony Semiconductor Corp.,</b> 14-1, Asa hi-sho 4, Atsuigi-shi, Kanagawa-ken, 243, Japan	<b>TOJ</b>	<b>Toshiba (Tokyo Shibaura) Electric Co.,</b> 2-1, 5-chome, Ginza Chuo-ku, Tokyo, Japan
<b>SPG</b>	<b>Sprague Electric (UK) Ltd,</b> 159 High St., Yiewsley, W. Drayton, Middlesex, UB7 7RY, UK	<b>TRU</b>	<b>Transitron Electronic Corp.,</b> 168 Albion St., Wakefield, MA, 01881, USA
		<b>ZEU</b>	<b>Zeltex Inc.,</b> 940 Detroit Ave, Concord, CA, 94518, USA

# Appendix D

## IC Manufacturers'

### House Numbers

(General Note: Manufacturers often adopt their own 'in-house' serial numbering for their ICs. Listed below are the initial letters of numerical series used by different manufacturers.)

<b>AD</b>	Analog Devices	<b>OP</b>	Precision Monolithics
<b>ADO</b>	Analog Devices	<b>P</b>	Teledyne-Philbrick
<b>AM</b>	Advanced Micro Devices; Datel	<b>PF</b>	Teledyne-Philbrick
<b>AMD</b>	Advanced Micro Devices	<b>PG</b>	General Instruments (obs.)
<b>AMLM</b>	Advanced Micro Devices	<b>PP</b>	Teledyne-Philbrick
<b>AMSSS</b>	Advanced Micro Devices	<b>RA</b>	Radiation (now Harris)
<b>AMU</b>	Advanced Micro Devices	<b>RC</b>	Raytheon
<b>C</b>	Bell & Howell	<b>RL</b>	Raytheon
<b>CA</b>	RCA	<b>RM</b>	Raytheon
<b>CIA</b>	Teledyne-Philbrick	<b>RSN</b>	Raytheon
<b>CMP</b>	Precision Monolithics	<b>RV</b>	Raytheon
<b>CN</b>	Ferranti	<b>S</b>	Signetics
<b>DA</b>	Teledyne-Philbrick	<b>SA</b>	Teledyne-Philbrick
<b>EP</b>	Teledyne-Philbrick	<b>SE</b>	Signetics; Mullard
<b>ESL</b>	Teledyne-Philbrick	<b>SFC</b>	Thomson-CSF
<b>FSL</b>	Teledyne-Philbrick	<b>SG</b>	Silicon General
<b>FSS</b>	Ferranti	<b>SH</b>	Fairchild
<b>HA</b>	Harris	<b>SK</b>	RCA
<b>HEPC</b>	Motorola	<b>SL</b>	Plessey; Teledyne-Philbrick
<b>ICH</b>	Intersil	<b>SN</b>	Texas Instruments
<b>ICL</b>	Intersil	<b>SP</b>	Teledyne-Philbrick
<b>JM</b>	Fairchild	<b>SQ</b>	Teledyne-Philbrick
<b>JSF</b>	Thomson-CSF	<b>SSS</b>	Precision Monolithics
<b>L</b>	Analog Devices; SGS-ATES	<b>SU</b>	Signetics; Mullard
<b>LA</b>	Teledyne-Philbrick	<b>T</b>	Teledyne-Philbrick Transitron
<b>LF</b>	National Semiconductor	<b>TA</b>	AEG-Telefunken
<b>LH</b>	National Semiconductor	<b>TAA</b>	Proelectron Standard
<b>LM</b>	National Semiconductor	<b>TBA</b>	Proelectron Standard
<b>M</b>	Mitsubishi	<b>TBB</b>	Proelectron Standard
<b>MC</b>	Motorola Semiconductors	<b>TBC</b>	Proelectron Standard
<b>MCC</b>	Motorola Semiconductors	<b>TBE</b>	Proelectron Standard
<b>MCCF</b>	Motorola Semiconductors	<b>TCA</b>	Proelectron Standard
<b>MCE</b>	Motorola Semiconductors	<b>TDA</b>	Proelectron Standard
<b>MCH</b>	Motorola Semiconductors	<b>TDB</b>	Proelectron Standard
<b>MIC</b>	ITT Semiconductors	<b>TDC</b>	Proelectron Standard
<b>MLF</b>	Motorola; Teledyne-Philbrick	<b>TDE</b>	Proelectron Standard
<b>MLM</b>	Motorola Semiconductors	<b>TL</b>	AEG-Telefunken
<b>MLMC</b>	Motorola Semiconductors	<b>TOA</b>	Transitron
<b>MONO-OP</b>	Precision Monolithics	<b>TSC</b>	Transitron
<b>N</b>	Signetics; Mullard	<b>U</b>	Fairchild
<b>NC</b>	General Instruments (obs.)	<b>ULN</b>	Sprague
<b>NE</b>	Signetics; Mullard	<b>ULS</b>	Sprague
<b>NH</b>	National Semiconductor	<b>USL</b>	Teledyne-Philbrick
		<b>ZA</b>	Zeltex
		<b>ZEL</b>	Zeltex
		<b>ZLD</b>	Ferranti
		<b>ZN</b>	Ferranti
		<b>μA</b>	Fairchild



# Appendix E

## Tabulation Codes for Applications

<b>BDO</b>	Balanced differential-output amplifier	<b>PAA</b>	Parametric amplifier
<b>CDA</b>	Current-difference amplifier	<b>PIA</b>	Precision instrumentation amplifier
<b>CHP</b>	Chopper-stabilized amplifier	<b>PRA</b>	Programmable opamp
<b>CPR</b>	DC comparator	<b>QCD</b>	Quad current-difference amplifier
<b>DBD</b>	Dual balanced differential-output amplifier	<b>QCP</b>	Quad comparator
<b>DCP</b>	Dual Comparator	<b>QFE</b>	Quad fet-input opamp
<b>DFE</b>	Dual fet-input opamp	<b>Q GK</b>	Quad general-purpose, internally-compensated, opamp
<b>DGK</b>	Dual general purpose opamp	<b>QGU</b>	Quad general-purpose, uncompensated, opamp
<b>DGU</b>	Dual general-purpose uncompensated opamp	<b>QLQ</b>	Quad low-quiescent-power opamp
<b>DHS</b>	Dual high-slew-rate opamp	<b>QPI</b>	Quad precision instrumentation amplifier
<b>DLN</b>	Dual low-noise opamp	<b>QPR</b>	Quad programmable opamp
<b>DPI</b>	Dual precision instrumentation amplifier	<b>QSB</b>	Quad super-beta opamp
<b>DPR</b>	Dual programmable opamp	<b>SBA</b>	Super-beta opamp
<b>DSB</b>	Dual super-beta opamp	<b>TCP</b>	Triple comparator
<b>FET</b>	Fet-input opamp	<b>TFE</b>	Triple fet-input opamp
<b>GPK</b>	General-purpose, internally-compensated, opamp	<b>TGK</b>	Triple general-purpose, internally compensated, opamp
<b>GPU</b>	General-purpose, uncompensated, opamp	<b>TGU</b>	Triple general-purpose, uncompensated, opamp
<b>HCO</b>	High current output opamp	<b>TLN</b>	Triple low-noise opamp
<b>HIR</b>	High input resistance opamp	<b>TLP</b>	Triple low-quiescent-power opamp
<b>HPO</b>	High power output opamp	<b>TOT</b>	Triple operational transconductance amplifier
<b>HSR</b>	High slew rate opamp	<b>TPI</b>	Triple precision instrumentation amplifier
<b>HVO</b>	High voltage output opamp	<b>TPR</b>	Triple programmable opamp
<b>LBC</b>	Low input bias current opamp	<b>TSB</b>	Triple super-beta opamp
<b>LCD</b>	Low input offset current drift opamp	<b>VFA</b>	Voltage-follower amplifier
<b>LNA</b>	Low noise opamp	<b>WBA</b>	Wide-band opamp
<b>LOC</b>	Low input offset current opamp	<b>XHG</b>	Extra-high-gain opamp
<b>LOV</b>	Low input offset voltage opamp	<b>XLP</b>	Extra-low quiescent power opamp
<b>LQP</b>	Low quiescent power opamp	<b>XSR</b>	Extra-high slew rate opamp
<b>LVD</b>	Low input offset voltage drift opamp	<b>XWB</b>	Extra-wide-band opamp
<b>MWB</b>	Medium-wideband opamp		
<b>OTA</b>	Operational transconductance amplifier		

# Appendix G

## Codes for Leadout Connections

### *I: Connection Codes in Serial Order*

A	= Gain adjust, 1
A*	= Gain adjust, 2
B	= Bias adjust or set
C	= Case, package, screen
E+	= Input, non-inverting, low-level
E-	= Input, inverting, low-level
F	= Input frequency compensation, 1
F*	= Input frequency compensation, 2
G	= Ground, common, earth, zero volts
J+	= Input, non-inverting, high-level
J-	= Input, inverting, high-level
K	= Output, open collector
L	= Output, open emitter
M	= Metal casing
N	= Not connected, i.e. isolated lead
Q	= Special terminal (consult manufacturer's data)
R	= Output, 1
R*	= Output, 2
S	= Strobe
T	= Offset balance, trim or null, 1
T*	= Offset balance, trim or null, 2
V+	= +ve dc supply
V-	= -ve dc supply
W	= Guard ring
X	= Blank position, lead omitted
++	= +ve supplementary dc supply
--	= -ve supplementary dc supply
φ	= Output frequency compensation, 1
φ*	= Output frequency compensation, 2

### *II: Lead Assignments in Alphabetical Order*

Balance, offset, 1 = T
Balance, offset, 2 = T*
Bias adjust = B
Blank position, without lead = X
Case = C
Compensation, input, 1 = F
Compensation, input, 2 = F*
Compensation, output, 1 = φ
Compensation, output, 2 = φ*
DC supply, +ve = V+
DC supply, -ve = V-
Frequency compensation, input, 1 = F
Frequency compensation, input, 2 = F*
Frequency compensation, output, 1 = φ
Frequency compensation, output, 2 = φ*
Gain adjust, 1 = A
Gain adjust, 2 = A*
Ground = G
Guard ring = W
Input, inverting, high-level = J-
Input, non-inverting, high-level = J+
Input, inverting, low-level = E-
Input, non-inverting, low-level = E+
Input offset voltage, adjust, 1 = T
Input offset voltage, adjust, 2 = T*
Lead omitted, blank position = X
Lead in position but not connected = N
Metal case = M
Not connected, but lead in position = N
Null, offset, 1 = T
Null, offset, 2 = T*
Offset voltage adjust, 1 = T
Offset voltage adjust, 2 = T*
Output, 1 = R
Output, 2 = R*
Output, open-collector = K
Output, open-emitter = L
Package = C
Special purpose terminal (data sheet to be consulted) = Q
Strobe = S
Supply, dc, +ve = V+
Supply, dc, -ve = V-
Supply, dc, supplementary, +ve = ++
Supply, dc, supplementary, -ve = --
Trim (offset voltage), 1 = T
Trim (offset voltage), 2 = T*

Appendix F



Appendix F

