

KT 3153 A9	Si-N	SMD, Uni, 60V, 0,4A, >250MHz	35a	BC 817	35a
KT 3157 A	Si-P	Uni, Vid, 250V, 30mA, 0,2W	7d	BF 421 A	7c
KT 3165 A	Si-P	VHF/UHF, 40V, 30mA, >750MHz	24a	BF 979	24e
KT 3172 A9	Si-N	SMD, Uni, 20V, 0,2A	35a	BC 846	35a
KT 3174 AC-2	Si-N	Dual, 10V, 7,5mA, 0,15W	8-MDIP	-	-
KT 8101 A	Si-N	NF/S-L, 200V, 16A, 150W	18j	2SC3263	18j
KT 8101 B	Si-N	=KT 8101A: 160V	18j	2SC3263	18j
KT 8102 A	Si-P	NF/S-L, 200V, 16A, 150W	18j	2SA1294	18j
KT 8102 B	Si-P	=KT 8102A: 160V	18j	2SA1294	18j
KT 8107 A	Si-N+Di	TV-HA, 1500V, 8A, 100W, sat<1V(4,5A)	18j	BU 2508 D,DW	18j, 16j
KT 8107 B	Si-N	=KT 8107A: ohne/wo. Damper-Di	18j	BU 2508A	18j
KT 8107 B	Si-N+Di	=KT 8107A: sat<3V(4,5A)	18j	BU 2508 D,DW	18j, 16j
KT 8107 A1,B1	Si-N+Di	=KT 8107A1,B1: Iso	18c	BU 2508 DF	18j
KT 8107 Γ	Si-N	=KT 8107A: ohne/wo. Damper-Di, sat<3V	18j	BU 2508A	18j
KT 8107 B1,Γ1	Si-N	=KT 8107B1,Γ1: Iso	18c	BU 2508AF	18j
KT 8109 A	Si-N-Darl	S-L, 350V, 5A, 40W, B>180	17h	(2SD798)	17j
KT 8110 A	Si-N	S-L, 700V, 7A, 60W, 20MHz, <700/3200ns A=700/400V, B=700/350V, B=700/400V	17j	BUT 56 A	17j
KT 9115 A	Si-P	TV, Vid-E, 300V, 0,1A, 10W	14h	2SA1381	14h
KT 9115 B	Si-P	=KT 9115A: 150V	14h	2SA1381	14h
KT 9120 A	Si-P	NF/S-L, 45V, 12A, 50W, >50MHz	17j	2SA1329	17j
KT 9144 A9	Si-P	SMD, S, 500V, 50mA, >30MHz	39b	-	-
KT 9145 A9	Si-N	SMD, S, 500V, 50mA, >50MHz	39b	-	-
KT 9157 A	Si-N	Foto, L, 30V, 5A, 10W	14h	2SC3420	14b
KT 9166 A	Si-N	L, lo-sat, 60V, 15A, 50W, >90MHz	17j	-	-
KTA 200	Si-P	Uni, -/50V, 0,5A, 0,625W	7c	BC 327	7a
KTA 473	Si-P	=2SA473	17j	*2SA473	-
KTA 940	Si-P	=2SA940	17j	*2SA940	-
KTA 950	Si-P	=2SA950	7c(9mm)	*2SA950	-
KTA 968(A)	Si-P	=2SA968(A)	17j	*2SA968	-
KTA 1001	Si-P	SMD, Blitzg./Strobo, -/20V, 3A, 170MHz	39b	-	-
KTA 1015	Si-P	=2SA1015	7c	*2SA1015	-
KTA 1021	Si-P	Uni, -/30V, 0,5A, 0,4W	41c	BC 327	7a
KTA 1023	Si-P	Uni, -/120V, 0,8A, 1W, 120MHz	7c(9mm)	2SD1212	7c
KTA 1024	Si-P	Uni, -/150V, 0,05A, 1W	7c(9mm)	2SA1124	7c
KTA 1070	Si-P	Vid, -/200V, 0,1A, 1W	7c(9mm)	2SA1371	7c
KTA 1099	Si-P	Vid-L, -/120V, 0,3A, 8W	17c	-	-
KTA 1241	Si-P	Blitzg./Strobo, -/20V, 5A, 1W, 170MHz	7c(9mm)	2SB1446	9c
KTA 1266	Si-P	Uni, -/50V, 0,15A, 0,625W	7c	BC 556	7a
KTA 1267(L)	Si-P	=KTA 1266:	41c	BC 556	7a
KTA 1268	Si-P	Uni, ra, -/120V, 0,1A, 0,625W	7c	2SA1124	7c
KTA 1270	Si-P	Uni, -/30V, 0,5A, 0,625W	7c	BC 327	7a
KTA 1271	Si-P	NF-E, -/30V, 0,8A, 0,625W	7c	BC 327	7a
KTA 1272	Si-P	Uni, -/30V, 0,8A, 0,4W	41c	BC 327	7a
KTA 1273	Si-P	NF-E, -/30V, 2A, 1W, 120MHz	7c(9mm)	2SB892	7c
KTA 1274	Si-P	Uni, -/80V, 0,4A, 1W	7c(9mm)	BC 640	7c
KTA 1275	Si-P	TV-NF-E, -/160V, 1A, 1W, 20MHz	7c(9mm)	2SB1212	7c
KTA 1276	Si-P	NF-L, -/30V, 3A, 10W, 100MHz	17j	(2SA748)	17j
KTA 1298	Si-P	=2SA1298	35a	*2SA1298	-
KTA 1302	Si-P	=2SA1302	=16j	*2SA1302	-
KTA 1504	Si-P	SMD, Uni, -/50V, 0,15A	35a	BC 856	35a
KTA 1505	Si-P	SMD, Uni, -/30V, 0,5A	35a	BC 807	35a
KTA 1517	Si-P	SMD, Uni, ra, -/120V, 0,1A	35a	-	-
KTA 1657	Si-P	TV-HA, -/150V, 1,5A, 20W	17c	2SA1606	17c
KTA 1658	Si-P	NF-L, -/30V, 3A, 15W, 100MHz	17c	2SA1307	17c
KTA 1659	Si-P	NF/S-L, -/160V, 1,5A, 20W, 100MHz	17c	2SA1606	17c