

TRANSISTOR NUMBER	PM OA LT	PACK-AGE	LEAD INFO	VCB MAX	VCE MAX	VEB MAX	I C MAX	T J MAX	P TOT	F T MIN	C OB MAX	H FE	H FE BIAS	USE	MFR	EUR EQUIV	USA EQUIV	ISS
BDY82B	PS	TOP66	L32	40V	35V	5V	4A	150C	36WC			70/140	500MA	AHG	MIS	BD590	2N6126	0
BDY82C	PS	TOP66	L32	40V	35V	5V	4A	150C	36WC			120MN	500MA	AHG	MIS	BD590	2N6126	2
BDY83	PS	TOP66	L32	50V	50V	10V	4A	150C	36WC	2M		40/240	500MA	AHG	TOS	BD738	2N6107	0
BDY83A	PS	TOP66	L32	60V	50V	5V	4A	150C	36WC			40/80	500MA	AHG	MIS	BD590	2N6126	0
BDY83B	PS	TOP66	L32	60V	50V	5V	4A	150C	36WC			70/140	500MA	AHG	MIS	BD590	2N6126	0
BDY83C	PS	TOP66	L32	60V	50V	5V	4A	150C	36WC			120MN	500MA	AHG	MIS	BD590	2N6126	0
BDY87	NS	X03	L05	20V	20V	7V	8A	200C	35WC			200MN	8A	AHD	SID	BDY88		1
BDY88	NS	X03	L05	40V	40V	7V	8A	200C	35WC			200MN	8A	AHD	SID	BDY89		1
BDY89	NS	X03	L05	60V	60V	7V	8A	200C	35WC			200MN	8A	AHD	SID			1
BDY90	NS	T03	L05	120V	100V	6V	15A	175C	40WC	35M		30/120	5A	RHH	MUB			0
BDY91	NS	T03	L05	100V	80V	6V	15A	175C	40WC	35M		30/120	5A	RHH	MUB			0
BDY92	NS	T03	L05	80V	60V	6V	15A	175C	40WC	35M		30/120	5A	RHH	MUB			0
BDY93	NS	T03	L05	750V	350V	6V	6A	150C	30WC	4M		15/60	1A	AHE	MUB			0
BDY93/01	NS	T03	L05	800V	400V	6V	6A	150C	30WC	4M		15/60	1A	AHE	MUB	BU113		1
BDY94	NS	T03	L05	750V	300V	6V	6A	150C	30WC	4M		15/60	1A	AHE	MUB			0
BDY94/01	NS	T03	L05	800V	300V	6V	6A	150C	30WC	4M		15/60	1A	AHE	MUB	BU113		1
BDY95	NS	T03	L05	600V	250V	6V	6A	150C	30WC	4M		15/60	1A	AHE	MUB			0
BDY96	NS	T03	L05	750V	350V	6V	15A	150C	40WC	5M		15/60	2A	AHE	MUB			0
BDY96/01	NS	T03	L05	800V	400V	6V	15A	150C	40WC	5M		15/60	2A	AHE	MUB	BUX25		1
BDY97	NS	T03	L05	750V	300V	6V	15A	150C	40WC	5M		15/60	2A	AHE	MUB			0
BDY97/01	NS	T03	L05	800V	300V	6V	15A	150C	40WC	5M		15/60	2A	AHE	MUB	BUX25		1
BDY98	NS	T03	L05	600V	250V	6V	15A	150C	40WC	5M		15/60	2A	AHE	MUB			0
BDY99	NS	T03	L05	250V	250V	6V	10A	125C	40WC	4M		25/80	2A	AHP	RTC			1
BEL6107	PS	T05	L04	100V	70V	12V	1A5	200C	5WC	1M		35/100	200MA	AMH	BEL	BFS93	2N4033	2
BEL6109	PS	T05	L04	100V	55V	12V	1A5	200C	5WC	1M		35/100	200MA	AMH	BEL	BFS93	2N4033	2
BF108	NS	T05	L04	135V		3V	50MA	175C	800MWF	50M	3P	50TP	30MA	TVM	OBS	BF178		0
BF109	NS	T05	L04	135V	110V	2V	50MA	175C	2500MWF	80M	3R0	20MN	10MA	TVH	OBS	BF178		0
BF110	NS	T05	L04	170V	90V	3V	30MA	175C	600MWF	100M	7P	30MN	10MA	TVH	OBS	BF178		0
BF111	NS	T039	L04	200V		5V	80MA	175C	3WC	60M	3R5	20MN	60MA	TVE	SID	BF179		0
BF114	NS	T05	L04	135V		3V	40MA	175C	565MWF	40M	7P	20MN	10MA	TVM	OBS	BF178		0
BF115	NS	T072	L51	50V	30V	5V	30MA	175C	145MWF	115M	1R3	45/165	1MA	FRM	MUB	BF185		0
BF117	NS	T05	L04	140V	140V		100MA	175C	680MWF	40M	4P	25MN	30MA	TVE	ITB	BF179		0
BF118	NS	T05	L04	250V	250V	5V	100MA	175C	800MWF	60M	7P	25MN	30MA	ALE	ITB	BF337	2N4927	0
BF119	NS	T05	L04	160V	160V	5V	100MA	175C	800MWF	60M	7P	25MN	30MA	ALE	ITB	BF337	2N4927	0
BF120	NS	T018	L01	220V	220V	5V	50MA	175C	300MWF	55M	7P	20MN	10MA	ALE	OBS	BF337	2N4927	0
BF121	NS	X24	L52	40V	30V	4V	25MA	125C	330MWF	175M	DR28	30MN	4MA	TIG	ITB	BF167		0
BF123	NS	X24	L52	40V	25V	4V	25MA	125C	330MWF	275M	DR46	35MN	7MA	TIA	ITB	BF173		0
BF125	NS	X24	L52	40V	25V	4V	25MA	125C	330MWF	225M	DR46	35MN	7MA	TIA	ITB	BF173		0
BF127	NS	X24	L52	40V	30V	4V	25MA	125C	330MWF	175M	DR28	30MN	4MA	TIG	ITB	BF167		0
BF136	NS	T0106	L17	30V	30V		20MA	125C	200MWF	300M	2P	20/80	10MA	FRM	OBS	BF310	2N918	2
BF137	NS	T05	L04	160V	160V	5V	100MA	175C	680MWF	50M	4P	25MN	30MA	TVE	ITB	BF179		0
BF138	NS	T0106	L17	30V	30V		20MA	125C	200MWF	300M	2P2	20MN	10MA	FRM	OBS	BF371	2N3662	2
BF140	NS	T05	L04	135V		4V	50MA	175C	800MWF	40M	4P	15MN	20MA	TVH	OBS	BF178		0
BF140A	NS	T05	L04	150V		4V	30MA	175C	800MWF	40M	4P	15MN	20MA	TVH	OBS	BF178		0
BF140D	NS	T05	L04	180V		4V	50MA	175C	800MWF	35M	4P	15MN	20MA	TVE	OBS	BF179		0
BF140R	NS	T018	L01	135V		3V	50MA	175C	600MWF	90M	4P	20MN	10MA	TVH	OBS	BF178		0
BF140S	NS	T05	L01	135V		3V	50MA	175C	1WF	90M	4P	20MN	10MA	TVH	OBS	BF178		0
BF152	NS	T0106	L17	30V	12V	2V	25MA	125C	200MWF	600M	1P2	25MN	3MA	TUO	SGI	BF183		0
BF153	NS	T0106	L17	30V	12V	2V	25MA	125C	200MWF	300M	1P2	20MN	3MA	FRM	SGI	BF185		0
BF154	NS	T0106	L17	30V	20V	4V	50MA	125C	300MWF	200M	3P5	25MN	10MA	TIG	SGI	BF167		0
BF155	NS	T072	L06	40V	40V	3V	20MA	175C	175MWF	400M	0P8	20MN	2MA	TUG	SGI	BF180		0
BF155R	NS	T018	L01	155V		3V	50MA	175C	600MWF	90M	4P	20MN	10MA	TVH	NUC	BF178		0
BF155S	NS	T05	L01	155V		3V	50MA	175C	1WF	90M	4P	20MN	10MA	TVH	NUC	BF178		0
BF156	NS	T039	L04	120V	120V	5V	100MA	200C	800MWF	30M	12P	30MN	30MA	TVH	SGI	BF178		0
BF157	NS	T039	L04	150V	150V	5V	100MA	200C	800MWF	30M	12P	30MN	30MA	TVE	SGI	BF179C		0
BF157B	NS	T039	L04	175V	175V	5V	100MA	200C	800MWF	30M	12P	30MN	30MA	TVE	SGI	BF179C		0
BF158	NS	T0106	L17	30V	12V	2V	50MA	125C	200MWF	600M	1P2	20MN	4MA	TIA	SGI	BF173		0
BF159	NS	T0106	L17	40V	20V	2V	50MA	125C	200MWF	600M	1P2	20MN	4MA	TIA	SGI	BF173		0
BF160	NS	T0106	L17	30V	12V	2V	50MA	125C	200MWF	400M	1P2	20MN	3MA	FRM	SGI	BF185		0
BF160C	NS	T0106	L17	30V	13V	2V	50MA	125C	200MWF	400M	1P2	50MN	1MA	FRM	MCB	BF185		1
BF161	NS	T072	L06	50V	50V	4V	20MA	175C	175MWF	400M	DP45	20MN	3MA	TUO	SGI	BF183		0
BF162	NS	T0106	L17	40V	40V	4V	50MA	125C	200MWF	400M	2P4	30MN	4MA	FRM	SGI	BF200		0
BF163	NS	T0106	L17	40V	40V	4V	50MA	125C	200MWF	400M	0P8	30MN	4MA	TIG	SGI	BF167		0
BF164	NS	T0106	L17	40V	40V	4V	25MA	125C	200MWF	400M	1P6	30MN	4MA	TIG	SGI	BF167		0
BF165	NS	T0105	L04	30V	15V	4V	25MA	125C	300MWF	200M	3R5	20MN	2MA	FRM	SGI	BF185		0
BF166	NS	T072	L06	40V	40V	3V	25MA	175C	175MWF	400M	1P2	20MN	2MA	FRM	SGI	BF200		0
BF167	NS	T072	L51	40V	30V	4V	25MA	175C	150MWF	300M	0R3	30MN	4MA	TIG	MUB	BF167		0
BF168	NS	T018	L01	50V	30V	4V	25MA	175C	260MWF	275M	2P6	50MN	7MA	FRM	OBS	BF185		0
BF169	NS	T018	L01	50V	30V	5V	50MA	175C	300MWF	200M	6P	40MN	10MA	FRM	OBS	BF185		0
BF169R	NS	T0106	L17	50V	30V	5V	50MA	125C	300MWF	200M	6P	40MN	10MA	FRM	SAS	BF184		1
BF170	NS	T05	L04	160V	160V		50MA	175C	300MWF	50M		15MN	2MA	TVE	SAS	BF259		1
BF173	NS	T072	L51	40V	25V	4V	25MA	175C	260MWF	350M	0R3	40/100	7MA	TIA	MUB	BF173		0
BF174	NS	T039	L04	150V	150V		100MA	200C	800MWF	40M	7P	30MN	10MA	TVE	SGI	BF179C		0
BF175	NS	T072	L06	40V	40V	3V	25MA	175C	175MWF	250M	0P8	30MN	2MA	TIG	SGI	BF167		0
BF176	NS	T0105	L04	40V	40V	4V	50MA	125C	250MWF	225M	3P0	20MN	10MA	TIA	SGI	BF173		0