

Protection devices for system immunity

Quick reference guide



July 2005

Transient voltage suppressors: 200W Transils – STmite

Power* [W]	V _{RM} [V]	I _{RM} max @ V _{RM} [μA]	Part number unidirect.	V _{BR} min @ I _R		V _{CL} max @ I _{FP}		I _{FSM} [A]	Package
				[V]	[mA]	[V]	[A]		
200	5	50	SM2T6V8A	6.4	10	9.2	19.6	25	STmite
200	12	1	SM2T14A	13.3	1	19.9	9.0	25	STmite
200	16	1	SM2T18A	17.1	1	26	7	25	STmite
200	24	1	SM2T27A	25.7	1	38.9	4.6	25	STmite

Transient voltage suppressors: 400W Transils – Axial

Power* [W]	V _{RM} [V]	I _{RM} max @ V _{RM} [μA]	Part number		V _{BR} min @ I _R		V _{CL} max @ I _{FP}		I _{FSM} [A]	Package
			Unidirect.	Bidirect.	[V]	[mA]	[V]	[A]		
400	5.8	1000	BZW04-5V8	BZW04-5V8B	6.45	10	10.5	38	30	DO-15
400	10.2	5	BZW04-10	BZW04-10B	11.4	1	16.7	24	30	DO-15
400	12.8	5	BZW04-13	BZW04-13B	14.3	1	21.2	19	30	DO-15
400	15.3	1	BZW04-15	BZW04-15B	17.1	1	25.2	16	30	DO-15
400	25.6	1	BZW04-26	BZW04-26B	28.5	1	41.5	9.6	30	DO-15
400	28.2	1	BZW04-28	BZW04-28B	31.4	1	45.7	8.8	30	DO-15
400	30.8	1	BZW04-31	BZW04-31B	34.2	1	49.9	8	30	DO-15
400	33.3	1	BZW04-33	BZW04-33B	37.1	1	53.9	7.4	30	DO-15
400	47.8	1	BZW04-48	BZW04-48B	53.2	1	77	5.2	30	DO-15
400	239	1	BZW04-239	BZW04-239B	266	1	384	1.5	30	DO-15
400	299	1	BZW04-299	BZW04-299B	332	1	482	0.9	30	DO-15
400	342	1	BZW04-342	BZW04-342B	380	1	548	0.9	30	DO-15
400	376	1	BZW04-376	BZW04-376B	418	1	603	0.8	30	DO-15

Transient voltage suppressors: 400W Transils – SMA

Power* [W]	V _{RM} [V]	I _{RM} max @ V _{RM} [μA]	Part number		V _{BR} min @ I _R		V _{CL} max @ I _{FP}		I _{FSM} [A]	Package
			Unidirect.	Bidirect.	[V]	[mA]	[V]	[A]		
400	5	800	SMAJ5.0A-TR	SMAJ5.0CA-TR	6.4	10	9.2	43.5	40	SMA
400	6	800	SMAJ6.0A-TR	SMAJ6.0CA-TR	6.7	10	10.3	38.8	40	SMA
400	6.5	500	SMAJ6.5A-TR	SMAJ6.5CA-TR	7.2	10	11.2	35.7	40	SMA
400	10	5	SMAJ10A-TR	SMAJ10CA-TR	11.1	1	17	23.5	40	SMA
400	12	5	SMAJ12A-TR	SMAJ12CA-TR	13.3	1	19.9	20.1	40	SMA
400	13	1	SMAJ13A-TR	SMAJ13CA-TR	14.4	1	21.5	18.6	40	SMA
400	15	1	SMAJ15A-TR	SMAJ15CA-TR	16.7	1	24.4	16.4	40	SMA
400	18	1	SMAJ18A-TR	SMAJ18CA-TR	20	1	29.2	13.7	40	SMA
400	22	1	SMAJ22A-TR	SMAJ22CA-TR	24.4	1	35.5	11.2	40	SMA
400	24	1	SMAJ24A-TR	SMAJ24CA-TR	26.7	1	38.9	10.3	40	SMA
400	26	1	SMAJ26A-TR	SMAJ26CA-TR	28.9	1	42.1	9.5	40	SMA
400	28	1	SMAJ28A-TR	SMAJ28CA-TR	31.1	1	45.4	8.8	40	SMA
400	30	1	SMAJ30A-TR	SMAJ30CA-TR	33.3	1	48.4	8.3	40	SMA
400	33	1	SMAJ33A-TR	SMAJ33CA-TR	36.7	1	53.3	7.5	40	SMA
400	40	1	SMAJ40A-TR	SMAJ40CA-TR	44.4	1	64.5	6.2	40	SMA
400	43	1	SMAJ43A-TR	SMAJ43CA-TR	47.8	1	69.7	5.7	40	SMA
400	48	1	SMAJ48A-TR	SMAJ48CA-TR	53.3	1	77.4	5.2	40	SMA
400	58	1	SMAJ58A-TR	SMAJ58CA-TR	64.4	1	93.6	4.3	40	SMA
400	70	1	SMAJ70A-TR	SMAJ70CA-TR	77.8	1	113	3.5	40	SMA
400	85	1	SMAJ85A-TR	SMAJ85CA-TR	94.4	1	137	2.9	40	SMA
400	130	1	SMAJ130A-TR	SMAJ130CA-TR	144	1	209	1.9	40	SMA
400	170	1	SMAJ170A-TR	SMAJ170CA-TR	189	1	275	1.4	40	SMA
400	188	1	SMAJ188A-TR	SMAJ188CA-TR	209	1	328	1.4	40	SMA

Transient voltage suppressors: 600W Transils – Axial

Power* [W]	V _{RM} [V]	I _{RM} max @ V _{RM} [μA]	Part number		V _{BR} min @ I _r		V _{CL} max @ I _{pp}		I _{FSM} [A]	Package
			Unidirect.	Bidirect.	[V]	[mA]	[V]	[A]		
600	5.8	1000	BZW06-5V8	BZW06-5V8B	6.45	10	10.5	57	100	DO-15
600	6.4	500	BZW06-6V4	BZW06-6V4B	7.13	10	11.3	53	100	DO-15
600	10.2	5	BZW06-10	BZW06-10B	11.4	1	16.7	36	100	DO-15
600	12.8	5	BZW06-13	BZW06-13B	14.3	1	21.2	28	100	DO-15
600	13.6	5	BZW06-14	BZW06-14B	15.2	1	22.5	27	100	DO-15
600	15.3	1	BZW06-15	BZW06-15B	17.1	1	25.2	24	100	DO-15
600	18.8	1	BZW06-19	BZW06-19B	20.9	1	30.6	20	100	DO-15
600	23.1	1	BZW06-23	BZW06-23B	25.7	1	37.5	16	100	DO-15
600	25.6	1	BZW06-26	BZW06-26B	28.5	1	41.5	14.5	100	DO-15
600	28.2	1	BZW06-28	BZW06-28B	31.4	1	45.7	13.1	100	DO-15
600	30.8	1	BZW06-31	BZW06-31B	34.2	1	49.9	12	100	DO-15
600	33.3	1	BZW06-33	BZW06-33B	37.1	1	53.9	11.1	100	DO-15
600	47.8	1	BZW06-48	BZW06-48B	53.2	1	77	7.8	100	DO-15
600	273	1	BZW06-273	BZW06-273B	304	1	438	1.6	100	DO-15
600	342	1	BZW06-342	BZW06-342B	380	1	548	1.3	100	DO-15
600	376	1	BZW06-376	BZW06-376B	418	1	603	1.3	100	DO-15

Transient voltage suppressors: 600W Transils – Axial

Power* [W]	V _{RM} [V]	I _{RM} max @ V _{RM} [μA]	Part number		V _{BR} min @ I _r		V _{CL} max @ I _{pp}		I _{FSM} [A]	Package
			Unidirect.	Bidirect.	[V]	[mA]	[V]	[A]		
600	5.8	1000	P6KE6V8A	P6KE6V8CA	6.45	10	10.5	57	100	DO-15
600	6.4	500	P6KE7V5A	P6KE7V5CA	7.13	10	11.3	53	100	DO-15
600	12.8	1	P6KE15A	P6KE15CA	14.3	1	21.2	28	100	DO-15
600	15.3	1	P6KE18A	P6KE18CA	17.1	1	25.2	24	100	DO-15
600	23.1	1	P6KE27A	P6KE27CA	25.7	1	37.5	16	100	DO-15
600	25.6	1	P6KE30A	P6KE30CA	28.5	1	41.5	14.5	100	DO-15
600	28.2	1	P6KE33A	P6KE33CA	31.4	1	45.7	13.1	100	DO-15
600	30.8	1	P6KE36A	P6KE36CA	34.2	1	49.9	12	100	DO-15
600	33.3	1	P6KE39A	P6KE39CA	37.1	1	53.9	11.1	100	DO-15
600	47.8	1	P6KE56A	P6KE56CA	53.2	1	77	7.8	100	DO-15
600	58.1	1	P6KE68A	P6KE68CA	64.6	1	92	6.5	100	DO-15
600	70.1	1	P6KE82A	P6KE82CA	77.9	1	113	5.3	100	DO-15
600	171	1	P6KE200A	P6KE200CA	190	1	274	2.2	100	DO-15
600	213	1	P6KE250A	P6KE250CA	237	1	344	2	100	DO-15
600	256	1	P6KE300A	P6KE300CA	285	1	414	1.6	100	DO-15
600	342	1	P6KE400A	P6KE400CA	380	1	548	1.3	100	DO-15
600	376	1	P6KE440A	P6KE440CA	418	1	603	1.3	100	DO-15

Transient voltage suppressors: high temperature 600W Transils – SMB

Power* [W]	V _{RM} [V]	I _{RM} max @ V _{RM} [mA]	Part number unidirect.	V _{BR} min @ I _r		V _{CL} max @ I _{pp}		I _{FSM} [A]	Package
				[V]	[mA]	[V]	[A]		
600	20.5	2	SM6HT24A	22.8	1	33.2	18	75	SMB
600	23.1	2	SM6HT27A	25.7	1	37.5	16	75	SMB
600	25.6	2	SM6HT30A	28.5	1	41.5	14.5	75	SMB
600	30.8	2	SM6HT36A	34.2	1	49.9	12	75	SMB
600	33.3	2	SM6HT39A	37.1	1	53.9	11.1	75	SMB
600	36.8	2	SM6HT43A	40.9	1	59.3	10.1	75	SMB

*10/1000ms waveform

Transient voltage suppressors: 600W Transils – SMB

Power* [W]	V_{RM} [V]	I_{RM} max @ V_{RM} [μ A]	Part number		V_{BR} min @ I_R		V_{CL} max @ I_{PP}		I_{FSM} [A]	Package
			Unidirect.	Bidirect.	[V]	[mA]	[V]	[A]		
600	5.8	1000	SM6T6V8A	SM6T6V8CA	6.45	10	10.5	57	100	SMB
600	6.4	500	SM6T7V5A	SM6T7V5CA	7.13	10	11.3	53	100	SMB
600	8.55	10	SM6T10A	SM6T10CA	9.5	1	14.5	41	100	SMB
600	10.2	5	SM6T12A	SM6T12CA	11.4	1	16.7	36	100	SMB
600	12.8	5	SM6T15A	SM6T15CA	14.3	1	21.2	28	100	SMB
600	15.3	5	SM6T18A	SM6T18CA	17.1	1	25.2	24	100	SMB
600	18.8	5	SM6T22A	SM6T22CA	20.9	1	30.6	20	100	SMB
600	20.5	5	SM6T24A	SM6T24CA	22.8	1	33.2	18	100	SMB
600	23.1	5	SM6T27A	SM6T27CA	25.7	1	37.5	16	100	SMB
600	25.6	5	SM6T30A	SM6T30CA	28.5	1	41.5	14.5	100	SMB
600	28.2	5	SM6T33A	SM6T33CA	31.4	1	45.7	13.1	100	SMB
600	30.8	5	SM6T36A	SM6T36CA	34.2	1	49.9	12	100	SMB
600	33.3	5	SM6T39A	SM6T39CA	37.1	1	53.9	11.1	100	SMB
600	58.1	5	SM6T68A	SM6T68CA	64.6	1	92	6.5	100	SMB
600	85.5	5	SM6T100A	SM6T100CA	95	1	137	4.4	100	SMB
600	128	5	SM6T150A	SM6T150CA	143	1	207	2.9	100	SMB
600	171	5	SM6T200A	SM6T200CA	190	1	274	2.2	100	SMB
600	188	5	SM6T220A	SM6T220CA	209	1	328	2	100	SMB

Transient voltage suppressors: 600W Transils – SMB

Power* [W]	V_{RM} [V]	I_{RM} max @ V_{RM} [μ A]	Part number		V_{BR} min @ I_R		V_{CL} max @ I_{PP}		I_{FSM} [A]	Package
			Unidirect.	Bidirect.	[V]	[mA]	[V]	[A]		
600	5	800	SMBJ5.0A-TR	SMBJ5.0CA-TR	6.4	10	9.2	68	100	SMB
600	6	800	SMBJ6.0A-TR	SMBJ6.0CA-TR	6.7	10	10.3	61	100	SMB
600	6.5	500	SMBJ6.5A-TR	SMBJ6.5CA-TR	7.2	10	11.2	56	100	SMB
600	10	5	SMBJ10A-TR	SMBJ10CA-TR	11.1	1	17	37	100	SMB
600	12	5	SMBJ12A-TR	SMBJ12CA-TR	13.3	1	19.9	31	100	SMB
600	13	1	SMBJ13A-TR	SMBJ13CA-TR	14.4	1	21.5	29	100	SMB
600	15	1	SMBJ15A-TR	SMBJ15CA-TR	16.7	1	24.4	25.1	100	SMB
600	18	1	SMBJ18A-TR	SMBJ18CA-TR	20	1	29.2	21.5	100	SMB
600	22	1	SMBJ22A-TR	SMBJ22CA-TR	24.4	1	35.5	17.7	100	SMB
600	24	1	SMBJ24A-TR	SMBJ24CA-TR	26.7	1	38.9	16	100	SMB
600	26	1	SMBJ26A-TR	SMBJ26CA-TR	28.9	1	42.1	14.9	100	SMB
600	28	1	SMBJ28A-TR	SMBJ28CA-TR	31.1	1	45.4	13.8	100	SMB
600	30	1	SMBJ30A-TR	SMBJ30CA-TR	33.3	1	48.4	13	100	SMB
600	33	1	SMBJ33A-TR	SMBJ33CA-TR	36.7	1	53.3	11.8	100	SMB
600	40	1	SMBJ40A-TR	SMBJ40CA-TR	44.4	1	64.5	9.7	100	SMB
600	48	1	SMBJ48A-TR	SMBJ48CA-TR	53.3	1	77.4	8.1	100	SMB
600	58	1	SMBJ58A-TR	SMBJ58CA-TR	64.4	1	93.6	6.7	100	SMB
600	70	1	SMBJ70A-TR	SMBJ70CA-TR	77.8	1	113	5.5	100	SMB
600	85	1	SMBJ85A-TR	SMBJ85CA-TR	94.4	1	137	4.6	100	SMB
600	130	1	SMBJ130A-TR	SMBJ130CA-TR	144	1	209	3	100	SMB
600	170	1	SMBJ170A-TR	SMBJ170CA-TR	189	1	275	2.2	100	SMB
600	188	1	SMBJ188A-TR	SMBJ188CA-TR	209	1	328	2	100	SMB

Transient voltage suppressors: digital purpose 600W Transils – SMB

Power* [W]	V_{RM} [V]	I_{RM} max @ V_{RM} [μ A]	Part number unidirect.	V_{BR} min @ I_R		V_{CL} max @ I_{PP}		I_{FSM} [A]	Package
				[V]	[mA]	[V]	[A]		
600	3.3	200	SMLVT3V3	4.1	1	7.3	50	50	SMB
600	12	1	SMBJ12AVCL	13.2	1	15.8	17.5	50	SMB

*10/1000 μ s waveform

Transient voltage suppressors: 1500W Transils – Axial

Power* [W]	V _{RM} [V]	I _{RM} max @ V _{RM} [mA]	Part number		V _{BR} min @ I _R		V _{CL} max @ I _{PP}		I _{FSM} [A]	Package
			Unidirect.	Bidirect.	[V]	[mA]	[V]	[A]		
1500	5	300	1N5908	–	6	1	7.6	30	200	DO-201
1500	5.8	1000	1.5KE6V8A	1.5KE6V8CA	6.45	10	10.5	143	200	DO-201
1500	6.4	500	1.5KE7V5A	1.5KE7V5CA	7.13	10	11.3	132	200	DO-201
1500	10.2	5	1.5KE12A	1.5KE12CA	11.4	1	16.7	90	200	DO-201
1500	12.8	1	1.5KE15A	1.5KE15CA	14.3	1	21.2	71	200	DO-201
1500	15.3	1	1.5KE18A	1.5KE18CA	17.1	1	25.2	59.5	200	DO-201
1500	18.8	1	1.5KE22A	1.5KE22CA	20.9	1	30.6	49	200	DO-201
1500	20.5	1	1.5KE24A	1.5KE24CA	22.8	1	33.2	45	200	DO-201
1500	25.6	1	1.5KE30A	1.5KE30CA	28.5	1	41.5	36	200	DO-201
1500	28.2	1	1.5KE33A	1.5KE33CA	31.4	1	45.7	33	200	DO-201
1500	30.8	1	1.5KE36A	1.5KE36CA	34.2	1	49.9	30	200	DO-201
1500	33.3	1	1.5KE39A	1.5KE39CA	37.1	1	53.9	28	200	DO-201
1500	40.2	1	1.5KE47A	1.5KE47CA	44.7	1	64.3	23.2	200	DO-201
1500	47.8	1	1.5KE56A	1.5KE56CA	53.2	1	77	19.5	200	DO-201
1500	53	1	1.5KE62A	1.5KE62CA	58.9	1	85	17.7	200	DO-201
1500	58.1	1	1.5KE68A	1.5KE68CA	64.6	1	92	16.3	200	DO-201
1500	70.1	1	1.5KE82A	1.5KE82CA	77.9	1	113	13.3	200	DO-201
1500	85.5	1	1.5KE100A	1.5KE100CA	95	1	137	11	200	DO-201
1500	154	1	1.5KE180A	1.5KE180CA	171	1	246	6.1	200	DO-201
1500	171	1	1.5KE200A	1.5KE200CA	190	1	274	5.5	200	DO-201
1500	188	1	1.5KE220A	1.5KE220CA	209	1	328	4.6	200	DO-201
1500	213	1	1.5KE250A	1.5KE250CA	237	1	344	5	200	DO-201
1500	256	1	1.5KE300A	1.5KE300CA	285	1	414	5	200	DO-201
1500	299	1	1.5KE350A	1.5KE350CA	332	1	482	4	200	DO-201
1500	342	1	1.5KE400A	1.5KE400CA	380	1	548	4	200	DO-201
1500	376	1	1.5KE440A	1.5KE440CA	418	1	603	3.5	200	DO-201

Transient voltage suppressors: 1500W Transils – SMC

Power* [W]	V _{RM} [V]	I _{RM} max @ V _{RM} [mA]	Part number		V _{BR} min @ I _R		V _{CL} max @ I _{PP}		I _{FSM} [A]	Package
			Unidirect.	Bidirect.	[V]	[mA]	[V]	[A]		
1500	5	300	SM5908	–	6	1	7.6	30	200	SMC
1500	5.8	1000	SM15T6V8A	SM15T6V8CA	6.45	10	10.5	143	200	SMC
1500	6.4	500	SM15T7V5A	SM15T7V5CA	7.13	10	11.3	132	200	SMC
1500	8.55	10	SM15T10A	SM15T10CA	9.5	1	14.5	103	200	SMC
1500	10.2	5	SM15T12A	SM15T12CA	11.4	1	16.7	90	200	SMC
1500	12.8	5	SM15T15A	SM15T15CA	14.3	1	21.2	71	200	SMC
1500	15.3	5	SM15T18A	SM15T18CA	17.1	1	25.2	59.5	200	SMC
1500	18.8	5	SM15T22A	SM15T22CA	20.9	1	30.6	49	200	SMC
1500	20.5	5	SM15T24A	SM15T24CA	22.8	1	33.2	45	200	SMC
1500	23.1	5	SM15T27A	SM15T27CA	25.7	1	37.5	40	200	SMC
1500	25.6	5	SM15T30A	SM15T30CA	28.5	1	41.5	36	200	SMC
1500	28.2	5	SM15T33A	SM15T33CA	31.4	1	45.7	33	200	SMC
1500	30.8	5	SM15T36A	SM15T36CA	34.2	1	49.9	30	200	SMC
1500	33.3	5	SM15T39A	SM15T39CA	37.1	1	53.9	28	200	SMC
1500	58.1	5	SM15T68A	SM15T68CA	64.6	1	92	16.3	200	SMC
1500	85.5	5	SM15T100A	SM15T100CA	95	1	137	11	200	SMC
1500	128	5	SM15T150A	SM15T150CA	143	1	207	7.2	200	SMC
1500	171	5	SM15T200A	SM15T200CA	190	1	274	5.5	200	SMC
1500	188	5	SM15T220A	SM15T220CA	209	1	328	4.6	200	SMC

*10/1000ms waveform

Transient voltage suppressors: 1500W Transils – SMC

Power* [W]	V_{RM} [V]	$I_{FSM} \max$ @ V_{RM} [mA]	Part number		$V_{BR} \min$ @ I_R		$V_{CL} \max$ @ I_{PP}		I_{FSM} [A]	Package
			Unidirect.	Bidirect.	[V]	[mA]	[V]	[A]		
1500	5	800	SMCJ5.0A-TR	SMCJ5.0CA-TR	6.4	10	9.2	171	200	SMC
1500	6	800	SMCJ6.0A-TR	SMCJ6.0CA-TR	6.7	10	10.3	152	200	SMC
1500	6.5	500	SMCJ6.5A-TR	SMCJ6.5CA-TR	7.2	10	11.2	140	200	SMC
1500	10	5	SMCJ10A-TR	SMCJ10CA-TR	11.1	1	17	92	200	SMC
1500	12	5	SMCJ12A-TR	SMCJ12CA-TR	13.3	1	19.9	79	200	SMC
1500	13	1	SMCJ13A-TR	SMCJ13CA-TR	14.4	1	21.5	73	200	SMC
1500	15	1	SMCJ15A-TR	SMCJ15CA-TR	16.7	1	24.4	64	200	SMC
1500	18	1	SMCJ18A-TR	SMCJ18CA-TR	20	1	29.2	53	200	SMC
1500	22	1	SMCJ22A-TR	SMCJ22CA-TR	24.4	1	35.5	44	200	SMC
1500	24	1	SMCJ24A-TR	SMCJ24CA-TR	26.7	1	38.9	40	200	SMC
1500	26	1	SMCJ26A-TR	SMCJ26CA-TR	28.9	1	42.1	37	200	SMC
1500	28	1	SMCJ28A-TR	SMCJ28CA-TR	31.1	1	45.4	34	200	SMC
1500	30	1	SMCJ30A-TR	SMCJ30CA-TR	33.3	1	48.4	32	200	SMC
1500	33	1	SMCJ33A-TR	SMCJ33CA-TR	36.7	1	53.3	29	200	SMC
1500	40	1	SMCJ40A-TR	SMCJ40CA-TR	44.4	1	64.5	24	200	SMC
1500	48	1	SMCJ48A-TR	SMCJ48CA-TR	53.3	1	77.4	20	200	SMC
1500	58	1	SMCJ58A-TR	SMCJ58CA-TR	64.4	1	93.6	16	200	SMC
1500	70	1	SMCJ70A-TR	SMCJ70CA-TR	77.8	1	113	13.9	200	SMC
1500	85	1	SMCJ85A-TR	SMCJ85CA-TR	94.4	1	137	11.5	200	SMC
1500	130	1	SMCJ130A-TR	SMCJ130CA-TR	144	1	209	7.5	200	SMC
1500	170	1	SMCJ170A-TR	SMCJ170CA-TR	189	1	275	5.7	200	SMC
1500	188	1	SMCJ188A-TR	SMCJ188CA-TR	209	1	328	4.6	200	SMC

Transient voltage suppressors: 5000W Transils – Axial

Power* [W]	V_{RM} [V]	$I_{FSM} \max$ @ V_{RM} [mA]	Part number		$V_{BR} \min$ @ I_R		$V_{CL} \max$ @ I_{PP}		I_{FSM} [A]	Package
			Unidirect.	Bidirect.	[V]	[mA]	[V]	[A]		
5000	10	5	BZW50-10	BZW50-10B	11.1	1	18.8	266	500	R6
5000	15	5	BZW50-15	BZW50-15B	16.6	1	26.9	186	500	R6
5000	22	5	BZW50-22	BZW50-22B	24.4	1	39.4	127	500	R6
5000	27	5	BZW50-27	BZW50-27B	30	1	48.3	103	500	R6
5000	33	5	BZW50-33	BZW50-33B	36.6	1	59	85	500	R6
5000	39	5	BZW50-39	BZW50-39B	43.3	1	69.4	72	500	R6
5000	56	5	BZW50-56	BZW50-56B	62.2	1	99.6	50	500	R6
5000	68	5	BZW50-68	BZW50-68B	75.6	1	121	41	500	R6
5000	82	5	BZW50-82	BZW50-82B	91	1	145	34	500	R6
5000	100	5	BZW50-100	BZW50-100B	111	1	179	28	500	R6
5000	150	5	BZW50-150	BZW50-150B	166	1	269	19	500	R6
5000	180	5	BZW50-180	BZW50-180B	200	1	322	16	500	R6

Transient voltage suppressors for automotive Transils – Axial

Part number	V_{RM} [V]	$I_{RM} \max$ $T_c = 25^\circ C$ [mA]	$I_{RM} \max$ $T_c = 85^\circ C$ [mA]	$V_{BR} \min$ $T_c = 25^\circ C$ [V]	$V_{BR} \max$ $T_c = 25^\circ C$ [V]	I_R $T_c = 25^\circ C$ [mA]	$V_{CL} \max$ $T_c = 25^\circ C$ [V]	I_{PP} $T_c = 25^\circ C$ [A]	C typ [nF]	Package
LDP24A	24	50	300	25	32	1	38	30	8	R6

*10/1000ms waveform

Surge suppressors for telecom intrabuilding and terminals: Trisils – SMA

I _{pp} max* [A]	V _{RM} [V]	I _{RM} max @ V _{RM} [μA]	Part number	V _R @ I _R		V _{BO} max @ I _{BO}		I _r min [mA]	C typ @ V _r = 2V [pF]	Package
				[V]	[μA]	[V]	[mA]			
30	56	2	SMP30-62	62	5	82	800	150	40	SMA
30	61	2	SMP30-68	68	5	90	800	150	40	SMA
30	90	2	SMP30-100	100	5	133	800	150	35	SMA
30	108	2	SMP30-120	120	5	160	800	150	30	SMA
30	117	2	SMP30-130	130	5	173	800	150	30	SMA
30	162	2	SMP30-180	180	5	240	800	150	25	SMA
30	180	2	SMP30-200	200	5	267	800	150	25	SMA
30	198	2	SMP30-220	220	5	293	800	150	20	SMA
30	216	2	SMP30-240	240	5	320	800	150	20	SMA
30	243	2	SMP30-270	270	5	360	800	150	20	SMA

Surge suppressors for telecom terminals: Trisils – SMA

I _{pp} max* [A]	V _{RM} [V]	I _{RM} max @ V _{RM} [μA]	Part number	V _R @ I _R		V _{BO} max @ I _{BO}		I _r min [mA]	C typ @ V _r = 2V [pF]	Package
				[V]	[μA]	[V]	[mA]			
50	56	2	SMP50-62	62	5	82	800	150	40	SMA
50	61	2	SMP50-68	68	5	90	800	150	40	SMA
50	90	2	SMP50-100	100	5	133	800	150	35	SMA
50	108	2	SMP50-120	120	5	160	800	150	30	SMA
50	117	2	SMP50-130	130	5	173	800	150	30	SMA
50	162	2	SMP50-180	180	5	240	800	150	25	SMA
50	180	2	SMP50-200	200	5	267	800	150	25	SMA
50	198	2	SMP50-220	220	5	293	800	150	25	SMA
50	216	2	SMP50-240	240	5	320	800	150	25	SMA
50	243	2	SMP50-270	270	5	360	800	150	25	SMA

Surge suppressors for telecom terminals: Trisils – SMB

I _{pp} max* [A]	V _{RM} [V]	I _{RM} max @ V _{RM} [μA]	Part number	V _R @ I _R		V _{BO} max @ I _{BO}		I _r min [mA]	C typ @ V _r = 2V [pF]	Package
				[V]	[μA]	[V]	[mA]			
50	56	2	SMTPA62	62	5	82	800	150	40	SMB
50	61	2	SMTPA68	68	5	90	800	150	40	SMB
50	90	2	SMTPA100	100	5	133	800	150	35	SMB
50	108	2	SMTPA120	120	5	160	800	150	30	SMB
50	117	2	SMTPA130	130	5	173	800	150	30	SMB
50	162	2	SMTPA180	180	5	240	800	150	25	SMB
50	180	2	SMTPA200	200	5	267	800	150	25	SMB
50	198	2	SMTPA220	220	5	293	800	150	25	SMB
50	216	2	SMTPA240	240	5	320	800	150	25	SMB
50	243	2	SMTPA270	270	5	360	800	150	25	SMB

Surge suppressors for telecom terminals: Trisils – Axial

I _{pp} max* [A]	V _{RM} [V]	I _{RM} max @ V _{RM} [μA]	Part number	V _R @ I _R		V _{BO} max @ I _{BO}		I _r min [mA]	C typ @ V _r = 2V [pF]	Package
				[V]	[μA]	[V]	[mA]			
50	56	2	TPA62	62	5	82	800	150	40	DO-15
50	90	2	TPA100	100	5	133	800	150	40	DO-15
50	108	2	TPA120	120	5	160	800	150	35	DO-15
50	117	2	TPA130	130	5	173	800	150	30	DO-15
50	162	2	TPA180	180	5	240	800	150	30	DO-15
50	180	2	TPA200	200	5	267	800	150	25	DO-15
50	198	2	TPA220	220	5	293	800	150	25	DO-15
50	216	2	TPA240	240	5	320	800	150	25	DO-15
50	243	2	TPA270	270	5	360	800	150	25	DO-15

*10/1000μs waveform

Surge suppressors for telecom equipment: Trisils – SMB

I _{pp} max* [A]	V _{RM} [V]	I _{RM} max @ V _{RM} [μA]	Part number	V _R @ I _R		V _{Bo} max @ I _{Bo}		I _h min [mA]	C typ @ V _R = 2V [pF]	Package
				[V]	[μA]	[V]	[mA]			
75	6	2	SMP75-8	8	5	15	800	50 (typ)	75	SMB
80	126	2	SMP80MC-140	140	5	190	800	150	27	SMB
80	144	2	SMP80MC-160	160	5	220	800	150	26	SMB
80	180	2	SMP80MC-200	200	5	275	800	150	26	SMB
80	207	2	SMP80MC-230	230	5	320	800	150	26	SMB
80	243	2	SMP80MC-270	270	5	370	800	150	26	SMB
100	126	2	SMP100MC-140	140	5	180	800	150	60	SMB
100	144	2	SMP100MC-160	160	5	205	800	150	50	SMB
100	180	2	SMP100MC-200	200	5	255	800	150	45	SMB
100	207	2	SMP100MC-230	230	5	295	800	150	40	SMB
100	243	2	SMP100MC-270	270	5	345	800	150	40	SMB
100	6	2	SMP100LC-8	8	5	25	800	50 (typ)	75	SMB
100	22	2	SMP100LC-25	25	5	40	800	150	65	SMB
100	32	2	SMP100LC-35	35	5	55	800	150	55	SMB
100	55	2	SMP100LC-65	65	5	85	800	150	90	SMB
100	81	2	SMP100LC-90	90	5	125	800	150	80	SMB
100	108	2	SMP100LC-120	120	5	160	800	150	75	SMB
100	126	2	SMP100LC-140	140	5	190	800	150	65	SMB
100	144	2	SMP100LC-160	160	5	205	800	150	65	SMB
100	180	2	SMP100LC-200	200	5	255	800	150	60	SMB
100	207	2	SMP100LC-230	230	5	295	800	150	60	SMB
100	243	2	SMP100LC-270	270	5	345	800	150	60	SMB
100	290	2	SMP100LC-320	320	5	400	800	150	50	SMB
100	325	2	SMP100LC-360	360	5	460	800	150	50	SMB
100	360	2	SMP100LC-400	400	5	540	800	150	45	SMB

Data Protection

Data protection: ESD unidirectional diodes array

Number of lines	V _{RM} [V]	I _{RM} max @ V _{RM} [μA]	Part number	V _{BR} min @ I _R		R _D typ [mΩ]	C typ @ 0Vbias [pF]	Package
				[V]	[mA]			
2	12	5	ESDA14V2L	14.2	1	650	90	SOT-23
2	24	1	ESDA25W	25	1	1100	65	SOT323-3L
2	3	1	ESDA6V1DCB	6.1	1	500	155	QFN
2	3	0.5	ESDALC6V1P3	6.1	1	1000	12	SOT-663
2	3	0.1	ESDA14V2DCB	14.2	1	800	80	QFN
2	3	2	ESDA5V3L	5.3	1	280	220	SOT-23
2	5.25	20	ESDA6V1L	6.1	1	350	140	SOT-23
4	12	5	ESDA14V2SC5	14.2	1	650	100	SOT23-5L
4	14	0.075	ESDA17SC6	17	1	700	85	SOT23-6L
4	15	0.1	ESDA19SC6	19	1	800	80	SOT23-6L
4	24	1	ESDA25SC6	25	1	1000	60	SOT23-6L
4	24	1	ESDA25W5	25	1	1900	30	SOT323-3L
4	3	2	ESDA5V3SC5	5.3	1	230	280	SOT23-5L
4	3	2	ESDA5V3SC6	5.3	1	230	280	SOT23-6L
4	5	10	ESDA6V1-4F1	6.1	1	350	250 (max)	Flip-Chip
4	3	0.5	ESDA6V1P6	6.1	1	1500	70	SOT-666
4	5.25	20	ESDA6V1SC5	6.1	1	350	190	SOT23-5L
4	5.25	20	ESDA6V1SC6	6.1	1	350	190	SOT23-6L
4	3	1	ESDA6V1W5	6.1	1	350	90	SOT323-5L
4	3	0.5	ESDALC6V1P6	6.1	1	1500	12	SOT-666
4	3	1	ESDALC6V1W5	6.1	1	1100	12	SOT323-5L
4	3	0.5	ESDALC6V1P5	6.1	1	1500	12	SOT665-5L
4	3	0.5	ESDALC6V1F1	6.1	1	1000	12	Flip-Chip
5	3	0.5	ESDA6V1-5P6	6.1	1	1500	70	SOT-666

*10/1000μs waveform

Data protection: ESD unidirectional diodes array

Number of lines	V_{RM} [V]	I_{RM} max @ V_{RM} [μ A]	Part number	V_{BR} min @ I_R		R_o typ [m Ω]	C typ @ 0Vbias [pF]	Package
				[V]	[mA]			
5	14	0.075	ESDA17-5SC6	17	1	1000	35	SOT23-6L
5	15	0.1	ESDA19-5SC6	19	1	1000	35	SOT23-6L
5	3	1	ESDA6V1-5W6	6.1	1	610	50	SOT323-6L
5	3	0.5	ESDA6V1-5P6	6.1	1	1500	70	SOT666-6L
6	5	2	ESDA6V1U1	6.1	1	500	100	SO-8
18	5	2	ESDA6V1S3	6.1	1	500	120	SO-20

Data protection: ESD biidirectional diodes array

Number of lines	V_{RM} [V]	I_{RM} max @ V_{RM} [μ A]	Part number	V_{BR} min @ I_R		R_o typ [m Ω]	C typ @ 0Vbias [pF]	Package
				[V]	[mA]			
4	12	1	ESDA14V2-4BF1	14.2	1	3200	15 (max)	Flip-Chip
4	12	1	ESDA14V2-BP6	14.2	1	1500	20	SOT-666
4	3	1	ESDA6V1-4BF1	6.1	1	1100	35	Flip-Chip
4	3	1	ESDA6V1-4BC6	6.1	1	450	45	SOT23-6L
4	5	1	ESDA6V1BC6	6.1	1	1350	20	SOT23-6L
6	24	2	ESDA25B1	25	1	1500	15	SO-8
2	12	1	ESDALC14V2-2PB5	14.2	1	tbd	tbd	SOT-665
2	24	1	ESDALC25-2PB5	25	1	tbd	tbd	SOT-665

Data protection: USB port protection

Array Function	Part number	V_{RM} [V]	I_{RM} max @ V_{RM} [μ A]	V_{BR} min @ I_R		C typ [pF]	Package
				[V]	[mA]		
USB 1.1 Port protection	USB6B1	5.25	10	6	1	15	SO-8
USB 2.0 Port protection	USBLC6-4SC6	5	2	6	1	3	SOT23-6L
USB 2.0 Port protection	USBLC6-2SC6	5	1	6	1	2.5	SOT23-6L
USB 2.0 Port protection	USBLC6-2P6	5	1	6	1	2.5	SOT-666

Rail-to-rail protection for xDSL, modem and ethernet

Array Function	Part number	V_{RRM} [V]	I_R max @ 15V [μ A]	C max @ 5V [pF]	V_f max @ 50mA [V]	IEC61000-4-2 Std level	HBM Mil Std 883E class	Package
Rail-to-Rail 4-line	DA108S1RL	18	2	35	1.2	4	3	SO-8
Rail-to-Rail 6-line	DA112S1RL	18	2	35	1.2	4	3	SO-8
R-to-R. 6-line Low Capa.	DALC112S1	18	2	7	1.3	3	3	SO-8
R-to-R. 6-line Low Capa.	DALC112S1RL	18	2	7	1.3	3	3	SO-8
R-to-R. 4-line Low Capa.	DALC208SC6	9	1	7	1.2	4	3	SOT23 - 6L

Protection ICs

Fixed voltage protection for telecom relay

I_{pp} max* [A]	V_{RM} [V]	I_{RM} max @ V_{RM} [μ A]	Part number	V_R min @ I_R		V_{BO} max @ I_{BO}		I_H min [mA]	Package
				[V]	[μ A]	[V]	[mA]		
30	135	5	THBT15011D	150	50	210	400	150	SO-8
30	135	5	THBT16011D	160	50	230	400	150	SO-8
30	180	5	THBT20011D	200	50	290	400	150	SO-8
30	240	5	THBT27011D	270	50	380	400	150	SO-8
100	120	5	TLP140G	140	50	200	500	150	D ² PAK
100	120	5	TLP140G-1	140	50	200	500	150	I ² PAK
100	180	5	TLP200G	200	50	290	500	150	D ² PAK
100	180	5	TLP200G-1	200	50	290	500	150	I ² PAK
100	230	5	TLP270G	270	50	400	500	150	D ² PAK
100	230	5	TLP270G-1	270	50	400	500	150	I ² PAK

*10/1000ms waveform

Continued on back cover

Fixed voltage protection for telecom solid state relay

$I_{PP} \text{ max}^*$ [A]	Part number	$V_R \text{ min} @ I_R$		$V_{BO} \text{ max} (50\text{Hz})$	$I_H \text{ min}$ [mA]	Package
		[V]	[μA]	[V]		
2 x 35	SSRP105B1	+ 105 / -180	10	+ 165 / - 225	150 (neg polarity) / 100 (pos polarity)	SO-8
2 x 15	SSRP130B1	+ 130 / - 185	10	+ 200 / - 280	150	SO-8

Fixed voltage protection for SLIC

$I_{PP} \text{ max}^*$ [A]	V_{RM} [V]	$I_{RM} \text{ max} @ V_{RM}$ [μA]	Part number	$V_R \text{ min} @ I_R$		$V_{BO} \text{ max}$ [V]	$I_H \text{ min}$ [mA]	Package
				[V]	[mA]			
40	63	100	THDT6511D	65	1	85	150	SO-8

Protection ICs programmable voltage SLIC protection

$I_{PP} \text{ max}^*$ [A]	Part number	V_{RM} [V]	$I_{RM} \text{ max}$ $@ V_{RM}$ [μA]	Max oper. voltage [V]	$V_{DEL} \text{ max} (10/700\text{ms})$ [V]	$I_H \text{ min}$ [mA]	Package
2 x 15	LCDP1521	150	5	150	5	150	SO-8
30	LCP02-150B1	-105 / 90	5	-110 to +95	8	150	SO-8 Wide
100	LCP02-150M	-105 / 90	5	-110 to +95	6 (+ suppressor) / 8 (- suppressor)	150	PowerSO-10
30	LCP1521S	150	5	150	7	150	SO-8
30	LCP152DEE	150	5	150	7	150	QFN 3x3
100	LCP3121	60	5	80	-	100	SO-8

Protection ICs programmable current and voltage line card protection

$I_{PP} \text{ max}^*$ [A]	V_{LG} [V]	$I_{LGL} \text{ max} @ V_{GL}$ [μA]	Part number	$V_{ret} \text{ min} @ I_{LGL}$		$V_{SWON} \text{ max} @ I_{SWOFF} \text{ min}$		Package
				[V]	[mA]	[V]	[mA]	
100	175	10	CLP190D5	190	1	260	150	PPAK
30	200	10	CLP30-200B1	-	-	290	150	SO-8
100	200	10	CLP200M	215	1	290	150	PowerSO-10
100	240	10	CLP270M	270	1	380	150	PowerSO-10

ISDN and U interface protection

$I_{PP} \text{ max}^*$ [A]	V_{RM} [V]	$I_{RM} \text{ max} @ V_{RM}$ [μA]	Part number	$V_{BR} \text{ min} @ I_R$		$V_{BO} \text{ max} @ I_{BO}$		$I_H \text{ min}$ [mA]	Package
				[V]	[mA]	[V]	[mA]		
30	70	10	TPI8011N	80	1	120	800	150	SO-8
30	105	10	TPI12011N	120	1	180	800	150	SO-8

T1/E1 interface protection

$I_{PP} \text{ max}^*$ [A]	V_{RM} [V]	$I_{RM} \text{ max} @ V_{RM}$ [μA]	Part number	$V_{BO} \text{ max} @ I_{BO}$		$I_H \text{ min}$ [mA]	Package
				[V]	[mA]		
30	28	4	TPN3021	38	300	30	SO-8

Bridge and protection all-in-one for telecom terminals

$I_{PP} \text{ max}^*$ [A]	V_{RM} [V]	$I_{RM} \text{ max} @ V_{RM}$ [μA]	Part number	$V_{BO} \text{ max} @ I_{BO}$		$I_H \text{ min}$ [mA]	Package
				[V]	[mA]		
30	200	5	TSI200B1	290	400	150	SO-8
30	220	5	TSI220B1	330	400	150	SO-8

Overvoltage and overcurrent protection for telecom line

$I_{PP} \text{ max}^*$ [A]	V_{RM} [V]	$I_{RM} \text{ max} @ V_{RM}$ [μA]	Part number	$V_{BO} \text{ max} @ I_{BO}$		$I_H \text{ min}$ [mA]	Package
				[V]	[mA]		
30	60	6	TPP25011	340	200	180	SO-8

*10/ 000 μs waveform



© STMicroelectronics - July 2005 - Printed in Italy - All rights reserved

The STMicroelectronics corporate logo is a registered trademark of the STMicroelectronics group of companies. TRANSIL, TRISIL and IPAD are STMicroelectronics trademarks. All other names are the property of their respective owners.

For selected STMicroelectronics sales offices fax:

France +33 1 55489569; Germany +49 89 4605454; Italy +39 02 8250449; Japan +81 3 57838216; Singapore +65 6481 5124;
Sweden +46 8 58774411; Switzerland +41 22 9292900; United Kingdom and Eire +44 1628 890391; USA +1 781 861 2678

Full product information at www.st.com