

Leaded Devices	SMD-Packages										
	SOD-123	SOD-323	SCD-80	SOT-23	SOT143	SOT-323	SOT-343	SOT-363	SCT-595	SOT-89	SOT-223
1N4001										BAW78A	BAS78A
1N4002										BAW78B	BAS78B
1N4003										BAW78C	BAS78C
1N4004									BAW 78 M	BAW78D	BAS78D
1N4001 (2x)										BAW79A	BAS79A
1N4002 (2x)										BAW79B	BAS79B
1N4003 (2x)										BAW79C	BAS79C
1N4004 (2x)										BAW79D	BAS79D
1N4148		BAS 16-02W	BAS 16-03W	BAS16 BAL/BAR74 BAL/BAR99		BAS16W				BAS16S	
1N4148 (2x)				BAV70 BAV74 BAV99 BAW56	BAS28 BAW100	BAV70W BAV74W BAV99W BAW56W	BAS28W			BAV70S BAV99S BAW56S	
1N4148 (4x)					BGX50A (Bridge)						
1N914				SMBD914							
2N2222				SMBT2222						SXT2222	PZT2222
2N2222A				SMBT2222A						SXT2222A	PZT2222A
2N2484				BC846B		BC846BW				BC 846 S / PN	
2N2857				BFS17P							
2N2907				SMBT2907						SXT2907	PZT2907
2N2907A				SMBT2907A						SXT2907A	PZT2907A
2N3019										BCX56-16	BCP56-16
2N3053				BSS79						BCX55	BCP55
2N3440				BFN26						BFN18	BFN38
2N3563				BSS79B							
2N3904				SMBT3904						SMBT3904 S / PN	SXT3904 PZT3904
2N3906				SMBT3906						SMBT3906 S	SXT3906 PZT3906
2N4032				BC856		BC856W				BC856S	BCP52M BCX52 BCP52
2N4036										BCP53M	BCX53 BCP53
2N4037										BCP51M	BCX51 BCP51
2N4123				BSS81B							
2N4124				SMBT4124							
2N4125				BSS80B							

Leaded Devices	SMD-Packages										
	SOD-123	SOD-323	SCD-80	SOT-23	SOT143	SOT-323	SOT-343	SOT-363	SCT-595	SOT-89	SOT-223
2N4126				SMBT4126							
2N5086				SMBT5086							
2N5087				SMBT5087							
2N5415				BFN25						BFN17	BFN37
2N5551				BCX41							
2N6426				BCV27						BCV29	BCP29
2N6427				SMBT6427						BCV49	BCP49
2N6428				SMBT6428							
2N6429				SMBT6429							
2N6515				BFN24						BFN16	BFN36
2N6516				BFN26						BFN18	BFN38
2N6518				BFN25						BFN17	BFN37
2N6519				BFN27						BFN19	BFN39
2N6718				BCX41							
2N6724										BCV29	BCP29
2N6725										BCV29	BCP29
BA282	BA582	BA592	BA892	BAT18 BAT18-04 BAT18-05 BAT18-06							
BA389	BA585	BA595		BA885							
BAR12-1											
		BAR65-03W	BAR65-02W								
		BAR63-03W	BAR63-02W	BAR63 BAR63-04 BAR63-05 BAR63-06		BAR63-04W BAR63-05W BAT63-06W					
		BAR64-03W	BAR64-02W	BAR64 BAR64-04 BAR64-05 BAR64-06	BAR64-07	BAR64-04W BAR64-05W BAR64-06W					
BAS40-02		BAS140W									
BAS40-02 (2x)				BAS40-04 BAS40-05 BAS40-06	BAS40-07	BAS40-04W BAS40-05W BAS40-06W	BAS40-07W				

Leaded Devices	SMD-Packages										
	SOD-123	SOD-323	SCD-80	SOT-23	SOT143	SOT-323	SOT-343	SOT-363	SCT-595	SOT-89	SOT-223
BAS45				BAS116							
BAS45 (2x)				BAV170 BAV199 BAW156							
BAS70-02		BAS170W									
BAS70-02 (2x)				BAS70-04 BAS70-05 BAS70-06	BAS70-07	BAS70-04W BAS70-05W BAS70-06W	BAS70-07W		BAS70-04S BAS70-06S		
		BAS125W		BAS125 BAS125-04 BAS125-05 BAS125-06	BAS125-07	BAS125-04W BAS125-05W BAS125-06W	BAS125-07W				
	BAT14-098	BAT14-03W									
	BAT15-098	BAT15-03W									
		BAT17W		BAT17 BAT17-04 BAT17-05 BAT17-06		BAT17-04W BAT17-05W BAT17-06W					
BAT16-046		BAT62-03W	BAT62-02W	BAT62				BAT62-07W			
		BAT63-03W		BAT63	BAT63-099R						
BAT85		BAT64-03W	BAT64-02W	BAT64 BAT64-04 BAT64-05 BAT64-06	BAT64-07	BAT64-04W BAT64-05W BAT64-06W		BAT64-07W			
	BAT65	BAT165									
		BAT68-03W		BAT68 BAT68-04 BAT68-05 BAT68-06	BAT68-07	BAT68W BAT68-04W BAT68-05W BAT68-06W	BAT68-07W				
BAV19				BAS19							
BAV20				BAS20							
BAV21				BAS21							
BAV23					BAW101						
BB112	BB512										
BB304				BB804							
BB409	BB419	BB439									
BB505	BB515	BB535	BB555								
BB609	BB619C	BB639C	BB659C								

Leaded Devices	SMD-Packages										
	SOD-123	SOD-323	SCD-80	SOT-23	SOT143	SOT-323	SOT-343	SOT-363	SCT-595	SOT-89	SOT-223
	BB419	BB439									
	BB620	BB640									
	BB512										
		BB545	BB565								
		BBY51-03W	BBY51-02W	BBY51							
		BBY52-03W	BBY52-02W	BBY52							
		BBY53-03W	BBY53-02W	BBY53							
		BB669	BB689								
		BB837	BB857								
		BBY56-03W	BBY56-02W								
		BB644	BB664								
		BBY55-03W	BBY55-02W								
		BBY57-03W	BBY57-02W								
		BBY58-03W	BBY58-02W								
BC182				SMBT6428/ 29							
BC212				SMBT5086/ 87							
BC327				BC807		BC807W					
BC328				BC808		BC808W					
BC337				BC817		BC817W					
BC338				BC818		BC818W					
BC368									BCX68	BCP68	
BC369									BCX69	BCP69	
BC516				BCV26					BCV28	BCP28	
				BCV46					BCV48	BCP48	
				SMBTA63/64						PZTA63/64	
BC517				BCV27					BCV29	BCP29	
				SMBT6427						PZTA14	
BC546				BC846		BC846W		BC846S / PN			
BC547				BC847		BC847W		BC847S			
BC548				BC848		BC848W					
BC549				BC849		BC849W					
BC550				BC850		BC850W					
BC556				BC856		BC856W		BC856S			
BC557				BC857		BC857W		BC857S / PN			
BC558				BC858		BC858W					

Leaded Devices	SMD-Packages										
	SOD-123	SOD-323	SCD-80	SOT-23	SOT143	SOT-323	SOT-343	SOT-363	SCT-595	SOT-89	SOT-223
BC559				BC859		BC859W					
BC560				BC860		BC860W					
BC617				BCV47						BCV29	BCP49 PZTA13
				SMBTA13							
BC618				BCV47						BCV49	BCP49
BC635									BCP54M	BCX54	BCP54
BC636									BCP51M	BCX51	BCP51
BC637									BCP55M	BCX55	BCP55
BC638									BCP52M	BCX52	BCP52
BC639									BCP56M	BCX56	BCP56
BC640									BCP53M	BCX53	BCP53
BC875											BSP50
BC876											BSP60
BC877											BSP51
BC878											BSP61
BC879											BSP52
BC880											BSP62
BCX12				BCX41							
BCX13				BCX42							
BCX22				BCX41							
BCX23				BCX42							
BCX58				BCW60							
BCX59				BCX70							
BCX73				BCW65							
BCX74				BCW66							
BCX75				BCW67							
BCX76				BCW68							
BCX78				BCW61							
BCX79				BCX71							
BCY56				BC850		BC850W					
BCY57				BC849		BC849W					
BD135									BCP54M	BCX54	BCP54
BD136									BCP51M	BCX51	BCP51
BD137									BCP55M	BCX55	BCP55
BD138									BCP52M	BCX52	BCP52
BD139									BCP56M	BCX56	BCP56
BD140									BCP53M	BCX53	BCP53

Leaded Devices	SMD-Packages										
	SOD-123	SOD-323	SCD-80	SOT-23	SOT143	SOT-323	SOT-343	SOT-363	SCT-595	SOT-89	SOT-223
BF240				BF840							
BF241				BF841							
BF414											
BF420										BFN20	BF720
BF421										BFN21	BF721
BF422				BFN22						BF622	BF722
BF423				BFN23						BF623	BF723
BF506				BF660							
BF544				BF543							
BF763				BF517							
BF959				BF799							
BF961					BF995						
BF963					BF993						
BF964S					BF994S						
BF966S					BF996S						
BF970				BF569							
BF979S				BF579							
BF987				BF999							
BF988					BF998						
BFP22				BFN24						BFN16	BFN36
BFP23				BFN25						BFN17	BFN37
BFP25				BFN26						BFN18	BFN38
BFP26				BFN27						BFN19	BFN39
BFQ23				BFT93							
BFQ51				BFT92							
BFQ69				BFQ81	BFP81						
BFR90				BFR35AP BFR92P		BFR92W					
BFR91				BFR93P							
BFR91A				BFR93A	BFP93A	BFR93W					
BFR96S				BFR106	BFG19S	BFR106				BFQ19S	
BFW16A										BFQ17P	
BFW92				BFS17P							
MPF26											
MPS2222				SMBT2222						SXT2222	PZT2222
MPS2222A				SMBT2222A						SXT2222A	PZT2222A
MPS2907				SMBT2907						SXT2907	PZT2907

Leaded Devices	SMD-Packages										
	SOD-123	SOD-323	SCD-80	SOT-23	SOT143	SOT-323	SOT-343	SOT-363	SCT-595	SOT-89	SOT-223
MPS2907A				SMBT2907A						SXT2907A	PZT2907A
MPS3904				SMBT3904				SMBT3904S / PN		SXT3904	PZT3904
MPS3906				SMBT3906				SMBT3906S		SXT3906	PZT3906
MPSA05				SMBTA05							
MPSA06				SMBTA06					SMBTA06M		
MPSA13				SMBTA13							PZTA13
MPSA14				SMBTA14							PZTA14
MPSA20				SMBTA20							
MPSA42				SMBTA42					SMBTA42M	SXTA42	PZTA42
MPSA43				SMBTA43						SXTA43	PZTA43
MPSA55				SMBTA55							
MPSA56				SMBTA56					SMBTA56M		
MPSA63				SMBTA63							PZTA63
MPSA64				SMBTA64							PZTA64
MPSA92				SMBTA92					SMBTA92M	SXTA92	PZTA92
MPSA93				SMBTA93						SXTA93	PZTA93