17. SUGGESTED REPLACEMENT TRANSISTORS

LINE No.	1 TYPE NO. TO BE REPLACED	The Following Type Numbers Are Suggested By The Manufacturer As Their Nearest Replacement To The Type In The Left Column											
		TYPE NO.	MFR.	TYPE NO.	MFR.	TYPE NO.	MFR.	TYPE NO.	MFR.	TYPE NO.	MFR.	TYPE NO.	MFR.
1▼	2N5296	BD949	PHIN	TIP31	TII	2N5296	SODI						
2▼	2N5297	BD951	PHIN	TIP31A	TII	2N5297	SODI						
3▼	2N5298	BD951	PHIN	TIP31A	TII	2N5298	SODI						
4▼	2N5322	2N4036	PHIN	2N5322	SGAI	2N5322	TII						
5▼	2N5323	2N4036	PHIN	2N5323	SGAI	2N5323	TII						
6▼	2N5354	BC328	PHIN										
7▼	2N5356	BC328	PHIN										
8▼	2N5365	BC327	PHIN										
9▼	2N5366	BC327	PHIN										
10▼	2N5367	BC327	PHIN										
11▼	2N5369	2N2222	PHIN	2N5373	MEHK								
12▼	2N5447	BC328	PHIN	2N5449	MEHK								
13▼	2N5448	2N2907	PHIN	2N5450	MEHK								
14▼	2N5449	2N2222	PHIN	2N5447	MEHK								
15▼	2N5451	2N2222	PHIN										
16▼	2N5490	BD203	PHIN	TIP41	TII	2N5490	SODI						
17▼	2N5491	BD203	PHIN	TIP41	TII	2N5491	SODI						
18▼	2N5492	BDX77	PHIN	TIP41A	TII	2N5492	SODI						
19▼	2N5493	BDX77	PHIN	TIP41A	TII	2N5493	SODI						
20▼	2N5494	BD203	PHIN	TIP41	TII	2N5494	SODI						
21▼	2N5495	BD203	PHIN	TIP41	TII	2N5495	SODI						
22▼	2N5496	BDX77	PHIN	TIP41B	TII	2N5496	SODI						
23▼	2N5497	BDX77	PHIN	TIP41B	TII	2N5497	SODI						
24▼	2N5550	BF337	PHIN	BC394	SGAI								
25▼	2N5551	BF337	PHIN	BC394	SGAI								
26▼	2N5589	BLY87A	PHIN										
27▼	2N5590	BLY88A	PHIN										
28▼	2N5591	BLY89A	PHIN										
29▼	2N5635	2N3632	PHIN										
30▼	2N5636	BLV21	PHIN										
31▼	2N5641	BLY91A	PHIN										
32▼	2N5642	BLY92A	PHIN										
33▼	2N5643	BLY93A	PHIN										
34▼	2N5644	BLX67	PHIN										
35▼	2N5645	BLX68	PHIN										
36▼	2N5646	BLX94A	PHIN										
37▼	2N5655	2N6175	RCA	PTC124	MAL	TIP63	TII	2N5655	MOTA	BF338	PHIN		
38▼		BUX86	PHIN										
39▼	2N5656	2N6176	RCA	PTC124	MAL	TIP63	TII	2N5656	MOTA	BUX86	PHIN		
40▼	2N5657	2N6177	RCA	PTC124	MAL	TIP64	TII	2N5657	MOTA	BUX86	PHIN		
41▼	2N5685	2N5578	RCA	2N5685	MOTA								
42▼	2N5686	2N5578	RCA	2N5686	MOTA								
43▼	2N5699	2N5847	MOTA	BLX67	PHIN								
44▼	2N5700	BLX68	PHIN										
45▼	2N5701	BLX69A	PHIN										
46▼	2N5702	BFS22A	PHIN										
47▼	2N5704	BLY88A	PHIN										
48▼	2N5705	BLY89A	PHIN										
49▼	2N5706	BLY89A	PHIN										
50▼	2N5709	BLX15	PHIN										
51▼	2N5776	BLX95	PHIN										
52▼	2N5804	BUX82	PHIN	SVT7533	TRWS	TIP558	TII	SVT7533	TRWS				
53▼	2N5805	BUX82	PHIN	SVT7533	TRWS	TIP559	TII	SVT7533	TRWS				
54▼	2N5838	BUX82	PHIN	SVT7523	TRWS	2N5838	TII	SVT7523	TRWS				
55▼	2N5839	BUX82	PHIN	SVT7523	TRWS	2N5839	TII	SVT7523	TRWS				
56▼	2N5840	BUX82	PHIN	SVT7523	TRWS	2N5840	TII	SVT7523	TRWS				
57▼	2N5846	MRF231	MOTA										
58▼	2N5848	2N5849	MOTA	BLY88A	PHIN								
59▼	2N5849	BLY87A	PHIN										
60▼	2N5862	BLY94	PHIN										
61▼	2N5869	BDX91	PHIN										
62▼	2N5870	BDX93	PHIN										
63▼	2N5915	BLX68	PHIN										
64▼	2N5916	BLX91A	PHIN										
65▼	2N5917	MRF5174	MOTA	BLX91A	PHIN								
66▼	2N5918	MRF321	MOTA	BLX93A	PHIN								
67▼	2N5919A	MRF323	MOTA										
68▼	2N5922	BLV20	PHIN										
69▼	2N5935	2N6032	RCA	2N6341	MOTA								
70▼	2N5936	2N6033	RCA	2N6338	MOTA								
71▼	2N5941	BLX14	PHIN										
72▼	2N5942	BLX15	PHIN										
73▼	2N5974	2N6489	RCA	PTC164	MAL	TIP42A	TII	2N5974	MOTA				
74▼	2N5975	2N6490	RCA	PTC164	MAL	TIP42B	TII	2N5975	MOTA				
75▼	2N5976	2N6491	RCA	PTC164	MAL	TIP42C	TII	2N5976	MOTA				
76▼	2N5977	2N6486	RCA	PTC165	MAL	TIP41A	TII	2N5977	MOTA				
77▼	2N5978	2N6487	RCA	PTC165	MAL	TIP41B	TII	2N5978	MOTA				
78▼	2N5979	2N6488	RCA	PTC165	MAL	TIP41C	TII	2N5979	MOTA				
79▼	2N5980	2N6489	RCA	PTC164	MAL	TIP74A	TII	2N6489	MOTA	MJE2955	MOTA		
80▼	2N5981	2N6490	RCA	PTC164	MAL	TIP74B	TII	MJE2955	MOTA				
81▼	2N5982	2N6491	RCA	PTC164	MAL	TIP74C	TII	2N6491	MOTA	2N5988	MOTA		
82▼	2N5983	2N6486	RCA	PTC165	MAL	TIP73A	TII	MJE3055	MOTA				
83▼	2N5984	2N6487	RCA	PTC165	MAL	TIP73B	TII	MJE3055	MOTA				
84▼	2N5985	2N6488	RCA	PTC165	MAL	TIP73C	TII	2N6488	MOTA	2N5991	MOTA		
85▼	2N5986	2N6489	RCA	TIP74A	TII	2N5986	MOTA						
86▼	2N5987	2N6490	RCA	TIP74B	TII	2N5987	MOTA						
87▼	2N5988	2N6491	RCA	TIP74C	TII	2N5988	MOTA						
88▼	2N5989	2N6486	RCA	TIP73A	TII	2N5989	MOTA						
89▼	2N5990	2N6487	RCA	TIP73B	TII	2N5990	MOTA						
90▼	2N5991	2N6488	RCA	TIP73C	TII	2N5991	MOTA						
91▼	2N5992	BLY93A	PHIN										
92▼	2N5993	BLY88A	PHIN										
93▼	2N5994	BLY94	PHIN										
94▼	2N5995	BLY87A	PHIN										
95▼	2N5996	BLY88A	PHIN										
96▼	2N6034	2N6666	RCA	TIP125	TII	2N6034	MOTA	BD676	PHIN				
97▼	2N6035	RCA125	RCA	TIP125	TII	2N6035	MOTA	BD678	PHIN				
98▼	2N6036	RCA126	RCA	TIP126	TII	2N6036	MOTA	BD680	PHIN				
99▼	2N6037	2N6386	RCA	TIP120	TII	2N6037	MOTA	BD675	PHIN				
100▼	2N6038	RCA120	RCA	TIP120	TII	2N6038	MOTA	BD677	PHIN				
101▼	2N6039	RCA121	RCA	TIP121	TII	2N6039	MOTA	BD679	PHIN				
102▼	2N6040	RCA125	RCA	TIP105	TII	2N6040	MOTA						
103▼	2N6041	RCA126	RCA	TIP106	TII	2N6041	MOTA						
104▼	2N6042	RCA126	RCA	TIP107	TII	2N6042	MOTA						
105▼	2N6043	RCA120	RCA	TIP100	TII	2N6043	MOTA						
106▼	2N6044	RCA121	RCA	TIP101	TII	2N6044	MOTA						
107▼	2N6045	2N6531	RCA	TIP102	TII	2N6045	MOTA						
108▼	2N6050	BDX64	PHIN	2N6050	TII								
109▼	2N6051	BDX64A	PHIN	2N6051	TII								
110▼	2N6052	BDX64B	PHIN										

Datasheet.Live