

2 N 5086	USA,Fer,Mot Phi,Tix,++	Si-P	LF, In, 50/50V, 0,05A, 0,625W, 120MHz, F<3dB(1kHz) hFE=150...500	7e	TO-92	BC 560	7a	BC 214, BC 416, BC 560, 2SA872(A), ++
2 N 5087		Si-P	=2N5086: hFE=250...800, 150MHz, F<2dB(1kHz)	7e	TO-92	BC 560	7a	BC 214, BC 416, BC 560, 2SA872(A), ++
2 N 5088	USA,Mic,Mot Nsc,Phi	Si-N	LF, In, 35/30V, 0,05A, 0,625W, 175MHz, F<3dB(1kHz) hFE=300...900	7e	TO-92	BC 550	7a	BC 169, BC 184, BC 239, BC 549, ++
2 N 5089		Si-N	=2N5088: 30/25V, hFE=400...1200, F<2dB(1kHz)	7e	TO-92	BC 550	7a	BC 169, BC 184, BC 239, BC 549, ++
2 N 5090	Mot,Rca,Sca Sem,Tho,Tix	Si-N	VHF/UHF Drv,Out, 55/30V, 0,4A, PQ>1,2W(400MHz)	49a	TO-60			-
2 N 5091	Sca,Ssi,Stc	Si-P	LF,S, 350/300V, 1A, 4W(Tc=25°), 10MHz	2a	TO-5			MJ 5416, 2N5416
2 N 5092	Sca,Ssi,Stc	Si-N	LF,S, 400/350V, 1A, 4W(Tc=25°), 15MHz	2a	TO-5			BSS 49, BUY 55, BUY 59...60, 2N3439
2 N 5093	Sca,Ssi,Stc	Si-P	LF,S, 400/350V, 1A, 4W(Tc=25°), 10MHz	2a	TO-5			MJ 5416
2 N 5094	Sca,Ssi,Stc	Si-P	LF,S, 450/400V, 1A, 4W(Tc=25°), 10MHz	2a	TO-5			MJ 5416
2 N 5095	Sca,Ssi,Stc	Si-N	LF,S, 500/400V, 1A, 4W(Tc=25°), 15MHz	2a	TO-5			BUY 55, BUY 59...60, 2N3439
2 N 5096	Sca,Ssi,Stc	Si-P	LF,S, 500/450V, 1A, 4W(Tc=25°), 10MHz	2a	TO-5			MJ 5416
2 N 5097	Sca,Ssi,Stc	Si-N	LF,S, 600/450V, 1A, 4W(Tc=25°), 15MHz	2a	TO-5			BUY 60
2 N 5098	Sca,Ssi,Stc	Si-N	LF,S, 700/500V, 1A, 4W(Tc=25°), 15MHz	2a	TO-5			-
2 N 5099	Sca,Ssi,Stc	Si-N	LF,S, 800/550V, 1A, 4W(Tc=25°), 15MHz	2a	TO-5			-
2 N 5100	Sca,Ssi,Stc	Si-P	S, P, 450/400V, 1A, 10W, >20MHz	43m	=TO-37			-
2 N 5101	Sca,Ssi,Stc	Si-N	S, P, 500/400V, 1A, 10W, >50MHz	43m	=TO-37			(BD 410, BUW 63, BUW 93...95, BUW 40A,B)4
2 N 5102	Rca,Sem,Tix	Si-N	VHF P, 100V, 3,3A, PQ=15W(136MHz)	49a	TO-60			BLY 35, 2N3632
2 N 5103	Isi,Nsc,++	N-FET	Uni, 25V, Idss>1mA, Up<4V	5k	TO-72			2N5246, 2N5360, 2SK161
2 N 5104	Isi,Nsc,++	N-FET	Uni, 25V, Idss>2mA, Up<4V	5k	TO-72			2N5246, 2N5360, 2SK107
2 N 5105	Isi,Nsc,++	N-FET	Uni, 25V, Idss>5mA, Up<4V	5k	TO-72			BF 256, BFS 80, BFW 11, 2N5485, ++
2 N 5106		Si-N	S, RadH, 60V, 0,6A, 0,8W, >250MHz	2a				-
2 N 5107		Si-N	=2N5106: 0,36W, RadH	2a				-
2 N 5108(A)		Si-N	UHF Os,Drv, 55V, 0,4A, PQ>1W(1GHz)	2a				-
2 N 5109		Si-N	VHF/UHF A, 40V, 0,4A, >1200MHz	2a				BFS 50, MRF 515, MRF 629, 2N3948, ++
2 N 5110		Si-P	LF,S, 40V, 1A, 0,5W, >1MHz	2a				-
2 N 5111		Si-P	=2N5110: 80V	2a				BC 161, BCX 60, BSS 18, BSV 15...17, ++
2 N 5112		Si-P	=2N5110: 34W	49a				-
2 N 5113		Si-P	=2N5110: 80V, 34W	49a				-
2 N 5114	USA,Nsc,Phi	P-FET	S, 30V, Idss>30mA, Up<10V	2a	TO-18			-
2 N 5115	USA,Nsc,Phi	P-FET	S, 30V, Idss>15mA, Up<6V	2a	TO-18			-
2 N 5116	USA,Nsc,Phi	P-FET	S, 30V, Idss>6mA, Up<4V	2a	TO-18			-
2 N 5117	Isi,Sol	Si-P	Dual, In, 45/45V, 10mA, 0,75W, >100MHz, F<4dB(1k) ΔhFE=0,9...1, ΔUbe<3mV	TO-77	(CBE-EBC-)			BFX 11, 2N3726, 2N40415...16
2 N 5118		Si-P	=2N5117: ΔhFE=0,85...1, ΔUbe=5mV	TO-77	(CBE-EBC-)			BFX 11, 2N3726, 2N40415...16
2 N 5119		Si-P	=2N5117: ΔhFE=0,8...1, ΔUbe<5mV	TO-77	(CBE-EBC-)			BFX 11, 2N3726, 2N40415...16
2 N 5120		Si-P	=2N5117: 0,5W	TO-71	(CBE-EBC-)			(BFX 11, 2N3726, 2N40415...1)6
2 N 5121		Si-P	=2N5118: 0,5W	TO-71	(CBE-EBC-)			(BFX 11, 2N3726, 2N40415...1)6
2 N 5122		Si-P	=2N5119: 0,5W	TO-71	(CBE-EBC-)			(BFX 11, 2N3726, 2N40415...1)6
2 N 5123		Si-P	=2N5117: 0,75W					-
2 N 5124		Si-P	=2N5117: 0,75W					-
2 N 5125		Si-P	=2N5117: 0,75W					-
2 N 5126	Fch,Sem,Tdy	Si-N	Hf,If, agc, 20V, 0,03A, 0,2W, >300MHz	8a	TO-106	BF 255	7d	BF 240...241, BF 254...255, BF 594...595, ++
2 N 5127	USA,Mic,Nsc	Si-N	Hf,If, 20V, 0,1A, 0,2W, >150MHz	8a	TO-106	BF 255	7d	BF 240...241, BF 254...255, BF 594...595, ++
2 N 5128	USA,Mic,Nsc	Si-N	Uni, 15/12V, 0,5A, 0,3W, >200MHz	8a	TO-105			BC 337...338, BC 635, 2N2221...22(A), ++
2 N 5129		Si-N	=2N5128: 0,2W	8a	TO-106			BC 337...338, BC 635, 2N2221...22(A), ++
2 N 5130	USA,Mic,Nsc	Si-N	Hf, 30V, 0,05A, 0,2W, >450MHz	8a	TO-106			BF 314, BF 502, BF 505, BF 507, BF 562, ++
2 N 5131	USA,Nsc	Si-N	Uni, 20/15V, 0,2A, 0,2W, >100MHz	8a	TO-106			BC 168, BC 183, BC 238, BC 548, ++
2 N 5132	USA,Mic,Nsc	Si-N	Hf, 20V, 0,05A, 0,2W, >200MHz	8a	TO-106			BF 240...241, BF 254...255, BF 594...595, ++
2 N 5133	USA,Mic,Nsc	Si-N	S, 20/18V, 0,05A, 0,2W, >40MHz	8a	TO-106			BC 168, BC 183, BC 238, BC 548, ++
2 N 5134	USA,Mic,Nsc	Si-N	S, 20/10V, 0,1A, 0,2W, >250MHz, <26/26ns	8a	TO-106			BSS 11...12, BSV 89...92, 2N2368...69(A), ++
2 N 5135	USA,Mic,Nsc	Si-N	Uni, 30/25V, 0,2A, 0,3W, >40MHz	8a	TO-105			BC 168, BC 183, BC 238, BC 548, ++
2 N 5136	USA,Mic,Nsc	Si-N	Uni, 30/20V, 0,5A, 0,3W, >40MHz	8a	TO-105			BC 337...338, BC 635, BC 637, BC 639, ++
2 N 5137		Si-N	=2N5136: 0,22W	8a	TO-106			BC 337...338, BC 635, BC 637, BC 639, ++
2 N 5138	USA,Mic,Nsc	Si-P	Uni, 50/30V, 0,05A, 0,2W, >30MHz	8a	TO-106			BC 212, BC 257, BC 307, BC 557, ++
2 N 5139	USA,Mic,Nsc	Si-P	S, 20/20V, 0,1A, 0,2W, >300MHz, <65/230ns	8a	TO-106			BSW 24, 2N3209, 2N4034...35, 2N4125...26, ++
2 N 5140	USA,Mic,Nsc	Si-P	S, 5/5V, 0,05A, 0,2W, >400MHz, <35/35ns	8a	TO-106			BSX 36, 2N4258, 2N4313, 2N5056...57
2 N 5141	USA,Mic,Nsc	Si-P	S, 6/6V, 0,1A, 0,2W, >300MHz, <115/170ns	8a	TO-106			BSW 24, 2N3209, 2N4034...35, 2N4125...26, ++
2 N 5142	USA,Mic,Nsc	Si-P	Uni, 20/20V, 0,5A, 0,3W, >100MHz, <120/225ns	8a	TO-105			BC 327...328, BC 636, 2N2906...07(A), ++
2 N 5143		Si-P	=2N5142: 0,2W	8a	TO-106			BC 327...328, BC 636, 2N2906...07(A), ++
2 N 5144	Fch	Si-N	S, RadH, 50/30V, 0,5A, 0,36W, >300MHz, <45/65ns	2a	TO-18			-
2 N 5145	Fch	Si-N	=2N5144: 0,8W, RadH	2a	TO-39			-
2 N 5146	Fch,Mot	Si-P	4x PNP, 40/40V, 1,5A, 0,6W, 250MHz, 22/46ns	14-FLP	TO-86			-
2 N 5147	USA,Nsc,Tix	Si-P	=2N4999: 1W	2a	TO-39			BSS 17, 2N5322
2 N 5148	USA,Nsc,Tix	Si-N	=2N4998: 1W	2a	TO-39			BSS 15, 2N5320
2 N 5149	USA,Nsc,Tix	Si-P	=2N5001: 1W	2a	TO-39			BSS 17, 2N5322
2 N 5150	USA,Nsc,Tix	Si-N	=2N5000: 1W	2a	TO-39			BSS 15, 2N5320
2 N 5151	USA,Sgs,Tix	Si-P	=2N5003: 1W	2a	TO-39			BUY 90, 2N6192...93
2 N 5152	USA,Sgs,Tix	Si-N	=2N5002: 1W	2a	TO-39			BUY 90, 2N6192...93
2 N 5153	USA,Sgs,Tix	Si-P	=2N5005: 1W	2a	TO-39			BUY 90, 2N6192...93
2 N 5154	USA,Sgs,Tix	Si-N	=2N5004: 1W	2a	TO-39			BUY 34, BUY 80, 2N5338...39
2 N 5155	USA,Del,Mot	Ge-P	S, P, 140/120V, 15/25A, 106W	23a	TO-3			-
2 N 5156	USA,Del,Mot	Ge-P	S, P, 100/60V, 10A, 93W	23a	TO-3			AL 100...101, AUY 37, 2N2290, 2N2293, ++
2 N 5157	USA,Mot,Tix	Si-N	S, P, 700/400V, 3,5A, 100W(Tc=75°)	23a	TO-3			BUS 11(A), BUX 46(A), 2SC3091, 2SC3155, ++
2 N 5158	Tdy	N-FET	S, Chopper, 40V, Idss<100mA, Up<8V	2a	TO-46			BFS 74, BFS 77, BSV 78, 2N3970, ++
2 N 5159	Tdy	N-FET	S, Chopper, 40V, Idss<100mA, Up<10V	2a	TO-46			BFS 74, BFS 77, BSV 78, 2N3970, ++
2 N 5160	Mot,Ray	Si-P	VHF/UHF Drv,Out, 60/40V, 0,4A, PQ=1,2W(400MHz)	2a	TO-39			-
2 N 5161	Mot,Ray	Si-P	VHF P, 60/40V, 1,5A, PQ=8,5W(175MHz)	49a	TO-60			-
2 N 5162	Mot,Ray	Si-P	VHF P, 60/40V, 5A, PQ=35W(175MHz)	49a	TO-60			-
2 N 5163	USA,Mic,Nsc	N-FET	VHF, 25V, Idss>1mA, Up<8V	8b	TO-106			BF 244...245, BFS 72, BFW 10, 2N3823
2 N 5164	Gen,Mot	50Hz-Thy	50V, 13A(Tc=67°), 20A-, Igt/Ih<40/<50mA	29b	TO-203			MCR 3818-2, 2N3870, MCR 3835-2, MCR 63-2
2 N 5165		50Hz-Thy	=2N5164: 200V	29b	TO-203			MCR 3818-4, 2N3871, MCR 3835-4, MCR 63-4
2 N 5166		50Hz-Thy	=2N5164: 400V	29b	TO-203			MCR 3818-6, 2N3872, MCR 3835-6, MCR 63-6
2 N 5167		50Hz-Thy	=2N5164: 600V	29b	TO-203			MCR 3818-8, 2N3873, MCR 3835-8, MCR 63-8
2 N 5164...5167 R		50Hz-Thy	=2N5164...5167:	29d	TO-203			-
2 N 5168		50Hz-Thy	=2N5164:	21b	=TO-48			MCR3918-2, T12N100, MCR3935-2, MCR64-2
2 N 5169		50Hz-Thy	=2N5165:	21b	=TO-48			MCR3918-4, T12N200, MCR3935-4, MCR64-4
2 N 5170		50Hz-Thy	=2N5165:	21b	=TO-48			MCR3918-6, T12N400, MCR3935-6, MCR64-6
2 N 5171		50Hz-Thy	=2N5166:	21b	=TO-48			MCR3918-8, T12N600, MCR3935-8, MCR64-8
2 N 5168...5171 R		50Hz-Thy	=2N5168...5171:	21d	=TO-48			-
2 N 5172	USA,Mic,Nsc	Si-N	Uni, 25/25V, 0,1A, 0,36W, 200MHz	7c	TO-98			BC 168, BC 183, BC 238, BC 548, ++