

2 N 5452	Isi,Nsc,Six Sol	N-FET	Dual, In, 50V, Idss=0.5...5mA, Up=1...4.5V F<0.5dB(100Hz), ΔIdss=0.95...1, ΔUgs<5mV	TO-71	(SDG-SDG-)				BFQ 10...16, 2N3921...22, 2N3954...59
2 N 5453		N-FET	=2N5452: ΔUgs<10mV	TO-71	(SDG-SDG-)				BFQ 10...16, 2N3921...22, 2N3954...59
2 N 5454		N-FET	=2N5452: ΔUgs<15mV	TO-71	(SDG-SDG-)				BFQ 10...16, 2N3921...22, 2N3954...59
2 N 5455	Fch	Si-P	S, 15/15V, 0.3A, 0.34W, >450MHz, <30/40ns	(2N3014) 2a	TO-18				BSX 36
2 N 5456		Si-P	=2N5455: 25/25V	(2N3013) 2a	TO-18				BSX 36
2 N 5457	Isi,Mic,Mot Nsc,Six,++	N-FET	Uni, sym, 25V, Idss=1...5mA, Up=0.5...6V	7d	TO-92	BF 245	7f		2SK246, 2SK330
2 N 5458		N-FET	=2N5457: Idss=2...9mA, Up=1...7V	7d	TO-92	BF 245	7f		BFS 71, 2N3822, 2N4221, 2N5361, ++
2 N 5459		N-FET	=2N5457: Idss=4...16mA, Up=2...8V	7d	TO-92	BF 245	7f		BF 244B...245B, BFS 72, 2N3823, 2N4222, ++
2 N 5460	Isi,Mot,Nsc Phi,Sol	P-FET	Uni, In, 40V, Idss=1...5mA, Up=0.75...6V, F<2.5dB(100Hz)	7c	TO-92				2SJ103, 2SJ105
2 N 5461		P-FET	=2N5460: Idss=2...9mA, Up=1...7.5V	7c	TO-92				BF 320B
2 N 5462		P-FET	=2N5460: Idss=4...16mA, Up=1.8...9V	7c	TO-92				2N4360
2 N 5463		P-FET	=2N5460: 60V	7c	TO-92				-
2 N 5464		P-FET	=2N5461: 60V	7c	TO-92				-
2 N 5465		P-FET	=2N5462: 60V	7c	TO-92				-
2 N 5466	USA	Si-N	S P, 500/400V, 3A, 140W, >2.5MHz	23a	TO-3				BUX 15, BUX 45, 2SC3041, 2SD640, ++
2 N 5467		Si-N	=2N5466: 700/400V	23a	TO-3				BUS 11(A), BUX 47(A), BUX 82...83, ++
2 N 5468		Si-N	=2N5466: 70W	22a	TO-66				BUT 93, BUY 63...64, MJ 4380...81, ++
2 N 5469		Si-N	=2N5466: 700/400V, 70W	22a	TO-66				BUT 11(A), BUY 46(A), MJ 4381, 3SC3490++
2 N 5470	Rca	Si-N	UHF A,Drv, 55V, 0.2A, PQ=2W(1GHz)	Koax					2N5920
2 N 5471	Mot	P-FET	Uni, sym, 40V, Idss>0.02mA, Up<4V	5n	TO-72				2N5797
2 N 5472	Mot	P-FET	Uni, sym, 40V, Idss>0.05mA, Up<4V	5n	TO-72				2N5797
2 N 5473	Mot	P-FET	Uni, sym, 40V, Idss>0.1mA, Up<6V	5n	TO-72				2N5798
2 N 5474	Mot	P-FET	Uni, sym, 40V, Idss>0.2mA, Up<7V	5n	TO-72				2N5798
2 N 5475	Mot	P-FET	Uni, sym, 40V, Idss>0.4mA, Up<8V	5n	TO-72				BF 320A, 2N3909, 2N3820, 2N5799
2 N 5476	Mot	P-FET	Uni, sym, 40V, Idss>0.8mA, Up<9V	5n	TO-72				2N5800
2 N 5477	USA,Mot	Si-N	=2N5336: 7A, 60W	(2N6182) 49m	TO-59				(2N3487...92) ⁶
2 N 5478	USA,Mot	Si-N	=2N5337: 7A, 60W	(2N6183) 49m	TO-59				(2N3487...92) ⁶
2 N 5479	USA,Mot	Si-N	=2N5338: 7A, 60W	(2N6184) 49m	TO-59				(2N3488...89, 2N3491...92) ⁶
2 N 5480	USA,Mot	Si-N	=2N5339: 7A, 60W	(2N6185) 49m	TO-59				(2N3488...89, 2N3491...92) ⁶
2 N 5481	Trw	Si-N	UHF Drv,Out, 50/30V, 0.2A, 5W, 3GHz	55r					BFQ 68
2 N 5482	Trw	Si-N	UHF Drv,Out, 50/30V, 0.35A, 10W, 3GHz	55r					BFQ 68, BFQ 136, BFT 99
2 N 5483	Trw	Si-N	UHF Drv,Out, 45/30V, 0.7A, 20W, 3GHz	55r					BFQ 136
2 N 5484	USA,EUR,Mic	N-FET	VHF/UHF, 25V, Idss=1...5mA, Up=0.3...3V, F<3dB(100M)	7d	TO-92				BF 410A,B
2 N 5485		N-FET	=2N5484: Idss=4...10mA, Up=0.5...4V, F<4dB(400MHz)	7d	TO-92				BF 256A,B
2 N 5486		N-FET	=2N5484: Idss=8...20mA, Up=2...6V, F<4dB(400MHz)	7d	TO-92				BF 256B,C, 2N5397
2 N 5487	USA,Trw	Si-N	S, 120/80V, 5A, 15W(Tc=25°), >40MHz, <125/450ns	2a	=TO-5				BUX 34, BUY 80, 2N4895...97
2 N 5487-1		Si-N	=2N5487: 1.2W	2a	TO-5				BUX 34, BUY 80, 2N4895...97
2 N 5487-3		Si-N	=2N5487: 1.5W	2a°					BUX 34, BUY 80, 2N4895...97
2 N 5488	USA,Trw	Si-N	S, 150/100V, 5A, 15W(Tc=25°), <125/550n	2a	=TO-5				BUY 80, 2N4897
2 N 5488-1		Si-N	=2N5488: 1.2W	2a	TO-5				BUY 80, 2N4897
2 N 5488-3		Si-N	=2N5488: 1.5W	2a°					BUY 80, 2N4897
2 N 5489	USA	Si-N	S P, 125/100V, 40A, 300W, >0.5MHz	49m	TO-114				2N6309...11
2 N 5490	USA,Mot,Tho	Si-N	LFS P, 60/40V, 7A, 50W, >0.8MHz, <5/15μs	17j	TO-220AB	BD 243 C	17j		BD 243A, BD 543A, BD 797, BD 807, ++
2 N 5491		Si-N	=2N5490:	17j	TO-220AA	BD 243 C	17j		BD 243A, BD 543A, BD 797, BD 807, ++
2 N 5492		Si-N	=2N5490: 75/55V	17j	TO-220AB	BD 243 C	17j		BD 243B, BD 543B, BD 799, BD 809, ++
2 N 5493		Si-N	=2N5492:	17j	TO-220AA	BD 243 C	17j		BD 243B, BD 543B, BD 799, BD 809, ++
2 N 5494		Si-N	=2N5490: 60/40V	17j	TO-220AB	BD 243 C	17j		BD 243A, BD 543A, BD 797, BD 807, ++
2 N 5495		Si-N	=2N5495:	17j	TO-220AA	BD 243 C	17j		BD 243A, BD 543A, BD 797, BD 807, ++
2 N 5496		Si-N	=2N5490: 90/70V	17j	TO-220AB	BD 243 C	17j		BD 243B, BD 543C, BD 801, 2SD550, ++
2 N 5497		Si-N	=2N5498:	17j	TO-220AA	BD 243 C	17j		BD 243B, BD 543C, BD 801, 2SD550, ++
2 N 5498	USA,Fch	Si-N	S P, 150/130V, 15A, 200W, >1MHz	23a	TO-3				BDX 50, BUW 57...58, BUX 40, 2N3773, ++
2 N 5505	Tsc	P-FET	Dual, In, 30V, Idss<7mA, Up<4V, F<2dB(1k), ΔUgs<5mV	TO-71	(SDG-SDG-)				-
2 N 5506		P-FET	=2N5505: ΔUgs<15mV	TO-71	(SDG-SDG-)				-
2 N 5507		P-FET	=2N5505: ΔUgs<5mV	TO-71	(SDG-SDG-)				-
2 N 5508		P-FET	=2N5505: ΔUgs<15mV	TO-71	(SDG-SDG-)				-
2 N 5509		P-FET	=2N5505: Up<5V, ΔUgs<25mV	TO-71	(SDG-SDG-)				-
2 N 5510		P-FET	=2N5505: Idss<5mA, ΔUgs<5mV	TO-71	(SDG-SDG-)				-
2 N 5511		P-FET	=2N5505: Idss<5mA, ΔUgs<15mV	TO-71	(SDG-SDG-)				-
2 N 5512		P-FET	=2N5505: Idss<5mA, ΔUgs<5mV	TO-71	(SDG-SDG-)				-
2 N 5513		P-FET	=2N5505: Idss<5mA, ΔUgs<15mV	TO-71	(SDG-SDG-)				-
2 N 5514		P-FET	=2N5505: Idss<5mA, Up<5V, ΔUgs<25mV	TO-71	(SDG-SDG-)				-
2 N 5515	Isi,Nsc,Six Sol,Tix	N-FET	Dual, In, 40V, Idss=0.5...7.5mA, Up=0.7...4V Ur<30nV(10Hz), ΔIdss=0.95...1, ΔUgs<5mV	TO-71	(SDG-SDG-)				BFQ 10...16, 2N5045...47, 2N5452...54
2 N 5516		N-FET	=2N5515: ΔUgs<5mV	TO-71	(SDG-SDG-)				BFQ 10...16, 2N5045...47, 2N5452...54
2 N 5517		N-FET	=2N5515: ΔUgs<10mV	TO-71	(SDG-SDG-)				BFQ 10...16, 2N5045...47, 2N5452...54
2 N 5518		N-FET	=2N5515: ΔUgs<15mV	TO-71	(SDG-SDG-)				BFQ 10...16, 2N5045...47, 2N5452...54
2 N 5519		N-FET	=2N5515: ΔIdss=0.9...1, ΔUgs<15mV	TO-71	(SDG-SDG-)				BFQ 10...16, 2N5045...47, 2N5452...54
2 N 5520		N-FET	=2N5515: Ur<15nV(10Hz)	TO-71	(SDG-SDG-)				BFQ 10...16, 2N5045...47, 2N5452...54
2 N 5521		N-FET	=2N5516: Ur<15nV(10Hz)	TO-71	(SDG-SDG-)				BFQ 10...16, 2N5045...47, 2N5452...54
2 N 5522		N-FET	=2N5517: Ur<15nV(10Hz)	TO-71	(SDG-SDG-)				BFQ 10...16, 2N5045...47, 2N5452...54
2 N 5523		N-FET	=2N5518: Ur<15nV(10Hz)	TO-71	(SDG-SDG-)				BFQ 10...16, 2N5045...47, 2N5452...54
2 N 5524		N-FET	=2N5519: Ur<15nV(10Hz)	TO-71	(SDG-SDG-)				BFQ 10...16, 2N5045...47, 2N5452...54
2 N 5525	Tix	Si-N-Darl	Uni, 40/30V, 0.2A, 0.36W, >200MHz, hFE>5000	7c	TO-92				BC 517, BC 617, BC 875, MPS-A25...26, ++
2 N 5526		Si-N-Darl	=2N5525: hFE>1000	7c	TO-92				BC 517, BC 617, BC 875, MPS-A25...26, ++
2 N 5527	Sol,Ssi,Stc	Si-N	S P, RadH, 60/40V, 5A, 5W(Tc=25°), >200MHz	2a	TO-5				-
2 N 5528		Si-N	=2N5527: RadH, 10A, 35W	49m	TO-59				-
2 N 5529		Si-N	=2N5527: RadH, 10A, 35W	49m	TO-61				-
2 N 5530		Si-N	=2N5527: RadH, 10A, 35W, Iso	49a	TO-61				-
2 N 5531	Sol,Ssi,Stc	Si-N	S P, RadH, 90/75V, 5A, 5W(Tc=25°), >200MHz	2a	TO-5				-
2 N 5532		Si-N	=2N5531: RadH, 10A, 35W	49m	TO-59				-
2 N 5533		Si-N	=2N5531: RadH, 10A, 35W	49m	TO-61				-
2 N 5534		Si-N	=2N5531: RadH, 10A, 35W, Iso	49a	TO-61				-
2 N 5535	Sol,Ssi,Stc	Si-N	S P, RadH, 60/50V, 20A, 50W, >150MHz	49m	TO-61				-
2 N 5536		Si-N	=2N5535: RadH, Iso	49a	TO-61				-
2 N 5537		Si-N	=2N5535: RadH, 90/75V	49m	TO-61				-
2 N 5538		Si-N	=2N5535: RadH, 90/75V, Iso	49a	TO-61				-
2 N 5539	Sol,Ssi,Stc	Si-N	S P, 175/130V, 20A, 100W(Tc=100°), >20MHz, <0.5/2μs	49m	TO-63				2N2818, 2N2822
2 N 5540	Sol,Ssi,Stc	Si-N	S P, 325/300V, 10A, 50W(Tc=100°), >20MHz, <1.5/3μs	49m	TO-61				-
2 N 5541	Sol,Ssi,Stc	Si-N	S P, 175/130V, 5A, 8.75W(Tc=100°), >20MHz, <0.5/2μs	2a	TO-5				BUY 48...49
2 N 5542	Sol,Ssi,Stc	Si-N	S P, 175/130V, 10A, 50W(Tc=100°), >20MHz, <0.5/2μs	49m	TO-61				-