

2 N 6622	Amp	Si-N	S P, 800V, 10A, 45W(Tc=100°), >4MHz	23a	TO-3				BUS 12(A), BUW 26, BUW 35...36, BUX 81, ++
2 N 6648	Mot,Rca	Si-P-Darl+Di	LFS P, 40/40V, 10/15A, 100W, >20MHz, hFE=1k...20k	23a	TO-3				BDV 64, BDX 84, BDX 86, MJ 2500, ++
2 N 6649		Si-P-Darl+Di	=2N6648: 60/60V	{2N6383 {2N6384	23a	TO-3			BDV 64, BDX 84A, BDX 86A, MJ 2500, ++
2 N 6650		Si-P-Darl+Di	=2N6648: 80V	{2N6385	23a	TO-3			BDV 64A, BDX 84B, BDX 86B, MJ 2501, ++
2 N 6653	Gsi,Stc	Si-N	S P, 350/300V, 20A, 150W, >25MHz, <250/1850ns	23a	TO-3				BUV 24, BUX 24, 2SC3085
2 N 6654		Si-N	=2N6653: 400/350V	23a	TO-3				BUV 24, BUX 24, 2SC3085
2 N 6655		Si-N	=2N6653: 450/400V	23a	TO-3				BUV 24, BUX 24, 2SC3085
2 N 6656	Sgs,Six	MOS-N-FET-e	35/15V, 2/3A, 25W, on<1.8Ω, <10/10ns	23a	TO-3				-
2 N 6657	Sgs,Six	MOS-N-FET-e	60/15V, 2/3A, 25W, on<3Ω, <10/10ns	23a	TO-3				-
2 N 6658	Sgs,Six	MOS-N-FET-e	90/15V, 2/3A, 25W, on<4Ω, <10/10ns	23a	TO-3				-
2 N 6659	Mot,Phi,Sgs Six	MOS-N-FET-e	35/15V, 2/3A, 6.2W(Tc=25°), on<1.8Ω(1A), <10/10ns	2a	TO-39				-
2 N 6660		=2N6659	MOS-N-FET-e	60/15V, 2/3A, 6.2W(Tc=25°), on<3Ω(1A), <10/10ns	2a	TO-39			-
2 N 6661		MOS-N-FET-e	90/15V, 2/3A, 6.2W(Tc=25°), on<4Ω(1A), <10/10ns	2a	TO-39				-
2 N 6665	Miv	Si-N	UHF, In, 20V, 0.125A, 0.45W, 2GHz	5g	TO-72				2SC2408, (BFR 95) <sup>6</sup>
2 N 6666	Mot,Rca	Si-P-Darl+Di	P, 40/40V, 8/15A, 65W, >20MHz, hFE=1k...20k	{2N6386 17j {2N6387 17j	TO-220				BD 644, BD 896, BDW 74, BDX 54, ++
2 N 6667		Si-P-Darl+Di	=2N6666: 60/60V	{2N6388 17j	TO-220				BD 646, BD 898, BDW 74A, BDX 54A, ++
2 N 6668		Si-P-Darl+Di	=2N6666: 80/80V	{2N6388 17j	TO-220				BD 648, BD 900, BDW 74B, BDX 54B, ++
2 N 6669	Rca	Si-N	LFS P, 40/30V, 10A, 40W, >10MHz, 230/600ns	17j	TO-220				BD 705, BD 743, BD 805, BD 905, ++
2 N 6670	Rca	Si-N	AM P, 80/50V, 1.5A, PQ=5W(40MHz)	13m	TO-202				-
2 N 6671	Fer,Rca,Tho	Si-N	S P, 450/300V, 5/10A, 150W, >15MHz, <600/2900ns	23a	TO-3				BUW 24...26, BUW 34...36, BUW 72, ++
2 N 6672		Si-N	=2N6671: 550/350V	23a	TO-3				BUW 25...26, BUW 35...36, BUX 80, ++
2 N 6673		Si-N	=2N6671: 650/400V	23a	TO-3				BUW 26, BUW 35...36, BUX 80...81, ++
2 N 6674	Fer,Rca,Tho	Si-N	S P, 450/300V, 10/20A, 175W, >15MHz, <700/300ns	23a	TO-3				BUV 25, BUW 44, BUW 75, BUX 25, ++
2 N 6675		Si-N	=2N6674: 650/400V	23a	TO-3				BUS 13(A), BUW 44...46, BUX 48(A...C), ++
2 N 6676	USA,Mot,Tho	Si-N	S P, 450/300V, 15/20A, 175W, >15MHz <700/3000ns	23a	TO-3				BUV 25, BUW 44...46, BUX 25, BUX 48, ++
2 N 6677		Si-N	=2N6676: 550/350V	23a	TO-3				BUS 13(A), BUW 45...46, BUX 48A...C), ++
2 N 6678		Si-N	=2N6676: 650/400V	23a	TO-3				BUS 13(A), BUW 45...46, BUX 48A...C), ++
2 N 6679	Mot	Si-N	UHF, 30V, 70mA, >4GHz	52r	SOT-100				BFO 82, BFO 196, 2SC3603
2 N 6681	Tho,Uni	50Hz-Thy	100V, 1A=, Igt/Ih<0.2<5mA	7n	TO-92	(BRX 49)	7a		TAG 59A, BT 149A, MCR 606-3
2 N 6682		50Hz-Thy	=2N6681: 200V	7n	TO-92	(BRX 49)	7a		TAG 59B, BT 149B, MCR 606-4
2 N 6683		50Hz-Thy	=2N6681: 400V	7n	TO-92	(BRX 49)	7a		TAG 59D, BT 149D, MCR 606-6
2 N 6684		50Hz-Thy	=2N6681: 600V	7n	TO-92	(BRX 49)	7a		TAG 59M, BT 149M, MCR 606-8
2 N 6685		50Hz-Thy	=2N6681: 800V	7n	TO-92	(BRX 49) <sup>4</sup>	7a		(TAG 615-800) <sup>4</sup>
2 N 6686	Fer,Rca	Si-N	S P, 260/160V, 25/50A, 200W, >20MHz, <450/1250ns	23a	TO-3				BUV 12, BUW 73, BUX 12
2 N 6687		Si-N	=2N6686: 280/180V	23a	TO-3				BUV 12, BUW 73, BUX 12
2 N 6688		Si-N	=2N6686: 300/200V, 20A	23a	TO-3				BUV 12, BUW 73, BUX 12
2 N 6689	Rca	Si-N	S P, 450/300V, 15A, 175W, >15MHz, <700/3000ns	49a	TO-61				-
2 N 6690		Si-N	=2N6689: 650/400V	49a	TO-61				-
2 N 6691	Rca	Si-N	S P, 450/300V, 15A, 175W, >15MHz, <700/3000ns	49a	TO-61				-
2 N 6692		Si-N	=2N6691: 550/350V	49a	TO-61				-
2 N 6693		Si-N	=2N6691: 650/400V	49a	TO-61				-
2 N 6702	Rca,Sgs	Si-N	S P, 140/90V, 7/10A, 50W, >50MHz, <350/1500ns	17j	TO-220				BU 409, BUW 64A...C, TIP 150...152, ++
2 N 6703		Si-N	=2N6702: 160/110V	17j	TO-220				BU 409, BUW 64C, TIP 150...152, ++
2 N 6704		Si-N	=2N6702: 180/130V	17j	TO-220				BU 409, BUW 64C, TIP 150...152, ++
2 N 6705	Gen,Nsc	Si-N	Uni, 60/45V, 1/2A, 1.2W, >50MHz	{2N6708 30c {2N6709 30c	TO-237	2SC4135	30j		2SD1281...82, (BD 517, BD 525,++) <sup>6</sup>
2 N 6706		Si-N	=2N6705: 80/60V	{2N6710 30c	TO-237	2SC4135	30j		2SD1281...82, (BD 519, BD 527,++) <sup>6</sup>
2 N 6707		Si-N	=2N6705: 100/80V	{2N6705 30c	TO-237	2SC4135	30j		2SD1281...82, (BD 529) <sup>6</sup>
2 N 6708	Gen,Nsc	Si-P	Uni, 60/45V, 1/2A, 1.2W, >50MHz	{2N6705 30c {2N6706 30c	TO-237	2SA1593	30j		2SB957...958, (BD 518, BD 526,++) <sup>6</sup>
2 N 6709		Si-P	=2N6708: 80/60V	{2N6707 30c	TO-237	2SA1593	30j		2SB957...958, (BD 520, BD 528,++) <sup>6</sup>
2 N 6710		Si-P	=2N6708: 100/80V	{2N6708 30c	TO-237	2SA1593	30j		2SB957...958, (BD 530) <sup>6</sup>
2 N 6711	Gen,Nsc	Si-N	Vid, 160/160V, 0.1/0.3A, 1.2W, 50MHz	30c	TO-237	(MPS-U10) <sup>6</sup>	13m		(BF 380...382, BF 460...462, BF 757...759) <sup>6</sup>
2 N 6712		Si-N	=2N6711: 250/250V	30c	TO-237	(MPS-U10) <sup>6</sup>	13m		(BF 381...382, BF 460...462, BF 757...759) <sup>6</sup>
2 N 6713		Si-N	=2N6711: 300/300V	30c	TO-237	(MPS-U10) <sup>6</sup>	13m		(BF 382, BF 461...462, BF 758...759) <sup>6</sup>
2 N 6714	Gen,Nsc	Si-N	Uni, 40/30V, 2A, 1.2W, >50MHz	{2N6726 30e {2N6727 30e	TO-237	(2SC4135) <sup>6</sup>	30j		2SD1078...79, (BD 509, BD 517,++) <sup>6</sup>
2 N 6715		Si-N	=2N6714: 50/40V	{2N6728 30e	TO-237	(2SC4135) <sup>6</sup>	30j		2SD1078...79, (BD 509, BD 517,++) <sup>6</sup>
2 N 6716	Gen,Nsc	Si-N	Uni, 60/60V, 2A, 1.2W, >50MHz	{2N6729 30e {2N6730 30e	TO-237	(2SC4135) <sup>6</sup>	30j		2SD1281...82, (BD 517, BD 525,++) <sup>6</sup>
2 N 6717		Si-N	=2N6716: 80/80V	{2N6729 30e	TO-237	(2SC4135) <sup>6</sup>	30j		2SD1281...82, (BD 519, BD 527,++) <sup>6</sup>
2 N 6718		Si-N	=2N6716: 100/100V	{2N6730 30e	TO-237	(2SC4135) <sup>6</sup>	30j		2SD1281...82, (BD 529) <sup>6</sup>
2 N 6719	Gen,Nsc	Si-N	S,Vid, 300/300V, 0.1A, 1.2W, >30MHz	30e	TO-237	(MPS-U10) <sup>6</sup>	13m		2SC2870, 2SC2924, 2SC3408, (BF617,++) <sup>6</sup>
2 N 6720	Nsc	Si-N	S,Vid, 175/150V, 1A, 2W, >30MHz	30e	TO-237				2SC2885, 2SC2946, (BF 466...468,++) <sup>6</sup>
2 N 6721		Si-N	=2N6721: 225/200V	30e	TO-237				2SC2885, 2SC2946, (BF 467...468,++) <sup>6</sup>
2 N 6722		Si-N	=2N6721: 275/250V	30e	TO-237				2SC2885, 2SC2946, (BF 468, BF 668,++) <sup>6</sup>
2 N 6723		Si-N	=2N6721: 325/300V	30e	TO-237				2SC2885, 2SC2946, (BF 468, BF 668,++) <sup>6</sup>
2 N 6724	Gen,Nsc	Si-N-Darl	LF Drv,Out, 50/40V, 2A, 1W, >100MHz, hFE>15000	30e	TO-237				2SD1222, 2SD1759, (BD 411...412) <sup>6</sup>
2 N 6725		Si-N-Darl	=2N6724: 60/50V	30e	TO-237				2SD1222, 2SD1759
2 N 6726	Gen,Nsc	Si-P	LF Drv,Out, 40/30V, 2A, 1.2W, >50MHz	{2N6714 30e {2N6715 30e	TO-237	(2SA1593) <sup>6</sup>	30j		2SB838...839, (BD 518, BD 526,++) <sup>6</sup>
2 N 6727		Si-P	=2N6726: 50/40V	{2N6716 30e	TO-237	(2SA1593) <sup>6</sup>	30j		2SB838...839, (BD 518, BD 526,++) <sup>6</sup>
2 N 6728	Gen,Nsc	Si-P	Uni, 60/60V, 2A, 1.2W, >50MHz	{2N6717 30e {2N6718 30e	TO-237	(2SA1593) <sup>6</sup>	30j		2SB957...958, (BD 518, BD 526,++) <sup>6</sup>
2 N 6729		Si-P	=2N6728: 80/80V	{2N6717 30e	TO-237	(2SA1593) <sup>6</sup>	30j		2SB957...958, (BD 520, BD 528,++) <sup>6</sup>
2 N 6730		Si-P	=2N6728: 100/100V	{2N6718 30e	TO-237	(2SA1593) <sup>6</sup>	30j		2SB957...958, (BD 530) <sup>6</sup>
2 N 6731	Nsc	Si-N	Uni, 100/80V, 1A, 2W, >50MHz	{2N6732 30e {2N6731 30e	TO-237	(2SC4135) <sup>6</sup>	30j		2SD1281...84, (BD529) <sup>6</sup>
2 N 6732	Nsc	Si-P	Uni, 100/100V, 1A, 2W, >50MHz	{2N6732 30e {2N6731 30e	TO-237	(2SA1593) <sup>6</sup>	30j		2SB957...960, (BD530) <sup>6</sup>
2 N 6733	Gen,Nsc	Si-N	Vid, 160/160V, 0.1A, 1.2W, >50MHz	30e	TO-237	(MPS-U10) <sup>6</sup>	13m		2SC2870, 2SC2924, 2SC3408, (BF 617,++) <sup>6</sup>
2 N 6734		Si-N	=2N6733: 250/250V	30e	TO-237	(MPS-U10) <sup>6</sup>	13m		2SC2870, 2SC2924, 2SC3408, (BF 617,++) <sup>6</sup>
2 N 6735		Si-N	=2N6733: 300/300V	30e	TO-237	(MPS-U10) <sup>6</sup>	13m		2SC2870, 2SC2924, 2SC3408, (BF 617,++) <sup>6</sup>
2 N 6737	Nsc	Si-N	S, 80/45V, >300MHz, <~60ns	30e	TO-237				-
2 N 6738	Fer,Rca	Si-N	S P, 450/300V, 8/10A, 100W, >15MHz, <600/2900ns	17j	TO-220	BUT 56 A	17j		BUT 54, BUT 56(A), 2SC3039, 2SC4106, ++
2 N 6739		Si-N	=2N6738: 550/350V	17j	TO-220	BUT 56 A	17j		BUT 54, BUT 56(A), 2SC3039, 2SC4106, ++
2 N 6740		Si-N	=2N6738: 650/400V	17j	TO-220	BUT 56 A	17j		BUT 54, BUT 56(A), MJE 13006...07, ++
2 N 6751	Fer,Rca	Si-N	S P, 800/400V, 10/10A, 150W, >15MHz, <500/3400ns	23a	TO-3				BUS 12(A), BUW 35...36, BUX 80...81, ++
2 N 6752		Si-N	=2N6751: 850/450V	23a	TO-3				BUS 12(A), BUW 36, BUX 81, MJ 8504, ++
2 N 6753		Si-N	=2N6751: 900/500V	23a	TO-3				BUS 12A, BUW 36, BUX 81, MJ 8504, ++
2 N 6754		Si-N	=2N6751: 1000/500V	23a	TO-3				BUS 12A, BUX 81, MJ 8504, 2SC3215, ++
2 N 6755		MOS-N-FET-e	=2N6756: 60/20V, 8/25A, on<0.25Ω(8A)	23a	TO-3				2SK398...399, 2SK500, 2SK633
2 N 6756	USA,Inr,Mot	MOS-N-FET-e	VFET, 100V, 14/30A, 75W, on<0.18Ω(9A), <105/85ns	23a	TO-3				BUZ 36, BUZ 350, 2SK622
2 N 6757		MOS-N-FET-e	=2N6758: 150/20V, 8/12A, on<0.6Ω(5A)	23a	TO-3				2SK399, 2SK401, 2SK631, 2SK633
2 N 6758	USA,Inr,Mot	MOS-N-FET-e	VFET, 200/20V, 9/15A, 75W, on<0.4Ω(6A), <80/90ns	23a	TO-3				2SK412, 2SK633
2 N 6759	USA,Inr,Mot	MOS-N-FET-e	VFET, 350/20V, 4.5/7A, 75W, on<1.5Ω(3A), <65/90ns	23a	TO-3				BUZ 63, 2SK259...260
2 N 6760	USA,Inr,Mot	MOS-N-FET-e	VFET, 400/20V, 5.5/8A, 75W, on<1Ω(3.5A), <65/90ns	23a	TO-3				BUZ 63, 2SK260, 2SK298
2 N 6761		MOS-N-FET-e	=2N6762: 450/20V, 4/6A, on<2Ω(2.5A)	23a	TO-3				BUZ 84, 2SK351