

| TRANSISTOR NUMBER | P O A L T | M O A L T | PACK-AGE | LEAD INFO | V _{CE} MAX | V _{CE} MAX | V _{CE} MAX | I _C MAX | T _J MAX | P TOT | F _T MIN | C _{OB} MAX | H _{FE} | H _{FE} BIAS | USE | MFR | ALTERNATIVES AND NOTES |
|-------------------|-----------------------|-----------------------|----------|-----------|---------------------|---------------------|---------------------|--------------------|--------------------|--------|--------------------|---------------------|-----------------|----------------------|-----|-----|------------------------|
| 2N5765 | N S | | X56D | M01 | 55V | 25V | 3V | 1500mA | 175C | 19WC | - | 12P | 20mn | 100mA | RMA | TRW | |
| 2N5766 | N S | | X56D | M01 | 55V | 25V | 3V | 200mA | 175C | 5WC | - | 12P | 20mn | 50mA | RMA | TRW | |
| 2N5767 | N S | | X56D | M01 | 55V | 25V | 3V | 350mA | 175C | 10WC | - | 5P0 | 20mn | 100mA | RMA | TRW | |
| 2N5768 | N S | | X56D | M01 | 55V | 25V | 3V | 700mA | 175C | 20WC | - | 10P | 20mn | 100mA | RMA | TRW | |
| 2N5769 | N S | | T092 | L14 | 40V | 15V | 4V | 500mA | 150C | 625mWF | 500M | 4P0 | 40/120 | 10mA | VMS | NAT | BSS11 2N2369A |
| 2N5770 | N S | | T092 | L14 | 30V | 15V | 4V | 50mA | 150C | 625mWF | 900M | 1P7 | 20mn | 3mA | ULS | NAT | 2N5179 |
| 2N5771 | P S | | T092 | L14 | 15V | 15V | 4V | 50mA | - | 310mWF | 700M | 3P0 | 50/120 | 10mA | ULA | NAT | 2N4958 |
| 2N5772 | N S | | T092 | L14 | 40V | 15V | 5V | 500mA | 150C | 625mWF | 350M | 5P0 | 30/120 | 30mA | VMS | NAT | BSS11 2N2369A |
| 2N5773 | N S | | X27 | L64 | 65V | 35V | 3V | 500mA | 200C | 5WC | - | 4P5 | 20/200 | 100mA | UMP | TRW | |
| 2N5774 | N S | | X44 | X44 | 65V | 35V | 3V | 1500mA | 200C | 18WC | - | 14P | 20/200 | 100mA | UMP | TRW | |
| 2N5775 | N S | | X80B | - | 65V | 35V | 3V | 3A | 175C | 40WC | - | 26P | 10/150 | 100mA | RMG | TRW | |
| 2N5776 | N S | | X80B | - | 65V | 35V | 3V | 6A | 175C | 70WC | - | 50P | 10/150 | 200mA | RMG | TRW | |
| 2N5781 | P S | | T039 | L04 | 80V | 65V | 5V | 3500mA | 200C | 10WC | 8M | - | 20/100 | 1A | RHG | RCA | 2N6193 |
| 2N5782 | P S | | T039 | L04 | 65V | 50V | 5V | 3500mA | 200C | 10WC | 8M | - | 20/100 | 1200mA | RHG | RCA | 2N6193 |
| 2N5783 | P S | | T039 | L04 | 45V | 40V | 5V | 3500mA | 200C | 10WC | 8M | - | 20/100 | 1600mA | RHG | RCA | 2N6193 |
| 2N5784 | N S | | T039 | L04 | 80V | 65V | 5V | 3500mA | 200C | 10WC | 1M | - | 20/100 | 1A | RHG | RCA | 6SV64 2N5784 |
| 2N5785 | N S | | T039 | L04 | 65V | 50V | 5V | 3500mA | 200C | 10WC | 1M | - | 20/100 | 1200mA | RHG | RCA | 6SV64 2N5784 |
| 2N5786 | N S | | T039 | L04 | 45V | 40V | 5V | 3500mA | 200C | 10WC | 1M | - | 20/100 | 1600mA | RHG | RCA | 6SV64 2N5784 |
| 2N5793 | N S | | T077 | N01 | 75V | 40V | 6V | 600mA | 200C | 600mWF | 250M | 8P0 | 40/120 | 150mA | DUA | MOT | BFX10 2N3409 |
| 2N5794 | N S | | T077 | N01 | 75V | 40V | 6V | 600mA | 200C | 600mWF | 250M | 8P0 | 100mn | 150mA | DUA | MOT | BFX10 2N3409 |
| 2N5795 | P S | | T077 | N01 | 60V | 60V | 5V | 600mA | 200C | 600mWF | 200M | 8P0 | 40/120 | 150mA | DUA | MOT | BFX11 2N4015 |
| 2N5796 | P S | | T077 | N01 | 60V | 60V | 5V | 600mA | 200C | 600mWF | 200M | 8P0 | 100mn | 150mA | DUA | MOT | BFX11 2N4015 |
| 2N5804 | N S | | T03 | L05 | 300V | 225V | 6V | 5A | 200C | 110WC | 15M | - | 10/100 | 5A | RHE | RCA | BUX16C 2N5157 |
| 2N5805 | N S | | T03 | L05 | 375V | 300V | 6V | 5A | 200C | 110WC | 15M | - | 10/100 | 5A | RHE | RCA | BUX16C 2N5157 |
| 2N5810 | N S | | X10 | L20 | 35V | 25V | 5V | 750mA | 135C | 500mWF | 100M | 15P | 45mn | 500mA | AMG | GES | BC338 2N5818 |
| 2N5811 | P S | | X10 | L20 | 35V | 25V | 5V | 750mA | 135C | 500mWF | 100M | 15P | 45mn | 500mA | AMG | GES | BC328 2N5819 |
| 2N5812 | N S | | X10 | L20 | 35V | 25V | 5V | 750mA | 135C | 500mWF | 135M | 15P | 60mn | 500mA | AMG | GES | BC338 2N5819 |
| 2N5813 | P S | | X10 | L20 | 35V | 25V | 5V | 750mA | 135C | 500mWF | 135M | 15P | 60mn | 500mA | AMG | GES | BC328 2N5819 |
| 2N5814 | N S | | X10 | L20 | 50V | 40V | 5V | 750mA | 135C | 500mWF | 100M | 15P | 60/120 | 2mA | AMG | GES | BC337 2N5818 |
| 2N5815 | P S | | X10 | L20 | 50V | 40V | 5V | 750mA | 135C | 500mWF | 100M | 15P | 60/120 | 2mA | AMG | GES | BC327 2N5819 |
| 2N5816 | N S | | X10 | L20 | 50V | 40V | 5V | 750mA | 135C | 500mWF | 120M | 15P | 100mn | 2mA | AMG | GES | BC337 2N5818 |
| 2N5817 | P S | | X10 | L20 | 50V | 40V | 5V | 750mA | 135C | 500mWF | 120M | 15P | 100mn | 2mA | AMG | GES | BC327 2N5819 |
| 2N5818 | N S | | X10 | L20 | 50V | 40V | 5V | 750mA | 135C | 500mWF | 135M | 15P | 150mn | 2mA | AMG | GES | BC337 2N5818 |
| 2N5819 | P S | | X10 | L20 | 50V | 40V | 5V | 750mA | 135C | 500mWF | 135M | 15P | 150mn | 2mA | AMG | GES | BC327 2N5819 |
| 2N5820 | N S | | X10 | L20 | 70V | 60V | 5V | 750mA | 135C | 500mWF | 100M | 15P | 20mn | 500mA | AMH | GES | BC337 2N5819 |
| 2N5821 | P S | | X10 | L20 | 70V | 60V | 5V | 750mA | 135C | 500mWF | 100M | 15P | 20mn | 500mA | AMH | GES | BC327 2N5819 |
| 2N5822 | N S | | X10 | L20 | 70V | 60V | 5V | 750mA | 135C | 500mWF | 120M | 15P | 25mn | 500mA | AMH | GES | BC337 2N5819 |
| 2N5823 | P S | | X10 | L20 | 70V | 60V | 5V | 750mA | 135C | 500mWF | 120M | 15P | 25mn | 500mA | AMH | GES | BC327 2N5819 |
| 2N5824 | N S | | X10 | L20 | 50V | 40V | 5V | 100mA | 125C | 360mWF | 90M | 4P0 | 60/120 | 2mA | ALG | GES | BC237 2N5825 |
| 2N5825 | N S | | X10 | L20 | 50V | 40V | 5V | 100mA | 125C | 360mWF | 90M | 4P0 | 100mn | 2mA | ALG | GES | BC237 2N5825 |
| 2N5826 | N S | | X10 | L20 | 50V | 40V | 5V | 100mA | 125C | 360mWF | 90M | 4P0 | 150mn | 2mA | ALG | GES | BC237 2N5825 |
| 2N5827 | N S | | X10 | L20 | 50V | 40V | 5V | 100mA | 125C | 360mWF | 90M | 4P0 | 250mn | 2mA | ALN | GES | BC237 2N5825 |
| 2N5827A | N S | | X10 | L20 | 50V | 40V | 5V | 100mA | 125C | 360mWF | 90M | 4P0 | 250mn | 2mA | ALN | GES | BC237 2N5825 |
| 2N5828 | N S | | X10 | L20 | 50V | 40V | 5V | 100mA | 125C | 360mWF | 90M | 4P0 | 400mn | 2mA | ALG | GES | BC237 2N5825 |
| 2N5828A | N S | | X10 | L20 | 50V | 40V | 5V | 100mA | 125C | 360mWF | 90M | 4P0 | 400mn | 2mA | ALN | GES | BC237 2N5825 |
| 2N5829 | P S | | T072 | L06 | 30V | 30V | 3V | 30mA | 200C | 200mWF | 1200M | 0P8 | 20/150 | 2mA | ULA | MOT | 2N4261 |
| 2N5830 | N S | | T092 | L14 | 120V | 100V | 5V | 600mA | 150C | 625mWF | 100M | 4P0 | 80/500 | 10mA | TVH | FCD | BCX22 2N4001 |
| 2N5831 | N S | | T092 | L14 | 160V | 140V | 5V | 600mA | 150C | 625mWF | 100M | 4P0 | 80/250 | 10mA | TVH | FCD | BFT57 2N5551 |
| 2N5832 | N S | | T092 | L14 | 160V | 140V | 5V | 600mA | 150C | 625mWF | 100M | 4P0 | 175mn | 10mA | TVH | NAT | 2N5551 |
| 2N5833 | N S | | T092 | L14 | 200V | 180V | 6V | 600mA | 150C | 625mWF | 100M | 4P0 | 50/250 | 10mA | TVH | FCD | 2N6517 |
| 2N5834 | P S | | T05 | L04 | 60V | 40V | 4V | 1A | 175C | 5WC | - | - | 10mn | 250mA | VMA | TIS | BC161 2N4037 |
| 2N5835 | N S | | T072 | L06 | 15V | 10V | 3V | 15mA | 200C | 200mWF | 2500M | 0P8 | 25mn | 10mA | SLG | MOT | |
| 2N5836 | N S | | T046 | L01 | 15V | 10V | 3V | 200mA | 200C | 2WC | 2G | 3P5 | 25mn | 50mA | SMG | MOT | |
| 2N5837 | N S | | T046 | L01 | 10V | 5V | 3V | 300mA | 200C | 2WC | 1700M | 5P0 | 25mn | 100mA | SMG | MOT | BFT17 2N5650 |
| 2N5838 | N S | | T03 | L05 | 275V | 250V | 6V | 3A | 200C | 100WC | 5M | - | 8/40 | 3A | RHE | RCA | BUX16C 2N5157 |
| 2N5839 | N S | | T03 | L05 | 300V | 275V | 6V | 3A | 200C | 100WC | 5M | - | 10/50 | 2A | RHE | RCA | BUX16C 2N5157 |
| 2N5840 | N S | | T03 | L05 | 375V | 350V | 6V | 3A | 200C | 100WC | 5M | - | 10/50 | 2A | RHE | RCA | BUX16C 2N5157 |
| 2N5841 | N S | | T072 | L06 | 20V | 10V | 3V | 100mA | 200C | 350mWF | 2200M | 1P5 | 25/200 | 25mA | SMS | MOT | |
| 2N5842 | N S | | T072 | L06 | 20V | 10V | 3V | 100mA | 200C | 350mWF | 1700M | 1P5 | 25/250 | 25mA | SMS | MOT | |
| 2N5843 | P S | | T077 | N01 | 50V | 40V | 5V | 50mA | 200C | 600mWF | 200M | 6P0 | 50/150 | 1mA | DUA | MOT | 5% DVBE BFX11 |
| 2N5844 | P S | | T077 | N01 | 50V | 40V | 5V | 50mA | 200C | 600mWF | 250M | 6P0 | 100mn | 1mA | DUA | MOT | 5% DVBE BFX11 |
| 2N5845 | N S | | T092 | L14 | 50V | 40V | 6V | 1A | 150C | 625mWF | 300M | 9P0 | 25/150 | 500mA | VMS | MOT | 2N5859 |
| 2N5845A | N S | | T092 | L14 | 50V | 40V | 6V | 1A | 150C | 625mWF | 200M | 9P0 | 35/150 | 500mA | VMS | MOT | 2N5859 |
| 2N5846 | N S | | X26 | L59 | 36V | 18V | 4V | 1A | 200C | 10WC | - | 25P | 5mn | 250mA | VMP | MOT | |
| 2N5847 | N S | | X28 | L65 | 36V | 18V | 4V | 2A | 200C | 20WC | - | 90P | 5mn | 500mA | VHP | MOT | |
| 2N5848 | N S | | X28 | L65 | 48V | 24V | 4V | 3500mA | 200C | 50WC | - | 125P | 3mn | 1200mA | RHP | MOT | |
| 2N5849 | N S | | X28 | L65 | 48V | 24V | 4V | 7A | 200C | 100WC | - | 230P | 3mn | 2500mA | RHP | MOT | |
| 2N5851 | N S | | T072 | L06 | 30V | 15V | 4V | 100mA | 200C | 500mWC | 800M | 1P5 | 40mn | 10mA | SMG | MOT | 2N5852 |
| 2N5852 | N S | | T072 | L06 | 30V | 15V | 4V | 100mA | 200C | 500mWC | 1100M | 1P5 | 40mn | 10mA | SMG | MOT | 2N5852 |
| 2N5853 | P S | | T061 | L46 | 100V | 80V | 6V | 10A | 200C | 66WC | 15M | - | 30/90 | 5A | RHG | KER | BDY69 2N5677 |
| 2N5854 | N S | | T061 | L46 | 100V | 80V | 6V | 10A | 200C | 66WC | 20M | - | 30/90 | 5A | RHH | KER | BDY63 2N5731 |
| 2N5855 | N S | | T0105 | L04 | 60V | 60V | 5V | 1A | 125C | 750mWF | 15M | 100P | 50/300 | 150mA | AMG | FCD | BFS96 2N4036 |
| 2N5856 | P S | | T0105 | L04 | 60V | 60V | 5V | 1A | 125C | 750mWF | 200M | 12P | 50/300 | 50mA | AMG | FCD | BFY50 2N2297 |
| 2N5857 | P S | | T0105 | L04 | 80V | 80V | 5V | 1A | 125C | 750mWF | 15M | 100P | 50/300 | 150mA | AMG | FCD | BFS93 2N4037 |
| 2N5858 | N S | | T0105 | L04 | 80V | 80V | 5V | 1A | 125C | 750mWF | 200M | 12P | 50/300 | 50mA | AMG | FCD | BSW66 2N1893 |