

AN 7140*	LIN-IC	NF-E, 24V, 4A, 5W(13V/4Ω)	9-SIL	
AN 7145 M	LIN-IC	2x NF-E, 24V, 4A, 2x4,5W(16V/8Ω)	18-DILP	
AN 7156 N*	LIN-IC	2x NF-E, 24V, 4A, 2x5,5W(13V/4Ω)	12-SILP	
AN 7158(N)*	LIN-IC	2x NF-E, 24V, 4A, 2x7,5W(16V/4Ω)	12-SILP	
AN 7160*	LIN-IC	NF-E, 24V, 4A, 17W(13V/4Ω)	12-SILP	
AN 7161 N	LIN-IC	2x NF-E, 26V, 4A, 23W(15V/4Ω), BTL	12-SILP	
AN 7171 K	LIN-IC	2x NF-E, 24V, 6A, 2x>9W(13V/4Ω), ON=+5V	16-SQL	
AN 7178	LIN-IC	2x NF-E, 18V, 4A, 2x5,7W(12V/3Ω)	12-SIP	
AN 7222(N)	LIN-IC	AM/FM-ZF, AFC, AGC, Demod.	18-DIP	
AN 7311*	LIN-IC	Auto-/Car-Radio, 2x NF-V, 18V	9-SIP	
BA 159	Si-Di	S, TV-Clamping, 1000V, 0,4A, <300ns	31a	
BA 222*	LIN-IC	CR Timer, Ucc=4,5...16V	7-SIP	
BA 401*	LIN-IC	TV-Ton-ZF, FM-ZF	5-SIP	
BA 402*	LIN-IC	TV-Ton-ZF, FM-ZF	7-SIP	
BA 514*	LIN-IC	NF-V+E, 2W(9V/4Ω)	8-SIL	
BA 527*	LIN-IC	NF-E, 0,8W(6V/4Ω)	9-SIP	
BA 532	LIN-IC	NF-E, 5,8W(13V/4Ω)	10-SIL	
BA 1310*	LIN-IC	FM-Multiplex Stereo-Decoder	14-DIP	
BA 1320*	LIN-IC	FM-Multiplex Stereo-Decoder, Ucc=12V	16-DIP	
BA 1330*	LIN-IC	=BA 1320: Ucc=3,6...6V	16-DIP	
BA 5102 A	LIN-IC	VC, Audio-A/W-Verst., Logic	18-DIP	
BA 5410	LIN-IC	2x NF-E, 20V, 2x5,2W(12V/3Ω)	10-SIL	
BA 6109	LIN-IC	VC, Motor-Tr(reversible), 18V, 0,8A	10-SIL	
BA 6209	LIN-IC	VC, Motor-Tr(reversible), 18V, 1,6A	10-SIL	
BA 6222	LIN-IC	VC, Motor-Tr(reversible), 18V, 2,2A	10-SIL	
BA 6247	LIN-IC	2x Motor-Tr(reversible), 18V, 2W	10-SIL	
BAT 42	Si-Di	Schottky-Di, 30V, 0,2A, <5ns	31a	
BC 141	Si-N	NF-Tr/E, 100V, 1A, 0,75W, >50MHz	2a	BC 161
BC 161	Si-P	NF-Tr/E, 60V, 1A, 0,75W, >50MHz	2a	BC 141
BC 327	Si-P	NF-Tr, 50V, 0,8A, 0,625W, 100MHz	7a	BC 337
BC 337	Si-N	NF-Tr, 50V, 0,8A, 0,625W, 100MHz	7a	BC 327
BC 546	Si-N	Uni, 80V, 0,1A, 0,5W, 300MHz	7a	BC 556
BC 550	Si-N	=BC 547: ra	7a	BC 560
BC 556	Si-P	Uni, 80V, 0,1A, 0,5W, 150MHz	7a	BC 546
BC 560	Si-P	=BC 557: ra	7a	BC 550
BC 639	Si-N	NF-Tr/E, 100V, 1A, 0,8W, 130MHz	7c	BC 640
BC 640	Si-P	NF-Tr/E, 100V, 1A, 0,8W, 50MHz	7c	BC 639
BC 807(SMD)	Si-P	SMD, NF-Tr, 50V, 0,5A, 100MHz	35a	BC 817
BC 817(SMD)	Si-N	SMD, NF-Tr, 50V, 0,5A, 200MHz	35a	BC 807
BC 846(SMD)	Si-N	SMD, Uni, 80V, 0,1A, 300MHz	35a	BC 856
BC 848 C(SMD)	Si-N	SMD, Uni, 30V, 0,1A, 300MHz	35a	BC 858C
BC 850 C(SMD)	Si-N	SMD, Uni, ra, 50V, 0,1A, 300MHz	35a	BC 860
BC 856 B(SMD)	Si-P	SMD, Uni, 80V, 0,1A, 150MHz	35a	BC 846
BC 858 C(SMD)	Si-P	SMD, Uni, 30V, 0,1A, 150MHz	35a	BC 848C
BC 860 B(SMD)	Si-P	SMD, Uni, ra, 50V, 0,1A, 150MHz	35a	BC 850
BC 879	Si-N-Darl+Di	NF/S, 100V, 1A, 0,8W, 200MHz, B>2000	7c	BC 880
BC 880	Si-P-Darl+Di	NF/S, 100V, 1A, 0,8W, 200MHz, B>2000	7c	BC 879
BD 139	Si-N	NF-L, 100V, 1,5A, 12,5W(Tc=45°),>50MHz	14h	BD 140
BD 140	Si-P	NF-L, 100V, 1,5A, 12,5W(Tc=45°),>50MHz	14h	BD 139
BD 189	Si-N	NF-L, 70V, 4A, 40W, 2MHz	14h	BD 190
BD 190	Si-P	NF-L, 70V, 4A, 40W, >2MHz	14h	BD 189
BD 237	Si-N	NF-L, 100V, 2A, 25W, >3MHz	14h	BD 238
BD 238	Si-P	NF-L, 100V, 2A, 25W, >3MHz	14h	BD 237
BD 243 C	Si-N	NF-L, 115V, 6A, 65W, >3MHz	17j	BD 244 C
BD 244 C	Si-P	NF-L, 115V, 6A, 65W, >3MHz	17j	BD 243 C
BD 245 C	Si-N	NF-L, 115V, 10A 80W >3MHz	18j	BC 246 C