

BC153	TO-106	40	40	5	20	40	50 50	0.1 1	5 5	0.25	10							3	4	62
BC154	TO-106	40	40	5	10	40	160 160	0.1 1	5 5	0.25	10							2.5	4	62
BC160	TO-39	40	40	5	100	40	40	250	100	1	1	1.7*	1A	30	50	50	650		19	67
BC160-6	TO-39	40	40	5	100	40	40	100	100	1	1	1.7*	1A	30	50	50	650		19	67
BC160-10	TO-39	40	40	5	100	40	63	160	100	1	1	1.7*	1A	30	50	50	650		19	67
BC160-16	TO-39	40	40	5	100	40	100	250	100	1	1	1.7*	1A	30	50	50	650		19	67
BC161	TO-39	60	60	5	100	60	40	250	100	1	1	1.7*	1A	30	50	50	650		19	67
BC161-6	TO-39	60	60	5	100	60	40	100	100	1	1	1.7*	1A	30	50	50	650		19	67
BC161-10	TO-39	60	60	5	100	60	63	160	100	1	1	1.7*	1A	30	50	50	650		19	67
BC161-16	TO-39	60	60	5	100	60	100	250	100	1	1	1.7*	1A	30	50	50	650		19	67
BC167A	TO-92 (74)	45	6	15	50	125	260*	2	5	0.2 0.6	10 100	4.5	150	10				10	1	04
BC167B	TO-92 (74)	45	6	15	50	240	500*	2	5	0.2 0.6	10 100	4.5	150	10				10	1	04
BC168A	TO-92 (74)	20	5	15	30	125	260*	2	5	0.2 0.6	10 100	4.5	150	10				10	1	04
BC168B	TO-92 (74)	20	5	15	30	240	500*	2	5	0.2 0.6	10 100	4.5	150	10				10	1	04
BC168C	TO-92 (74)	20	5	15	30	450	900*	2	5	0.2 0.6	10 100	4.5	150	10				10	1	04
BC169B	TO-92 (74)	20	5	15	30	240	500*	2	5	0.2 0.6	10 100	4.5	150	10				4 4 4	1 2	04
BC169C	TO-92 (74)	20	5	15	30	450	900*	2	5	0.2 0.6	10 100	4.5	150	10				4 4 4	1 2	04
BC170A	TO-106	20	20	5	100	15	35 30	100 30	1 1	0.25 0.4	1 30	0.7	1 30							04
BC170B	TO-106	20	20	5	100	15	80 60	250 30	1 1	0.25 0.4	1 30	0.7	1 30							04
BC170C	TO-106	20	20	5	100	15	200 150	600 30	1 1	0.25 0.4	1 30	0.7	1 30							04
BC171	TO-106	45	5	15	45	125	500*	2	5	0.25 0.6	10 100			150	10			6	1	04
BC171A	TO-106	45	5	15	45	40 125	260* 2	0.01 5	5 5	0.25 0.6	10 100	0.55	0.7* 2					6	1	04
<p>Test Conditions:</p> <ol style="list-style-type: none"> <li><math>I_C = 200 \mu A, V_{CE} = 5V, R_S = 2 k\Omega, f = 1 kHz, BW = 200 Hz</math></li> <li><math>I_C = 200 \mu A, V_{CE} = 5V, R_S = 2 k\Omega, WB</math></li> <li><math>I_C = 30 \mu A, V_{CE} = 5V, R_S = 10 k\Omega, f = 1 kHz, BW = 200 Hz</math></li> <li><math>I_C = 20 \mu A, V_{CE} = 5V, R_S = 10 k\Omega, f = 1 kHz, BW = 150 Hz</math></li> <li><math>I_C = 200 \mu A, V_{CE} = 5V, R_G = 2 k\Omega, f = 20 Hz to 15 kHz</math></li> <li><math>I_C = 100 \mu A, V_{CE} = 5V, R_G = 2 k\Omega, f = 10 Hz to 10 kHz</math></li> <li><math>I_C = 50 \mu A, V_{CE} = 5V, R_S = 10 k\Omega, BW = 10 Hz to 15 kHz</math></li> <li><math>I_C = 50 \mu A, V_{CE} = 5V, R_S = 10 k\Omega, f = 1 kHz, BW = 200 Hz</math></li> <li><math>I_C = 200 \mu A, V_{CE} = 2V, R_S = 2 k\Omega, f = 1 kHz, BW = 200 Hz</math></li> <li><math>I_C = 10 \mu A, V_{CE} = 5V, R_S = 10 k\Omega, WB</math></li> <li><math>I_C = 150 mA, V_{CE} = 10V, I_{B1} = I_{B2} = 15 mA</math></li> <li><math>I_C = 150 mA, I_{B1} = I_{B2} = 15 mA</math></li> <li><math>I_C = 10 mA, I_{B1} = 3 mA, I_{B2} = 1 mA</math></li> <li><math>I_C = 100 mA, I_{B1} = 40 mA, I_{B2} = 20 mA</math></li> <li><math>V_{CC} = 10V, I_C = 100 mA, I_{B1} = I_{B2} = 10 mA</math></li> <li><math>I_C = 150 mA, V_{CE} = 6V, I_{B1} = I_{B2} = 15 mA</math></li> <li><math>I_C = 10 mA, I_{B1} = 1 mA, I_{B2} = -1 mA</math></li> <li><math>I_C = 300 mA, I_{B1} = I_{B2} = 30 mA, V_{CC} = 25V</math></li> <li><math>V_{CC} = 20V, I_C = 100 mA, I_{B1} = I_{B2} = 5 mA</math></li> </ol>																				