

BCP 48	Si-P-Darl	=BCV 46: 1,5W	≈39°j	-	
BCP 49	Si-N-Darl	=BCV 47: 1,5W	≈39°j	-	
BCP 51	Si-P	=BCX 51: 1,5W	≈39°j	-	
BCP 52	Si-P	=BCX 52: 1,5W	≈39°j	-	
BCP 53	Si-P	=BCX 53: 1,5W	≈39°j	-	
BCP 54	Si-N	=BCX 54: 1,5W	≈39°j	-	
BCP 55	Si-N	=BCX 55: 1,5W	≈39°j	-	
BCP 56	Si-N	=BCX 56: 1,5W	≈39°j	-	
BCP 68	Si-N	=BCX 68: 1,5W	≈39°j	-	
BCP 69	Si-P	=BCX 69: 1,5W	≈39°j	-	
BCR 3 AM-10	Triac	500V, 3A(Tc=71°), Igt<30mA	13j	(TAG 232-600)	17j 4
BCR 3 AM-12	Triac	600V, 3A(Tc=71°), Igt<30mA	13j	(TAG 232-600)	17j 4
BCR 3 AM-4	Triac	200V, 3A(Tc=71°), Igt<30mA	13j	(TAG 232-600)	17j 4
BCR 3 AM-8	Triac	400V, 3A(Tc=71°), Igt<30mA	13j	(TAG 232-600)	17j 4
BCR 6 AM-10	Triac	500V, 6A(Tc=103°), Igt<30mA	17j	(TAG 232-600)	17j 7
BCR 6 AM-12	Triac	600V, 6A(Tc=103°), Igt<30mA	17j	(TAG 232-600)	17j 7
BCR 6 AM-4	Triac	200V, 6A(Tc=103°), Igt<30mA	17j	(TAG 232-600)	17j 7
BCR 6 AM-6	Triac	300V, 6A(Tc=103°), Igt<30mA	17j	(TAG 232-600)	17j 7
BCR 6 AM-8	Triac	400V, 6A(Tc=103°), Igt<30mA	17j	(TAG 232-600)	17j 7
BCR 108	Si-N+R	SMD, 50V, 0,1A, Rb=2,2kΩ, Rbe=47kΩ	35a	-	
BCR 112	Si-N+R	SMD, 50V, 0,1A, Rb=4,7kΩ, Rbe=4,7kΩ	35a	-	
BCR 119	Si-N+R	SMD, 50V, 0,1A, Rb=4,7kΩ, Rbe=0	35a	-	
BCR 133	Si-N+R	SMD, 50V, 0,1A, Rb=10kΩ, Rbe=10kΩ	35a	-	
BCR 135	Si-N+R	SMD, 50V, 0,1A, Rb=10kΩ, Rbe=47kΩ	35a	-	
BCR 141	Si-N+R	SMD, 50V, 0,1A, Rb=22kΩ, Rbe=22kΩ	35a	-	
BCR 142	Si-N+R	SMD, 50V, 0,1A, Rb=22kΩ, Rbe=47kΩ	35a	-	
BCR 146	Si-N+R	SMD, 50V, 0,1A, Rb=47kΩ, Rbe=22kΩ	35a	-	
BCR 148	Si-N+R	SMD, 50V, 0,1A, Rb=47kΩ, Rbe=47kΩ	35a	-	
BCR 183	Si-P+R	SMD, 50V, 0,1A, Rb=10kΩ, Rbe=10kΩ	35a	-	
BCR 185	Si-P+R	SMD, 50V, 0,1A, Rb=10kΩ, Rbe=47kΩ	35a	-	
BCR 191	Si-P+R	SMD, 50V, 0,1A, Rb=22kΩ, Rbe=22kΩ	35a	-	
BCR 192	Si-P+R	SMD, 50V, 0,1A, Rb=22kΩ, Rbe=47kΩ	35a	-	
BCR 198	Si-P+R	SMD, 50V, 0,1A, Rb=47kΩ, Rbe=47kΩ	35a	-	
BCV 26	Si-P-Darl	SMD, 40V, 0,5A, 200MHz, B>20000	35a	-	
BCV 27	Si-N-Darl	SMD, 40V, 0,5A, 200MHz, B>20000	35a	-	
BCV 28	Si-P-Darl	=BCV 26:	39b	-	
BCV 29	Si-N-Darl	=BCV 27:	39b	-	
BCV 46	Si-P-Darl	=BCV 26: 80V	35a	-	
BCV 47	Si-N-Darl	=BCV 27: 80V	35a	-	
BCV 48	Si-P-Darl	=BCV 46:	39b	-	
BCV 49	Si-N-Darl	=BCV 47:	39b	-	
BCV 71	Si-N	NF/S, 80V, 0,1A, 300MHz, B=110...220	35a	BC 846	35a
BCV 71 R	Si-N	=BCV 71:	35d	-	
BCV 72	Si-N	=BCV 71: B=200...450	35a	BC 846	35a
BCV 72 R	Si-N	=BCV 72:	35d	-	
BCW 10	Si-N	NF, 25V, 0,5A(ss), 0,3W, >150MHz	40e	BC 337	7a
BCW 11	Si-P	NF, 25V, 0,5A(ss), 0,3W, >150MHz	40e	BC 327	7a
BCW 12	Si-N	=BCW 10: 35V	40e	BC 337	7a
BCW 13	Si-P	=BCW 11: 35V	40e	BC 327	7a
BCW 14	Si-N	=BCW 10: 35V	40e	BC 337	7a
BCW 15	Si-P	=BCW 11: 35V	40e	BC 327	7a
BCW 16	Si-N	=BCW 10: 45V	40e	BC 337	7a
BCW 17	Si-P	=BCW 11: 45V	40e	BC 327	7a