

Typ type	Art device	Bild figure	Ersatztyp replacement	Bild figure	Typ type	Art device	Bild figure	Ersatztyp replacement	Bild figure
TD 482	Si-Di	31a	1N4148	31a	TI 3031	Ge-P	23a	AL 102	23a
TD 490	Si-Di	31a	BA 159	31a	TIC 39 A...Y	50Hz-Thy	2a	TIC 106 M	17e
TD 702	Si-Di	31a	BA 159	31a	TIC 44	50Hz-Thy	7a	BRX 49	7a
TD 861	Si-Di	31a	1N4148	31a	TIC 45	50Hz-Thy	7a	BRX 49	7a
TD 1011	Si-P	7c	BC 556	7a	TIC 46	50Hz-Thy	7a	BRX 49	7a
TD 1095	Si-Di	31a	1N4148	31a	TIC 47	50Hz-Thy	7a	BRX 49	7a
TD 960016-1	Ge-Di	31a	AA 133	31a	TIC 60	50Hz-Thy	7n	BRX 49	7a
TE 00291	Si-N		MJE 340	14h	TIC 61	50Hz-Thy	7n	BRX 49	7a
TE 404	Si-N	15j	BD 243 C	17j	TIC 62	50Hz-Thy	7n	BRX 49	7a
TE 441	Si-N	14h	BF 459	14h	TIC 63	50Hz-Thy	7n	BRX 49	7a
TE 00671	Si-P-Darl	23a	MJ 2501	23a	TIC 64	50Hz-Thy	7n	BRX 49	7a
TE 01372	Si-N		BC 546	7a	TIC 101 A...Y	50Hz-Thy	17r	TIC 106 M	17e
TEO 1088	Si-N-Darl	17j	BD 901	17j	TIC 102 A...Y	50Hz-Thy	17r	(TAB 626/600)	17e
TED 1089	Si-P-Darl	17j	BD 902	17j	TIC 106 A	50Hz-Thy	17e	TIC 106 M	17e
TED 1299	Si-N	23a	BD 317	23a	TIC 106 B	50Hz-Thy	17e	TIC 106 M	17e
TEO 1300	Si-P	23a	BD 318	23a	TIC 106 C	50Hz-Thy	17e	TIC 106 M	17e
TF 65	Ge-P	2a	AC 151	2a	TIC 106 D	50Hz-Thy	17e	TIC 106 M	17e
TF 66	Ge-P	2a	AC 188 K	3a	TIC 106 E	50Hz-Thy	17e	TIC 106 M	17e
TF 78	Ge-P	2a	(AD 162)	22a	TIC 106 F	50Hz-Thy	17e	TIC 106 M	17e
TF 80	Ge-P		(AL 102)	23a	TIC 106 M	50Hz-Thy	17e	TIC 106 M	17e
TF 286	Si-N	2a	BC 141	2a	TIC 106 N	50Hz-Thy	17e	-	-
TF 1095	Si-Di	31a	1N4148	31a	TIC 106 S	50Hz-Thy	17e	-	-
TI 143	Si-N		BF 199	7d	TIC 106 Y	50Hz-Thy	17e	TIC 106 M	17e
TI 144	Si-N		BF 199	7d	TIC 107 A...Y	50Hz-Thy	17e	TIC 106 M	17e
TI 400	Ge-P		AF 239 S	5g	TIC 108 A	50Hz-Thy	17e	(TIC 106 M)	17e
TI 401	Ge-P		AF 239 S	5g	TIC 108 B	50Hz-Thy	17e	(TIC 106 M)	17e
TI 402	Ge-P		AF 239 S	5g	TIC 108 C	50Hz-Thy	17e	(TIC 106 M)	17e
TI 403	Ge-P		AF 239 S	5g	TIC 108 D	50Hz-Thy	17e	(TIC 106 M)	17e
TI 650 C	N-FET	7e	BF 245	7f	TIC 108 E	50Hz-Thy	17e	(TIC 106 M)	17e
TI 704 C	N-FET	7e	BF 245	7f	TIC 108 F	50Hz-Thy	17e	(TIC 106 M)	17e
TI 908	Si-N		BC 337	7a	TIC 108 M	50Hz-Thy	17e	(TIC 106 M)	17e
TI 3027	Ge-P	23a	AL 102	23a	TIC 108 N	50Hz-Thy	17e	-	-
TI 3028	Ge-P	23a	AL 102	23a	TIC 108 S	50Hz-Thy	17e	-	-
TI 3029	Ge-P	23a	AL 102	23a	TIC 108 Y	50Hz-Thy	17e	(TIC 106 M)	17e
TI 3030	Ge-P	23a	AL 102	23a	TIC 116 A...M	50Hz-Thy	17e	TAB 626/600	17e
					TIC 122 B...F	50Hz-Thy	17e	-	-
					TIC 126 A...M	50Hz-Thy	17e	-	-
					TIC 163 A...F	50Hz-Thy	18e	-	-