

2 SC 1005 A	Si-N	=2SC1005: 1400/600V	23a	BU 208 A	23a
2 SC 1006	Si-N	Uni, ra, 50V, 0,03A, 0,3W, 90MHz	2a	BC 550	7a
2 SC 1007	Si-N	Uni, 60V, 0,2A, 0,3W, 250MHz, 95/240ns	2a	BC 546	7a
2 SC 1008	Si-N	Uni, 80V, 0,7A, 0,8W, 75MHz, 120/300ns	2a	BC 141	2a
2 SC 1008 A	Si-N	=2SC1008: 100V	2a	BC 141	2a
2 SC 1009(A)	Si-N	SMD, HF-ra, 50V, 0,05A, 250MHz	35a	BC 846	35a
2 SC 1010	Si-N	Uni, ra, 50V, 0,03A, 0,3W, 90MHz	2a	BC 550	7a
2 SC 1012(Z)	Si-N	Vid, 165V, 0,06A, 0,75W, >80MHz	2a	BF 259	2a
2 SC 1012 A(AZ)	Si-N	=2SC1012: 250V	2a	BF 259	2a
2 SC 1013	Si-N	NF/S-L, 35V, 1,5A, 7W, 70MHz	13n	(2SC4135)	30j
2 SC 1014	Si-N	=2SC1013: 50V	13n	(2SC4135)	30j
2 SC 1015	Si-N	UHF-L, 40V, 3A, PQ=14W(450MHz)	55r	-	-
2 SC 1016	Si-N	UHF-Tr/E, 35V, 0,5A, PQ=1,3W(500MHz)	51r	-	-
2 SC 1017	Si-N	AM-E, 75V, 1A, PQ=0,06W(27MHz)	13n	-	-
2 SC 1018	Si-N	AM-E, 75V, 1A, PQ=1,4W(27MHz)	13n	-	-
2 SC 1019	Si-N	UHF-L, 60V, 4A, PQ=28W(500MHz)	60c	-	-
2 SC 1020	Si-N	UHF-L, 60V, 8A, PQ=45W(500MHz)	60c	-	-
2 SC 1021	Si-N	VHF-L, 60V, 6A, PQ=45W(90MHz)	55r	-	-
2 SC 1022	Si-N	VHF-L, 60V, 6A, PQ=45W(150MHz)	55r	-	-
2 SC 1023	Si-N	HF, 25V, 25mA, 200MHz	7c	BF 255	7d
2 SC 1024	Si-N	TV-VA, 60V, 3A, 25W, 8MHz	22a	BD 243 C	17j
2 SC 1025	Si-N	S-L, TV-HA, 200V, 3A, 25W, 8MHz	22a	BU 406	17j
2 SC 1026	Si-N	HF, 25V, 25mA, 200MHz	7c	BF 255	7d
2 SC 1027	Si-N	S-L, 250/80V, 6A, 50W	23a	BU 608	23a
2 SC 1030	Si-N	NF-L, 150/80V, 6A, 50W, 10MHz	23a	2SC3263	18j
2 SC 1031	Si-N	S-L, 300/300V, 2A, 30W, 15MHz, <5/15µs	22a	BU 406	17j
2 SC 1032	Si-N	HF, 25V, 25mA, 0,15W, 200MHz	7c	BF 255	7d
2 SC 1033	Si-N	Nix, Vid, 200/150V, 25mA, 0,3W, 150MHz	2a	BF 420 A	7c
2 SC 1033 A	Si-N	=2SC1033: 250/200V	2a	BF 420 A	7c
2 SC 1034	Si-N	S-L, TV-HA, 1100V, 1A, 25W, 5MHz	22a	-	-
2 SC 1035	Si-N	VHF/UHF-V, ra, 30V, 0,02A, 700MHz	5g	2SC2570 A	7f
2 SC 1036	Si-N	VHF/UHF-M/O, 30V, 0,02A, 700MHz	5g	2SC2570 A	7f
2 SC 1044	Si-N	VHF/UHF, ra, 1000MHz	5g	2SC2570 A	7f
2 SC 1045	Si-N	TV-VA, 1000/550V, 1A, 25W	23a	(BU 208 A)	23a
2 SC 1046	Si-N	TV-HA, 1000/400V, 3A, 25W	23a	BU 208 A	23a
2 SC 1046 N	Si-N	=2SC1046: 1200/400V	23a	BU 208 A	23a
2 SC 1047	Si-N	AM/FM, 30V, 20mA, 650MHz	7c	BF 255	7d
2 SC 1048	Si-N	Vid, 200V, 0,05A, 0,6W, 120MHz	2a	BF 259	2a
2 SC 1050	Si-N	S-L, TV-VA, 300/300V, 1A, 40W, 5MHz	23a	BU 608	23a
2 SC 1051	Si-N	NF/S-L, 150/100V, 7A, 60W, 8MHz	23a	2SC3263	18j
2 SC 1051 L	Si-N	=2SC1051: 100/80V	23a	BD 245 C	18j
2 SC 1052	Si-N	S, 75V, 1A, 0,8W, <50/70ns	2a	-	-
2 SC 1053	Si-N	S, 75V, 0,7A, 0,8W, <40/60ns	2a	-	-
2 SC 1054	Si-N	VHF, ra, 35V, 0,05A, 700MHz	5g	2SC2570 A	7f
2 SC 1055(H)	Si-N	S-L, 130/80V, 7A, 25W, 25(H=14)MHz	22a	BU 406	17j
2 SC 1056	Si-N	Vid, 260/260V, 0,1A, 0,75W, 180MHz	2a	BF 259	2a
2 SC 1059	Si-N	NF/Vid-L, 300/300V, 0,15A, 8W(Tc=70°)	22a	2SC1505	17j
2 SC 1060	Si-N	NF/S-L, 50V, 3A, 25W, 8MHz	17j	BD 243 C	17j
2 SC 1061(K)	Si-N	NF/S-L, 50V, 3A, 25W, 8MHz	17j	BD 243 C	17j
2 SC 1062	Si-N	S, Vid, 200/200V, 0,1A, 0,7W, 35MHz	2a	BF 259	2a
2 SC 1063	Si-N	S, 10V, 1A, 0,75W, <60/100ns	2a	-	-
2 SC 1064	Si-N	S, 60V, 1A, 0,8W	2a	-	-
2 SC 1065	Si-N	S, 90V, 1A, 0,8W, 400MHz	2a	-	-
2 SC 1066	Si-N	UHF, 20V, 25mA, 800MHz	2a	2SC2570 A	7f
2 SC 1067	Si-N	VHF, 35V, 0,05A, 500MHz	2a	BF 198, BF 199	7d
2 SC 1069	Si-N	S, 100V, 1A, 0,8W, <60/120ns	2a	-	-