

2 SK 979	Sak	MOS-N-FET-e	VFET, 450/20V, 10A, 120W, on=0,5Ω(5A), <160/250ns	18p	TO-3P	2SK896, 2SK1488, 2SK1752...53, 2SK1785,++
2 SK 980	Hit	N-FET	SMD, Video-Frequ., 12V, 40mA, Idss=8...32mA Up=0,1...2,5V	35f	SOT-23	-
2 SK 981(A)	Mat	MOS-N-FET-e	=2SK762(A): 15W	=30c	(I Type)	-
2 SK 982	Tos	MOS-N-FET-e	Interface, S, 60/20V, 0,2/0,8A, 0,4W, on<1Ω(50mA) 14/75ns	7c	TO-92	BS 170, BST 170, 2SK422...423, 2SK1336,++
2 SK 987	Mit	MOS-N-FET-e	VFET, 500/30V, 5A, 40W, on<1,6Ω(3A)	17c	SOT-186	2SK1232, 2SK1351, 2SK1608, 2SK1627,++
2 SK 988	Mit	MOS-N-FET-e	VFET, 500/30V, 10A, 45W, on<0,9Ω(5A)	17c	SOT-186	2SK2364
2 SK 989	Mit	MOS-N-FET-e	VFET, 500/30V, 10A, 120W, on<0,9Ω(5A), 100/150ns	=18p	(TO-3PFM)	2SK1488, 2SK1753, 2SK1785, 2SK2362,++
2 SK 990	Mit	MOS-N-FET-e	VFET, 500/30V, 15A, 150W, on<0,65Ω(8A), 160/250ns	=18p	(TO-3PFM)	2SK1610, 2SK1678, 2SK1745, 2SK1757,++
2 SK 991	Nec	MOS-N-FET-e*	VFET, LogL, 100/15V, ±4/8A, 35W, <0,5Ω(2A), 46/220ns	17p	TO-220	2SK702, 2SK1474
2 SK 992	Nec	MOS-N-FET-e*	=2SK991: Iso, 30W	17c	SOT-186	BUK 542-100, 2SK703, 2SK1260, 2SK1265
2 SK 993	Nec	MOS-N-FET-e*	VFET, LogL, 60/15V, ±8/16A, 35W, <0,25Ω(4A), 80/230ns	17p	TO-220	BUK 552-100, 2SK1114, 2SK2175
2 SK 994	Nec	MOS-N-FET-e*	=2SK993: Iso, ±7/14A, 30W	17c	SOT-186	BUK 542-60, 2SK1033, 2SK1256, 2SK1344,++
2 SK 995	Mat	MOS-N-FET-e	FREDFET, 550/20V, 5/10A, 60W, <1,8Ω(3A), 50/365ns	16c	(TOP-3F)	BUK 627-600
2 SK 996	Mat	MOS-N-FET-e	VFET, 600/20V, 4/8A, 50W, on<1,8Ω(2A), 40/360ns	17c	SOT-186	2SK1118, 2SK1404, 2SK1637, 2SK2044,++
2 SK 997	Nec	N-FET	C-Mic Inp, 20V, 10mA, Idss=0,1...0,5mA, Up=0,1...1	40a	(SST)	-
2 SK 998	Nec	N-FET	UHF, 20V, 35mA, Idss=8...32mA, Up=0,35...2,2V	7d	TO-92	-
2 SK 1000	Nec	N-FET	AM Tuner, 22V, 50mA, Idss=10...50mA, Up<2,5V	40a	(SST)	-
2 SK 1001	Nec	N-FET	=2SK1000: SMD	35f	SOT-23	-
2 SK 1002	Nec	N-FET	C-Mic, 20V, 10mA, Idss=0,12...0,5mA, Up<1V, Ur<3μV	40a	(SST)	-
2 SK 1006	Fjd	MOS-N-FET-e	VFET, 450/30V, 5A, 40W, on<1,6Ω(2,5A), 60/130ns	=15c		2SK1231...32, 2SK1351, 2SK1608, 2SK1626++
2 SK 1007	Fjd	MOS-N-FET-e	=2SK1006: 60W	17p	TO-220	BUZ 41A...42, 2SK893, 2SK1156, 2SK1246,++
2 SK 1008	Fjd	MOS-N-FET-e	=2SK1006: 500/30V, 4,5A, 60W, on<2,2Ω(2,5A)	17p	TO-220	BUZ 41A...42, 2SK893, 2SK1156, 2SK1246,++
2 SK 1009	Fjd	MOS-N-FET-e	VFET, 450/30V, 7A, 80W, on<1,3Ω(3A), 70/130ns	17p	TO-220	IRF 840, IRF 842, 2SK894, 2SK1495...96,++
2 SK 1010	Fjd	MOS-N-FET-e	=2SK1009: 500/30V, 6A, on<1,6Ω(3A), 70/130ns	17p	TO-220	IRF 840, IRF 842, 2SK894, 2SK1496,++
2 SK 1011	Fjd	MOS-N-FET-e	VFET, 450/30V, 10A, 100W, on<0,65Ω(5A), 110/240ns	18p	TO-3P	BUZ 339, 2SK896, 2SK1488, 2SK1785,++
2 SK 1012	Fjd	MOS-N-FET-e	=2SK1011: 500/30V, on<0,9Ω(5A)	18p	TO-3P	BUZ 339, 2SK896, 2SK1488, 2SK1785,++
2 SK 1013	Fjd	MOS-N-FET-e	VFET, 450/30V, 13A, 125W, on<0,8Ω(6A), 140/240ns	18p	TO-3P	2SK1610, 2SK1678, 2SK1745, 2SK1757,++
2 SK 1014	Fjd	MOS-N-FET-e	=2SK1013: 500/30V, 12A, on<0,74Ω(6A)	18p	TO-3P	2SK1610, 2SK1678, 2SK1745, 2SK1757,++
2 SK 1015	Fjd	MOS-N-FET-e	VFET, 450/30V, 18A, 125W, <0,45Ω(8A), 170/230ns	18p	TO-3P	2SK1517...18, 2SK1499...1500, 2SK2057,++
2 SK 1016	Fjd	MOS-N-FET-e	=2SK1015: 500/30V, 15A, on<0,55Ω(8A)	18p	TO-3P	2SK899, 2SK1678, 2SK1745, 2SK1757,++
2 SK 1017	Fjd	MOS-N-FET-e	VFET, 450/30V, 20A, 150W, on<0,35Ω(10A), 250/490ns	18p	TO-3P	2SK1517...18, 2SK1409, 2SK1680, 2SK2057,++
2 SK 1018	Fjd	MOS-N-FET-e	=2SK1017: 500/30V, 18A, on<0,45Ω(10A), 250/490ns	18p	TO-3P	2SK1518, 2SK1498, 2SK1680, 2SK2057,++
2 SK 1019	Fjd	MOS-N-FET-e	VFET, 450/30V, 35A, 300W, on<0,2Ω(15A), 360/900ns	77p	TOP-3L	2SK1519...20, 2SK1628...29, 2SK1971,++
2 SK 1020	Fjd	MOS-N-FET-e	=2SK1019: 500/30V, 30A, on<0,25Ω(15A)	77p	TOP-3L	2SK1520, 2SK1629, 2SK1971
2 SK 1021	Fjd	MOS-N-FET-e	VFET, 800/30V, 3A, 60W, on<6Ω(1,5A), 85/160ns	17p	TO-220	BUZ 81, 2SK1501, 2SK1639, 2SK1643,++
2 SK 1022	Fjd	MOS-N-FET-e	=2SK1021: 900/30V, 2,5A, on<7,3Ω(1,5A)	17p	TO-220	BUK 456-1000, 2SK1601, 2SK1638, 2SK1793,++
2 SK 1023	Fjd	MOS-N-FET-e	VFET, 800/30V, 4A, 60W, on<4,5Ω(2A), 95/170ns	17p	TO-220	BUZ 81, 2SK1501, 2SK1639, 2SK1643,++
2 SK 1024	Fjd	MOS-N-FET-e	=2SK1023: 900V, 3,5A	17p	TO-220	2SK1457, 2SK1501, 2SK1639, 2SK1643,++
2 SK 1025	Mit	MOS-N-FET-e	VFET, 50/30V, 20A, 45W, on<0,08Ω(10A)	17c	SOT-186	BUK 445-50, BUZ 11F, 2SK1095, 2SK1420,++
2 SK 1026	Mit	MOS-N-FET-e	VFET, 250/30V, 20A, 150W, on<0,26Ω(10A)	=18p	(TO-3PFH)	2SK944, 2SK1641, 2SK1673...74, 2SK2075,++
2 SK 1027	Mit	MOS-N-FET-e	=2SK1026: 300/30V, on<0,29Ω(10A)	=18p	(TO-3PFH)	2SK1409, 2SK1517, 2SK1674, 2SK1680,++
2 SK 1029	Tos	MOS-N-FET-e	VFET, 500/20V, ±10/20A, 200W, <0,5Ω(10A), 450/400ns	77p	TOP-3L	2SK694
2 SK 1030	Mat	MOS-N-FET-e	VFET, 800/20V, 3A, 50W, on<5Ω(2A), 55/40ns	17c	SOT-186	2SK1356, 2SK1460, 2SK1995
2 SK 1030 A	Mat	MOS-N-FET-e	=2SK1030: 900/20V	17c	SOT-186	2SK1356, 2SK1460, 2SK1995
2 SK 1031	Hit	N-FET	SMD, LF, 50V, 10mA, Idss=0,6...6,5mA, Up=0,4...5V	35f	SOT-23	-
2 SK 1032	Mat	MOS-N-FET-e	VFET, 800/20V, 8A, 120W, on<1,7Ω(5A), 110/120ns	18p	TO-3P	2SK684, 2SK1342, 2SK1358, 2SK1502, ++
2 SK 1032 A	Mat	MOS-N-FET-e	=2SK1032: 900/20V	18p	TO-3P	2SK1342, 2SK1358, 2SK1462, 2SK1614, ++
2 SK 1033	Mat	MOS-N-FET-e	VFET, LogL, 60/20V, 12A, 45W, <0,1Ω(6A), 90/540ns	17c	SOT-186	2SK1093, 2SK1256, 2SK1305...06, 2SK1344,++
2 SK 1034	Mat	MOS-N-FET-e	VFET, LogL, 100/20V, 15A, 45W, <0,18Ω(6A), 50/385ns	17c	SOT-186	2SK1288, 2SK1306, 2SK1558
2 SK 1035	Mat	MOS-N-FET-e	VFET, LogL, 150/20V, 12A, 45W, <0,35Ω(6A), 50/420ns	17c	SOT-186	-
2 SK 1036	Mat	MOS-N-FET-e	VFET, 250/20V, 10/20A, 50W, on<0,3Ω(5A), 60/320ns	17c	SOT-186	2SK1762, 2SK2011, 2SK2426
2 SK 1037	Mat	MOS-N-FET-e	VFET, 250/20V, 50W	17c	SOT-186	-
2 SK 1038	Mat	MOS-N-FET-e	VFET, 400/20V, 5A, 50W, on<1,8Ω(3A)	17c	SOT-186	BUK 445-400, 2SK530, 2SK1377, 2SK1990,++
2 SK 1039	Mat	MOS-N-FET-e	VFET, 400/20V, 8A, 50W, on<1,4Ω(5A)	17c	SOT-186	2SK1566...67, 2SK1609, 2SK2116...17,++
2 SK 1040	Mat	MOS-N-FET-e	VFET, 400/20V, 10A, 100W, on<1Ω(5A)	16c(p)	(TOP-3F)	BUZ 326, BUZ 351, 2SK1488, 2SK1785,++
2 SK 1041	Mat	MOS-N-FET-e	VFET, 400/20V, 15A, 120W, on<0,55Ω(8A)			BUK 637-400, BUZ 323
2 SK 1042	Mat	MOS-N-FET-e	VFET, 400/20V, 20A, 130W, on<0,45Ω(10A)			2SK868
2 SK 1043	Nec	GaAs-N-FET-d	UHF...K-Band, 4V, Idss=12...60mA, Up=0,3...2V F<1,4/Gp=10dB(12GHz)	51(SGSD)	=SOT-173	-
2 SK 1044	Mit	MOS-N-FET-e	VFET, 800/30V, 5A, 150W, on<1,7Ω(2,5A), 80/270ns	=18c	(TO-3PFM)	2SK727, 2SK793, 2SK1461, 2SK1649...50,++
2 SK 1045	Mit	MOS-N-FET-e	=2SK1044: 900/30V, on<2Ω(2,5A)	=18c	(TO-3PFM)	2SK727, 2SK1341, 2SK1649...50, 2SK1794,++
2 SK 1046	Nec	GaAs-N-FET-d	UHF...K-Band, 4V, 70mA, Idss=15...70mA, Up=0,3...2V F<1,4/Gp=10dB(12GHz)	51(SGSD)	=SOT-173	-
2 SK 1047	Mit	MOS-N-FET-e	VFET, 250/30V, 20A, 150W, on<0,26Ω(10A)	=18c	(TO-3PFM)	2SK944, 2SK1673...74, 2SK1641, 2SK2075,++
2 SK 1048	Mit	MOS-N-FET-e	=2SK1047: 300/30V, on<0,29Ω(10A)	=18c	(TO-3PFM)	2SK868(A), 2SK1674
2 SK 1049	Mit	MOS-N-FET-e	VFET, 450/30V, 15A, 150W, on<0,65Ω(8A), 160/250ns	=18c	(TO-3PFM)	2SK1610, 2SK1678, 2SK1745, 2SK1757,++
2 SK 1050	Mit	MOS-N-FET-e	=2SK1050: 500/30V, on<0,78Ω(8A)	=18c	(TO-3PFM)	2SK1610, 2SK1678, 2SK1745, 2SK1757,++
2 SK 1051	Mit	MOS-N-FET-e	VFET, 50/30V, 40A, 120W, on<0,03Ω(20A)	=18c	(TO-3PFM)	BUZ 347...348, 2SK1124, 2SK2096, 2SK2233,++
2 SK 1052	Say	MOS-N-FET-e	VFET, 450/20V, 0,5/2A, 30W, on<7Ω(0,3A), 18/100ns	17p	TO-220	-
2 SK 1053	Say	MOS-N-FET-e	VFET, 450/20V, 1/4A, 40W, on<4,5Ω(0,5A), 19/95ns	17p	TO-220	-
2 SK 1056	Hit	MOS-N-FET-e*	VFET, 120/15V, 7A, 100W, 180/60ns	{2SJ160	18d,p(?)	(2SK405, 2SK413...414)
2 SK 1057	Hit	MOS-N-FET-e*	=2SK1056: 140/15V	{2SJ161	18d,p(?)	(2SK405, 2SK413...414)
2 SK 1058	Hit	MOS-N-FET-e*	=2SK1056: 160/15V	{2SJ162	18d,p(?)	(2SK400)
2 SK 1059(Z)	Nec	MOS-N-FET-e	VFET, 60/20V, ±5/20A, 20W, on<0,135Ω(3A), 50/140ns	30p	TO-251	2SK1112, 2SK1471, 2SK1719, 2SK1949
2 SK 1060(Z)	Nec	MOS-N-FET-e	=2SK1059: 100/20V, on<0,27Ω(3A)	30p	Z: TO-252	-
2 SK 1061	Tos	MOS-N-FET-e	=2SK982: 0,3W	{2SJ167	41c	2SK1474, 2SK1804, 2SK2016
2 SK 1062	Tos	MOS-N-FET-e	=2SK982: SMD	{2SJ168	35a	BS 170, BST 170, 2SK422...423, 2SK1336
2 SK 1063	Hit	MOS-N-FET-e*	=2SK559: 125W	23a	TO-3	BST 82, 2SK1848
2 SK 1064	Hit	MOS-N-FET-e*	=2SK560: 125W	23a	TO-3	2SK788, 2SK899, 2SK1610, 2SK1678, ++
2 SK 1065	Say	N-FET	=2SK968:	35e(2mm)	SOT-323	-
2 SK 1066	Say	N-FET	=2SK436:	35f(2mm)	SOT-323	-
2 SK 1067	Say	MOS-N-FET-d	=2SK543:	35e(2mm)	SOT-323	-
2 SK 1068	Say	N-FET	=2SK546: SMD	35f(2mm)	SOT-323	-
2 SK 1069	Say	N-FET	=2SK771: SMD	35f(2mm)	SOT-323	-
2 SK 1070	Hit	N-FET	=2SK435: SMD	35f	SOT-23	-
2 SK 1073	Mit	MOS-N-FET-e	=2SK1074: Iso, 45W	17c	SOT-186	2SK1356, 2SK1460, 2SK1995
2 SK 1074	Mit	MOS-N-FET-e	VFET, 800V, 3A, 120W, on<3,6Ω(1,5A), 70/140ns	=18p	(TO-3PFM)	2SK603, 2SK726, 2SK954, 2SK1339
2 SK 1078	Tos	MOS-N-FET-e	=2SK940: SMD	39b	SOT-89	2SK1697, 2SK1727, 2SK2109, 2SK2111,++
2 SK 1079	Tos	MOS-N-FET-e	=2SK941: SMD	39b	SOT-89	2SK1079, 2SK1485, 2SK1728, 2SK2112
2 SK 1081	Fjd	MOS-N-FET-e	VFET, 800/30V, 7A, 125W, on<2,2Ω(3A), 145/250ns	18p	TO-3P	BUK 638-800, 2SK684, 2SK1032, 2SK1502,++