

2 N 6763		MOS-N-FET-e	=2N6764: 60/20V, 31/60A, on<0,08Ω(20A)	23a	TO-3				BUZ 24, BUZ 349, 2SK561, 2SK906
2 N 6764	USA,Inr,Mot	MOS-N-FET-e	VFET, 100/20V, 38/70A, 150W, <55mΩ(24A), <135/225ns	23a	TO-3				BUZ 345, 2SK850
2 N 6765		MOS-N-FET-e	=2N6766: 150/20V, 16/50A, on<0,12Ω(16A)	23a	TO-3				BUZ 36, BUZ 350, 2SK622
2 N 6766	USA,Inr,Mot	MOS-N-FET-e	VFET, 200/20V, 30/60A, 150W, <85mΩ(19A), <135/225ns	23a	TO-3				-
2 N 6767		MOS-N-FET-e	=2N6768: 350/20V, 12/20A, on<0,4Ω(7,75A)	23a	TO-3				BUZ 64, BUZ 325, 2SK312, 2SK351
2 N 6768	USA,Inr,Mot	MOS-N-FET-e	VFET, 400/20V, 14/25A, 150W, <0,3Ω(9A), <100/225ns	23a	TO-3				BUZ 323, BUZ 338, 2SK788, 2SK899
2 N 6769		MOS-N-FET-e	=2N6770: 450/20V, 11/20A, on<0,5Ω(7A)	23a	TO-3				BUZ 45, BUZ 339, BUZ 384, 2SK512, ++
2 N 6770	USA,Inr,Mot	MOS-N-FET-e	VFET, 500/20V, 12/25A, 150W, <0,4Ω(7,75A), <85/220ns	23a	TO-3				BUZ 45, BUZ 339, BUZ 384, 2SK512, ++
2 N 6771	Fer,Rca	Si-N	S P, 450/300V, 1/2A, 40W, >10MHz, <450/3100ns	17j	TO-220				BUW 40(A,B), BUX 84...85, TIP 49...50, ++
2 N 6772		Si-N	=2N6771: 550/350V	17j	TO-220				BUW 40A,B, BUX 84...85, 2SC3352, ++
2 N 6773		Si-N	=2N6771: 650/400V	17j	TO-220				BUW 40B, BUX 84...85, 2SC3352, ++
2 N 6774	Rca	Si-N+Di	S P, 450/300V, 15/20A, 175W, >15MHz, <700/3000ns	23a	TO-3				-
2 N 6775		Si-N+Di	=2N6774: 550/350V	23a	TO-3				-
2 N 6776		Si-N+Di	=2N6774: 650/400V	23a	TO-3				-
2 N 6782	Inr,Mot	MOS-N-FET-e	VFET, 100/20V, 3,5/14A, 15W, <0,6Ω(2,25A), <40/45ns	2a	TO-39				(2SK429...430) ⁴
2 N 6784	Inr,Mot	MOS-N-FET-e	VFET, 200/20V, 2,25/9A, 15W, <1,5Ω(1,5A), <35/50ns	2a	TO-39				BST 95
2 N 6786	Inr	MOS-N-FET-e	VFET, 400/20V, 1,25/5,5A, 15W, <3,6Ω(0,8A), <35/65ns	2a	TO-39				(2SK535, 2SK579...580) ⁴
2 N 6788	Inr,Mot,Six	MOS-N-FET-e	VFET, 100/20V, 6/24A, 20W, <0,3Ω(3,5A), <110/110ns	2a	TO-39				-
2 N 6790	Inr,Six	MOS-N-FET-e	VFET, 200/20V, 3,5/14A, 20W, <0,8Ω(2,25A), <90/100ns	2a	TO-39				-
2 N 6792	Inr,Six	MOS-N-FET-e	VFET, 400/20V, 2/10A, 20W, <1,8Ω(1,25A), <75/95ns	2a	TO-39				-
2 N 6794	Inr,Six	MOS-N-FET-e	VFET, 500/20V, 1,5/6,5A, 20W, on<3Ω(3A), <70/90ns	2a	TO-39				-
2 N 6796	Inr,Six	MOS-N-FET-e	VFET, 100/20V, 8/32A, 25W, <0,18Ω(5A), <105/85ns	2a	TO-39				-
2 N 6798	Inr,Six	MOS-N-FET-e	VFET, 200/20V, 5,5/22A, 25W, <0,4Ω(3,5A), <80/90ns	2a	TO-39				-
2 N 6800	Inr,Six	MOS-N-FET-e	VFET, 400/20V, 3/14A, 25W, on<1Ω(2A), <65/90ns	2a	TO-39				-
2 N 6802	Inr,Six	MOS-N-FET-e	VFET, 500/20V, 3,5/11A, 25W, <1,5Ω(1,5A), <60/85ns	2a	TO-39				-
2 N 6804	Inr	MOS-P-FET-e	VFET, 100/20V, 11/50A, 75W, <0,3Ω(2,25A), <200/280ns	23a	TO-3				2SJ112...113
2 N 6806	Inr	MOS-P-FET-e	VFET, 200/20V, 6,5/28A, 75W, <0,8Ω(4A), <150/180ns	23a	TO-3				2SJ56, 2SJ114
2 N 6823	Mot	MOS-N-FET-e	VFET, 600/20V, 3/15A, 100W, <2,8Ω(3A), <150/260ns	23a	TO-3				BUZ 307, BUZ 360...361, 2SK415, 2SK954
2 N 6826	Mot	MOS-N-FET-e	VFET, 600/20V, 6/30A, 150W, <1,6Ω(6A), <230/300ns	23a	TO-3				BUZ 94, BUZ 332A, 2SK684, 2SK1032
2 N 6833	Mot	Si-N	SMPS, 850/450V, 5/10A, 80W, >15MHz, <400/3300ns	17j	TO-220	BUT 11 A	17j		BUT11(A), BUT46(A), BUW46(A), 2SC3047, ++
2 N 6834		Si-N	=2N6833: 125W	23a	TO-3	BU 426 A	18j		BU426(A), BU526(A), BUS11(A), BUW11(A)++
2 N 6835	Mot	Si-N	SMPS, 850/450V, 8/16A, 150W, >10MHz, <300/2750ns	23a	TO-3	S 2530 A	23a		BU426(A), BU526(A), BUS12(A), BUW12(A)++
2 N 6836	Mot	Si-N	SMPS, 850/450V, 15/20A, 175W, >10MHz, <600/3350ns	23a	TO-3				BUS 13(A), BUW 46, BUX 48(A...C), ++
2 N 6837	Mot	Si-N	SMPS, 850/450V, 20/30A, 250W, >10MHz, <600/3050ns	23a	TO-3				BUS 14(A), BUS 98(A), BUX 348(A), ++
2 N 6845	Mot	MOS-P-FET-e	VFET, 100/20V, 4/16A, 20W, <0,6Ω(2,25A), <160/120ns	2a	TO-39				-
2 N 6847	Mot	MOS-P-FET-e	VFET, 200/20V, 2,5/10A, 20W, <1,5Ω(2,25A), <160/120ns	2a	TO-39				-
2 N 6849	Mot	MOS-P-FET-e	VFET, 100/20V, 6,5/25A, 25W, <0,3Ω(4,1A), <200/280ns	2a	TO-39				-
2 N 6851	Mot	MOS-P-FET-e	VFET, 200/20V, 4/20A, 25W, <0,8Ω(2,4A), <150/160ns	2a	TO-39				-
2 N 6895	Inr	MOS-P-FET-e	VFET, 100V, 1,16/5A, 8,33W, <3,65Ω(0,74A), <70/95ns	2a	TO-39				-
2 N 6896	Inr	MOS-P-FET-e	VFET, 100/20V, 6/20A, 60W, <0,6Ω(3,8A), <160/150ns	23a	TO-3				2SJ55...56, 2SJ115, 2SJ118...119
2 N 6897	Inr	MOS-P-FET-e	VFET, 100/20V, 12/30A, 100W, <0,3Ω(7,6A), <235/450ns	23a	TO-3				2SJ112...113, 2SJ127, 2SJ131
2 N 6898	Inr	MOS-P-FET-e	VFET, 100/20V, 25/60A, 150W, <0,2Ω(15,8A), <300/650ns	23a	TO-3				-
2 N 6901	Inr	MOS-N-FET-e	VFET, LogL, 100/10V, 1,69/5A, 8,33W, <1,4Ω(1,07A)	2a	TO-39				-
2 N 6902	Inr	MOS-N-FET-e	VFET, LogL, 100/10V, 12/30A, 75W, on<0,2Ω(7,6A)	23a	TO-3				2N6765
2 N 6903	Inr	MOS-N-FET-e	VFET, LogL, 200/10V, 0,98/4A, 8,33W, <3,65Ω(0,62A)	2a	TO-39				-
2 N 6904	Inr	MOS-N-FET-e	VFET, LogL, 200/10V, 8/20A, 75W, on<0,6Ω(5,1A)	23a	TO-3				-
2 N 6905	Six	N-FET	Dual, 55V, Idss=0,5...10mA, ΔUgs<5mV	TO-71					-
2 N 6906		N-FET	=2N6905: ΔUgs<10mV	TO-71					-
2 N 6907		N-FET	=2N6905: ΔUgs<25mV	TO-71					-
2 N 6908	Six	N-FET	30V, Up<-1,8V	5	TO-72				-
2 N 6909	Six	N-FET	30V, Up<-2,3V	5	TO-72				-
2 N 6910	Six	N-FET	30V, Up<-3,5V	5	TO-72				-
2 N 6928	Tho	Si-N	S P, 450/300V, 8A, 100W, <500/2900ns, sat<1V(8A)	17j	TO-220	BUT 56 A	17j		MJE 13006...07, BUT 12(A), BUT 56(A), ++
2 N 6929		Si-N	=2N6928: 550/350V	17j	TO-220	BUT 56 A	17j		MJE 13006...07, BUT 12(A), BUT 56(A), ++
2 N 6930		Si-N	=2N6928: 650/400V	17j	TO-220	BUT 56 A	17j		MJE 13006...07, BUT 12(A), BUT 56(A), ++
2 N 6931	Tho	Si-N	S-Reg, 450/300V, 10/15A, 150W, >10MHz, <800/3000ns	18j	TO-3P	BUW 13 A	18j		BUV47(A), BUW12(A), BUW13(A), 2SC4157, ++
2 N 6932		Si-N	=2N3932: 650/400V	18j	TO-3P	BUW 13 A	18j		BUV47(A), BUW12(A), BUW13(A), 2SC4157, ++
2 N 6933	Tho	Si-N	S-Reg, 450/300V, 15/23A, 175W, >10MHz, <800/3000ns	18j	TO-3P	BUW 13 A	18j		BUP 23(A...C), BUW48(A), BUW13(A), ++
2 N 6934		Si-N	=2N6933: 550/350V	18j	TO-3P	BUW 13 A	18j		BUP 23(A...C), BUW48(A), BUW13(A), ++
2 N 6935		Si-N	=2N6933: 650/400V	18j	TO-3P	BUW 13 A	18j		BUP 23(A...C), BUW48(A), BUW13(A), ++
2 N 6962	Six	MOS-N-FET-e	VFET, 100V, 30A, on=0,6Ω	49	TO-61				-
2 N 6963	Six	MOS-N-FET-e	VFET, 200V, 30A, on=0,09Ω	49	TO-61				-
2 N 6964	Six	MOS-N-FET-e	VFET, 400V, 15A, on=0,3Ω	49	TO-61				-
2 N 6965	Six	MOS-N-FET-e	VFET, 500V, 13A, on=0,4Ω	49	TO-61				-
2 N 6975	Inr	MOS-N-FET-e	VFET, 400/20V, 5/10A, 100W, <100/1400ns	23a	TO-3				-
2 N 6976		MOS-N-FET-e	=2N6975: 500/20V	23a	TO-3				-
2 N 6977		MOS-N-FET-e	=2N6975: <100/900ns	23a	TO-3				-
2 N 6978		MOS-N-FET-e	=2N6975: 500/20V, <100/900ns	23a	TO-3				-
2 N 6985	Mot	Si-N	UHF, Push-Pull, 60/30V, 16A, PQ=125W(400MHz)						-
2 N 6986	Mot	Si-N	UHF, Push-Pull, 60/30V, 16A, PQ=100W(500MHz)						-
2 N 7000	Mot,Six	MOS-N-FET-e	VFET, 60/40V, 0,2/0,5A, 0,4W, <5Ω(0,5A), <10/10ns	7e	TO-92				BS 170, BST 70, BST 72
2 N 7001	Six	MOS-N-FET-e	SMD, VFET, 240V, 50mA, <45Ω, <30/-ns	35	SOT-23				-
2 N 7002	Mot,Six	MOS-N-FET-e	SMD, VFET, 60V, ±115/800mA, <7,5Ω(0,5A), <20/20ns	35a	SOT-23				-
2 N 7004	Six	MOS-N-FET	VFET, 100V, 1A, on=0,6Ω		4-DIP				-
2 N 7005	Six	MOS-N-FET	VFET, 200V, 0,6A, on=1,5Ω		4-DIP				-
2 N 7006	Six	MOS-N-FET	VFET, 350V, 0,32A, on=5Ω		4-DIP				-
2 N 7007	Six	MOS-N-FET	240V, 70mA, 0,4W, on<45Ω, <30/-ns	7	TO-92				-
2 N 7008	Six	MOS-N-FET	60V, 0,15A, 0,4W, on<7,5Ω, <20/-ns	7	TO-92				-
2 N 7010	Six	MOS-N-FET	VFET, 60V, 1,3A, on=0,35Ω	30	TO-237				-
2 N 7012	Six	MOS-N-FET	VFET, 60/20V, 1,2/10A, 1W, <0,35Ω(1A), <50/55ns		4-DIP				-
2 N 7013	Six	MOS-N-FET	VFET, 40V, 1,2A, on=0,3Ω		4-DIP				-
2 N 7016	Six	MOS-N-FET	VFET, 60V, 0,6A, on=1Ω		4-DIP				-
2 N 7051	Nsc	Si-N-Darl	100/100V, hFE>20k, >100MHz	7e	TO-92				-
2 N 7052	Nsc	Si-N-Darl	100/100V, hFE>10k, >100MHz	7	TO-92				-
2 N 7053	Nsc	Si-N-Darl	100/100V, hFE>10k, >100MHz						-
2 N 7056	Sgs	MOS-FET	VFET, 200V, 19A, 70W, on<0,1Ω(16A)	18	TO-3P Iso				-
2 N 7059	Sgs	MOS-FET	VFET, 500V, 8A, 70W, on<0,45Ω(7A)	18	TO-3P Iso				-
2 N 7071	Six	MOS-N-FET-e	VFET, 100/20V, 23/92A, 100W, <0,1Ω(15A), <150/140ns	18f	TO-254 Iso				BUK 426-100, (2SK622, 2SK629) ³
2 N 7072	Six	MOS-N-FET-e	VFET, 200/20V, 16/64A, 100W, <0,2Ω(10A), <150/140ns	18f	TO-254 Iso				(BUZ 350) ³
2 N 7073	Six	MOS-N-FET-e	VFET, 400/20V, 9/36A, 100W, 0,55Ω(5,5A), <100/170ns	18f	TO-254 Iso				2SK1225, 2SK1328, (BUZ 330...331, BUZ 501) ³
2 N 7074	Six	MOS-N-FET-e	VFET, 500/20V, 7/28A, 100W, <0,85Ω(4,5A), <90/160ns	18f	TO-254 Iso				2SK1206, (BUZ 330...331, BUZ 332A) ³
2 N 7075	Six	MOS-N-FET-e	VFET, 100/20V, 30/120A, 150W, <65mΩ(24A), <185/225ns	18f	TO-254 Iso				(BUZ 349, 2SK906) ³
2 N 7076	Six	MOS-N-FET-e	VFET, 200/20V, 28/112A, 150W, <0,1Ω(18A), <185/225ns	18f	TO-254 Iso				(BUZ 341, 2SK851) ³

DataSheet.Live