

TRANSISTOR NUMBER	PM OA LT	PACK-AGE	LEAD INFO	VCB MAX	VCE MAX	VEB MAX	I C MAX	T J MAX	P TOT	F T MIN	C OB MAX	H FE	H FE BIAS	USE	MFR	EUR EQUIV	USA EQUIV	ISS
2N1552	PG	T03	L05	100V	50V	50V	20A	110C	106WC			10/30	10A	AHH	MOB		2N1166	0
2N1552A	PG	T03	L05	100V	50V	50V	20A	110C	106WC			10/30	10A	AHH	MOB		2N1166	0
2N1553	PG	T03	L05	40V	20V	20V	20A	110C	106WC			30/60	10A	AHG	MOB		2N1166	0
2N1553A	PG	T03	L05	40V	20V	20V	20A	110C	106WC			30/60	10A	AHG	MOB		2N1166	0
2N1554	PG	T03	L05	60V	30V	30V	20A	110C	106WC			30/60	10A	AHG	MOB		2N1166	0
2N1554A	PG	T03	L05	60V	30V	30V	20A	110C	106WC			30/60	10A	AHG	MOB		2N1166	0
2N1555	PG	T03	L05	80V	40V	40V	20A	110C	106WC			30/60	10A	AHG	MOB		2N1166	0
2N1555A	PG	T03	L05	80V	40V	40V	20A	110C	106WC			30/60	10A	AHG	MOB		2N1166	0
2N1556	PG	T03	L05	100V	50V	50V	20A	110C	106WC			30/60	10A	AHH	MOB		2N1166	0
2N1556A	PG	T03	L05	100V	50V	50V	20A	110C	106WC			30/60	10A	AHH	MOB		2N1166	0
2N1557	PG	T03	L05	40V	20V	20V	20A	110C	106WC			50/100	10A	AHG	MOB		2N1166	0
2N1557A	PG	T03	L05	40V	20V	20V	20A	110C	106WC			50/100	10A	AHG	MOB		2N1166	0
2N1558	PG	T03	L05	60V	30V	30V	20A	110C	106WC			50/100	10A	AHG	MOB		2N1166	0
2N1558A	PG	T03	L05	60V	30V	30V	20A	110C	106WC			50/100	10A	AHG	MOB		2N1166	0
2N1559	PG	T03	L05	80V	40V	40V	20A	110C	106WC			50/100	10A	AHG	MOB		2N1166	0
2N1559A	PG	T03	L05	80V	40V	40V	20A	110C	106WC			50/100	10A	AHG	MOB		2N1166	0
2N1560	PG	T03	L05	100V	50V	50V	20A	110C	106WC			50/100	10A	AHH	MOB		2N1166	0
2N1560A	PG	T03	L05	100V	50V	50V	20A	110C	106WC			50/100	10A	AHH	MOB		2N1166	0
2N1561	PG	T0107	L04	25V	25V	3V	500MA	100C	250MWF	250M	10P	5MN	200MA	VMP	MOB		2N1561	0
2N1562	PG	T0107	L04	25V	25V	2V	500MA	100C	250MWF	225M	10P	5MN	200MA	VMP	MOB		2N1561	0
2N1564	NS	T05	L04	80V	60V	5V	100MA	175C	600MWF	60M	10P	15/50	5MA	RLH	OBS	BSW54	2N2219A	0
2N1565	NS	T039	L04	80V	60V	5V	100MA	175C	600MWF	60M	10P	30MN	5MA	RLH	SES	BSW54	2N2219A	0
2N1566	NS	T039	L04	80V	60V	5V	100MA	175C	600MWF	60M	10P	60/200	5MA	RLH	SES	BSW54	2N2219A	0
2N1566A	NS	T039	L04	80V	60V	8V	100MA	175C	600MWF	100M	6P	60/200	5MA	RLH	SES	BSW54	2N2219A	0
2N1572	NS	T05	L04	125V	80V	5V	100MA	175C	600MWF	12M	10P	15/50	5MA	ALH	T1B	BFY65	2N1990	0
2N1573	NS	T05	L04	125V	80V	5V	100MA	175C	600MWF	30M	10P	30/100	5MA	ALH	T1B	BFY65	2N1990	0
2N1574	NS	T05	L04	125V	80V	5V	100MA	175C	600MWF	30M	10P	60/200	5MA	ALH	T1B	BFY65	2N1990	0
2N1585	NG	T05	L04	25V	15V		100MA	75C	300MWF	200M	3P5	20MN	10MA	RMG	OBS	ASY29	2N1304	2
2N1586	NS	TC22	L37		10V	6V	25MA	75C	125MWF	5M	30P	9/27	1MA	RLG	OBS	BC107B	2N930	2
2N1587	NS	TC22	L37		20V	6V	25MA	75C	125MWF	5M	30P	9/27	1MA	RLG	OBS	BC107B	2N930	2
2N1588	NS	TC22	L37		40V	6V	25MA	75C	125MWF	5M	30P	9/27	1MA	RLG	OBS	BC107B	2N930	2
2N1589	NS	TC22	L37		10V	6V	25MA	75C	125MWF	5M	30P	25/75	1MA	RLG	OBS	BC107B	2N930	2
2N1590	NS	TC22	L37		20V	6V	25MA	75C	125MWF	5M	30P	25/75	1MA	RLG	OBS	BC107B	2N930	2
2N1591	NS	TC22	L37		40V	6V	25MA	75C	125MWF	5M	30P	25/75	1MA	RLG	OBS	BC107B	2N930	2
2N1592	NS	TC22	L37		10V	6V	25MA	75C	125MWF	5M	30P	70/210	1MA	RLG	OBS	BC107B	2N930	2
2N1593	NS	TC22	L37		20V	6V	25MA	75C	125MWF	5M	30P	70/210	1MA	RLG	OBS	BC107B	2N930	2
2N1594	NS	TC22	L37		40V	6V	25MA	75C	125MWF	5M	30P	70/210	1MA	RLG	OBS	BC107B	2N930	2
2N1605	NG	T05	L04	25V	24V	12V	100MA	100C	200MWF	6M	24P	40/120	20MA	RMS	RCU	ASY29	2N1304	0
2N1605A	NG	T05	L04	40V		12V	100MA	100C	200MWF	2M	24P	40MN	20MA	RMS	RCU	ASY29	2N1304	0
2N1606	PS	T05	L04	10V		6V	50MA	175C	100MWF	7M		6/30	15MA	RLG	OBS	BFS95	2N4036	2
2N1607	PS	T05	L04	10V		6V	50MA	175C	100MWF	10M		6/30	15MA	RLG	OBS	BFS95	2N4036	2
2N1608	PS	T05	L04	10V		6V	50MA	175C	100MWF	25M		6/30	15MA	RLG	OBS	BFS95	2N4036	2
2N1609	PG	TC37	L47		60V		1A5	75C	4.5WC			30/75	100MA	RHS	OBS		2N2284	2
2N1610	PG	TC37	L47		40V		1A5	75C	4.5WC			50/125	100MA	RHS	OBS		2N2284	2
2N1611	PG	TC37	L47		40V		1A5	75C	4.5WC			30/75	100MA	RHS	OBS		2N2284	2
2N1612	PG	TC37	L47		40V		1A5	75C	4.5WC			50/125	100MA	RHS	OBS		2N2284	2
2N1613	NS	T05	L04	75V	50V	7V	600MA	175C	800MWF	80M	25P	40/120	150MA	AMG	SGI	BFY50	2N2297	0
2N1613A	NS	T05	L04	75V	50V	7V	1A	175C	1WF	60M	25P	40/120	150MA	AMH	OBS	BFR23	2N4929	2
2N1613B	NS	T05	L04	120V	75V	7V	1A	175C	1WF	60M	25P	40/120	150MA	AMH	OBS	BFR23	2N4929	2
2N1613S	NS	T039	L04	75V	50V	7V	1A	175C	800MWF	60M	25P	40/120	150MA	RMG	MOB	BFY50	2N1613	2
2N1613/46	NS	T046	L01	75V	50V	7V	500MA	175C	500MWF	80M	25P	40/120	150MA	RMG	OBS	BFY50	2N1613	2
2N1615	NS	T05	L04	120V	100V		200MA	175C	600MWF	2M	100P	25MN	5MA	ALE	OBS	BF257	2N4927	2
2N1616	NS	T061	L46	60V	60V	8V	5A	175C	85WC	3M		15/75	2A	AHH	SES		2N1618	0
2N1616A	NS	T061	L46	60V	60V	8V	7A5	175C	85WC	3M		20/60	2A	AHH	OBS	BDY63	2N1618	2
2N1617	NS	T061	L46	80V	70V	8V	5A	175C	85WC	3M		15/75	2A	AHH	SES		2N1618	0
2N1617A	NS	T061	L46	80V	80V	8V	5A	175C	85WC	3M		20/60	2A	AHH	OBS	BDY63	2N1725	2
2N1618	NS	T061	L46	100V	80V	8V	5A	175C	85WC	3M		15/75	2A	AHH	SES		2N1618	0
2N1618A	NS	T061	L46	100V	80V	8V	5A	175C	85WC	3M		20/60	2A	AHH	OBS	BDY63	2N1725	2
2N1620	NS	T061	L46	100V	80V	8V	7A5	175C	60WC	3M		15/75	2A	AHH	OBS	BDY63	2N1725	2
2N1622	NG	T05	L04	90V	60V	20V	100MA	75C	120MWF	500K		40MN	5MA	ALG	OBS	AC176	2N2430	2
2N1623	PS	T05	L04		20V		50MA	175C	250MWF	100K	100P	9/40	1MA	ALG	OBS	BFS95	2N4036	2
2N1624	NG	T05	L04		20V		300MA	75C	150MWF	5M	25P	60/180	30MA	RMG	OBS	ASY29	2N1304	2
2N1631	PG	T05	L04	34V		1V	10MA	85C	80MWF	20M	4P	80TP	1MA	RLG	RCU	AF124	2N990	0
2N1632	PG	T05	L04	34V		1V	10MA	85C	80MWF	20M	4P	80TP	1MA	RLG	RCU	AF124	2N990	0
2N1633	PG	T05	L04	34V		1V	10MA	85C	80MWF	20M	4P	75TP	1MA	RLG	RCU	AF124	2N990	0
2N1634	PG	T05	L04	34V		1V	10MA	85C	80MWF	20M	4P	75TP	1MA	RLG	RCU	AF124	2N990	0
2N1635	PG	T05	L04	34V		1V	10MA	85C	80MWF	20M	4P	75TP	1MA	RLG	RCU	AF124	2N990	0
2N1636	PG	T05	L04	34V		1V	10MA	85C	80MWF	20M	4P	75TP	1MA	RLG	RCU	AF124	2N990	0
2N1637	PG	T05	L04	34V		1V	10MA	85C	80MWF	20M	4P	80TP	1MA	RLG	RCU	AF124	2N990	0
2N1638	PG	T01	L02	34V		1V	10MA	85C	80MWF	20M	4P	75TP	1MA	RLG	RCU	AF124	2N990	0
2N1639	PG	T05	L04	34V		1V	10MA	85C	80MWF	50M	4P	75TP	1MA	RLG	RCU	AF124	2N990	0
2N1640	PS	T05	L04		20V		50MA	175C	250MWF	200K	75P	6MN	100UA	ALG	OBS	BC177	2N3965	2
2N1641	PS	T05	L04		10V		50MA	175C	250MWF	400K	75P	10MN	100UA	ALG	OBS	BC177	2N3965	2
2N1642	PS	T05	L04		6V		50MA	175C	250MWF	600K	75P	15MN	100UA	ALG	OBS	BC177	2N3965	2
2N1643	PS	T05	L04	25V			50MA	175C	250MWF	350K	75P	10/25	1MA	ALG	OBS	BC177	2N3965	2