

2 N 5174	Gen,Spr	Si-N	Uni, 90/75V, 0,025A, 0,36W	7c	TO-98			BSS 38, BSX 21, 2SC1890(A), 2SC2240, ++	
2 N 5175	Gen,Spr	Si-N	Uni, 130/100V, 0,025A, 0,2W, hFE=55...160	7c	TO-98			BSS 38, BSX 21, 2SC1890A, 2SC2240, ++	
2 N 5176		Si-N	=2N5175: hFE=140...300	7c	TO-98			BSS 38, BSX 21, 2SC1890A, 2SC2240, ++	
2 N 5177	Trw	Si-N	HF P, 55/35V, 4A, 40W, >200MHz		60c			-	
2 N 5178	Trw	Si-N	HF P, 55/35V, 8A, 70W, >200MHz		60c			-	
2 N 5179	USA,Mot,Nsc Rca,Sgs,Tix	Si-N	VHF/UHF, In, 20/12V, 0,05A, 0,2W, 1400MHz F<4,5dB(200MHz), Gp=21dB(200MHz)	5g	TO-72	2SC2570 A	7f	BF 377...378, BF 689, BF 763, 2N2857, ++	
2 N 5180	USA,Rca,Tix	Si-N	VHF, In, 30V, 0,18W, 900MHz		5g	TO-104		BF 314, BF 502, BF 505, BF 507, BF 562++	
2 N 5181	USA,Nsc,Rca	Si-N	HF,IF, 45V, 0,05A, 0,18W, 700MHz		5k	TO-104		BF 198...199, BF 224...225, BF 310...311,++	
2 N 5182	USA,Nsc,Rca	Si-N	HF,IF, 45V, 4mA, 0,18W, 700MHz		5k	TO-104		BF 198...199, BF 224...225, BF 310...311,++	
2 N 5183	USA,Rca	Si-N	Uni, 18/18V, 1A, 0,5W, 200MHz, <75/575ns		2a	TO-18		BC 337...338, BC 635, 2N2221...22(A), ++	
2 N 5184	Rca,Sem	Si-N	Vid, -1/20V, 0,05A, 0,5W, 100MHz		2a	TO-18		BF 297...299, BFT 57...59, 2SC3467, ++	
2 N 5185		Si-N	=2N5184: 1W		2a <sup>9</sup>	=TO-18 <sup>9</sup>		BF 297...299, BFT 57...59, 2SC3467, ++	
2 N 5186	Rca,Sem	Si-N	S, 10V, 0,3A, 0,3W, 600MHz, <25/25ns		2a	TO-52		BSS 10...12, BSX 19...20, 2N3261, ++	
2 N 5187	Rca,Sca,Sem	Si-N	SS, 25/10V, 0,5A, 0,3W, 600MHz, <12/14ns		2a	TO-52		BSS 10, BSX 26, BSX 39, 2N3261	
2 N 5188	USA,Rca	Si-N	S, 60/25V, 1A, 0,8W, 325MHz, <35/50ns		2a	TO-39		BSS 27, BSV 77, BSV 95, 2SC1635, ++	
2 N 5189	USA,Rca,Tix	Si-N	S, 60/35V, -2A, 1W, >250MHz, <40/70ns		2a	TO-39		BSS 27, BSV 77, BSV 95, 2SC1635, ++	
2 N 5190	Mot,Nsc,Sgs	Si-N	LFS P, 40/40V, 4/7A, 40W, >2MHz	{2N5193	14h	TO-126	BD 189	14h	BD 185, BD 437, BD 785, MJE 240...244, ++
2 N 5191		Si-N	=2N5190: 60/60V	{2N5194	14h	TO-126	BD 189	14h	BD 187, BD 439, BD 787, MJE 240...244, ++
2 N 5192		Si-N	=2N5190: 80/80V	{2N5195	14h	TO-126	BD 189	14h	BD 189, BD 441, BD 789, MJE 240...244, ++
2 N 5193	Mot,Nsc,Sgs	Si-P	LFS P, 40/40V, 4/7A, 40W, >2MHz	{2N5190	14h	TO-126	BD 190	14h	BD 186, BD 438, BD 786, MJE 250...254, ++
2 N 5194		Si-P	=2N5193: 60/60V	{2N5191	14h	TO-126	BD 190	14h	BD 188, BD 440, BD 788, MJE 250...254, ++
2 N 5195		Si-P	=2N5193: 80/80V	{2N5192	14h	TO-126	BD 190	14h	BD 190, BD 442, BD 788, MJE 250...254, ++
2 N 5196	Isi,Nsc,Six Tho,Tix,++	N-FET	Dual, In, 50V, 0,5W, Idss=0,7...7mA, Up=0,7...4V, F<0,5dB(100Hz), ΔIdss=0,95...1, ΔUgs<5mV, Δyfs=0,97...1		TO-71	(SDG-SDG-)			-
2 N 5197		N-FET	=2N5196: ΔUgs<5mV		TO-71	(SDG-SDG-)			-
2 N 5198		N-FET	=2N5196: ΔUgs<10mV, Δyfs=0,95...1		TO-71	(SDG-SDG-)			-
2 N 5199		N-FET	=2N5196: ΔUgs<15mV, Δyfs=0,95...1		TO-71	(SDG-SDG-)			-
2 N 5200	Fch,Sca	Si-N	UHF, RadH, 20V, 0,1A, 0,3W, >900MHz, hFE=50...150		2a	TO-46			-
2 N 5201		Si-N	=2N5200: >1100MHz, hFE=75...150		2a	TO-46			-
2 N 5202	USA,Rca	Si-N	LFS P, 100/50V, 4A, 35W, >60MHz, <440/1600ns		22a	TO-66			BDV 10...12, 2SD772
2 N 5203		Si-N	=BFW 35		2a				+BFW 35
2 N 5204	USA,Tho,Tag	50Hz-Thy	600V, 22A(Tc=40°), 35A~, Igt/Ih<40/<100mA		21b	TO-48			C 228M, 2N3899, MCR 3935-8, C 35M, ++
2 N 5205		50Hz-Thy	=2N5204: 800V		21b	TO-48			MCR 3935-10, C 35M, MCR 64-10, TAG 35-800
2 N 5206		50Hz-Thy	=2N5204: 1000V		21b	TO-48			C 35P, MCR 64-10, TAG 35-1000
2 N 5207		50Hz-Thy	=2N5204: 1200V		21b	TO-48			-
2 N 5208	Mot	Si-P	FM/VHF, In, 30V, 0,05A, 0,35W, >300MHz		7f	TO-92	BF 324	7a	BF 324, BF 414, BF 506, BF 914, BF 936++
2 N 5209	USA,Fer,Mot Mic,Nsc,Tix	Si-N	LF, In, 50/50V, 0,05/0,1A, 0,625W, 80MHz, F<3dB(1kHz), hFE=100...300	{2N5086	7e	TO-92			BC 184, BC 413...414, BC 550, 2SC2240, ++
2 N 5210		Si-N	=2N5209: F<2dB(1kHz), hFE=200...600	{2N5087	7e	TO-92			BC 184, BC 413...414, BC 550, 2SC2240, ++
2 N 5211	Itt	Si-N	VHF Drv, 80/80V, 0,6A, 0,8W, >200MHz		2a	TO-39			BFS 23, BLY 34
2 N 5212	Itt	Si-N	VHF Drv,Out, 80/80V, 0,6A, 7,5W, >200MHz		43a	TO-37			-
2 N 5213	Itt	Si-N	VHF/UHF Drv,Out, 70/70V, 0,5A, PQ=3W(200MHz)		43a	TO-37			-
2 N 5214	Itt	Si-N	VHF P, 95/95V, 5A, PQ=30W(150MHz)						(BLY 94, 2SC2182) <sup>4</sup>
2 N 5215	Itt,Tix	Si-N	VHF P, 70/70V, 1A, PQ=10W(200MHz)		49a	TO-60			BLY 60, 2N3632
2 N 5216	Itt	Si-N	VHF/UHF P, 80/80V, 1,5A, PQ=15W(400MHz)						(BLW 94, BLX 94, MRF 323, 2SC1118) <sup>4</sup>
2 N 5217	Itt	Si-N	VHF/UHF Drv,Out, 80/80V, 0,5A, PQ=4W(400MHz)						(BLW 94, BLX 94, MRF 323, 2SC1118) <sup>4</sup>
2 N 5218	USA	Si-N	S P, 220/200V, 10A, 50W(Tc=100°), >40MHz		49m	TO-61			2N5540
2 N 5219	USA,Mot,Tix	Si-N	Uni, 20/15V, 0,1A, 0,35W, >150MHz		7e	TO-92			BC 168, BC 183, BC 238, BC 548, ++
2 N 5220	USA,Mot,Tix	Si-N	Uni, 15/15V, 0,5A, 0,625W, >100MHz	{2N5221	7e	TO-92			BC 337...338, BC 635, BC 637, BC 639, ++
2 N 5221	USA,Mot,Tix	Si-P	Uni, 15/15V, 0,5A, 0,35W, >100MHz	{2N5220	7e	TO-92			BC 327...328, BC 636, BC 638, BC 640, ++
2 N 5222	USA,Mot,Tix	Si-N	AM/FM, TV IF, 20/15V, 0,05A, >450MHz		7f	TO-92			BF 198...199, BF 224...225, BF 310...311,++
2 N 5223	USA,Mot,Tix	Si-N	Uni, 25/20V, 0,1A, 0,625W, >150MHz	{2N5227	7e	TO-92			BC 168, BC 183, BC 238, BC 548, ++
2 N 5224	USA,Mot	Si-N	LFS, 25/12V, 0,2A, 0,625W, >250MHz, <45/60ns		7e	TO-92			BSS 10...12, BSX 19...20, 2N2368...69(A),++
2 N 5225	USA,Mot,Tix	Si-N	Uni, 25/25V, 0,5A, 0,625W, >50MHz	{2N5226	7e	TO-92			BC 337...338, BC 635, BC 637, BC 639, ++
2 N 5226	USA,Mot,Tix	Si-P	Uni, 25/25V, 0,5A, 0,625W, >50MHz	{2N5225	7e	TO-92			BC 327...328, BC 636, BC 638, BC 640, ++
2 N 5227	USA,Mot,Tix	Si-P	Uni, 30/30V, 0,05A, 0,625W, >100MHz		7e	TO-92			BC 213, BC 258, BC 308, BC 558, ++
2 N 5228	USA,Mot	Si-P	LFS, 5/5V, 0,05A, 0,625W, >300MHz, <75/140ns		7e	TO-92			BSW 24, BSX 36, 2N4258, 2N4313, ++
2 N 5229	Mot,Ssi	Si-P	Chopper, 15/10/15V, 0,05A, 0,5W, on=1...6Ω		2a	TO-46			2N2944
2 N 5230	Mot,Ssi	Si-P	Chopper, 30/20/30V, 0,05A, 0,5W, on=2...8Ω		2a	TO-46			2N2945
2 N 5231	Mot,Ssi	Si-P	Chopper, 50/30/50V, 0,05A, 0,5W, on=2...10Ω		2a	TO-46			2N2946
2 N 5232(A)	USA,Mic,Nsc	Si-N	Uni, In, 70/50V, 0,1A, 0,36W, >250MHz		7c, 7a	TO-98, 92			2SC1775(A), 2SC2240, 2SC2389, 2SC2459,++
2 N 5233	Csr	Si-N	Uni, 80/60V, 0,1A, 0,33W, hFE=100...300		7c	TO-98			BC 546, 2SC1890(A), 2SD755...756(A), ++
2 N 5234		Si-N	=2N5233: hFE=250...500		7c	TO-92			BC 546, 2SC1890(A), 2SD755...756(A), ++
2 N 5235		Si-N	=2N5233: hFE=400...800		7c	TO-92			BC 546, 2SC1890(A), 2SD755...756(A), ++
2 N 5236	Fch,Sca,Ssi	Si-N	HF Os, IF, RadH, 40/20V, 0,15A, 0,6W, >500MHz		2a	TO-39			-
2 N 5237	USA	Si-N	S, 150/120V, 5A, 8,75W(Tc=25°), 25MHz, <0,5/2μs		2a	TO-5			BUY 80, 2N4879
2 N 5238		Si-N	=2N5237: 200/170V		2a	TO-5			BUY 48...49
2 N 5239	USA,Rca,Tix	Si-N	S P, 300/225V, 5A, 100W, >2MHz		23a	TO-3			BU 606...608, BUX 16A...C, 2SC2624, ++
2 N 5240		Si-N	=2N5239: 375/300V		23a	TO-3			BU 606...608, BUX 16B...C, 2SC2624, ++
2 N 5241	USA,Mot,Tix	Si-N	S P, 400/400V, 5A, 125W(Tc=62°), 5MHz, <0,8/1,7μs		23a	TO-3			BUX 16C, BUX 18C, BUX 45, 2SD640, ++
2 N 5242	Fch	Si-P	S, 20/20V, 0,5/1A, 0,5W, >170MHz, <45/95ns		8a	TO-105			2N3467...68, 2N5022...23, 2SA742, ++
2 N 5243		Si-P	=2N5242: 30/30V		8a	TO-105			2N3467...68, 2N5022...23, 2SA742, ++
2 N 5244	Fch,Itt,Sgs	Si-P	S, RadH, 40/40V, 0,1A, 0,36W, >450MHz, <55/150ns		2a	TO-18			-
2 N 5245	USA,Isi,Mot Tho,Tix,++	N-FET	VHF, 30V, Idss=5...15mA, Up=1...6V		7f	SOT-30	BF 245	7f	BF 244...245, BFS 80, BFW 11, 2N4416, ++
2 N 5246		N-FET	=2N5245: Idss=1,5...7mA, Up0,5...4V		7f	SOT-30	BF 245	7f	2SK107, 2SK161
2 N 5247		N-FET	=2N5245: Idss=8...24mA, Up=1,5...8V		7f	SOT-30	BF 245	7f	BF 244...245, BFW 10
2 N 5248	USA,Isi,Tix	N-FET	VHF, 30V, Idss=4...20mA, Up=1...8V		7e	TO-92	BF 245	7f	BF 244...245, BFS 72, 2N3823
2 N 5249(A)	Gen,Sem,Spr	Si-N	LF, In, 70/50V, 0,1A, 0,36W, A: F<3dB(1kHz)		7c	TO-98			2SC1775(A), 2SC2240, 2SC2389, 2SC2459,++
2 N 5250	USA	Si-N	S P, 125/100V, 90A, 350W, >10MHz, <2/2μs		49m	TO-114			2N6309...11
2 N 5251		Si-N	=2N5250: 180/150V		49m	TO-114			2N6309...11
2 N 5252	Ssi,Stc	Si-N	S,Vid, 300/300V, 1A, 1W, >30MHz, hFE=40...120		2a	TO-39			BFQ 38...40, BSS 48...49, 2N3439...40
2 N 5253		Si-N	=2N5252: hFE=80...250		2a	TO-39			BFQ 38...40, BSS 48...49, 2N3439...40
2 N 5254	Fch,Isi	Si-P	Dual, In, 40/40V, 0,05A, 0,43W, >40MHz, F<3dB(1k) ΔhFE=, ΔUbe=		TO-77P	(CBE-EBC-)			BFX 11, 2N3726, 2N4015...15
2 N 5255		Si-P	=2N5254: F<2,5dB(1kHz), ΔhFE=0,8...1, ΔUbe<5mV		TO-77P	(CBE-EBC-)			BFX 11, 2N3726, 2N4015...15
2 N 5256		Si-P	=2N5254: F<2,5dB(1kHz), ΔhFE=0,9...1, ΔUbe<3mV		TO-77P	(CBE-EBC-)			BFX 11, 2N3726, 2N4015...15
2 N 5254...56/78		Si-P	=2N5254...56: 0,5W, >60MHz		TO-77	(CBE-EBC-)			BFX 11, 2N3726, 2N4015...15
2 N 5262	USA,Rca	Si-N	S, 75/50V, 2A, 1W, 350MHz, 18/35ns		2a	TO-39			BSS 14, 2N3507
2 N 5263	Amp	Si-N	Min, S, 30/15V, 0,025A, >1GHz			TO-122			-
2 N 5264	USA	Si-N	S P, 400/180V, 7/10A, 87W, >50MHz		23a	TO-3			BU 606...608, BUX 18B...C, 2SC2656, ++
2 N 5265	Isi,Mot	P-FET	Uni, 60V, Idss>0,5mA, Up<3V		5n	TO-72			-