

| | | | | | | |
|-------------------|-----------|---|------------|----------------|---------|----|
| 2 SC 936(A) | Si-N | TV-VA, 1000/500(A=600)V, 1A, 22W, 7MHz | 23a | 2SC1413 | 23a | * |
| 2 SC 937 | Si-N | TV-HA, 1200/500V, 2.5A, 22W, 4MHz | 23a | 2SC1413 | 23a | * |
| 2 SC 938 | Si-N | Uni, 60V, 0.2A, 0.25W, 100MHz | 7c | BC 639 | 7c | |
| 2 SC 939 | Si-N | TV-HA, 150V, 5A, 50W, 20MHz | 23a | BU 608 | 23a | |
| 2 SC 940 | Si-N | =2SC939: 200V, 9A | 23a | BU 608 | 23a | |
| 2 SC 941(TM) | Si-N | HF, 35V, 0.02A, 0.2W, 120MHz | 7c | BF 255 | 7d | |
| 2 SC 943 | Si-N | Uni, 60V, 0.2A, 0.3W, 220MHz | 2a | BC 546 | 7a | |
| 2 SC 944(S) | Si-N | Uni, 60V, 0.1A, 0.25W, 250MHz, 20/300ns | 7c | BC 546 | 7a | |
| 2 SC 945(T) | Si-N | Uni, 60V, 0.1A, 0.25W, 250MHz | 7c | BC 546 | 7a | |
| 2 SC 945 L | Si-N | =2SC945: ra | 7c | BC 550 | 7a | |
| 2 SC 947(Z) | Si-N | VHF/UHF, 25V, 15mA, 650MHz | 5g | 2SC2570 A | 7f | |
| 2 SC 948(Z) | Si-N | VHF/UHF, 25V, 15mA, 800MHz | 5g | 2SC2570 A | 7f | |
| 2 SC 949 | Si-N | Uni, ra, 45V, 0.05A, 0.2W, 200MHz | 7c | BC 550 | 7a | |
| 2 SC 950 | Si-N | Uni, 30V, 0.1A, 0.3W, 100MHz | 7c | BC 546 | 7a | |
| 2 SC 951 | Si-N | =2SC950: 60V | 7c | BC 546 | 7a | |
| 2 SC 952 | Si-N | =2SC950: 100V | 7c | 2SC2632 | 7c(9mm) | |
| 2 SC 953 | Si-N | Uni, 30V, 0.2A, 0.6W, 90MHz | 8a | BC 337 | 7a | |
| 2 SC 954 | Si-N | Uni, 60V, 0.4A, 0.6W, 90MHz | 8a | BC 337 | 7a | |
| 2 SC 955 | Si-N | Uni, 20V, 0.05A, 0.15W, 150MHz | 8a | BC 546 | 7a | |
| 2 SC 956 | Si-N | Uni, 50V, 0.05A, 0.15W, 200MHz | 8a | BC 546 | 7a | |
| 2 SC 957 | Si-N | VHF, 30V, 0.1A, 0.36W, 700MHz | 2a | BF 198, BF 199 | 7d | |
| 2 SC 959(S) | Si-N | Uni, 120V, 0.7A, 0.7W, 100MHz | 2a | (BC 141) | 2a | 7 |
| 2 SC 960(S) | Si-N | =2SC959: | 43m | (2SC4135) | 30j | 4 |
| 2 SC 961 | Si-N | NF/S-L, 120/90V, 7A, 60W, 13MHz | 23a | BD 245 C | 18j | |
| 2 SC 962 | Si-N | =2SC961: 100/80V | 23a | BD 245 C | 18j | |
| 2 SC 963 | Si-N | Uni, 35V, 0.05A, 0.25W, 200MHz, B=70 | 2a | BC 546 | 7a | |
| 2 SC 964 | Si-N | =2SC963: B=100 | 2a | BC 546 | 7a | |
| 2 SC 965 | Si-N | =2SC963: 45V, <300ns | 2a | BC 546 | 7a | |
| 2 SC 966 | Si-N | Uni, 30V, 0.2A, 0.5W, 70MHz | 2a | BC 337 | 7a | |
| 2 SC 967 | Si-N | Uni, 30V, 0.5A, 0.5W, 70MHz | 2a | BC 337 | 7a | |
| 2 SC 968 | Si-N | Uni, 50V, 0.5A, 0.5W, 70MHz | 2a | BC 337 | 7a | |
| 2 SC 969 | Si-N | Uni, 50V, 0.2A, 0.5W, 60MHz | 2a | BC 337 | 7a | |
| 2 SC 970 | Si-N | Uni, 50V, 0.5A, 0.5W, 70MHz | 2a | BC 337 | 7a | |
| 2 SC 971 | Si-N | Uni, 50V, 0.5A, 1W, 70MHz | 2a° | BC 337 | 7a | |
| 2 SC 972 | Si-N | Uni, 70V, 0.4A, 0.6W, 80MHz | 2a | BC 141 | 2a | |
| 2 SC 979 | Si-N | Uni, 70V, 0.1A 0.3W, 250MHz, 25/430ns | 2a | BC 546 | 7a | |
| 2 SC 979 A | Si-N | =2SC979: 100V | 2a | 2SC2632 | 7c(9mm) | |
| 2 SC 980(G,GTM) | Si-N | Uni, 70V, 0.1A, 0.2W, 400MHz, 25/630ns | 7c | BC 546 | 7a | |
| 2 SC 980 A(G,GTM) | Si-N | =2SC980: 90V | 7c | 2SC2632 | 7c(9mm) | |
| 2 SC 981 | Si-N | NF/S-L, 100V, 5A, 25W, 10MHz | 22a | BD 243 C | 17j | |
| 2 SC 982(TM) | Si-N-Darl | NF/S, 40V, 0.3A, 0.4W, B>5000 | 7c | (BC 879) | 7c | 13 |
| 2 SC 983 | Si-N | Vid, 250/150V, 0.05A, 0.6W, 120MHz | 9b | BF 420 A | 7c | |
| 2 SC 984 | Si-N | Uni, 50V, 0.5A, 0.35W, 230MHz | 2a | BC 639 | 7c | |
| 2 SC 984 H | Si-N | =2SC984: 100V | 2a | BC 639 | 7c | |
| 2 SC 993 | Si-N | Uni, 25V, 0.2A, 0.2W, 400MHz | 2a | (BC 546) | 7a | 8 |
| 2 SC 995 | Si-N | Vid, 300/300V, 0.15A, 0.8W, 100MHz | 2a | BF 259 | 2a | |
| 2 SC 996 | Si-N | =2SC995: | 43a | (BF 459) | 14h | 4 |
| 2 SC 997 | Si-N | HF/ZF, 40V, 25mA, 600MHz | 5k | BF 198, BF 199 | 7d | |
| 2 SC 999 | Si-N | TV-HA, 1500/700V, 1.5A, 50W, 1MHz | 23a | (BU 208 A) | 23a | |
| 2 SC 999 A | Si-N | =2SC999: 1500/650V, 2.5A, 4MHz | 23a | BU 208 A | 23a | |
| 2 SC 1000(G) | Si-N | Uni, ra, 55V, 0.1A, 0.2W, 80MHz | 7c | BC 550 | 7a | |
| 2 SC 1000 GTM | Si-N | =2SC1000: 60V, 0.4W | 7c | 2SC2632 | 7c(9mm) | |
| 2 SC 1001 | Si-N | UHF-Tr/E, 40V, 0.5A, PQ>1,2W(470MHz) | 2a(E=case) | - | - | |
| 2 SC 1004 | Si-N | TV-HA/VA, 1100/700V, 0.5A, 50W | 23a | - | - | |
| 2 SC 1004 A | Si-N | =2SC1004: 1500/800V | 23a | - | - | |
| 2 SC 1005 | Si-N | TV-HA, 1100/600V, 5A, 50W, 3MHz | 23a | BU 208 A | 23a | |