

2 N 5826		Si-N	=2N5824: hFE=150...300	7a	SOT-30				BC 167, BC 182, BC 237, BC 547, ++
2 N 5827		Si-N	=2N5824: hFE=250...500	7a	SOT-30				BC 167, BC 182, BC 237, BC 547, ++
2 N 5827 A		Si-N	=2N5827: In, F<5dB(1kHz)	7a	SOT-30				BC 414, BC 550, 2SC1775(A), 2SC2390, ++
2 N 5828		Si-N	=2N5824: hFE=400...800	7a	SOT-30				BC 167, BC 182, BC 237, BC 547, ++
2 N 5828 A		Si-N	=2N5828: In, F<5dB(1kHz)	7a	SOT-30				BC 414, BC 550, 2SC1775(A), 2SC2390, ++
2 N 5829	Mot,Sca,Tho	Si-P	UHF, In, 30/30V, 0.03A, 0.2W, 1.5GHz	5g	TO-72				BF 316, BF 439, BF 516, BF 606, BFR 38++
2 N 5830	Fch,Nsc,Spr	Si-N	S,Vid, 120/100V, 0.6A, 0.625W, >100MHz, hFE=80...500	7e	TO-92				BF 391...393, BFP 22, MPS-A42...43
2 N 5831		Si-N	=2N5830: 160/140V, hFE=80...250	7e	TO-92				BF 391...393, BFP 22, MPS-A42...43
2 N 5832		Si-N	=2N5830: 160/140V, hFE=175...500	7e	TO-92				BF 391...393, BFP 22, MPS-A42...43
2 N 5833		Si-N	=2N5830: 200/180V, hFE=50...250	7e	TO-92				BF 391...393, BFP 22, MPS-A42...43
2 N 5834	Mot,Tix	Si-P	VHF Drv,Out, 60/40V, 1A, PQ=2.5W(175MHz)	2	TO-5				
2 N 5835	Mot,Sca	Si-N	SS,UHF, 15/10V, 15mA, 0.2W, >2.5GHz	5g	TO-72				BFR 15, BFR 99, BFP 66...67
2 N 5836	Mot,Sca	Si-N	SS,UHF, 15/10V, 0.2A, >2GHz	2a	TO-46				(BFR 95)6
2 N 5837	Mot,Sca	Si-N	SS,UHF, 10/5V, 0.3A, >1.7GHz	2a	TO-46				(2SC1253, 2SC1366, 2SC1952)6
2 N 5838	USA,Mot,Tix	Si-N	S P, 275/250V, 3/5A, 100W, >5MHz, 860/1400ns	23a	TO-3	BU 608	23a		BU 606...608, BUX 16A...C, BUW 71, ++
2 N 5839		Si-N	=2N5838: 300/275V, 670/2100ns	23a	TO-3	BU 608	23a		BU 606...608, BUX 16B...C, BUW 71, ++
2 N 5840		Si-N	=2N5838: 375/350V	23a	TO-3	BU 608	23a		BU 606...608, BUX 16B...C, BUW 71, ++
2 N 5841	Mot,Sca	Si-N	SS,UHF, 20/10V, 0.1A, 0.35W, >2.7GHz, 0.58/0.5ns	5g	TO-72				2SC3337, (BFR 95)6
2 N 5842		Si-N	=2N5841: 2GHz	5g	TO-72				2SC3337, (BFR 95)6
2 N 5843	Fch,Mot	Si-P	Dual, In, 50/40V, 0.05A, 0.6W, >200MHz, F<6dB(1kHz) hFE=50...150	TO-77	(CBE-EBC-)				BFX 11, 2N4015...16
2 N 5844		Si-P	=2N5843: >250MHz, hFE=100...300	TO-77	(CBE-EBC-)				BFX 11, 2N4015...16
2 N 5845	Mot,Spr	Si-N	S, 50/40V, 1A, 0.625W, >200MHz, <45/70ns	7e	TO-92				2N3736...37, 2N4013...14
2 N 5845 A		Si-N	=2N5845: >250MHz, <40/65ns	7e	TO-92				2N3736...37, 2N4013...14
2 N 5846	Mot	Si-N	HF P, 36/18V, 1A, PQ>3.5W(50MHz)	49a	TO-102				
2 N 5847	Mot	Si-N	HF P, 36/18V, 2A, PQ>8W(50MHz)	49a	SOT-147				
2 N 5848	Mot	Si-N	HF P, 48/24V, 3.5A, PQ>20W(50MHz)	55r	SOT-120				MRF 234
2 N 5849	Mot,Tho	Si-N	HF P, 48/24V, 7A, PQ>40W(50MHz)	55r	Mot,Tho				
2 N 5851	Mot,Sca,Ssi	Si-N	SS,UHF, 30/15V, 0.1A, 0.5W, 1.1GHz, 1.6/1.6ns	5g	TO-72				
2 N 5852	Mot,Sca,Ssi	Si-N	=2N5851: 1.4GHz	5g	TO-72				
2 N 5853	USA	Si-P	S P, 100/80V, 10A, 66W(Tc=100°), >15MHz	49a	TO-61				2N5290...91
2 N 5854		Si-N	=2N5853: >20MHz	49a	TO-61				2N5288...89
2 N 5855	Fch	Si-P	Uni, 60/60V, 1A, 0.75W, >100MHz	(2N5856 8a	TO-105	BC 640	7c		BC 327A, BC 638, BC 640, 2SB647, ++
2 N 5856	Fch	Si-N	Uni, 60/60V, 1A, 0.75W, >100MHz	(2N5855 8a	TO-105	BC 639	7c		BC 337A, BC 637, BC 639, 2SB647, ++
2 N 5857		Si-P	=2N5855: 80/80V	(2N5858 8a	TO-105	BC 640	7c		BC 640, 2SB647, 2SB910, 2SB1041, ++
2 N 5858		Si-N	=2N5856: 80/80V	(2N5857 8a	TO-105	BC 639	7c		BC 639, 2SD667, 2SD1226, 2SD1768, ++
2 N 5859	Mot,Sca,Ssi	Si-N	S, 80/40V, 2A, 1W, >250MHz, <36/70ns	2a	TO-39				BSS 14, 2N5262
2 N 5860	Sca,Ssi	Si-N	S, 90/45V, 2A, 1W, >250MHz, <26/70ns	2a	TO-39				
2 N 5861	Mot,Sca,Ssi	Si-N	S, 100/50V, 2A, 1W, >200MHz, <26/70ns	2a	TO-39				
2 N 5862	Mot,Tix	Si-N	VHF P, 65/35V, 8A, PQ=90W(150MHz)	55r	SOT-147				
2 N 5864	USA,Mot	Si-P	Uni, 90/70V, 1.5A, 1.25W, >50MHz, <130/750ns	2a	TO-39				BCX 60, BSS 17, BSV 17, 2N5322
2 N 5865	USA,Mot	Si-P	Uni, 70/50V, 1A, 1.25W, >100MHz, <120/500ns	2a	TO-39				BCX 60, BSS 17, BSX 59...61, 2N3444, ++
2 N 5867	USA,Mot,Tix	Si-P	LFS P, 60/60V, 5/7A, 87.5W, >4MHz	(2N5869 23a	TO-3				BD 246A, BDV 92, BDX 92, 2N5871...72, ++
2 N 5868		Si-P	=2N5867: 80/80V	(2N5870 23a	TO-3				BD 246B, BDV 94, BDX 94, 2N5872, ++
2 N 5869	USA,Mot,Tix	Si-N	LFS P, 60/60V, 5/7A, 87.5W, >4MHz	(2N5867 23a	TO-3				BD 245A, BDV 91, BDX 91, 2N5873...74, ++
2 N 5870		Si-N	=2N5869: 80/80V	(2N5868 23a	TO-3				BD 245B, BDV 93, BDX 93, 2N5874, ++
2 N 5871	USA,Mot,Sgs	Si-P	LFS P, 60/60V, 7/10A, 115W, >4MHz, -/ <1.8μs hFE=20...100	(2N5873 23a	TO-3	BD 318	23a		BD 312, BD 546A, BDW 22A, 2N5875...76, ++
2 N 5872	Rca,Tix	Si-P	=2N5871: 80/80V	(2N5871 23a	TO-3	BD 318	23a		BD 314, BD 546B, BDW 22B, 2N5876, ++
2 N 5873	USA,Mot,Sgs	Si-N	LFS P, 60/60V, 7/10A, 115W, >4MHz, -/ <1.8μs hFE=20...100	(2N5871 23a	TO-3	BD 317	23a		BD 545A, BD 311, BDW 21A, 2N5877...78, ++
2 N 5874		Si-N	=2N5873: 80/80V	(2N5872 23a	TO-3	BD 317	23a		BD 545A, BD 313, BDW 21B, 2N5878, ++
2 N 5875	USA,Mot,Sgs	Si-P	LFS P, 60/60V, 10/15A, 150W, >4MHz, -/ <1.8μs hFE=20...100	(2N5877 23a	TO-3	BD 318	23a		BD 312, BD 546A, BDW 22A, 2N5879...80, ++
2 N 5876		Si-P	=2N5875: 80/80V	(2N5878 23a	TO-3	BD 318	23a		BD 314, BD 546B, BDW 22B, 2N5880, ++
2 N 5877	USA,Mot,Sgs	Si-N	LFS P, 60/60V, 10/15A, 150W, >4MHz, -/ <1.8μs hFE=20...100	(2N5875 23a	TO-3	BD 317	23a		BD 311, BD 545A, BDW 21A, 2N5881...82, ++
2 N 5878		Si-N	=2N5877: 80/80V	(2N5876 23a	TO-3	BD 317	23a		BD 313, BD 545B, BDW 21B, 2N5882, ++
2 N 5879	USA,Mot,Rca	Si-P	LFS P, 60/60V, 15/20A, 160W, >4MHz, -/ <1.8μs hFE=20...100	(2N5881 23a	TO-3	BD 318	23a		BD 316, BD 746A, BDW 52A, 2N6029...31, ++
2 N 5880		Si-P	=2N5879: 80/80V	(2N5882 23a	TO-3	BD 318	23a		BD 316, BD 746B, BDW 52B, 2N6029...31, ++
2 N 5881	USA,Mot,Rca	Si-N	LFS P, 60/60V, 15/20A, 160W, >4MHz, -/ <1.8μs hFE=20...100	(2N5879 23a	TO-3	BD 317	23a		BD 315, BD 745A, BDW 51A, 2N5620...31, ++
2 N 5882		Si-N	=2N5881: 80/80V	(2N5880 23a	TO-3	BD 317	23a		BD 315, BD 745B, BDW 51B, 2N5620...31, ++
2 N 5883	USA,Mot,Sgs	Si-P	LFS P, 60/60V, 25/30A, 200W, >4MHz, -/ <1.8μs hFE=20...100	(2N5885 23a	TO-3				BD 367, BD 369, MJ 4502, 2N4399
2 N 5884		Si-P	=2N5883: 80/80V	(2N5886 23a	TO-3				BD 369, MJ 4502
2 N 5885	USA,Mot,Sgs	Si-N	LFS P, 60/60V, 25/30A, 200W, >4MHz, -/ <1.8μs hFE=20...100	(2N5883 23a	TO-3				BD 366, BD 368, BDY 29, MJ 802, ++
2 N 5886		Si-N	=2N5885: 80/80V	(2N5884 23a	TO-3				BD 368, BDY 29, MJ 802, 2SD797, ++
2 N 5887	Gpd,Mot,Stc	Ge-P	LFS P, 20/15/20V, 7A, 57W, hFE=15...350, >0.25MHz	22a	TO-66				
2 N 5888		Ge-P	=2N5887: 30/25/20V	22a	TO-66				
2 N 5889		Ge-P	=2N5887: 30/25/20V, hFE=30...70	22a	TO-66				
2 N 5890		Ge-P	=2N5887: 45/35/20V, hFE=30...70	22a	TO-66				
2 N 5891		Ge-P	=2N5887: 60/45/20V, hFE=30...70	22a	TO-66				
2 N 5892		Ge-P	=2N5887: 75/60/20V, hFE=30...70	22a	TO-66				
2 N 5893		Ge-P	=2N5887: 30/25/20V, hFE=60...120	22a	TO-66				
2 N 5894		Ge-P	=2N5887: 45/25/20V, hFE=60...120	22a	TO-66				
2 N 5895		Ge-P	=2N5887: 60/45/20V, hFE=60...120	22a	TO-66				
2 N 5896		Ge-P	=2N5887: 75/60/20, hFE=60...120	22a	TO-66				
2 N 5897		Ge-P	=2N5887: 30/25/20V, hFE=100...200	22a	TO-66				
2 N 5898		Ge-P	=2N5887: 45/30/20V, hFE=100...200	22a	TO-66				
2 N 5899		Ge-P	=2N5887: 60/45/20V, hFE=100...200	22a	TO-66				
2 N 5900		Ge-P	=2N5887: 75/60/20V, hFE=100...200	22a	TO-66				
2 N 5901		Ge-P	=2N5887: 30/25/20V, hFE=175...350	22a	TO-66				
2 N 5902	Isi,Nsc,Six	N-FET	Dual, In, 40V, Idss=0.03...0.5mA, Up=0.6...4.5V, F<3dB(100Hz), ΔIdss=0.95...1, ΔUgs<5mV	TO-99	(SDG-SDG-)				
2 N 5903	Sol	N-FET	=2N5902: ΔUgs<5mV	TO-99	(SDG-SDG-)				
2 N 5904		N-FET	=2N5902: ΔUgs<10mV	TO-99	(SDG-SDG-)				
2 N 5905		N-FET	=2N5902: ΔUgs<15mV	TO-99	(SDG-SDG-)				
2 N 5906		N-FET	=2N5902: F<1dB(100Hz)	TO-99	(SDG-SDG-)				
2 N 5907		N-FET	=2N5903: F<1dB(100Hz)	TO-99	(SDG-SDG-)				
2 N 5908		N-FET	=2N5904: F<1dB(100Hz)	TO-99	(SDG-SDG-)				