

2 SA 1658	Kec	Si-P	LFS P, 30/30V, 3A, 15W, 100MHz	17c	SOT-186	2SA1307	17c	2SA1305, 2SA1307, 2SA1440, 2SB1274, ++
2 SA 1659	Kec	Si-P	LFS P, 160/160V, 1.5A, 20W, 100MHz	17c	SOT-186	2SA1606	17c	2SA1306A,B9, 2SA1332, 2SA1606, ++ ³
2 SA 1660	Kec	Si-P	SMD, Uni, 150/150V, 0.05A, 120MHz	39b	SOT-89			2SA1200, 2SB807
2 SA 1661	Kec	Si-P	SMD, Uni, 120/120V, 0.8A, 120MHz	39b	SOT-89			2SA1201, 2SB806
2 SA 1662	Kec	Si-P	SMD, Uni, 80/80V, 0.4A, 120MHz	39b	SOT-89			2SA1202, 2SB767
2 SA 1663	Kec	Si-P	SMD, Uni, 30/30V, 1.5A, 120MHz	39b	SOT-89			2SA1369, 2SB1121
2 SA 1664	Kec	Si-P	SMD, Uni, 35/30V, 0.8A, 120MHz	39b	SOT-89			BCX 51...53, 2SA1204, 2SA1364, 2SB766A
2 SA 1666	Hit	Si-P	SMD, HFS, 20/15V, 0.2A, 35/70ns	35a	SOT-23			
2 SA 1667	Sak	Si-P	TV Audio P, 150/150V, 2A, 25W, 20MHz	(2SC4381) 17c	TO-220 Iso	2SA1606	17c	2SA1304, 2SA1306, 2SA1606, 2SB1338, ++
2 SA 1668	Sak	Si-P	=2SA1667: 200/200V	(2SC4382) 17c	TO-220 Iso	(2SA1606) ⁷	17c	2SA1306B, 2SB1096
2 SA 1669	Say	Si-P	SMD, UHF, 20/15V, 50mA, 3000MHz, F=2dB(900MHz)	35a	SOT-23			
2 SA 1670	Sak	Si-P	P, 80/80V, 6A, 60W, 20MHz, 250/600ns	(2SC4385) 18c	TO-3P Iso	(BD 246 C) ³	18j	(BD 246B...F, 2SA1264, 2SB688, 2SB775, ++) ³
2 SA 1671	Sak	Si-P	P, 120/120V, 8A, 75W, 20MHz, 250/900ns	(2SC4386) 18c	TO-3P Iso	(2SA1186) ³	18j	(2SA1186, 2SA1382, 2SB1459, 2SB1312, ++) ³
2 SA 1672	Sak	Si-P	P, 140/140V, 10A, 80W, 20MHz, 300/1100ns	(2SC4387) 18c	TO-3P Iso	(2SA1186) ³	18j	(2SA1146, 2SA1186, 2SA1265, 2SA1491, ++) ³
2 SA 1673	Sak	Si-P	P, 180/180V, 15A, 85W, 20MHz, 600/1100ns	(2SC4388) 18c	TO-3P Iso	(2SA1294) ³	18j	(2SA1294, 2SA1386A, 2SA1492, 2SA1516, ++) ³
2 SA 1674	Mat	Si-P	LF, 80/80V, 1/1.5A, 1W, 120MHz	(2SC4391) 9c		BC 640	7c	BC 640, 2SB1130, 2SB1236, 2SB1437, ++
2 SA 1676	Say	Si-P+A	SMD, S, 50/50V, 0, 1/0.2A, 200MHz, Rb=Rbe=47kΩ	(2SC4396) 35a(2mm)	SOT-323			
2 SA 1677	Say	Si-P+R	=2SA1676: Rb=Rbe=22kΩ	(2SC4397) 35a(2mm)	SOT-323			
2 SA 1678	Say	Si-P+R	=2SA1676: Rb=Rbe=10kΩ	(2SC4398) 35a(2mm)	SOT-323			
2 SA 1679	Shi	Si-P	S P, 60/40V, 5A, 10W, <300/2000ns, sat<0.3V	15c	(ITO-220)	2SA1307	17c	2SA1307, 2SA1469, 2SA1741
2 SA 1680	Tos	Si-P	60/50V, 2A, 0.9W, 100/400ns, sat<0.5V(1A)	(2SC4408) 7c(9mm)	TO-92L	2SB892	7c(9mm)	2SA1315, 2SA1382, 2SB1459, 2SB1312, ++
2 SA 1681	Tos	Si-P	=2SA1680: SMD	(2SC4409) 39b	SOT-89			2SA1736, 2SB1123...1124, 2SB1520
2 SA 1682	Tos	Si-P	SMD, CTV Vid, 300/300V, 50/100mA, 70MHz	(2SC4412) 35a	SOT-23			BF 821, BFN 27
2 SA 1683	Say	Si-P	100/80V, 0.5/0.8A, 0.3W, 120MHz, 50/580ns	(2SC4414) 41c				
2 SA 1684	Nec	Si-P	LF,HF P, 120/120V, 1.5/3A, 20W, 150MHz	(2SC4431) 17c	SOT-186	2SA1606	17c	2SA1306(A,B), 2SA1393, 2SA1332, 2SB1186+
2 SA 1685	Say	Si-P	=2SA1607:	(2SC4443) 35a(2mm)	SOT-323			(2SA1607)
2 SA 1687	Say	Si-P	SMD, 60/50V, hi-Ueb=15V, 0.15/0.3A, 130MHz, 50/520ns	(2SC4446) 35a(2mm)	SOT-323			(2SA1252, 2SA1311)
2 SA 1688	Say	Si-P	=2SA1256:	35a(2mm)	SOT-323			
2 SA 1689	Say	Si-P	Vid, 300/300V, 0.05/0.1A, 0.5W, 70MHz	(2SC4449) 7c	TO-92	BF 421 A	7c	BF 421(A), BF 437, 2SA1371
2 SA 1690	Rhm	Si-P	SMD, -/400V, 0, 1/0.2A	39b	SOT-89			2SA1740
2 SA 1692	Say	Si-P	30/25V, hi-Ueb=15V, 2A, 15W, 110MHz, 330/1350ns	=14h	(TO-126LP)			
2 SA 1693	Sak	Si-P	lo-sat<0.5V(1A), hi-hFE=500...1200	(2SC3807) 18j	TO-3P	BD 246 C	18j	BD 246B...F, 2SA1264, 2SB775...776, ++
2 SA 1694	Sak	Si-P	P, 80/80V, 6A, 60W, 20MHz, 180/1310ns	(2SC4466) 18j	TO-3P	2SA1186	18j	2SA1146, 2SA1186, 2SA1264, 2SB688, ++ ¹⁷
2 SA 1695	Sak	Si-P	P, 120/120V, 8A, 80W, 20MHz, 140/1610ns	(2SC4467) 18j	TO-3P	(2SB817) ¹⁷	18j	(BD 246D...F, 2SA1265, 2SA1645, 2SB817) ¹⁷
2 SA 1696	Say	Si-P	140/140V, 10A, 100W, 20MHz, sat<0.5V(5A)	(2SC4468) 18j	TO-3P			(2SA1475) ³
2 SA 1697	Say	Si-P	Vid P, 120/120V, 0, 4/0.6A, 10W(50°), 400MHz	(2SC4473) 17c	TO-220 Iso			
2 SA 1697	Say	Si-P	Vid P, 200/200V, 0, 2/0.3A, 10W(50°), 300MHz	(2SC4474) 17c	TO-220 Iso			
2 SA 1698	Mat	Si-P	HF, Vid, 300/300V, 70/100mA, 1.2W(Ta=25°), >50MHz	14h	TO-126	BF 472	14h	BF 418, BF 472, 2SA1353, 2SA1381
2 SA 1699	Say	Si-P	S,Drv, 400/400V, 0,2/0.4A, 0.6W, 70MHz	(2SC4002) 7c	TO-92			2SA1251, 2SA1625, 2SB1074, 2SB1488
2 SA 1700	Say	Si-P	=2SA1699: 10W	(2SC4003) 30j	TO-251/252			2SA1498
2 SA 1701	Say	Si-P	S, 15/15V, 1.5/3A, 0.9W, 300MHz	(2SC4481) 9c				
2 SA 1702	Say	Si-P	S, 25/20V, 5/8A, 1W, 320MHz, 40/210ns	9c		2SB1446	9c	2SA1431, 2SB1288, 2SB1305...07, 2SB1319
2 SA 1703	Say	Si-P	30/25V, 1.5/3A, 1W, 180MHz, sat<0.5V(0.5A)	(2SC4483) 9c		2SB892	7c(9mm)	2SB926...927, 2SB892, 2SB1229
2 SA 1704	Say	Si-P	30/25V, 2.5/5A, 1W, 150MHz, sat<0.6V(1.5A)	(2SC4484) 9c		2SB985	7c(9mm)	2SB892, 2SB985
2 SA 1705	Say	Si-P	LFS, 60/50V, 1/2A, 0.9W, 150MHz, 40/330ns	9c		2SB892	7c(9mm)	2SA1315, 2SB892, 2SB1229
2 SA 1706	Say	Si-P	lo-sat<0.5V(0.5A)	(2SC4485) 9c				
2 SA 1706	Say	Si-P	NFS, 60/50V, 2/4A, 1W, 150MHz, 60/480ns	9c		2SB892	7c(9mm)	2SA1315, 2SB892, 2SB1229
2 SA 1707	Say	Si-P	lo-sat<0.7V(1A)	(2SC4486) 9c				
2 SA 1707	Say	Si-P	LFS, 60/50V, 3/6A, 1W, 150MHz, 70/485ns	9c		2SB985	7c(9mm)	2SB985, 2SB1066
2 SA 1707	Say	Si-P	lo-sat<0.7V(2A)	(2SC4487) 9c				
2 SA 1708	Say	Si-P	LFS, 120/100V, 1/2A, 1W, 120MHz, 80/740ns	9c		(2SB1212) ¹⁷	7c(9mm)	
2 SA 1708	Say	Si-P	lo-sat<0.6V(0.4A)	(2SC4488) 9c				
2 SA 1709	Say	Si-P	LFS, 120/100V, 2/3A, 1W, 120MHz, 80/790ns	9c				
2 SA 1709	Say	Si-P	lo-sat<0.6V(1A)	(2SC4489) 9c				
2 SA 1710	Say	Si-P	LF Drv,Vid, 300/300V, 0, 1/0.2A, 1W, 70MHz	(2SC4490) 9c		BF 421 A	7c	BF 421A, BF 437, BF 493, 2SA1371
2 SA 1711	Tos	Si-P	S, 20/20V, 0,03A, 0.2W, 950MHz, 15/110ns	41c				BSS 11...12, BSV 90...92, 2SC2901, ++
2 SA 1712	Tos	Si-P	=2SA1711: SMD	35a	SOT-23			
2 SA 1714	Nec	Si-P-Darl	S P, 100/100V, 3A, 12W, hFE=2k...20k, 150/1800ns	14h	TO-126	(BD 680) ¹³	14h	(BD 680, BD 682, 2N6036) ¹³
2 SA 1715	Nec	Si-P-Darl+Di	100/100V, 5A, 25W, 180MHz, hFE=2k...20k, 300/1600ns	15j	(MP-40)			2SB1339
2 SA 1716	Nec	Si-P-Darl+Di	100/100V, 8A, 30W, 100MHz, hFE=4k...20k, 200/2200ns	15j	(MP-40)			2SB1343
2 SA 1717	Nec	Si-P-Darl+Di	100/100V, 10A, 40W, 100MHz, hFE=4k...20k, 200/2200ns	15j	(MP-40)			
2 SA 1718	Nec	Si-P-Darl	=2SA1715: Iso	17c	SOT-186			2SB1098, 2SB152, 2SB1430
2 SA 1719	Nec	Si-P-Darl	=2SA1716: Iso	17c	SOT-186			2SB1099, 2SB1431
2 SA 1720	Nec	Si-P-Darl	=2SA1717: Iso	17c	SOT-186			2SB1432
2 SA 1721	Tos	Si-P	SMD, Nixie, Video, 300/300V, 0, 1A, 55MHz	(2SC4497) 35a	SOT-23			BFN 27
2 SA 1722	Say	Si-P+R	SMD, S, 50/50V, 0, 1/0.2A, Rb=2.2kΩ, Rbe=10kΩ	35a(2mm)	SOT-323			
2 SA 1722	Say	Si-P+R	200MHz	(2SC4498) 35a(2mm)	SOT-323			
2 SA 1723	Say	Si-P	Display Video, 30/20V, 0.3A, 5W, 1500MHz	14h	TO-126			
2 SA 1724	Say	Si-P	SMD, Display Video, 30/20V, 0, 3/0.6A, 1500MHz	39b	SOT-89			
2 SA 1725	Sak	Si-P	=2SA1726: Iso, 30W	17c	TO-220 Iso	2SB1018	17c	2SA1442, 2SA1470, 2SB1097, 2SB1290
2 SA 1726	Sak	Si-P	LF P, 80/80V, 6A, 50W, 20MHz, 180/1310ns	(2SC4512) 17j	TO-220	BD 244 C	17j	BD 244B...F, BD 544B...C, BD 800, BD 810++
2 SA 1727(F5)	Rhm	Si-P	S, 400/400V, 0.5/1A, 10W, 12MHz, 600/3700ns	30c	TO-251			2SA1400
2 SA 1728	Say	Si-P	SMD, S, 50/40V, 0.5/1A, 350MHz, 60/170ns	35a	F5: TO-252			
2 SA 1729	Say	Si-P	SMD, S, 50/40V, 1.5/3A, 300MHz, 50/150ns	(2SC4520) 39b	SOT-89			
2 SA 1730	Say	Si-P	SMD, S, 50/40V, 3/6A, 300MHz, 50/150ns	(2SC4521) 39b	SOT-89			
2 SA 1731	Say	Si-P	S P, 50/40V, 5/8A, 15W, 300MHz, 50/150ns	(2SC4522) 30c	TO-251/252			
2 SA 1732	Say	Si-P	S P, 50/40V, 8/12A, 15W, 250MHz, 50/150ns	(2SC4523) 30c	TO-251/252			
2 SA 1733 K	Rhm	Si-P	SMD, HF, 30/20V, 0.03A, >200MHz, F=3.5dB(10MHz)	35a	SOT-23	BC 856	35a	BC 856...860, BCF 29...30, BCW 29...30, ++
2 SA 1734	Tos	Si-P	SMD, S, 40/30V, 1, 2A, 100MHz, 100/300ns	(2SC4539) 39b	SOT-89			2SA1681, 2SB1123, 2SB1313
2 SA 1735	Tos	Si-P	lo-sat<0.5V(0.7A)					
2 SA 1735	Tos	Si-P	SMD, S, 60/50V, 1A, 100MHz, 100/350ns	(2SC4540) 39b	SOT-89			2SA1681, 2SB1122...1123, 2SB1313
2 SA 1736	Tos	Si-P	lo-sat<0.5V(0.5A)					
2 SA 1736	Tos	Si-P	SMD, S, 60/50V, 3A, 100MHz, 100/300ns	(2SC4541) 39b	SOT-89			2SB1124, 2SB1572
2 SA 1736	Tos	Si-P	lo-sat<0.5V(1.5A)					
2 SA 1737	Mat	Si-P	=2SA1487: SMD	39b	SOT-89			
2 SA 1738	Mat	Si-P	SMD, S, 15/15V, 50/100mA, 1500MHz, 12/20ns	35a	SOT-23			BSR 12, 2SA1764
2 SA 1739	Mat	Si-P	=2SA1738:	35a(2mm)	SOT-323			2SA1610, 2SA1763
2 SA 1740	Say	Si-P	=2SA1699: SMD	39b	SOT-89			2SA1812
2 SA 1741	Nec	Si-P	=2SA1441:	17c	TO-220 Iso	+2SA1441		+2SA1441