

TRANSISTOR NUMBER	P M O A L T	PACK-AGE	LEAD INFO	V _{CE} MAX	V _{CE} MAX	V _{EB} MAX	I _C MAX	T _J MAX	P TOT	F _r MIN	C _{OB} MAX	H _{FE}	H _{FE} BIAS	USE	MFR	ALTERNATIVES AND NOTES	
2N5271	N S	TO39	L04	200V	-	7V	5A	-	600mWF	-	6P0	-	-	SMS	MOT	BSS45	2N5154
2N5272	N S	TO18	L01	40V	20V	-	200mA	200C	360mWF	500M	4P0	100mn	10mA	ULS	OBS	BSX20	2N2369
2N5276	N S	TO18	L01	25V	15V	-	-	200C	360mWF	600M	-	30/90	1mA	RLS	TIS	Radiation Screened	
2N5279	N S	TO5	L04	400V	-	7V	1A	200C	5WC	15M	10P	40/160	20mA	RME	SIT	BUX53	2N3439
2N5280	N S	TO5F	L44	400V	-	7V	1A	200C	15WC	15M	10P	40/160	20mA	RME	SIT	2N4063	
2N5281	P S	TO5	L04	175V	150V	-	1A	175C	2WC	20M	20P	20/200	1mA	AME	SIT	BFT19	2N5415
2N5282	P S	TO5	L04	325V	300V	-	1A	175C	2WC	20M	20P	20/200	1mA	AME	SIT	BFT19B	2N5416
2N5284	N S	TO59	L63	120V	80V	6V	5A	200C	50WC	60M	250P	30/90	2500mA	RHH	KER	2N5288	
2N5285	N S	TO59	L63	120V	80V	6V	5A	200C	50WC	70M	250P	70/200	2500mA	RHH	KER	2N5289	
2N5286	P S	TO59	L63	100V	100V	5V	5A	200C	50WC	60M	250P	30/90	2500mA	RHH	KER	2N5290	
2N5287	P S	TO59	L63	100V	100V	5V	5A	200C	50WC	70M	250P	70/200	2500mA	RHH	KER	2N5291	
2N5288	N S	TO61	L46	120V	100V	6V	10A	200C	100WC	30M	275P	30/90	5A	RHH	KER	2N5957	
2N5289	N S	TO61	L46	120V	100V	6V	10A	200C	100WC	40M	275P	70/200	5A	RHH	KER	2N5957	
2N5290	P S	TO61	L46	100V	100V	6V	10A	200C	100WC	30M	500P	30/90	5A	RHH	KER	2N5009	
2N5291	P S	TO61	L46	100V	100V	6V	10A	200C	100WC	40M	500P	70/200	5A	RHH	KER	2N5009	
2N5292	P S	TO18	L01	12V	12V	4V	100mA	200C	360mWF	800M	4P5	40/100	30mA	ULS	OBS	BSW25	2N3546
2N5293	N S	TO66	L33	80V	75V	7V	4A	150C	36WC	800K	-	30/120	500mA	AHH	RCA	BDX72	2N6293
2N5294	N S	TO220	L32	80V	75V	7V	4A	150C	36WC	800K	-	30/120	500mA	AHH	RCA	BD589	2N6123
2N5295	N S	TO66	L33	60V	50V	5V	4A	150C	36WC	800K	-	30/120	1A	AHG	RCA	BDX72	2N6293
2N5296	N S	TO220	L32	60V	50V	5V	4A	150C	36WC	800K	-	30/120	1A	AHG	RCA	BD589	2N6123
2N5297	N S	TO220	L33	80V	70V	5V	4A	150C	36WC	800K	-	20/80	1500mA	AHG	RCA	BDX72	2N6293
2N5298	N S	TO220	L32	80V	70V	5V	4A	150C	36WC	800K	-	20/80	1500mA	AHG	RCA	BD589	2N6123
2N5301	N S	TO3	L05	40V	40V	5V	30A	200C	200WC	2M	-	15/60	15A	AHG	MOT	BDX40	2N3772
2N5302	N S	TO3	L05	60V	60V	5V	30A	200C	200WC	2M	-	15/60	15A	AHH	MOT	BDX40	2N3772
2N5303	N S	TO3	L05	80V	80V	5V	20A	200C	200WC	2M	-	15/60	10A	AHH	MOT	BDX40	2N3772
2N5304	N S	TO61	L46	50V	40V	6V	10A	200C	25WC	100M	300P	30/120	2A	RHP	MOT	BDY63	
2N5305	N S	TO98	L21	25V	25V	12V	300mA	125C	400mWF	60M	10P	2Kmn	2mA	ALD	GES		
2N5306	N S	TO98	L21	25V	25V	12V	300mA	125C	400mWF	60M	10P	7Kmn	2mA	ALD	GES		
2N5306A	N S	TO98	L21	25V	25V	12V	300mA	125C	400mWF	60M	10P	7Kmn	2mA	ALD	GES		
2N5307	N S	TO98	L21	40V	40V	12V	300mA	125C	400mWF	60M	10P	2Kmn	2mA	ALD	GES		
2N5308	N S	TO98	L21	40V	40V	12V	300mA	125C	400mWF	60M	10P	7Kmn	2mA	ALD	GES		
2N5308A	N S	TO98	L21	40V	40V	12V	300mA	125C	400mWF	60M	10P	7Kmn	2mA	ALN	GES		
2N5309	N S	TO98	L21	70V	50V	5V	100mA	125C	360mWF	100M	6P0	100mn	2mA	ALG	GES	PBC107	2N5309
2N5310	N S	TO98	L21	70V	20V	5V	100mA	125C	360mWF	-	4P0	100mn	2mA	ALN	GES	BC184L	2N5210
2N5311	N S	TO98	L21	70V	20V	5V	100mA	125C	360mWF	-	4P0	250mn	2mA	ALN	GES	BC184L	2N5210
2N5312	P S	TO61	L60	80V	80V	6V	10A	200C	50WC	30M	500P	30/90	10A	AHS	OBS	2N5290	
2N5313	N S	TO61	L60	80V	80V	6V	10A	200C	50WC	30M	500P	30/90	10A	AHS	OBS	2N5288	
2N5314	P S	TO61	L60	100V	100V	6V	10A	200C	50WC	30M	500P	30/90	10A	AHS	OBS	2N5290	
2N5315	N S	TO61	L60	100V	100V	6V	10A	200C	50WC	30M	500P	30/90	10A	AHS	OBS	2N5288	
2N5316	P S	TO61	L60	80V	80V	6V	10A	200C	50WC	30M	500P	30/90	5A	AHS	OBS	2N5290	
2N5317	N S	TO61	L60	80V	80V	6V	10A	200C	50WC	30M	500P	30/90	5A	AHS	OBS	2N5288	
2N5318	P S	TO61	L60	100V	100V	6V	10A	200C	50WC	30M	500P	30/90	5A	AHS	OBS	2N5290	
2N5319	N S	TO61	L60	100V	100V	6V	10A	200C	50WC	30M	500P	30/90	5A	AHS	OBS	2N5288	
2N5320	N S	TO39	L04	100V	75V	7V	2A	200C	1WF	50M	-	30/130	500mA	AMH	RCA	BSS42	2N5320
2N5320-R	N S	TO5	L04	100V	75V	7V	2A	200C	10WC	50M	20P	33/50	500mA	RMS	FCD	BSS15	2N2102
2N5320-BR	N S	TO5	L04	100V	75V	7V	2A	200C	10WC	50M	20P	25/38	500mA	RMS	FCD	BSS15	2N2102
2N5320-O	N S	TO5	L04	100V	75V	7V	2A	200C	10WC	50M	20P	43/65	500mA	RMS	FCD	BSS15	2N2102
2N5320-Y	N S	TO5	L04	100V	75V	7V	2A	200C	10WC	50M	20P	56/85	500mA	RMS	FCD	BSS15	2N2102
2N5320-GN	N S	TO5	L04	100V	75V	7V	2A	200C	10WC	50M	20P	73/100	500mA	RMS	FCD	BSS15	2N2102
2N5320-BL	N S	TO5	L04	100V	75V	7V	2A	200C	10WC	50M	20P	95/145	500mA	RMS	FCD	BSS15	2N2102
2N5320-V	N S	TO5	L04	100V	75V	7V	2A	200C	10WC	50M	20P	1225mn	500mA	RMS	FCD	BSS15	2N2102
2N5320-W	N S	TO5	L04	100V	75V	7V	2A	200C	10WC	50M	20P	165mn	500mA	RMS	FCD	BSS15	2N2102
2N5321	N S	TO39	L04	75V	50V	5V	2A	200C	1WF	50M	-	40/250	500mA	AMG	STM	BSS16	2N5320
2N5321-R	N S	TO5	L04	75V	50V	5V	2A	200C	1WF	50M	20P	33/50	500mA	RMS	FCD	BSS16	2N5320
2N5321-BR	N S	TO5	L04	75V	50V	5V	2A	200C	1WF	50M	20P	25/38	500mA	RMS	FCD	BSS16	2N5320
2N5321-O	N S	TO5	L04	75V	50V	5V	2A	200C	1WF	50M	20P	43/65	500mA	RMS	FCD	BSS16	2N5320
2N5321-Y	N S	TO5	L04	75V	50V	5V	2A	200C	1WF	50M	20P	56/85	500mA	RMS	FCD	BSS16	2N5320
2N5321-GN	N S	TO5	L04	75V	50V	5V	2A	200C	1WF	50M	20P	73/100	500mA	RMS	FCD	BSS16	2N5320
2N5321-BL	N S	TO5	L04	75V	50V	5V	2A	200C	1WF	50M	20P	95/145	500mA	RMS	FCD	BSS16	2N5320
2N5321-V	N S	TO5	L04	75V	50V	5V	2A	200C	1WF	50M	20P	125mn	500mA	RMS	FCD	BSS16	2N5320
2N5321-W	N S	TO5	L04	75V	50V	5V	2A	200C	1WF	50M	20P	165mn	500mA	RMS	FCD	BSS16	2N5320
2N5322	P S	TO39	L04	100V	75V	7V	2A	200C	1WF	50M	-	30/130	500mA	AMH	STM	BSS17	2N5322
2N5322-R	P S	TO39	L04	100V	75V	7V	2A	200C	1WF	50M	40P	33/50	500mA	RMS	FCD	BSS17	2N4036
2N5322-BR	P S	TO39	L04	100V	75V	7V	2A	200C	1WF	50M	40P	25/38	500mA	RMS	FCD	BSS17	2N4036
2N5322-O	P S	TO39	L04	100V	75V	7V	2A	200C	1WF	50M	40P	43/65	500mA	RMS	FCD	BSS17	2N4036
2N5322-Y	P S	TO39	L04	100V	75V	7V	2A	200C	1WF	50M	40P	56/85	500mA	RMS	FCD	BSS17	2N4036
2N5322-GN	P S	TO39	L04	100V	75V	7V	2A	200C	1WF	20M	40P	73/100	500mA	RMS	FCD	BSS17	2N4036
2N5322-BL	P S	TO39	L04	100V	75V	7V	2A	200C	1WF	50M	40P	95/145	500mA	RMS	FCD	BSS17	2N4036
2N5322-V	P S	TO39	L04	100V	75V	7V	2A	200C	1WF	50M	40P	125mn	500mA	RMS	FCD	BSS17	2N4036
2N5322-W	P S	TO39	L04	100V	75V	7V	2A	200C	1WF	50M	40P	165mn	500mA	RMS	FCD	BSS17	2N4036
2N5323	P S	TO39	L04	75V	50V	5V	2A	200C	1WF	50M	-	40/250	500mA	AMG	STM	BSS18	2N5322
2N5323-R	P S	TO39	L04	75V	50V	5V	2A	200C	1WF	50M	40P	33/50	500mA	RMS	FCD	BSS18	2N4036