

| | | | | | | | | | |
|-------------|------------------------|----------|--|-------|------------|----------|---------|--|---|
| 2 N 2570 | Amp,Phi | Si-N | Chopper, 20V, 0,1A, 0,3W, >100MHz | 2a | TO-18 | | | | 2N2432, 2N4138 |
| 2 N 2571 | Amp | Si-N | Chopper, 20V, 0,5A, 0,3W, >100MHz | 2a | TO-18 | | | | |
| 2 N 2572 | Amp | Si-N | Chopper, 20V, 0,5A, 0,3W, >100MHz | 2a | TO-18 | | | | |
| 2 N 2573 | Mot,Slid | 50Hz-Thy | 25V, 17A(Tc=85°), 25A=, Igt/Ih<40/10mA | 23a | TO-3 | | | | 2N3668 |
| 2 N 2574 | | 50Hz-Thy | =2N2573: 50V | 23a | TO-3 | | | | 2N3668 |
| 2 N 2575 | | 50Hz-Thy | =2N2573: 100V | 23a | TO-3 | | | | 2N3668 |
| 2 N 2576 | | 50Hz-Thy | =2N2573: 200V | 23a | TO-3 | | | | 2N3669 |
| 2 N 2577 | | 50Hz-Thy | =2N2573: 300V | 23a | TO-3 | | | | 2N3670 |
| 2 N 2578 | | 50Hz-Thy | =2N2573: 400V | 23a | TO-3 | | | | 2N3670 |
| 2 N 2579 | | 50Hz-Thy | =2N2573: 500V | 23a | TO-3 | | | | |
| 2 N 2580(M) | Del,Stc | Si-N | S P, 400/400V, 10A, 150W, hFE=10...40 | 38a | TO-36 | | | | |
| 2 N 2581 | Del,Stc | Si-N | =2N2580: hFE=25...65 | 38a | TO-36 | | | | |
| 2 N 2582 | Del,Stc | Si-N | S P, 500/500V, 10A, 150W, hFE=10...40 | 38a | TO-36 | | | | |
| 2 N 2583 | Del,Stc | Si-N | =2N2582: hFE=25...65 | 38a | TO-36 | | | | |
| 2 N 2584 | Stc | Si-N | S P, 600/600V, 10A, 150W, hFE=10...40 | 38a | TO-36 | | | | |
| 2 N 2585 | Stc | Si-N | =2N2584: hFE=25...65 | 38a | TO-36 | | | | |
| 2 N 2586 | USA,EUR,Mic | Si-N | LF Inp In, 60V, 0,03A, 0,3W, 63MHz | 2a | TO-18 | | | | 2N2483...84, 2N3117, 2SC2240, 2SC2390, ++ |
| 2 N 2587 | Mot | Ge-P | UHF, 30V, 0,1A, 0,15W, >320MHz | 2a | TO-18 | | | | 2N3283...86 |
| 2 N 2588 | Tix | Ge-P | HF, 40V, 0,03A, 0,15W, >75MHz | 2a | TO-18 | | | | AF 106, AF 109R, AF 306 |
| 2 N 2589 | Stc | Si-N | S P, 150/150V, 7A, 85W | 49m | TO-63 | | | | 2N5542 |
| 2 N 2590 | USA | Si-P | Uni, 100V, 0,05A, 0,4W, >50MHz, hFE>40 | 2a | TO-46 | | | | BSS 68, BSV 68, 2SA970, 2SB715...16, ++ |
| 2 N 2591 | USA | Si-P | =2N2590: >70MHz, hFE>70 | 2a | TO-46 | | | | BSS 68, BSV 68, 2SA970, 2SB715...16, ++ |
| 2 N 2592 | USA | Si-P | =2N2590: >90MHz, hFE>115 | 2a | TO-46 | | | | BSS 68, BSV 68, 2SA970, 2SB715...16, ++ |
| 2 N 2593 | USA | Si-P | =2N2590: >110MHz, hFE>160 | 2a | TO-46 | | | | BSS 68, BSV 68, 2SA970, 2SB715...16, ++ |
| 2 N 2594 | USA,Tix | Si-N | LFS, 80V, 1A, 1W, >40MHz | 2a | TO-5 | | | | BC 140...141, 2N1990, 2N2102, 2N2405, ++ |
| 2 N 2595 | USA | Si-P | Uni, 80V, 0,05A, 0,4W, >30MHz, hFE>15 | 2a | TO-46 | | | | BSS 68, BSV 68, 2SA970, 2SB715...16, ++ |
| 2 N 2596 | USA | Si-P | =2N2595: >40MHz, hFE>30 | 2a | TO-46 | | | | BSS 68, BSV 68, 2SA970, 2SB715...16, ++ |
| 2 N 2597 | USA | Si-P | =2N2595: >60MHz, hFE>60 | 2a | TO-46 | | | | BSS 68, BSV 68, 2SA970, 2SB715...16, ++ |
| 2 N 2598 | USA | Si-P | Uni, 125V, 0,05A, 0,4W, >30MHz, hFE>20 | 2a | TO-46 | | | | BF 398, 2SA970, 2SA1049, 2SB716(A), ++ |
| 2 N 2599(A) | USA | Si-P | =2N2598: >40MHz, hFE>40 | 2a | TO-46 | | | | BF 398, 2SA970, 2SA1049, 2SB716(A), ++ |
| 2 N 2600(A) | USA | Si-P | =2N2598: >60MHz, hFE>60 | 2a | TO-46 | | | | BF 398, 2SA970, 2SA1049, 2SB716(A), ++ |
| 2 N 2601 | USA | Si-P | Uni, 60V, 0,05A, 0,4W, >20MHz, hFE>18 | 2a | TO-46 | | | | BSS 68, BSV 68, 2SA970, 2SB715...716, ++ |
| 2 N 2602 | USA | Si-P | =2N2601: >40MHz, hFE>36 | 2a | TO-46 | | | | BSS 68, BSV 68, 2SA970, 2SB715...716, ++ |
| 2 N 2603 | USA | Si-P | =2N2601: >60MHz, hFE>76 | 2a | TO-46 | | | | BSS 68, BSV 68, 2SA970, 2SB715...716, ++ |
| 2 N 2604 | USA,EUR,Mic | Si-P | LFS, In, 60V, 0,03A, 0,4W, >30MHz, hFE=40...120 | 2a | TO-46 | 2SA1124 | 7c(9mm) | | 2SA970, 2SA1016, 2SA1038...39, 2SA1136, ++ |
| 2 N 2605(A) | USA,EUR,Mic | Si-P | =2N2604: hFE=100...300(A: 150...300) | 2a | TO-46 | 2SA1124 | 7c(9mm) | | 2SA970, 2SA1016, 2SA1038...39, 2SA1136, ++ |
| 2 N 2606 | USA,Mot,Tix | P-FET | Uni, 30V, Idss>0,1mA, Up<4V | 2a | TO-18 | | | | 2N5797 |
| 2 N 2607 | USA,Mot,Tix | P-FET | Uni, 30V, Idss>0,3mA, Up<4V | 2a | TO-18 | | | | 2N5020 |
| 2 N 2608 | USA,Mot,Tix | P-FET | Uni, 30V, Idss>0,9mA, Up<4V | 2a | TO-18 | | | | 2N5460 |
| 2 N 2609 | USA,Mot,Tix | P-FET | Uni, 30V, Idss>2mA, Up<4V | 2a | TO-18 | | | | 2N5461 |
| 2 N 2610 | USA | Si-N | LFS, 45V, 0,025A, 0,15W | ≈1a | TO-22 | | | | BC 167, BC 182, BC 237, BC 547, ++ |
| 2 N 2611 | Sca,Ssi | Si-N | LFS, 120V, 1A, >4MHz | 43m | ≈TO-37 | | | | (BD 424, BD 524, 2SC2384, 2SC2481, ++) |
| 2 N 2612 | USA | Ge-P | LFS P, 65V, 15A, 75W | 23a | TO-3 | | | | 2N1551...52, 2N1555...56, 2N1559...60 |
| 2 N 2613 | Rca,Spe | Ge-P | LF, 30V, 0,05A, 0,12W | 2a | TO-1 | AC 151 | 2a | | AC 125...126, AC 151, 2SB54, 2SB56 |
| 2 N 2614 | Rca,Spe | Ge-P | LF, 40V, 0,05A, 0,12W | 2a | TO-1 | AC 151 | 2a | | 2N1191...94, 2SB56A |
| 2 N 2615 | USA,Sgs | Si-N | VHF,IF, 30V, 0,3W, >500MHz | 2a | TO-18 | | | | BF 224...225, BFR 37, BFW 30, BFX 73, ++ |
| 2 N 2616 | USA,Sgs | Si-N | VHF,IF, 30V, 0,05A, 0,3W, >600MHz | 2a | TO-18 | | | | BF 224...225, BFR 37, BFW 30, BFX 73, ++ |
| 2 N 2617 | Phc | Si-N | LF, 25V, 0,1A, 0,25W | 1a | TO-5 | | | | BC 168, BC 183, BC 238, BC 548, ++ |
| 2 N 2618 | Syl | Si-N | Uni, 60V, 0,75A, 0,6W, >200MHz | 2a | TO-5 | | | | BC 140...141, BC 300...302, 2N2218...19, ++ |
| 2 N 2618/46 | | Si-N | =2N2618: 0,4W | 2a | TO-46 | | | | BC 337A, BC 637, BC 639, 2SD667, ++ |
| 2 N 2620 | Tdy | N-FET | Uni, 50V, Idss<50mA, Up<20V | 2b | TO-5 | | | | |
| 2 N 2621 | Gen,Sty | Ge-P | LF,HF, 15V, 0,1A, 0,15W, >13MHz, hFE>15 | 2a | TO-5 | | | | ASY 26...27, 2N1309 |
| 2 N 2622 | Gen,Sty | Ge-P | =2N2621: 24V, >15MHz, hFE>15 | 2a | TO-5 | | | | ASY 26...27, 2N1309 |
| 2 N 2623 | Gen,Sty | Ge-P | =2N2621: 32V, >16MHz, hFE>20 | 2a | TO-5 | | | | ASY 26, 2N1309 |
| 2 N 2624 | Gen,Sty | Ge-P | LF,HF, 16V, 0,1A, 0,15W, >13MHz, hFE>15 | 2a | TO-5 | | | | ASY 26...27, 2N1309 |
| 2 N 2625 | Gen,Sty | Ge-P | =2N2624: 24V, >15MHz, hFE>15 | 2a | TO-5 | | | | ASY 26...27, 2N1309 |
| 2 N 2626 | Gen,Sty | Ge-P | =2N2624: 32V, >16MHz, hFE>20 | 2a | TO-5 | | | | ASY 26, 2N1309 |
| 2 N 2627 | Gen,Sty | Ge-P | LF,HF, 15V, 0,1A, 0,15W, >13MHz, hFE>15 | 2a | TO-5 | | | | ASY 26...27, 2N1309 |
| 2 N 2628 | Gen,Sty | Ge-P | =2N2627: 24V, >15MHz, hFE>15 | 2a | TO-5 | | | | ASY 26...27, 2N1309 |
| 2 N 2629 | Gen,Sty | Ge-P | =2N2627: 32V, >16MHz, hFE>20 | 2a | TO-5 | | | | ASY 26, 2N1309 |
| 2 N 2630 | Ssi,Sty | Ge-P | S, 18V, 0,1A, 0,3W, >300MHz | 2a | TO-18 | | | | |
| 2 N 2631 | USA,Rca,Tix | Si-N | VHF A,Drv, 80V, 1,5A, P0>3W(150MHz) | 2a | TO-39 | | | | BFS 23 |
| 2 N 2632 | USA | Si-N | S-L, 90/60V, 5A, 40W, >20MHz | 49m | TO-59 | | | | 2N5002, 2N5004, 2N5284...85 |
| 2 N 2633 | USA | Si-N | =2N2632: 120/80V | 49m | TO-59 | | | | 2N5284...85 |
| 2 N 2634 | USA | Si-N | =2N2632: 150/100V | 49m | TO-59 | | | | 2N5284...85 |
| 2 N 2635 | USA,Mot,Tix | Ge-P | S, 30V, 0,1A, 0,15W, >150MHz | 2a | TO-18 | | | | 2N2955...57 |
| 2 N 2636 | USA | Ge-P | S P, 100V, 25A, 100W | 23a | TO-3 | | | | 2N1652...53, 2N2286...87 |
| 2 N 2637 | USA | Ge-P | S P, 100V, 25A, 100W | 23a | TO-3 | | | | 2N1652...53, 2N2286...87 |
| 2 N 2638 | USA | Ge-P | S P, 100V, 25A, 100W | 23a | TO-3 | | | | 2N1652...53, 2N2286...87 |
| 2 N 2639 | USA,EUR | Si-N | Dual In, 45/45V, 0,03A, 0,5W, >40MHz, hFE=50...300 ΔhFE=0,9...1, ΔUbe>5mV | TO-77 | (CBE-EBC-) | | | | BFY 81, 2N2913...20 |
| 2 N 2640 | USA,EUR | Si-N | =2N4639: ΔhFE=0,8...1, ΔUbe<10mV | TO-77 | (CBE-EBC-) | | | | BFY 81, 2N2913...20 |
| 2 N 2641 | USA,EUR | Si-N | =2N2639: ΔhFE=, ΔUbe= | TO-77 | (CBE-EBC-) | | | | BFY 81, 2N2913...20 |
| 2 N 2642 | USA,EUR | Si-N | =2N2639: hFE=100...300, ΔhFE=0,9...1, ΔUbe<5mV | TO-77 | (CBE-EBC-) | | | | BFY 81, 2N2913...20 |
| 2 N 2643 | USA,EUR | Si-N | =2N2639: hFE=100...300, ΔhFE=0,8...1, ΔUbe<10mV | TO-77 | (CBE-EBC-) | | | | BFY 81, 2N2913...20 |
| 2 N 2644 | USA,EUR | Si-N | =2N2639: hFE=100...300, ΔhFE=, ΔUbe= | TO-77 | (CBE-EBC-) | | | | BFY 81, 2N2913...20 |
| 2 N 2645 | USA,Sgs | Si-N | Uni, 75V, 0,5A, 0,5W, >50MHz | 2a | TO-18 | | | | BC 639, BCX 24, 2N3700...01, 2SD667, ++ |
| 2 N 2646 | Gen,Mot,Phi Tho,Tix | UJT-P | 35/30V, iEM=2A, 0,3W, Ip<5mA, Iv>4mA, η=0,56...0,75, Rbb=4,7...9,1kΩ | 5e | TO-72 | | | | 2N4871 |
| 2 N 2646 P | Ssc | UJT-P | =2N2646: Ip<12μA | 5e | TO-72 | | | | |
| 2 N 2647 | | UJT-P | =2N2646: Ip<2μA, Iv>8mA, η=0,68...0,82 | 5e | TO-72 | | | | |
| 2 N 2648 | Csr,Idi | Ge-P | LFS, 30V, 1A, 0,3W, >10MHz | 2a | TO-5 | | | | |
| 2 N 2649 | Nsc | Si-N | LFS, 65V, 1A, 0,7W, >100MHz | 2a | TO-5 | | | | |
| 2 N 2650 | Nsc | Si-N | =2N2649: 140V | 2a | TO-5 | | | | |
| 2 N 2651 | USA,Fch | Si-N | S, 40V, 0,5A, 0,36W, >350MHz | 2a | TO-18 | | | | BSS 10, BSX 26, BSX 39, 2N3261 |
| 2 N 2652(A) | USA,Mot | Si-N | Dual, 100V, 0,5A, 0,6W, >60MHz, ΔUbe<3mV | TO-77 | (CBE-EBC-) | | | | BFX 70...72, 2N2060, 2N2223 |
| 2 N 2654 | Amp,Phc | Ge-P | VHF, 25V, 10mA, 0,1W, 250MHz | 5g | TO-12 | AF 239 S | 5g | | AF 109R, AF 139, AF 239(S) |
| 2 N 2655 | Sca,Tra | Si-N | LFS, 100V, 0,5A, 15W(Tc=25°) | 2a | TO-5 | | | | BUF 49, BUY 41, 2SC1860 |
| 2 N 2656 | Trw | Si-N | HF, 25V, 0,2A, 0,36W, >250MHz | 2a | TO-18 | | | | BC 168, BC 183, BC 238, BC 548, ++ |
| 2 N 2657 | USA,Nsc,Tix | Si-N | LFS, 80V, 5A, 4W(Tc=100°), >20MHz | 2a | TO-5 | | | | BFT 32...34, 2N4895...97, 2N5336...39 |
| 2 N 2658 | USA,Nsc,Tix | Si-N | =2N2657: 100V | 2a | TO-5 | | | | BFT 33...34, 2N4895...97, 2N5339 |
| 2 N 2659 | USA,Tix | Ge-P | LFS P, 50V, 3A, 15W(Tc=25°) | 2a | TO-5 | | | | 2N1039 |
| 2 N 2660 | USA,Tix | Ge-P | =2N2659: 70V | 2a | TO-5 | | | | 2N1040 |