

TYPE NO	CONSTRUCTION	PACKAGE & PINOUT	V _{DS}	I _D	T _J	P _{TOT}	V _{GS(OFF)} or V _{GS(TH)}	I _{DSS} or I _{D(ON)}	G _{FS}	R _{DS(ON)}	C _{ISS}	C _{RSS}	USE	MNF	SUBSTITUTE	
																MAX
BC264L	NJD	T092 A	30V	60mA	150C	300mWF	0.5/8V	2/12mA	2.5mSnn	-	6P0	2P0	ALN	TIS	BFW11	2N3684
BC264LA	NJD	T092 A	30V	60mA	150C	300mWF	0.5/8V	2/4.5mA	2.5mSnn	-	6P0	2P0	ALN	TIS	BFW54	2N3684
BC264LB	NJD	T092 A	30V	60mA	150C	300mWF	0.5/8V	3.5/7mA	2.5mSnn	-	6P0	2P0	ALN	TIS	BFW11	2N3684
BC264LC	NJD	T092 A	30V	60mA	150C	300mWF	0.5/8V	5/8mA	2.5mSnn	-	6P0	2P0	ALN	TIS	BFW11	2N3684
BC264LD	NJD	T092 A	30V	60mA	150C	300mWF	0.5/8V	7/12mA	2.5mSnn	-	6P0	2P0	ALN	TIS	BFW11	2N3684
BD512	PME	T0202 Fd	60V	1.5A	150C	10WC	1/3V	-	150mStp	10R	50P	-	AMM	ITT	-	-
BD522	NME	T0202 Fd	60V	1.5A	150C	10WC	0.8/2V	-	150mStp	4R0	35P	-	AMM	ITT	BSS97	-
BF244	NJD	T092 A	30V	10mA	150C	300mWF	0.5/8V	2/25mA	3/6.5mS	-	4P0	1P1	ALG	PHI	BFW61	2N3819
BF244A	NJD	T092 A	30V	10mA	125C	300mWF	0.5/0.8V	2/6.5mA	3/6.5mS	-	8P0	2P2	ALG	PHI	BFW61	2N5458
BF244A1	NJD	T092 A	30V	25mA	150C	300mWF	0.4/1V	2/3mA	3/6.5mS	-	4P0	1P6	ALG	PHI	-	-
BF244A2	NJD	T092 A	30V	25mA	150C	300mWF	0.7/1.4V	3/4.5mA	3/6.5mS	-	4P0	1P6	ALG	PHI	-	-
BF244A3	NJD	T092 A	30V	25mA	150C	300mWF	1.1/2.2V	4.5/6.5mA	3/6.5mS	-	4P0	1P6	ALG	PHI	-	-
BF244B	NJD	T092 A	30V	10mA	125C	300mWF	0.5/0.8V	6/15mA	3/6.5mS	-	8P0	2P2	ALG	PHI	BC264D	2N6451
BF244C	NJD	T092 A	30V	10mA	125C	300mWF	0.5/0.8V	12/25mA	3/6.5mS	-	8P0	2P2	ALG	PHI	BF347	2N6451
BF245	NJD	T092 B	30V	35mA	150C	300mWF	0.5/8V	2/25mA	3/6.5mS	-	8P0	2P0	ALG	PHI	BF811	2N6451
BF245A	NJD	T092 B	30V	35mA	150C	300mWF	0.5/8V	2/6.5mA	3/6.5mS	-	8P0	2P0	ALG	PHI	BFW56	2N3822
BF245B	NJD	T092 B	30V	35mA	150C	300mWF	0.5/8V	6/15mA	3/6.5mS	-	8P0	2P0	ALG	PHI	BF811	2N5459
BF245C	NJD	T092 B	30V	35mA	150C	300mWF	0.5/8V	12/25mA	3/6.5mS	-	8P0	2P0	ALG	PHI	BF244	2N5397
BF246	NJD	T092 A	25V	260mA	150C	300mWF	0.6/14.5V	30/250mA	8/50mS	-	30P	7P0	FGV	TEL	BSV78	2N4859
BF246A	NJD	T092 A	25V	260mA	150C	300mWF	0.6/14.5V	30/80mA	8/50mS	-	30P	7P0	FGV	TEL	BSV78	2N4392
BF246B	NJD	T092 A	25V	260mA	150C	300mWF	0.6/14.5V	60/140mA	8/50mS	-	30P	7P0	FGV	TEL	BSV78	2N4856
BF246C	NJD	T092 A	25V	260mA	150C	300mWF	0.6/14V	110/250mA	8/50mS	-	30P	7P0	FGV	TEL	BSV78	2N4856
BF247	NJD	T092 B	30V	260mA	150C	300mWF	0.6/15V	30/250mA	8/50mS	-	30P	7P0	FGV	TEL	BF348	2N6453
BF247A	NJD	T092 B	25V	260mA	150C	300mWF	0.6/14V	30/80mA	8/50mS	-	30P	7P0	FGV	TEL	BSV78	2N4392
BF247B	NJD	T092 B	25V	260mA	150C	200mWF	0.6/14V	60/140mA	8/50mS	-	30P	7P0	FGV	TEL	BSV78	2N4856
BF247C	NJD	T092 B	25V	260mA	150C	200mWF	0.6/14V	110/250mA	8/50mS	-	30P	7P0	FGV	TEL	BSV78	2N4856
BF256	NJD	T092 B	30V	30mA	150C	300mWF	0.5/7.5V	3/18mA	4.5mSnn	-	4P5	1P2	TUG	PHI	BF256L	2N5245
BF256A	NJD	T092 B	30V	10mA	150C	300mWF	0.5/7.5V	3/7mA	4.5mSnn	-	4P5	1P2	TUG	PHI	BF256LA	2N5246
BF256B	NJD	T092 B	30V	30mA	150C	300mWF	0.5/7.5V	6/13mA	4.5mSnn	-	4P5	1P2	TUG	PHI	BF256LB	2N5245
BF256B1	NJD	T092 B	30V	30mA	150C	300mWF	1.4/2.6V	6/8mA	4.5mSnn	-	4P5	1P2	TUG	PHI	-	-
BF256C	NJD	T092 B	30V	30mA	150C	300mWF	0.5/7.5V	11/18mA	4.5mSnn	-	4P5	1P2	TUG	PHI	BF256LC	2N4416
BF256L	NJD	T092 A	30V	30mA	150C	300mWF	0.5/7.5V	3/18mA	4.5mSnn	-	4P5	1P2	TUG	PHI	BF256	2N5245
BF256LA	NJD	T092 A	30V	10mA	150C	300mWF	0.5/7.5V	3/7mA	4.5mSnn	-	4P5	1P2	TUG	PHI	BF256A	2N5246
BF256LB	NJD	T092 A	30V	30mA	150C	300mWF	0.5/7.5V	6/13mA	4.5mSnn	-	4P5	1P2	TUG	PHI	BF256B	2N5245
BF256LC	NJD	T092 A	30V	30mA	150C	300mWF	0.5/7.5V	11/18mA	4.5mSnn	-	4P5	1P2	TUG	PHI	BF256C	2N4416
BF320	PJD	T092 A	15V	25mA	125C	200mWF	8Vmx	0.3/15mA	0.8/5mS	-	32P	16P	ALG	TIS	BFX83	2N3380
BF320A	PJD	T092 A	15V	25mA	125C	200mWF	8Vmx	0.3/4.5mA	0.8/5mS	-	32P	16P	ALG	TIS	BFX83	2N5270
BF320B	PJD	T092 A	15V	25mA	125C	200mWF	8Vmx	3/8.5mA	0.8/5mS	-	32P	16P	ALG	TIS	BFX83	2N3380
BF320C	PJD	T092 A	15V	25mA	125C	200mWF	8Vmx	7.5/15mA	0.8/5mS	-	32P	16P	ALG	TIS	BFX83	2N3380
BF327	NMD	SOT103 L	20V	100mA	150C	300mWF	1.5/3.8V	20/55mA	12mSnn	-	5P0	0P03	FGV	PHI	BF900	-
BF346	NJD	T092 B	15V	90mA	135C	300mWF	0.5/5.5V	2/80mA	16/60mS	-	-	5P6	ALG	TIS	BF818	2N6453
BF346A	NJD	T092 B	15V	90mA	135C	300mWF	0.5/5.5V	2/18mA	16/60mS	-	-	5P6	ALG	TIS	BF811	2N6451
BF346B	NJD	T092 B	15V	90mA	135C	300mWF	0.5/5.5V	12/35mA	16/60mS	-	-	5P6	ALG	TIS	BF244	2N6453
BF346C	NJD	T092 B	15V	90mA	135C	300mWF	0.5/5.5V	28/80mA	16/60mS	-	-	5P6	ALG	TIS	BF818	2N6453
BF347	NJD	T092 A	30V	12mA	150C	400mWF	1Vmx	0.5/2.5mA	3/7.5mS	350R	-	-	RLS	TIS	BF256A	2N3687
BF348	NJD	T092 B	40V	25mA	150C	200mWF	6Vmx	10/60mA	10/15mS	-	-	1P5	FGV	TIS	BFW61	2N5397
BF350	NMD	T072 H	15V	50mA	175C	400mWF	5Vmx	3/30mA	10mStp	-	20P	0P04	FGV	TIS	BF528	3N140
BF351	NMD	T072 H	24V	50mA	175C	400mWF	1.5V	5/30mA	14mStp	-	12P	0P04	FGV	TIS	BF528	3N140
BF352	NMD	T072 H	24V	50mA	175C	400mWF	2Vmx	5/30mA	14mStp	-	12P	0P04	FGV	TIS	BF353	3N187
BF353	NMD	T072 H	24V	50mA	175C	400mWF	3Vmx	5/30mA	12mStp	-	12P	0P02	FGV	TIS	BF905	3N140
BF354	NMD	T072 H	24V	50mA	175C	400mWF	3Vmx	7/15mA	1.5/3.5mS	-	3P5	0P02	FGV	TIS	BF528	3N187
BF410	NJD	T092 B	20V	30mA	150C	300mWF	3Vtp	0.7/18mA	2.5mSnn	-	5P0	0P4	VLA	PHI	BF245	-
BF410A	NJD	T092 B	20V	30mA	150C	300mWF	0.8Vtp	0.7/3mA	2.5mSnn	-	5P0	0P4	VLA	PHI	BF346	-
BF410B	NJD	T092 B	20V	30mA	150C	300mWF	1.5Vtp	2.5/7mA	4mSnn	-	5P0	0P4	VLA	PHI	BF346	-
BF410C	NJD	T092 B	20V	30mA	150C	300mWF	2.2Vtp	6/12mA	6mSnn	-	5P0	0P4	VLA	PHI	BF346	-
BF410D	NJD	T092 B	20V	30mA	150C	300mWF	3Vtp	10/18mA	7mSnn	-	5P0	0P4	VLA	PHI	BF346	-
BF510	NJD	T0236 B	20V	30mA	150C	300mWF	0.8Vtp	0.7/3mA	2.5mSnn	-	5P0	0P4	VLA	PHI	-	-
BF511	NJD	T0236 B	20V	30mA	150C	300mWF	1.5Vtp	2.5/7mA	4mSnn	-	5P0	0P4	VLA	PHI	-	-
BF512	NJD	T0236 B	20V	30mA	150C	300mWF	2.2Vtp	6/12mA	6mSnn	-	5P0	0P4	VLA	PHI	-	-
BF513	NJD	T0236 B	20V	30mA	150C	300mWF	3Vtp	10/18mA	7mSnn	-	5P0	0P4	VLA	PHI	-	-
BF543	NMD	SOT23 B	20V	30mA	150C	200mWF	1.5Vmx	2/6mA	9.5mSnn	-	2P7tp	P018tp	VLA	SIE	-	-
BF544	NMD	T082 C	20V	30mA	150C	200mWF	1.5Vmx	2/6mA	9.5mSnn	-	2P8tp	P035tp	VLA	SIE	-	-
BF800	NJD	T072 Ek	25V	10mA	200C	400mWF	6Vmx	0.3/1.2mA	200/700μS	-	2P6	0P8	ALN	TIS	BF801	2N4867
BF801	NJD	T072 Ek	25V	10mA	200C	400mWF	6Vmx	0.3/1.2mA	200/700μS	-	2P6	0P8	ALN	TIS	BF801	2N4867
BF802	NJD	T072 Ek	25V	10mA	200C	400mWF	6Vmx	0.3/1.2mA	200/700μS	-	2P6	0P8	ALN	TIS	BF800	2N3687A
BF803	NJD	T072 Ek	30V	1200μA	200C	400mWF	3Vmx	0.8mAmx	250/500μS	-	2P6	0P8	ALN	TIS	-	2N3687A
BF804	NJD	T072 Ek	30V	1200μA	200C	400mWF	5Vmx	0.3/1.2mA	250/500μS	-	2P6	0P8	ALN	TIS	BF800	2N3687A
BF805	NJD	T072 Ek	30V	10mA	200C	300mWF	6Vmx	3/13mA	300/500μS	-	3P5	1P5	ALN	TIS	BF806	2N4869
BF806	NJD	T072 Ek	30V	10mA	200C	300mWF	6Vmx	3/13mA	3/5.5mS	-	3P5	1P5	ALN	TIS	BF805	2N4869
BF808	NJD	T072 Ek	30V	10mA	200C	300mWF	5Vmx	1/6mA	0.8/2.5mS	-	2P5	0P4	ALN	TIS	BFW56	2N4868
BF810	NJD	T072 Ek	30V	10mA	200C	300mWF	6Vmx	5/20mA	5/9mS	-	6P0	1P8	ALN	TIS	BF811	2N6451
BF810A	NJD	T072 Ek	30V	20mA	15											