

2 N 893		GTO-Thy	=2N892	2a	TO-46	-	-	-
2 N 894		GTO-Thy	=2N892: 30V	2a	TO-46	-	-	-
2 N 895		GTO-Thy	=2N892: 30V	2a	TO-46	-	-	-
2 N 896		GTO-Thy	=2N892: 60V	2a	TO-46	-	-	-
2 N 897		GTO-Thy	=2N892: 60V	2a	TO-46	-	-	-
2 N 898		GTO-Thy	=2N892: 100V	2a	TO-46	-	-	-
2 N 899		GTO-Thy	=2N892: 100V	2a	TO-46	-	-	-
2 N 900		GTO-Thy	=2N892: 200V	2a	TO-46	-	-	-
2 N 901		GTO-Thy	=2N892: 200V	2a	TO-46	-	-	-
2 N 902	Ray	Si-N	LFS, 45V, 0,025A, 0,15W, >1MHz					(BC 167, BC 182, BC 237, BC 547,++) ⁴
2 N 903	Ray	Si-N	LFS, 45V, 0,025A, 0,15W, >2MHz					(BC 167, BC 182, BC 237, BC 547,++) ⁴
2 N 904	Ray	Si-N	LFS, 45V, 0,025A, 0,15W, >8MHz					(BC 167, BC 182, BC 237, BC 547,++) ⁴
2 N 905	Ray	Si-N	LFS, 45V, 0,025A, 0,15W, >2MHz					(BC 167, BC 182, BC 237, BC 547,++) ⁴
2 N 906	Ray	Si-N	LFS, 45V, 0,025A, 0,15W, >2MHz					(BC 167, BC 182, BC 237, BC 547,++) ⁴
2 N 907	Ray	Si-N	LFS, 45V, 0,025A, 0,15W, >12MHz					(BC 167, BC 182, BC 237, BC 547,++) ⁴
2 N 908	Ray	Si-N	LFS, 45V, 0,025A, 0,15W, >25MHz					(BC 167, BC 182, BC 237, BC 547,++) ⁴
2 N 909	USA,Fch	Si-N	Uni, 60V, 1A, 0,5W, >50MHz	2a	TO-18			BC 337A, BC 637, BC 639, BCX 24, ++
2 N 910	USA,Mot,Sgs	Si-N	LFS, 100V, 1A, 0,5W, >60MHz	2a	TO-18	BC 639	7c	BC 639, BCX 24, 2N3700...01, 2SD667, ++
2 N 911	USA,Mot,Sgs	Si-N	LFS, 100V, 1A, 0,5W, >50MHz	2a	TO-18	BC 639	7c	BC 639, BCX 24, 2N3700...01, 2SD667, ++
2 N 912	USA,Mot,Sgs	Si-N	LFS, 100V, 1A, 0,5W, >40MHz	2a	TO-18	BC 639	7c	BC 639, BCX 24, 2N3700...01, 2SD667, ++
2 N 913	Idi,Sca	Si-N	VHF, 25V, 0,36W, 350MHz	2a	TO-18			BF 224...225, BF 314, BF 502...503, ++
2 N 914(A)	USA,EUR	Si-N	S, 40V, 0,5A, 0,36W, <40/40ns	2a	TO-18			BSS 10, BSX 26, BSX 39, 2N3261
2 N 915	USA,EUR	Si-N	HF/S, 70V, 0,36W, >250MHz	2a	TO-18			BSW 63...64, 2N2221...22(A)
2 N 915 A		Si-N	=2N915: >500MHz	2a	TO-18			(BSW 63...64, 2N2221...22(A))
2 N 916(A)	USA,EUR	Si-N	VHF/S, 45V, 0,05A, 0,36W, >300MHz	2a	TO-18			BF 224...225, BSW 63...64, 2N2221...22(A)++
2 N 916 B		Si-N	=2N916: 60V, >500MHz	2a	TO-18			(BF224...225, BSW63...64, 2N2221...22(A)++)
2 N 917(A)	USA,EUR	Si-N	VHF/UHF, 30V, 0,05A, 0,2W, 900MHz	5g	TO-72			BF 377...378, BF 689, BF 763, 2N2857, ++
2 N 918	USA,EUR	Si-N	VHF/UHF, 30V, 0,05A, 0,2W, >600MHz	5g	TO-72	2SC2570 A	7f	BF 377...378, BF 689, BF 763, 2N2857, ++
2 N 919	Csr,Elc	Si-N	Uni, 25V, 0,22A, 0,36W, >200MHz, hFE>20	2a	TO-18			BC 168, BC 183, BC 238, BC 548, ++
2 N 920	Csr,Elc,Sgs	Si-N	=2N919: hFE>40	2a	TO-18			BC 168, BC 183, BC 238, BC 548, ++
2 N 921	Csr,Elc	Si-N	Uni, 50V, 0,2A, 0,36W, 400MHz, hFE>20	2a	TO-18			BC 167, BC 182, BC 237, BC 547, ++
2 N 922	Csr,Elc	Si-N	=2N921: hFE>40	2a	TO-18			BC 167, BC 182, BC 237, BC 547, ++
2 N 923	USA	Si-P	Uni, 40V, 0,05A, 0,15W, hfe>12	2a	TO-18			BC 212, BC 257, BC 307, BC 557, ++
2 N 924	USA	Si-P	Uni, 40V, 0,05A, 0,15W, hfe>24	2a	TO-18			BC 212, BC 257, BC 307, BC 557, ++
2 N 925	USA	Si-P	Uni, 50V, 0,05A, 0,15W, hfe>10	2a	TO-18			BC 212, BC 257, BC 307, BC 557, ++
2 N 926	USA	Si-P	Uni, 50V, 0,05A, 0,15W, hfe>20	2a	TO-18			BC 212, BC 257, BC 307, BC 557, ++
2 N 927	USA	Si-P	Uni, 70V, 0,05A, 0,15W, hfe>8	2a	TO-18			BC 212, BC 256, BC 266, BC 556, ++
2 N 928	USA	Si-P	Uni, 70V, 0,05A, 0,15W, hfe>18	2a	TO-18			BC 212, BC 256, BC 266, BC 556, ++
2 N 929	USA, EUR	Si-N	Uni, In, 45V, 0,03A, 0,5W, >30MHz	2a	TO-18	BC 550	7a	BC 414, BC 550, 2N2483...84, 2N3117, ++
2 N 929 A		Si-N	=2N929: 60V	2a	TO-18	BC 550	7a	BC 414, BC 550, 2N2483...84, 2N3117, ++
2 N 930	USA, EUR	Si-N	Uni, In, 45V, 0,03A, 0,5W, >30MHz	2a	TO-18	BC 550	7a	BC 414, BC 550, 2N2483...84, 2N3117, ++
2 N 930 A,B		Si-N	=2N929: 60V	2a	TO-18	BC 550	7a	BC 414, BC 550, 2N2483...84, 2N3117, ++
2 N 934	Ray,Sty	Ge-P	S, 13V, 0,2A, 0,15W, >35MHz	2a	TO-18			2N705, 2N960...967
2 N 935	USA	Si-P	Uni, 50V, 0,05A, 0,25W, hfe>9	2a	TO-18			(BC 212, BC 257, BC 307, BC 557,++)
2 N 936	USA	Si-P	Uni, 50V, 0,05A, 0,25W, hfe>18	2a	TO-18			(BC 212, BC 257, BC 307, BC 557,++)
2 N 937	USA	Si-P	Uni, 50V, 0,05A, 0,25W, hfe>36	2a	TO-18			(BC 212, BC 257, BC 307, BC 557,++)
2 N 938	USA	Si-P	Uni, 40V, 0,1A, 0,25W, hfe>9	2a	TO-18			(BC 212, BC 257, BC 307, BC 557,++)
2 N 939	USA	Si-P	Uni, 40V, 0,1A, 0,25W, hfe>18	2a	TO-18			(BC 212, BC 257, BC 307, BC 557,++)
2 N 940	USA	Si-P	Uni, 40V, 0,1A, 0,25W, hfe>36	2a	TO-18			(BC 212, BC 257, BC 307, BC 557,++)
2 N 941	USA	Si-P	S, Chopper, 25/8/25V, 0,05A, 0,25W	2a	TO-18			-
2 N 942	USA	Si-P	S, Chopper, 25/8/25V, 0,05A, 0,25W	2a	TO-18			-
2 N 943	USA	Si-P	S, Chopper, 40/18/40V, 0,05A, 0,25W	2a	TO-18			-
2 N 944	USA	Si-P	S, Chopper, 40/18/40V, 0,05A, 0,25W	2a	TO-18			-
2 N 945	USA	Si-P	S, Chopper, 50/50/50V, 0,05A, 0,25W	2a	TO-18			-
2 N 946	USA	Si-P	S, Chopper, 50/50/50V, 0,05A, 0,25W	2a	TO-18			-
2 N 947	USA	Si-N	S, 20V, 0,1A, 0,26W, >200MHz	2a	TO-18			BC 238, BC 548, BSY 62...63, 2N706A, ++
2 N 948	USA,Fch	50Hz-Thy	30V, 0,26A(Tc=125°), Igt/Ih<0,02/<1mA	2a	TO-46			(2N2322A) ⁶
2 N 949		50Hz-Thy	=2N948: 60V	2a	TO-46			(2N2324A) ⁶
2 N 950		50Hz-Thy	=2N948: 100V	2a	TO-46			(2N2324A) ⁶
2 N 951		50Hz-Thy	=2N948: 200V	2a	TO-46			(2N2326A) ⁶
2 N 955	Sem	Ge-N	UHF, S, 12V, 0,1A, 0,15W, 1GHz	2a	TO-18			-
2 N 955 A		Ge-N	=2N955: 0,5A	2a	TO-18			-
2 N 956	USA, EUR	Si-N	LF Drv 75V, 0,5W, 300MHz	2a	TO-18	BC 639	7c	BC 639, BCX 24, 2N3700...01, 2SD667, ++
2 N 957	USA,Fch	Si-N	Uni, 40V, 0,25W, >200MHz	2a	TO-18			BC 167, BC 182, BC 237, BC 547, ++
2 N 958	Trw	Si-N	Uni, 25V, 0,2A, 0,25W, >200MHz, hFE>20	24c	TO-50			(BC 168, BC 183, BC 238, BC 548,++) ⁶
2 N 959	Trw	Si-N	=2N958: hFE>40	24c	TO-50			(BC 168, BC 183, BC 238, BC 548,++) ⁶
2 N 960	USA,Mot,Tix	Ge-P	S, 15V, 0,1A, 0,15W, <50/85ns	2a	TO-18			ASZ 21, 2N705
2 N 961	USA,Mot,Tix	Ge-P	S, 12V, 0,1A, 0,15W, <50/85ns	2a	TO-18			ASZ 21, 2N705(A)
2 N 962	USA,Mot,Tix	Ge-P	S, 12V, 0,1A, 0,15W, <50/100ns	2a	TO-18			ASZ 21, 2N705(A)
2 N 963	USA,Mot,Tix	Ge-P	S, 12V, 0,1A, 0,15W, <50/120ns	2a	TO-18			ASZ 21, 2N705(A)
2 N 964(A)	USA,Mot,Tix	Ge-P	S, 15V, 0,1A, 0,15W, <50/85ns	2a	TO-18			ASZ 21, 2N705(A)
2 N 965	USA,Mot,Tix	Ge-P	S, 12V, 0,1A, 0,15W, <50/85ns	2a	TO-18			ASZ 21, 2N705(A)
2 N 966	USA,Mot,Tix	Ge-P	S, 12V, 0,1A, 0,15W, <50/85ns	2a	TO-18			ASZ 21, 2N705(A)
2 N 967	USA,Mot,Tix	Ge-P	S, 12V, 0,1A, 0,15W, <60/120ns	2a	TO-18			ASZ 21, 2N705(A)
2 N 968	USA,Mot	Ge-P	S, 15V, 0,2A, 0,15W, 50/70ns	2a	TO-18			2N705, 2N960...967
2 N 969	USA,Mot	Ge-P	S, 12V, 0,2A, 0,15W, 50/70ns	2a	TO-18			2N705, 2N960...967
2 N 970	USA,Mot	Ge-P	S, 12V, 0,2A, 0,15W, 65/100ns	2a	TO-18			2N705, 2N960...967
2 N 971	USA,Mot	Ge-P	S, 7V, 0,2A, 0,15W, 65/100ns	2a	TO-18			2N705, 2N960...967
2 N 972	USA,Mot	Ge-P	S, 15V, 0,2A, 0,15W, 50/75ns	2a	TO-18			2N705, 2N960...967
2 N 973	USA,Mot	Ge-P	S, 12V, 0,2A, 0,15W, 50/75ns	2a	TO-18			2N705, 2N960...967
2 N 974	USA,Mot	Ge-P	S, 12V, 0,2A, 0,15W, 65/100ns	2a	TO-18			2N705, 2N960...967
2 N 975	USA,Mot	Ge-P	S, 7V, 0,2A, 0,15W, 65/100ns	2a	TO-18			2N705, 2N960...967
2 N 976	USA	Ge-P	S, 15V, 0,1A, 0,1W, >250MHz	2a	TO-18			2N705, 2N960...967
2 N 977	USA	Ge-P	S, 15V, 0,2A, 0,15W, >400MHz	2a	TO-18			2N705, 2N960...967
2 N 978	USA,Mot,Sgs	Si-P	Uni, 30V, 0,6A, 0,33W, >40MHz	2a	TO-18			BC 327...328, BC 636, BC 638, BC 640, ++
2 N 979	USA	Ge-P	S, 20/15V, 0,1A, 0,06W, >100MHz	2a	TO-18			ASZ 21, 2N705, 2N960...967
2 N 980	USA	Ge-P	=2N979: 20/12V	2a	TO-18			ASZ 21, 2N705, 2N960...967
2 N 981	USA,Nsc	Si-N	Uni, 80V, 0,1A, 0,5W, >50MHz	2a	TO-18			BC 546, 2SC1890(A), 2SC2240, 2SC2459, ++
2 N 982	USA	Ge-P	S, 20V, 0,1A, 0,06W, 450MHz	2a	TO-18			ASZ 21, 2N705, 2N960...967
2 N 983	USA	Ge-P	=2N982: 15V	2a	TO-18			ASZ 21, 2N705, 2N960...967
2 N 984	USA	Ge-P	=2N982: 15V	2a	TO-18			ASZ 21, 2N705, 2N960...967
2 N 985	USA,Mot	Ge-P	S, 15V, 0,2A, 0,15W, <35/80ns	2a	TO-18			2N705, 2N960...967
2 N 986		Opto						