

2 N 1522	USA	Ge-P	LFS P, 50V, 50A, 87,5W	38a	TO-36	2N4049...50, 2N4052...53
2 N 1523	USA	Ge-P	=2N1522: 80V	38a	TO-36	2N4050, 2N4053
2 N 1524	USA	Ge-P	HF, 24V, 10mA, 0,08W, 33MHz	2a	TO-1	AF 124...127, AF 200
2 N 1524/33		Ge-P	=2N1524: 0,12W	5g	TO-33	AF 124...127, AF 200
2 N 1525	USA	Ge-P	HF, 24V, 10mA, 0,08W, 33MHz	1a	TO-40	AF 124...127, AF 200
2 N 1526	USA	Ge-P	HF, 24V, 10mA, 0,08W, 33MHz	2a	TO-1	AF 124...127, AF 200
2 N 1526/33		Ge-P	=2N1526: 0,12W	5g	TO-33	AF 124...127, AF 200
2 N 1527	USA	Ge-P	HF, 24V, 10mA, 0,08W, 33MHz	1a	TO-40	AF 124...127, AF 200
2 N 1528	Ray	Si-N	HF/S, 25V, 0,02A, 0,15W, 20MHz	2a	TO-5	BC 168, BC 183, BC 238, BC 548, ++
2 N 1529(A)	USA,Mot,Tix	Ge-P	LFS P, 40V, 5A, 106W, hFE>20	23a	TO-3	2N3611...18
2 N 1530(A)	USA,Mot,Tix	Ge-P	=2N1529: 60V	23a	TO-3	2N3612, 2N3614, 2N3615...18
2 N 1531(A)	USA,Mot,Tix	Ge-P	=2N1529: 80V	23a	TO-3	2N3615...18
2 N 1532(A)	USA,Mot,Tix	Ge-P	=2N1529: 100V	23a	TO-3	2N3616, 2N3618
2 N 1533(A)	USA,Mot,Tix	Ge-P	=2N1529: 120V	23a	TO-3	-
2 N 1534(A)	USA,Mot,Tix	Ge-P	LFS P, 40V, 5A, 106W, hFE>35	23a	TO-3	2N3611...18
2 N 1535(A)	USA,Mot,Tix	Ge-P	=2N1534: 60V	23a	TO-3	2N3612, 2N3614, 2N3615...18
2 N 1536(A)	USA,Mot,Tix	Ge-P	=2N1534: 80V	23a	TO-3	2N3615...18
2 N 1537(A)	USA,Mot,Tix	Ge-P	=2N1534: 100V	23a	TO-3	2N3616, 2N3618
2 N 1538(A)	USA,Mot,Tix	Ge-P	=2N1534: 120V	23a	TO-3	-
2 N 1539(A)	USA,Mot,Tix	Ge-P	LFS P, 40V, 5A, 106W, hFE>50	23a	TO-3	2N3611...18
2 N 1540(A)	USA,Mot,Tix	Ge-P	=2N1539: 60V	23a	TO-3	2N3612, 2N3614, 2N3615...18
2 N 1541(A)	USA,Mot,Tix	Ge-P	=2N1539: 80V	23a	TO-3	2N3615...18
2 N 1542(A)	USA,Mot,Tix	Ge-P	=2N1539: 100V	23a	TO-3	2N3616, 2N3618
2 N 1543(A)	USA,Mot,Tix	Ge-P	=2N1539: 120V	23a	TO-3	-
2 N 1544(A)	USA,Mot,Tix	Ge-P	LFS P, 40V, 5A, 106W, hFE>75	23a	TO-3	(2N3611...18)
2 N 1545(A)	USA,Mot,Tix	Ge-P	=2N1544: 60V	23a	TO-3	(2N3612, 2N3614, 2N3615...18)
2 N 1546(A)	USA,Mot,Tix	Ge-P	=2N1544: 80V	23a	TO-3	(2N3615...18)
2 N 1547(A)	USA,Mot,Tix	Ge-P	=2N1544: 100V	23a	TO-3	(2N3616, 2N3618)
2 N 1548(A)	USA,Mot,Tix	Ge-P	=2N1544: 120V	23a	TO-3	-
2 N 1549(A)	USA,Mot,Tix	Ge-P	LFS P, 40V, 15A, 106W, hFE>10	23a	TO-3	2N1651...53, 2N2285...87
2 N 1550(A)	USA,Mot,Tix	Ge-P	=2N1549: 60V	23a	TO-3	2N1651...53, 2N2285...87
2 N 1551(A)	USA,Mot,Tix	Ge-P	=2N1549: 80V	23a	TO-3	2N1652...53, 2N2286...87
2 N 1552(A)	USA,Mot,Tix	Ge-P	=2N1549: 100V	23a	TO-3	2N1652...53, 2N2286...87
2 N 1553(A)	USA,Mot,Tix	Ge-P	LFS P, 40V, 15A, 106W, hFE>30	23a	TO-3	2N1651...53, 2N2285...87
2 N 1554(A)	USA,Mot,Tix	Ge-P	=2N1553: 60V	23a	TO-3	2N1651...53, 2N2285...87
2 N 1555(A)	USA,Mot,Tix	Ge-P	=2N1553: 80V	23a	TO-3	2N1652...53, 2N2286...87
2 N 1556(A)	USA,Mot,Tix	Ge-P	=2N1553: 100V	23a	TO-3	2N1652...53, 2N2286...87
2 N 1557(A)	USA,Mot,Tix	Ge-P	LFS P, 40V, 15A, 106W, hFE>50	23a	TO-3	2N1651...53, 2N2285...87
2 N 1558(A)	USA,Mot,Tix	Ge-P	=2N1557: 60V	23a	TO-3	2N1651...53, 2N2285...87
2 N 1559(A)	USA,Mot,Tix	Ge-P	=2N1557: 80V	23a	TO-3	2N1652...53, 2N2286...87
2 N 1560(A)	USA,Mot,Tix	Ge-P	=2N1557: 100V	23a	TO-3	2N1652...53, 2N2286...87
2 N 1561	Mot	Ge-P	VHF A,Drv, 25V, 0,25A, PQ>0,5W(160MHz)	=2a	TO-107	(2N1692) ⁴
2 N 1562	Mot	Ge-P	VHF A,Drv, 25V, 0,25A, PQ>0,4W(160MHz)	=2a	TO-107	(2N1693) ⁴
2 N 1564	USA,Tix	Si-N	LF, 80V, 0,05A, 0,6W, >30MHz	2a	TO-5	BC 140...141, BC 300...301, 2N1889...90, ++
2 N 1565	USA,Tix	Si-N	LF, 80V, 0,05A, 0,6W, >60MHz	2a	TO-5	BC 140...141, BC 300...301, 2N1889...90, ++
2 N 1566	USA,Tix	Si-N	LF, 80V, 0,05A, 0,6W, >60MHz	2a	TO-5	BC 140...141, BC 300...301, 2N1889...90, ++
2 N 1566 A		Si-N	=2N1566: 0,1A, >100MHz	2a	TO-5	BC 140...141, BC 300...301, 2N1889...90, ++
2 N 1572	USA,Tix	Si-N	LF, 125V, 0,05A, 0,6W, >30MHz	2a	TO-5	BC 300, 2N1893(A), 2SD755...756(A), ++
2 N 1573	USA,Tix	Si-N	LF, 125V, 0,05A, 0,6W, >60MHz	2a	TO-5	BC 300, 2N1893(A), 2SD755...756(A), ++
2 N 1574	USA,Tix	Si-N	LF, 125V, 0,05A, 0,6W, >60MHz	2a	TO-5	BC 300, 2N1893(A), 2SD755...756(A), ++
2 N 1585	Cen	Ge-N	HF, 25V, 0,1A, 0,3W, 400MHz	2a	TO-5	-
2 N 1586	USA,Tix	Si-N	Uni, 15V, 0,025A, 0,125W, >5MHz	=1a	TO-22	BC 168, BC 183, BC 238, BC 548, ++
2 N 1587	USA,Tix	Si-N	=2N1586: 30V	=1a	TO-22	BC 168, BC 183, BC 238, BC 548, ++
2 N 1588	USA,Tix	Si-N	=2N1586: 60V	=1a	TO-22	BC 174, BC 182, BC 190, BC 546, ++
2 N 1589	USA,Tix	Si-N	Uni, 15V, 0,025A, 0,125W, >5MHz	=1a	TO-22	BC 168, BC 183, BC 238, BC 548, ++
2 N 1590	USA,Tix	Si-N	=2N1589: 30V	=1a	TO-22	BC 168, BC 183, BC 238, BC 548, ++
2 N 1591	USA,Tix	Si-N	=2N1589: 60V	=1a	TO-22	BC 174, BC 182, BC 190, BC 546, ++
2 N 1592	USA,Tix	Si-N	Uni, 15V, 0,025A, 0,125W, >5MHz	=1a	TO-22	BC 168, BC 183, BC 238, BC 548, ++
2 N 1593	USA,Tix	Si-N	=2N1592: 30V	=1a	TO-22	BC 168, BC 183, BC 238, BC 548, ++
2 N 1594	USA,Tix	Si-N	=2N1592: 60V	=1a	TO-22	BC 174, BC 182, BC 190, BC 546, ++
2 N 1595	USA,Tag,Tho	50Hz-Thy	50V, 1A(Tc=80°), 1,6A=, Igt/Ih<10/5mA, tq=10µs	2a	TO-39	BTX 30/50, T 1N100A, TAG 1-50, S 2600B++
2 N 1595 A		50Hz-Thy	=2N1595: Igt/Ih<2/5mA	2a	TO-39	TAG 2-50, MCR 1906-2, TAG 614-100
2 N 1596		50Hz-Thy	=2N1596: 100V	2a	TO-39	BTX30/100, T1N100A, TAG 1-100, S2600B,++
2 N 1596 A		50Hz-Thy	=2N1595A: 100V	2a	TO-39	TAG 2-100, MCR 1906-3, TAG 614-100
2 N 1597		50Hz-Thy	=2N1596: 200V	2a	TO-39	BTX30/200, T1N200A, TAG1-200, S2600B,++
2 N 1597 A		50Hz-Thy	=2N1595A: 200V	2a	TO-39	TAG 2-200, MCR 1906-4, TAG 614-200
2 N 1598		50Hz-Thy	=2N1596: 300V	2a	TO-39	BTX30/300, T1N300A, TAG1-300, S2600D,++
2 N 1598 A		50Hz-Thy	=2N1595A: 300V	2a	TO-39	TAG 2-300, MCR 1906-5, TAG 614-300
2 N 1599		50Hz-Thy	=2N1596: 400V	2a	TO-39	BTX30/400, T1N400A, TAG1-400, S2600D,++
2 N 1599 A		50Hz-Thy	=2N1595A: 400V	2a	TO-39	TAG 2-400, MCR 1906-6, TAG 614-400
2 N 1605	USA,Tix	Ge-N	LFS, 25V, 0,1A, 0,15W, >4MHz	2a	TO-5	ASY 28...29, ASY 73...75
2 N 1605 A		Ge-N	=2N1605: 40V	2a	TO-5	-
2 N 1606	Phc	Si-P	S, 10/10/10V, 0,05A, 0,1W, >7,2MHz	2a	TO-5	-
2 N 1607	Phc	Si-P	S, 10/10/10V, 0,05A, 0,1W, >10MHz	2a	TO-5	-
2 N 1608	Phc	Si-P	S, 10/10/10V, 0,05A, 0,1W, >25MHz	2a	TO-5	-
2 N 1609	Del	Ge-P	LFS P, 80V, 1,5A, 4,5W, hFE>30	43m	TO-37	-
2 N 1610	Del	Ge-P	=2N1609: hFE>50	43m	TO-37	-
2 N 1611	Del	Ge-P	=2N1609: 60V	43m	TO-37	-
2 N 1612	Del	Ge-P	=2N1609: 60V, hFE>50	43m	TO-37	-
2 N 1613(S)	USA,EUR	Si-N	Uni, 75V, 0,5A, 0,8W, >60MHz	2a	TO-5	BC 141
2 N 1613 A,L		Si-N	=2N1613: 1A, 1W	2a	TO-5	BC 141
2 N 1613 B		Si-N	=2N1613: 120V, 1A, 1W	2a	TO-5	(BC 141)
2 N 1614	USA	Ge-P	LFS, 65V, 0,3A, 0,24W, >0,5MHz	1a		ASY 48, ASY 77
2 N 1615	USA	Si-N	LFS, 100V, 0,2A, 0,6W, >2MHz	2a	TO-5	BC 141, BC 300, 2N1889...90, 2N1893(A),++
2 N 1616(/I)	USA,Tho	Si-N	S P, 60V, 5A, 60W, >3MHz	49m	TO-61	2N3487...92
2 N 1616 A		Si-N	=2N1616: 7,5A, 85W	49m	TO-61	2N3487...92
2 N 1617(/I)	USA,Tho	Si-N	S P, 80V, 5A, 60W, >3MHz	49m	TO-61	2N3487...92
2 N 1617 A		Si-N	=2N1617: 7,5A, 85W	49m	TO-61	2N3487...92
2 N 1618(/I)	USA,Tho	Si-N	S P, 100V, 5A, 60W, >3MHz	49m	TO-61	2N3488...89, 2N3491...92
2 N 1618 A		Si-N	=2N1618: 7,5A, 85W	49m	TO-61	2N3488...89, 2N3491...92
2 N 1619	USA,Tho	Si-N	S P, 60V, 5A, 60W, >3MHz	49m	TO-61	2N3487...92
2 N 1620(/I)	USA,Tho	Si-N	S P, 100V, 5A, 60W, >3MHz	49m	TO-61	2N3488...89, 2N3491...92
2 N 1622	USA	Ge-N	LFS, 90V, 0,12W, 1MHz	2a	TO-5	-