

2 N 1623	USA	Si-P	Uni, 50V, 0,05A, 0,25W	2a	TO-5	(BC 212, BC 257, BC 307, BC 557,++)
2 N 1624	USA	Ge-N	LFS, 25V, 0,15W, >5MHz	2a	TO-5	ASY 28...29, ASY 73...75
2 N 1631	USA	Ge-P	HF, 34V, 10mA, 0,08W, 45MHz	1a	TO-40	AF 124...126, AF 200
2 N 1632	USA	Ge-P	=2N1631:	2a	TO-1	AF 124...126, AF 200
2 N 1633	USA	Ge-P	HF, 34V, 10mA, 0,08W, 40MHz	1a	TO-40	AF 124...126, AF 200
2 N 1634	USA	Ge-P	=2N1633:	2a	TO-1	AF 124...126, AF 200
2 N 1635	USA	Ge-P	HF, 34V, 10mA, 0,08W, 45MHz	1a	TO-40	AF 124...126, AF 200
2 N 1636	USA	Ge-P	=2N1635:	2a	TO-1	AF 124...126, AF 200
2 N 1637	USA	Ge-P	HF, 34V, 10mA, 0,08W, 45MHz	2a	TO-1	AF 124...126, AF 200
2 N 1637/33		Ge-P	=2N1637: 0,12W	5g	TO-33	AF 124...126, AF 200
2 N 1638	USA	Ge-P	HF, 35V, 10mA, 0,08W, 40MHz	2a	TO-1	AF 124...126, AF 200
2 N 1638/33		Ge-P	=2N1638: 0,12W	5g	TO-33	AF 124...126, AF 200
2 N 1639	USA	Ge-P	HF, 34V, 10mA, 0,08W, 45MHz	2a	TO-1	AF 124...126, AF 200
2 N 1639/33		Ge-P	=2N1639: 0,12W	2a	TO-33	AF 124...126, AF 200
2 N 1640	Ssi,Tdy	Si-P	Chopper, 30V, 0,05A, 0,25W, hFE>6	2a	TO-5	(2N2946)
2 N 1641	Ssi,Tdy	Si-P	Chopper, 30V, 0,05A, 0,25W, hFE>10	2a	TO-5	(2N2946)
2 N 1642	Ssi,Tdy	Si-P	Chopper, 30V, 0,05A, 0,25W, hFE>15	2a	TO-5	(2N2946)
2 N 1643	Ssi,Tdy	Si-P	Chopper, 25V, 0,05A, 0,25W, hFE>10	2a	TO-5	(2N2946)
2 N 1644(A)	USA	Si-N	LFS, 60V, 0,6W, >50MHz	2a	TO-5	BC 140...141, BC 300...302, 2N3053, ++
2 N 1645	Wes	Ge-P	HF Drv, -20V, 0,3A, 1W, 600MHz	=2a	TO-38	-
2 N 1646	USA,Tix	Ge-P	HF/S, 15V, 0,05A, 0,15W	2a	TO-18	AF 106, AF 109R, AF 306
2 N 1647	USA	Si-N	S P, 80V, 5A, 40W, >3MHz, hFE>15	=21	=TO-111	2N5002, 2N5004, 2N5284...85, (BD 243B,++) ⁴
2 N 1648	USA	Si-N	=2N1647: 120V	=21	=TO-111	2N5284...85, (BD 243C, BD 539D,++) ⁴
2 N 1649	USA	Si-N	S P, 80V, 5A, 40W, >3MHz, hFE>30	=21	=TO-111	2N5002, 2N5004, 2N5284...85, (BD 243B,++) ⁴
2 N 1650	USA	Si-N	=2N1647: 120V	=21	=TO-111	2N5284...85, (BD 243C, BD 539D,++) ⁴
2 N 1651	USA,Mot	Ge-P	LFS P, 60V, 25A, 106W	23a	TO-3	2N2285...87
2 N 1652	USA,Mot	Ge-P	=2N1651: 100V	23a	TO-3	2N2286...87
2 N 1653	USA,Mot	Ge-P	=2N1651: 120V	23a	TO-3	2N2287
2 N 1654	USA	Si-P	Uni, 100V, 0,05A, 0,25W, hFE>20	2a	TO-5	BF 398, 2SA893(A), 2SA970, 2SA1285(A),++
2 N 1655	USA	Si-P	=2N1654: 125V, hFE>10	2a	TO-5	BF 398, 2SA893(A), 2SA970, 2SA1285(A),++
2 N 1656	USA	Si-P	=2N1654: 125V, hFE>20	2a	TO-5	BF 398, 2SA893(A), 2SA970, 2SA1285(A),++
2 N 1657	Ray,Tix	Si-N	LFS P, 60V, 2A, 55W		TO-53	2N1722...23, (BD 241, BD 535, BD 935,++)
2 N 1658(1/13)	USA	Ge-P	LFS P, 80V, 1A, 15W	=37	TO-13	-
2 N 1659(1/13)	USA	Ge-P	=2N1658: 60V	=37	TO-13	-
2 N 1660	Ray,Tix	Si-N	LFS P, 60V, 2A, 85W		TO-53	2N1722...23, (BD 239A, BD 241A, BD 935,++) ⁴
2 N 1661	Ray,Tix	Si-N	=2N1660: 80V		TO-53	2N1722...23, (BD 239B, BD 241B, BD 937,++) ⁴
2 N 1662	Ray,Tix	Si-N	=2N1660: 100V		TO-53	2N1722...23, (BD 239C, BD 241C, BD 937,++) ⁴
2 N 1663	Pbc	Si-N	S, 20V, 0,1A, 0,15W, -/65ns	2a	TO-9	BSV 89...92, BSX 92...93, 2N2368...69(A),++
2 N 1664	USA	Ge-P	LFS, 45V, 0,2A, 0,2W, 5MHz	2a	TO-5	ASY 48, ASY 76...77
2 N 1665	USA	Ge-P	HF, 15V, 0,05A, 0,15W	2a	TO-5	(AF 109R, AF 139, AF 239(S))
2 N 1666	Cen,Gpd	Ge-P	S P, 80V, 6A, 30W, hFE>15	23a	TO-3	AL 102...103, AUY 28, 2N3615...18, ++
2 N 1667	Cen,Gpd	Ge-P	S P, 60V, 6A, 30W, hFE>35	23a	TO-3	AL 102...103, AUY 28, 2N3615...18, ++
2 N 1668	Cen,Gpd	Ge-P	S P, 60V, 6A, 30W, hFE>20	23a	TO-3	AL 102...103, AUY 28, 2N3615...18, ++
2 N 1669	Cen,Gpd	Ge-P	S P, 80V, 6A, 30W, hFE>20	23a	TO-3	AL 102...103, AUY 28, 2N3615...18, ++
2 N 1670	USA	Ge-P	LFS, 100V, 0,12W, >10MHz	2a	TO-9	ACY 39, 2N2042...43
2 N 1671 A	Gen,Tho,Tix	UJT-P	30V, 50mA, Ip<25µA, Iv>8mA, η>0,47, Rbb=4,7...9,1kΩ	5e,2f	TO-33,TO-5	-
2 N 1671 AP		UJT-P	=2N1671A: Ip<12µA	5e,2f	TO-33,TO-5	-
2 N 1671 AX		UJT-P	=2N1671A	5e,2f	TO-33,TO-5	-
2 N 1671 B		UJT-P	=2N1671A: Ip<6µA	5e,2f	TO-33,TO-5	-
2 N 1671 BX		UJT-P	=2N1671A: Ip<6µA	5e,2f	TO-33,TO-5	-
2 N 1671 C		UJT-P	=2N1671A: Ip<2µA	5e,2f	TO-33,TO-5	2N2647
2 N 1671 CX		UJT-P	=2N1671A: Ip<2µA	5e,2f	TO-33,TO-5	2N2647
2 N 1672(A)	USA	Ge-N	LFS, 40V, 0,12W, >2MHz	2a	TO-5	-
2 N 1673	Cen	Ge-P	HF, 35V, 10mA, 0,08W, 5MHz	5g	TO-33	AF 124...127, AF 200
2 N 1674	Sem,Tra	Si-N	Uni, 45V, 0,025A, 0,2W, >20MHz	2a	TO-5	BC 167, BC 182, BC 237, 547, ++
2 N 1675	Wes	Si-N	S P, 100V, 10A, 100W, >120MHz	=2a	TO-38	(2SC2527) ⁴
2 N 1676	USA	Si-P	Chopper, 4,5/4,5/4,5V, 0,05A, 0,1W	2a	TO-5	-
2 N 1677	USA	Si-P	Chopper, 4,5/4,5/4,5V, 0,05A, 0,1W	2a	TO-5	-
2 N 1678	USA	Ge-P	HF/S, 60V, 0,12W, >25MHz	2a	TO-9	AF 118
2 N 1679	Sty,Tix	Si-N	LF Drv, 100V, 1A, 1W, >50MHz	2a	TO-39	BC 141, BSW 39, 2N1990, 2SC1069, ++
2 N 1680	Sty,Tix	Si-N	=2N1679: 60V	2a	TO-39	BC 140...141, BSW 27...28, 2SC1069, ++
2 N 1681	USA	Ge-P	LF, 30V, 0,2A, 0,18W, >5MHz	2a	TO-5	ASY 26, ASY 76...77
2 N 1682	USA	Si-N	HF/S, 25V, 0,5W, >200MHz	2a	TO-5	BFX 96...97, BSY 58, 2N2218...19(A), ++
2 N 1683	USA	Ge-P	HF/S, 13V, 0,1A, 0,15W, 80MHz	2a	TO-5	ASZ 21, 2N705, 2N960...67
2 N 1684	Syl	Ge-P	LFS, 25V, 0,1A, 0,1W	2a	TO-46	AC 125...126, AC 151, 2SB54, 2SB56
2 N 1685	Syl	Ge-N	LFS, 25V, 0,1A, 0,1W	2a	TO-46	AC 127, AC 176, AC 187, ASY 28...29
2 N 1686	Sem,Slid	GTO-Thy	30V, 1A, Igt/Ih<1/<5mA	2a	TO-5	-
2 N 1687		GTO-Thy	=2N1686: 60V	2a	TO-5	-
2 N 1688		GTO-Thy	=2N1686: 100V	2a	TO-5	-
2 N 1689		GTO-Thy	=2N1686: 200V	2a	TO-5	-
2 N 1690	USA,Tix	Si-N	S P, 80V, 0,5A, 40W		TO-57	(BD 169, BD 237, BD 239B, BD 241B,++) ⁴
2 N 1691	USA,Tix	Si-N	=2N1690: 120V		TO-57	(BD 239C, BD 241C, BD 939, 2SC2481,++) ⁴
2 N 1692	USA,Mot	Ge-P	VHF A,Drv, 25V, 0,25A, PQ>0,5W(160MHz)	49a	TO-102	(2N1561) ⁴
2 N 1693	USA,Mot	Ge-P	VHF A,Drv, 25V, 0,25A, PQ>0,4W(160MHz)	49a	TO-102	(2N1562) ⁴
2 N 1694	USA	Ge-N	LFS, 20V, 0,025A, 0,075W, 9MHz	2a	TO-5	(ASY 28...29, ASY 73...75)
2 N 1699	Syl	Ge-P	HF, 40V, 0,1W, 100MHz		TO-5	AF 106, AF 109R, AF 306
2 N 1700	USA,Fer,Rca	Si-N	LFS, 60V, 1A, 5W(Tc=25°)	2a	TO-5	BC 140...141, BSX 45...47, 2N3107...10, ++
2 N 1701	USA,Rca	Si-N	LFS P, 60V, 2,5A, 25W(Tc=25°)	2a	TO-8	(BD 177, BD 239A, BD 437, BD 935,++) ⁴
2 N 1702	USA,Fer,Rca	Si-N	LFS P, 60V, 5A, 75W	23a	TO-3	BD 245A, BDV 91, BDX 91, 2N4914...15, ++
2 N 1703	USA,Rca	Si-N	=2N1702:	38a	TO-36	(BD 245A, BDV 91, BDX 91, 2N4914...15,++) ⁴
2 N 1704	Csr,Etc	Si-N	Uni, 45V, 0,05A, 0,5W, 5MHz	2a	TO-5	BC 140...141, BC 300...302, 2N3053, ++
2 N 1705	USA,Mot	Ge-P	LF Drv, 18V, 0,4A, 0,2W, 4MHz	2a	TO-5	AC 128, AC 152...153, AC 188
2 N 1706	USA,Mot	Ge-P	LF Drv, 25V, 0,4A, 0,2W, 3MHz	2a	TO-5	AC 128, AC 152...153, AC 188
2 N 1707	USA,Mot	Ge-P	LF Drv, 30V, 0,4A, 0,2W, 3MHz	2a	TO-5	AC 128, AC 152...153, AC 188
2 N 1708	USA,Fer,Mot	Si-N	S, 25V, 0,2A, 0,3W, <40/75ns	2a	TO-46	BSS 11...12, BSX 19...20, 2N2368...69(A),++
2 N 1708 A		Si-N	=2N1708: 40V, 0,5A	2a	TO-46	BSS 10, BSX 26, BSX 39, 2N3261
2 N 1709	USA	Si-N	HF Os,Drv, 75V, 1,2A, 13W, 100MHz	2a	TO-8	(BD 139, BD 230, 2SC1398, 2SC2690,++) ⁴
2 N 1710	USA	Si-N	=2N1709: 60V	2a	TO-8	(BD 137, BD 228, 2SC1398, 2SC2690,++) ⁴
2 N 1711(S)	USA,EUR	Si-N	Uni, 75V, 0,5A, 0,8W, >70MHz	2a	TO-5	BC 141
2 N 1711 A,L		Si-N	=2N1711: 1A, 1W	2a	TO-5	BC 141
2 N 1711 B		Si-N	=2N1711: 120V, 1A, 1W	2a	TO-5	(BC 141)
2 N 1713	Rca,Sty	Ge-P	HF, 30V, 10mA, 0,08W, >100MHz	1g	TO-7	AF 106, AF 109R, AF 306
2 N 1714	USA,Tix	Si-N	Uni, 90V, 0,75A, 0,8W, >16MHz, hFE>20	2a	TO-5	BC 141, BSS 42...43, BSX 46...47, 2N5320++