

| | | | | | | | | | | | | | | | | | | | | | |
|----------|--------|----|----|---|-----|----|-----|------|------|------|------|------|------|-------|-----|-----|-----|-------|----|----|----|
| BCY58-9 | TO-18 | 32 | 32 | 7 | 10 | 32 | 40 | 0.01 | 5 | 0.35 | 0.6 | 0.85 | 10 | 6 | 125 | 10 | 800 | | 17 | 04 | |
| | | | | | | | 250 | 460 | 2 | 5 | 0.7 | 0.75 | 1.2 | 100 | | | | | 15 | | |
| | | | | | | | 160 | 630 | 10 | 1 | | 0.55 | 0.7* | 2 | | | 6 | | 1 | | |
| | | | | | | | 60 | | 100 | 1 | | | | | | | | | | | |
| BCY58-10 | TO-18 | 32 | 32 | 7 | 10 | 32 | 100 | 0.01 | 5 | 0.35 | 0.6 | 0.85 | 10 | 6 | 125 | 10 | 800 | | 17 | 04 | |
| | | | | | | | 380 | 630 | 2 | 5 | 0.7 | 0.75 | 1.2 | 100 | | | | | 15 | | |
| | | | | | | | 240 | 1000 | 10 | 1 | | 0.55 | 0.7* | 2 | | | 6 | | 1 | | |
| | | | | | | | 60 | | 100 | 1 | | | | | | | | | | | |
| BCY59 | TO-18 | 45 | 45 | 7 | 10 | 45 | 120 | 630 | 2 | 5 | 0.35 | 0.6 | 0.85 | 10 | 6 | 125 | 10 | 800 | | 17 | 04 |
| | | | | | | | 80 | 1000 | 10 | 1 | 0.7 | 0.75 | 1.2 | 100 | | | | | 15 | | |
| | | | | | | | 40 | | 100 | 1 | | 0.55 | 0.7* | 2 | | | 6 | | 1 | | |
| BCY59-7 | TO-18 | 45 | 45 | 7 | 10 | 45 | 120 | 220 | 2 | 5 | 0.35 | 0.6 | 0.85 | 10 | 6 | 125 | 10 | 800 | | 17 | 04 |
| | | | | | | | 80 | | 10 | 1 | 0.7 | 0.75 | 1.2 | 100 | | | | | 15 | | |
| | | | | | | | 40 | | 100 | 1 | | 0.55 | 0.7* | 2 | | | 6 | | 1 | | |
| BCY59-8 | TO-18 | 45 | 45 | 7 | 10 | 45 | 20 | | 0.01 | 5 | 0.35 | 0.6 | 0.85 | 10 | 6 | 125 | 10 | 800 | | 17 | 04 |
| | | | | | | | 180 | 310 | 2 | 5 | 0.7 | 0.75 | 1.2 | 100 | | | | | 15 | | |
| | | | | | | | 120 | 400 | 10 | 1 | | 0.55 | 0.7* | 2 | | | 6 | | 1 | | |
| | | | | | | | 45 | | 100 | 1 | | | | | | | | | | | |
| BCY59-9 | TO-18 | 45 | 45 | 7 | 10 | 45 | 40 | | 0.01 | 5 | 0.35 | 0.6 | 0.85 | 10 | 6 | 125 | 10 | 800 | | 17 | 04 |
| | | | | | | | 250 | 460 | 2 | 5 | 0.7 | 0.75 | 1.2 | 100 | | | | | 15 | | |
| | | | | | | | 160 | 630 | 10 | 1 | | 0.55 | 0.7* | 2 | | | 6 | | 1 | | |
| | | | | | | | 60 | | 100 | 1 | | | | | | | | | | | |
| BCY59-10 | TO-18 | 45 | 45 | 7 | 10 | 45 | 100 | | 0.01 | 5 | 0.35 | 0.6 | 0.85 | 10 | 6 | 125 | 10 | 800 | | 17 | 04 |
| | | | | | | | 380 | 630 | 2 | 5 | 0.7 | 0.75 | 1.2 | 100 | | | | | 15 | | |
| | | | | | | | 240 | 1000 | 10 | 1 | | 0.55 | 0.7* | 2 | | | 6 | | 1 | | |
| | | | | | | | 60 | | 100 | 1 | | | | | | | | | | | |
| BCY70 | TO-18 | 50 | 40 | 5 | 10 | 50 | 40 | | 0.1 | 1 | 0.25 | 0.6 | 0.9 | 10 | 6 | 250 | 10 | 420 | 6 | 6 | 71 |
| | | | | | | | 45 | | 1 | 1 | 0.5 | | 1.2 | 50 | | | | | 17 | | |
| | | | | | | | 50 | | 10 | 1 | | | | | | | | | | | |
| | | | | | | | 15 | | 50 | 1 | | | | | | | | | | | |
| BCY71 | TO-18 | 45 | 45 | 5 | 500 | 45 | 40 | | 0.01 | 1 | 0.25 | 0.6 | 0.9 | 10 | 6 | 200 | 20 | 2 | 6 | 71 | |
| | | | | | | | 80 | | 0.1 | 1 | 0.5 | | 1.2 | 50 | | 166 | 0.1 | | | | |
| | | | | | | | 90 | | 1 | 1 | | | | | | | | | | | |
| | | | | | | | 100 | 600 | 10 | 1 | | | | | | | | | | | |
| | | | | | | | 100 | 400* | 1 | 10 | | | | | | | | | | | |
| BCY71A | TO-18 | 45 | 45 | | 50 | 40 | 40 | | 0.01 | 1 | 0.25 | 0.6 | 0.9 | 10 | 6 | 300 | 10 | 2 | 6 | 71 | |
| | | | | | | | 80 | | 0.1 | 1 | 0.5 | | 1.2 | 50 | | 15 | 1 | | | | |
| | | | | | | | 90 | | 1 | 1 | | | | | | | | | | | |
| | | | | | | | 100 | 600 | 10 | 1 | | | | | | | | | | | |
| | | | | | | | 100 | 400* | 1 | 10 | | | | | | | | | | | |
| BCY72 | TO-18 | 25 | 25 | 5 | 50 | 20 | 40 | | 1 | 1 | 0.25 | | 10 | 6 | 200 | 10 | | 6 | 6 | 71 | |
| | | | | | | | 500 | 25 | 50 | 10 | 0.5 | | 1.2 | 50 | | 420 | | | 17 | | |
| BF153 | TO-106 | 30 | 12 | 2 | 100 | 15 | 20 | | 3 | 6 | 0.5 | | 10 | (CRE) | 300 | 3 | | GT | | 43 | |
| | | | | | | | | | | | | | | 1.2 | | | | 40 dB | | | |
| BF160 | TO106 | 30 | 12 | 2 | 500 | 15 | 20 | | 3 | 10 | 0.5 | | 10 | 1.7 | 400 | 10 | | Mm | | 43 | |

Test Conditions:

- $I_C = 200 \mu A, V_{CE} = 5V, R_S = 2 k\Omega, f = 1 kHz, BW = 200 Hz$
- $I_C = 200 \mu A, V_{CE} = 5V, R_S = 2 k\Omega, WB$
- $I_C = 30 \mu A, V_{CE} = 5V, R_S = 10 k\Omega, f = 1 kHz, BW = 200 Hz$
- $I_C = 20 \mu A, V_{CE} = 5V, R_S = 10 k\Omega, f = 1 kHz, BW = 150 Hz$
- $I_C = 200 \mu A, V_{CE} = 5V, R_G = 2 k\Omega, f = 20 Hz to 15 kHz$
- $I_C = 100 \mu A, V_{CE} = 5V, R_S = 2 k\Omega, f = 10 Hz to 10 kHz$
- $I_C = 50 \mu A, V_{CE} = 5V, R_S = 10 k\Omega, BW = 10 Hz to 15 kHz$
- $I_C = 50 \mu A, V_{CE} = 5V, R_S = 10 k\Omega, f = 1 kHz, BW = 200 Hz$
- $I_C = 200 \mu A, V_{CE} = 2V, R_S = 2 k\Omega, f = 1 kHz, BW = 200 Hz$
- $I_C = 10 \mu A, V_{CE} = 5V, R_S = 10 k\Omega, WB$
- $I_C = 150 mA, V_{CE} = 10V, I_{B1} = I_{B2} = 15 mA$
- $I_C = 10 mA, I_{B1} = 3 mA, I_{B2} = 1 mA$
- $I_C = 10 mA, V_{CE} = 6V, I_{B1} = I_{B2} = 15 mA$
- $V_{CC} = 20V, I_C = 100 mA, I_{B1} = I_{B2} = 5 mA$
- $I_C = 100 mA, I_{B1} = 40 mA, I_{B2} = 20 mA$
- $I_C = 10 mA, I_{B1} = 1 mA, I_{B2} = -1 mA$
- $V_{CC} = 10V, I_C = 100 mA, I_{B1} = I_{B2} = 10 mA$
- $I_C = 300 mA, I_{B1} = I_{B2} = 30 mA, V_{CC} = 25V$