

2 N 5494	Si-N	NF/S-L, 60W, 7A, 50W, >0.8MHz	17j	BD 243 C	17j
2 N 5495	Si-N	=2N5495	17j	BD 243 C	17j
2 N 5496	Si-N	NF/S-L, 90V, 7A, 50W, >0,8MHz	17j	BD 243 C	17j
2 N 5497	Si-N	=2N5498	17j	BD 243 C	17j
2 N 5550	Si-N	Vid, 160V, 0,6A, 0,625W, >100MHz	7e	BF 420 A	7c
2 N 5551	Si-N	=2N5550: 180V	7e	BF 420 A	7c
2 N 5629	Si-N	NF/S-L, 100V, 16A, 200W, >1MHz	23a	BD 317	23a
2 N 5630	Si-N	=2N5629: 120V	23a	MJ 15015	23a
2 N 5631	Si-N	=2N5629: 140V	23a	MJ 15015	23a
2 N 5632	Si-N	NF/S-L, 100V, 10A, 150W, >1MHz	23a	BD 317	23a
2 N 5633	Si-N	=2N5632: 120V	23a	MJ 15015	23a
2 N 5634	Si-N	=2N5632: 140V	23a	MJ 15015	23a
2 N 5638	N-FET	S, Chopper, 30V, Idss>50mA, <9/15ns	7d	-	-
2 N 5639	N-FET	S, Chopper, 30V, Idss>25mA, <14/30ns	7d	-	-
2 N 5640	N-FET	S, Chopper, 30V, Idss>5mA, <18/45ns	7d	-	-
2 N 5655	Si-N	NF/S/Vid-L, 275V, 0,5A, 20W, >10MHz	14h	MJE 340	14h
2 N 5656	Si-N	=2N5655: 325V	14h	MJE 340	14h
2 N 5657	Si-N	=2N5655: 375V	14h	MJE 340	14h
2 N 5770	Si-N	UHF, 30V, 0,05A, 0,7W, >900MHz	7e	2SC2570 A	7f
2 N 5777...5780	Opto			-	
2 N 5787	50Hz-Thy	30V, 0,24A, Igt/Ih<0,35/<10mA	8a	(TAG 103 X)	2a
2 N 5788	50Hz-Thy	=2N5787: 60V	8a	(BRX 49)	7a
2 N 5789	50Hz-Thy	=2N5787: 100V	8a	(BRX 49)	7a
2 N 5790	50Hz-Thy	=2N5787: 200V	8a	(BRX 49)	7a
2 N 5791	50Hz-Thy	=2N5787: 300V	8a	(BRX 49)	7a
2 N 5792	50Hz-Thy	=2N5787: 400V	8a	(BRX 49)	7a
2 N 5838	Si-N	S-L, 275/250V, 3A, 100W, >5MHz	23a	BU 608	23a
2 N 5839	Si-N	=2N5838: 300/275V	23a	BU 608	23a
2 N 5840	Si-N	=2N5838: 375/350V	23a	BU 608	23a
2 N 5855	Si-P	Uni, 60V, 1A, 0,75W, >100MHz	8a	BC 640	7c
2 N 5856	Si-N	Uni, 60V, 1A, 0,75W, >100MHz	8a	BC 639	7c
2 N 5857	Si-P	=2N5855: 80V	8a	BC 640	7c
2 N 5858	Si-N	=2N5856: 80V	8a	BC 639	7c
2 N 5871	Si-P	NF/S-L, 60V, 7A, 115W, >4MHz	23a	BD 318	23a
2 N 5872	Si-P	=2N5871: 80V	23a	BD 318	23a
2 N 5873	Si-N	NF/S-L, 60V, 7A, 115W, >4MHz	23a	BD 317	23a
2 N 5874	Si-N	=2N5873: 80V	23a	BD 317	23a
2 N 5875	Si-P	NF/S-L, 60V, 10A, 150W, >4MHz	23a	BD 318	23a
2 N 5876	Si-P	=2N5875: 80V	23a	BD 318	23a
2 N 5877	Si-N	NF/S-L, 60V, 10A, 150W, >4MHz	23a	BD 317	23a
2 N 5878	Si-N	=2N5877: 80V	23a	BD 317	23a
2 N 5879	Si-P	NF/S-L, 60V, 15A, 160W, >4MHz	23a	BD 318	23a
2 N 5880	Si-P	=2N5879: 80V	23a	BD 318	23a
2 N 5881	Si-N	NF/S-L, 60V, 15A, 160W, >4MHz	23a	BD 317	23a
2 N 5882	Si-N	=2N5881: 80V	23a	BD 317	23a
2 N 5974	Si-P	NF/S-L, 60V, 5A, 75W, >2MHz	16h	(BD 244 C)	17j 5
2 N 5975	Si-P	=2N5974: 80V	16h	(BD 244 C)	17j 5
2 N 5976	Si-P	=2N5974: 100V	16h	(BD 244 C)	17j 5
2 N 5977	Si-N	NF/S-L, 60V, 5A, 75W, >2MHz	16h	(BD 243 C)	17j 5
2 N 5978	Si-N	=2N5977: 80V	16h	(BD 243 C)	17j 5
2 N 5979	Si-N	=2N5977: 100V	16h	(BD 243 C)	17j 5
2 N 5980	Si-P	NF/S-L, 60V, 8A, 90W, >2MHz	16h	(BD 810)	17j 5
2 N 5981	Si-P	=2N5980: 80V	16h	(BD 810)	17j 5
2 N 5982	Si-P	=2N5980: 100V	16h	-	-
2 N 5983	Si-N	NF/S-L, 60V, 8A, 90W, >2MHz	16h	(BD 809)	17j 5
2 N 5984	Si-N	=2N5983: 80V	16h	(BD 809)	17j 5