

2 SD 650(H)	Si-N-Darl+Di	S-L, 400/400V, 6A, 80W, B>500	23a	BU 826	18j
2 SD 651(H)	Si-N-Darl	S-L, 400/400V, 4A, 30W, B>500	22a	-	
2 SD 652	Si-N-Darl	S-L, 500/500V, 6A, 80W, B=3000	23a	-	
2 SD 654	Si-N	Uni, 50V, 0,5A, 0,57W, 190MHz	2a	BC 141	2a
2 SD 655	Si-N	Uni, 30V, 0,7A, 0,5W, 250MHz	7c	BC 639	7c
2 SD 656	Si-N	S-L, 200/180V, 1,5A, 30W, >2MHz	22a	2SD1138	17j
2 SD 657	Si-N	S-L, 200/200V, 1,5A, 50W	23a	-	
2 SD 658	Si-N	TV-HA, 1500/600V, 5A, 50W	23a	BU 208 A	23a
2 SD 660	Si-N	Uni, S, 90V, 2A, 1W, 150/2100ns	2a	(2SC4135)	30j
2 SD 661	Si-N	Uni, ra, 35V, 0,1A, 0,4W, 200MHz	9c	BC 550	7a
2 SD 661 A	Si-N	=2SD661: 55V	9c	BC 550	7a
2 SD 662	Si-N	Vid, 250/200V, 0,07A, 0,6W, 80MHz	9c	BF 420 A	7c
2 SD 662 B	Si-N	=2SD662: 400/400V	9c	BF 487	7c
2 SD 663	Si-N-Darl	S-L, 500/500V, 6A, 80W, B>400	23a	-	
2 SD 664	Si-N-Darl+Di	NF/S-L, 80V, 7A, 40W, B>2000	22a	BD 901	17j
2 SD 665	Si-N	S-L, 200/200V, 15A, 150W, 15MHz	23a	2SC3263	18j
2 SD 666(A)	Si-N	Uni, 120V, 0,05A, 0,9W, 140MHz	7c(9mm)	2SC2632	7c(9mm)
2 SD 667(A)	Si-N	=2SD666(A): 1A	7c(9mm)	2SD1812	7c(9mm)
2 SD 668(A)	Si-N	NF/S/Vid-L, 180V, 0,05A, 20W, 140MHz	14h	BF 471	14h
2 SD 669(A)	Si-N	=2SD668: 1,5A	14h	2SC3117	14h
2 SD 670(H)	Si-N-Darl+Di	NF/S-L, 100V, 15A, 100W, B>1000	23a	BDW 83 C	18j
2 SD 671	Si-N	Uni, 30V, 0,5A, 0,6W, 150MHz	7c	BC 639	7c
2 SD 672	Si-N	S-L, 300V, 1A, 40W(Tc=45°), 20MHz	23a	-	
2 SD 673(A)	Si-N	NF/S-L, 120V, 7A, 60W, 8MHz	23a	2SC3263	18j
2 SD 674(A)	Si-N	=2SD673: 80W	23a	2SC3263	18j
2 SD 675(A)	Si-N	NF/S-L, 160V, 12A, 100W, 8MHz	23a	2SC3263	18j
2 SD 676(A)	Si-N	=2SD675: 125W	23a	2SC3263	18j
2 SD 677	Si-N	S-L, 450V, 5A, 100W	23a	BU 426 A	18j
2 SD 678	Si-N-Darl	NF/S-L, 60V, 3A, 25W, B>1000	17j	BD 901	17j
2 SD 678 A	Si-N-Darl	=2SD678: 80V	17j	BD 901	17j
2 SD 679	Si-N-Darl	NF/S-L, 70V, 4A, 40W, B>1000	17j	BD 901	17j
2 SD 679 A	Si-N-Darl	=2SD679: 90V	17j	BD 901	17j
2 SD 680	Si-N-Darl	NF/S-L, 90V, 6A, 60W, B>1000	23a	BDW 83 C	18j
2 SD 680 A	Si-N-Darl	=2SD680: 110V	23a	BDW 83 C	18j
2 SD 681	Si-N-Darl	NF/S-L, 100V, 8A, 80W, B>1000	23a	BDW 83 C	18j
2 SD 681 A	Si-N-Darl	=2SD681: 120V	23a	(BDW 83 C)	18j
2 SD 682	Si-N-Darl	NF/S-L, 120V, 8A, 110W, B>1000	23a	-	
2 SD 682 A	Si-N-Darl	=2SD682: 140V	23a	-	
2 SD 684	Si-N-Darl	S-L, 600/300V, 6A, 30W, B>1500	22a	2SD798	17j
2 SD 684 A	Si-N-Darl+Di	S-L, 600/400V, 6A, 30W, B>600	22a	2SD798	17j
2 SD 686	Si-N-Darl+Di	NF/S-L, 100V, 4A, 30W, B>2000	17j	BD 901	17j
2 SD 687	Si-N-Darl+Di	NF/S-L, 60V, 3A, 25W, B>2000	17j	BD 901	17j
2 SD 688	Si-N-Darl	NF/S, 100V, 1,5A, 8W(Tc=25°), B>2000	2a	(BD 679)	14h
2 SD 689	Si-N-Darl	=2SD688: 10W	17j	(BD 901)	17j
2 SD 690	Si-N	NF/S-L, 70V, 7A, 40W, 10MHz	22a	BD 809	17j
2 SD 691	Si-N-Darl+Di	NF/S-L, 100V, 6A, 40W, B>500	22a	BD 901	17j
2 SD 692	Si-N-Darl+Di	=2SD691: 50W	23a	BDW 83 C	18j
2 SD 693	Si-N-Darl+Di	S-L, 450/450V, 10A, 80W, B>150	23a	-	
2 SD 704	Si-N	NF/S-L, 50V, 5A, 40W, 10MHz	18j	BD 245 C	18j
2 SD 712	Si-N	NF/S-L, 100V, 4A, 30W, 8MHz	17j	BD 243 C	17j
2 SD 712 A	Si-N	=2SD712: 280V	17j	(BU 406)	17j
2 SD 713	Si-N	NF/S-L, 100V, 5A, 40W, 8MHz	17j	BD 243 C	17j
2 SD 715	Si-N-Darl	NF/S-L, 110V, 7A, 80W, B>2000	18j	BDW 83 C	18j
2 SD 716	Si-N	Hifi-NF-E, 100V, 6A, 60W, 12MHz	18j	BD 245 C	18j
2 SD 717	Si-N	Io-sat, 70V, 10A, 80W, 10MHz	18j	-	
2 SD 718	Si-N	NF/S-L, 120V, 8A, 80W, 12MHz	18j	BD 245 C	18j

4

7

6