

2 N 1052	USA	Si-N	S, 180V, 0,2A, 0,6W, 4MHz	2a	TO-5	BF 258...259, BF 658...659, 2N5058...59
2 N 1053	USA	Si-N	=2N1052: 200V	2a	TO-5	BF 258...259, BF 658...659, 2N5058...59
2 N 1054	USA	Si-N	=2N1052: 125V	2a	TO-5	BF 257...259, BF 657...659, 2N5058...59
2 N 1055	USA	Si-N	=2N1052: 100V	2a	TO-5	BF 257...259, BF 657...659, 2N5058...59
2 N 1056	USA	Ge-P	L.F.S, 70V, 0,3A, 0,24W	2a	TO-5	ASY 48, ASY 77, 2N2042...43
2 N 1057	USA	Ge-P	L.F.S, 45V, 0,3A, 0,24W	2a	TO-5	ASY 48, ASY 76...77, 2SB405ST
2 N 1058	Etc	Ge-N	L.F.S, -/20V, 0,05A, 0,05W	=1a	TO-22	AC 127, ASY 28, ASY 73...75
2 N 1059	Etc	Ge-N	L.F.S, 40V, 0,1A, 0,18W	=1a	TO-22	AC 127, ASY 28, ASY 73...75
2 N 1060	Wes	Si-N	S, 40V, 0,2A, 0,25W, <50/-ns	2a	TO-28	BSW 41, BSY 63, 2N708, 2N4123, ++
2 N 1065	Gen,Sty	Ge-P	H.F.S, 40V, 0,12W, >20MHz	2a	TO-9	ASY 76...77
2 N 1066	Gen,Phi	Ge-P	H.F, 40V, 10mA, 0,12W, 120MHz	5p	TO-33	AF 106, AF 109R, AF 306
2 N 1067	USA	Si-N	L.F.S P, 60V, 0,5A, 5W, 1,5MHz	2a	TO-8	(BD 137, BD 167, BD 525, BD 825,++) ⁴
2 N 1068	USA	Si-N	=2N1067: 1,5A, 10W	2a	TO-8	(BD 137, BD 167, BD 525, BD 825,++) ⁴
2 N 1069	USA	Si-N	L.F.S P, 60V, 4A, 50W	23a	TO-3	BD245A, BDV 91, 2N4914...15, 2N5068...69++
2 N 1070	USA	Si-N	L.F.S P, 60V, 4A, 50V	23a	TO-3	BD245A, BDV 91, 2N4914...15, 2N5068...69++
2 N 1072	Sty	Si-N	L.F.S, -/30V, 2A(ss), 12W	=2a	TO-38	(BD 135, BD 165, BD 509, BD 825,++) ⁴
2 N 1073	USA,Mot	Ge-P	L.F.S P, 40V, 10A, 85W	23a	TO-3	AL 100...101, AUY 21, 2N3611...18, ++
2 N 1073 A		Ge-P	=2N1073: 80V	23a	TO-3	AL 100...101, AUY 37, 2N3615...18, ++
2 N 1073 B		Ge-P	=2N1073: 120V	23a	TO-3	AL 100, AUY 38, 2N2290, 2N2293
2 N 1074	Ray,Sty	Si-N	L.F, 50V, 0,05A, 0,25W, hfe=14	2a	TO-9	BC 167, BC 182, BC 237, BC 547, ++
2 N 1075	Ray,Sty	Si-N	=2N1074: hfe=25	2a	TO-9	BC 167, BC 182, BC 237, BC 547, ++
2 N 1076	Ray,Sty	Si-N	=2N1074: hfe=50	2a	TO-9	BC 167, BC 182, BC 237, BC 547, ++
2 N 1077	Ray,Sty	Si-N	=2N1074: hfe=18	2a	TO-9	BC 167, BC 182, BC 237, BC 547, ++
2 N 1078	USA	Ge-P	L.F.S P, 60V, 3A, 20W		TO-13	-
2 N 1079	USA	Si-N	L.F.S P, 60V, 3A, 60W		TO-53	2N1722...23, (BD 241A, BD 535, BD 935,++) ⁴
2 N 1080	USA	Si-N	L.F.S P, 60V, 3A, 60W		TO-53	2N1722...23, (BD 241A, BD 535, BD 935,++) ⁴
2 N 1081	Tra	Si-N	L.F.S, 40V, 0,75A, 0,6W	2a	TO-5	BC 140...141, BC 300...302, 2N3053, ++
2 N 1082	Tra	Si-N	Uni, 25V, 0,05A, 0,2W, >17MHz	2a	TO-5	BC 168, BC 183, BC 238, BC 548, ++
2 N 1084	USA	Si-P	L.F, 60V, 2A, 5W(Tc=100°)	2a	TO-5	BC 461, BCX 60, 2N4235...36
2 N 1085	USA	Si-N	L.F, 60V, 2A, 5W(Tc=100°)	2a	TO-5	BC 441, BCX 40, 2N4238...39
2 N 1086(A)	USA	Ge-N	L.F.HF, 9V, 0,02A, 0,065W, 8MHz	=1a	TO-22	-
2 N 1087	USA	Ge-N	L.F.HF, 9V, 0,02A, 0,065W, 8MHz	=1a	TO-22	-
2 N 1090	USA	Ge-N	L.F.S, 25V, 0,4A, 0,12W, 7MHz	2a	TO-9	ASY 73...75
2 N 1091	USA	Ge-N	L.F.S, 25V, 0,4A, 0,12W, 13MHz	2a	TO-9	ASY 73...75
2 N 1092	USA	Si-N	L.F.S, 60V, 0,5A, 1,5MHz	2a	TO-5	BC 140...141, BC 300...302, 2N1613, ++
2 N 1093	USA	Ge-P	L.F.S, 30V, 0,3A, 0,15Wz	2a	TO-5	AC 125...126, AC 151...152, 2SB324
2 N 1094	Whs	Ge-P	UHF, 30V, 0,04A, 0,15W, 645MHz	2a	TO-28	AF 139, AF 239S
2 N 1095	USA	Si-N	L.F.S, 60V, 0,5W, 3MHz	=1a	TO-22	BC 140...141, BC 300...302, 2N3053, ++
2 N 1096	USA	Si-N	L.F.S, 90V, 0,5W, 3MHz	=1a	TO-22	BC 141, BC 300...301, 2N1889...90, ++
2 N 1097	USA	Ge-P	L.F, -/16V, 0,1A, 0,14W, hFE>34	2a	TO-5	AC 125...126, AC 151, 2SB54, 2SB56
2 N 1098	USA	Ge-P	=2N11097: hFE>25	2a	TO-5	AC 125...126, AC 151, 2SB54, 2SB56
2 N 1099	USA,Mot	Ge-P	L.F.S-L, 80V, 15A, 170W	38a	TO-36	2N1982, 2N2075, 2N2079, 2N2492...93, ++
2 N 1100	USA,Mot	Ge-P	=2N1099: 100V	38a	TO-36	2N2493
2 N 1101	USA	Ge-N	L.F, 20V, 0,1A, 0,18W	=1a	TO-22	AC 127, ASY 28...29, ASY 73...75
2 N 1102	USA	Ge-N	=2N1101: 40V	=1a	TO-22	-
2 N 1103	USA	Si-N	L.F.S, 45V, 0,02A, 0,125W, >10MHz	2a	TO-5	BC 167, BC 182, BC 237, BC 547, ++
2 N 1104	USA	Si-N	L.F.S, 45V, 0,02A, 0,125W, >20MHz	2a	TO-5	BC 167, BC 182, BC 237, BC 547, ++
2 N 1105	USA	Si-N	L.F, 60V, 0,5A, 0,8W	2a	TO-43	BC 140...141, BC 300...302, 2N3053, ++
2 N 1106	USA	Si-N	=2N1105: 100V	2a	TO-43	BC 141, BC 300, 2N1889...90, 2N1990, ++
2 N 1107	USA	Ge-P	H.F, 16V, 5mA, 0,03W, 40MHz	=1a	TO-22	AF 124...126, AF 200
2 N 1108	USA	Ge-P	H.F, 16V, 5mA, 0,03W, 35MHz	=1a	TO-22	AF 124...126, AF 200
2 N 1109	USA	Ge-P	H.F, 16V, 5mA, 0,03W, 35MHz	=1a	TO-22	AF 124...126, AF 200
2 N 1110	USA	Ge-P	H.F, 16V, 5mA, 0,03W, 35MHz	=1a	TO-22	AF 124...126, AF 200
2 N 1111(A,B)	USA	Ge-P	H.F, 20V, 5mA, 0,03W, 35MHz	=1a	TO-22	AF 124...126, AF 200
2 N 1114	USA	Ge-N	L.F.S, 25V, 0,2A, 0,15W, >7MHz	2a(B=case)	TO-5	AC 127, ASY 28...29, ASY 73...75
2 N 1115(A)	USA	Ge-P	L.F.S, 20V, 0,125A, 0,15W, >5MHz	1a		AC 125...126, AC 151, ASY 26...27
2 N 1116	USA	Si-N	L.F.S, 60V, 0,8A, 0,6W(Ta=100°), >6MHz	2a	TO-5	BC 140...141, BC 300...302, 2N3053, ++
2 N 1117	USA	Si-N	L.F.S, 60V, 0,8A, 0,6W(Ta=100°), >4MHz	2a	TO-5	BC 140...141, BC 300...302, 2N3053, ++
2 N 1118(A)	USA	Si-P	Uni, 25V, 0,05A, 0,15W	2a	TO-5	BC 213, BC 258, BC 308, BC 558, ++
2 N 1119	USA	Si-P	Uni, 10V, 0,05A, 0,15W	2a	TO-5	BC 213, BC 258, BC 308, BC 558, ++
2 N 1120	USA,Mot	Ge-P	L.F.S P, 80V, 15A, 90W	23a	TO-3	2N1551...52, 2N1555...56, 2N1559...60
2 N 1121	USA	Ge-N	H.F, -/15V, 0,02A, 0,065W, 8MHz	=1a	TO-22	-
2 N 1122	Spr,Ssi	Ge-P	H.F/S/Chopper, 12V, 0,05A, 0,025W	37d	TO-24	-
2 N 1122 A		Ge-P	=2N1122: 15V	37d	TO-24	-
2 N 1123	USA	Ge-P	L.F.S, 45V, 0,5A, 0,75W	37d°		(2N1189...90) ⁴
2 N 1124	USA	Ge-P	L.F.S, 40V, 0,25A, 0,3W	2a		2N1189...90, 2SB405ST
2 N 1125	USA	Ge-P	L.F.S, 40V, 0,25A, 0,3W	2a		2N1189...90, 2SB405ST
2 N 1126	USA	Ge-P	=2N1124: 1W	2a°	TO-26	(2N1189...90, 2SB405ST) ⁴
2 N 1127	USA	Ge-P	=2N1125: 1W	2a°	TO-26	(2N1189...90, 2SB405ST) ⁴
2 N 1128	USA	Ge-P	L.F, 25V, 0,25A, 0,15W	2a		AC 128, AC 152...153, AC 188, 2SB324
2 N 1129	USA	Ge-P	L.F, 25V, 0,25A, 0,15W	2a		AC 128, AC 152...153, AC 188, 2SB324
2 N 1130	USA	Ge-P	L.F, 30V, 0,25A, 0,15W	2a		AC 128, AC 152...153, AC 188, 2SB324
2 N 1131	USA, EUR	Si-P	L.F.S, 50V, 0,6A, 0,6W, >50MHz	2a	TO-5	BC 161, BC 303...304, 2N2904...05(A), ++
2 N 1131 A, AS		Si-P	=2N1131: 60V	2a	TO-5	BC 161, BC 303...304, 2N2904...05(A), ++
2 N 1132	USA, EUR	Si-P	L.F.S, 50V, 0,6A, 0,6W, >60MHz	2a	TO-5	BC 161, BC 303...304, 2N2904...05(A), ++
2 N 1132 A		Si-P	=2N1132: 60V	2a	TO-5	BC 161, BC 303...304, 2N2904...05(A), ++
2 N 1132 B		Si-P	=2N1132: 75V	2a	TO-5	BC 303, BSW 40, 2N4031, 2N4033, ++
2 N 1135(A)	Phc	Si-P	Uni, 12/12/12V, 0,05A, 0,1A, >5,6MHz	2a	TO-5	(BC 213, BC 258, BC 308, BC 558, ++)
2 N 1136	USA	Ge-P	L.F.S P, 60V, 6A, 60W, hFE>50	23a	TO-3	AL 102...103, AUY 28, 2N3615...18, ++
2 N 1136 A		Ge-P	=2N1136: 90V	23a	TO-3	AL 102...103, AUY 28, 2N3616, 2N3618
2 N 1136 B		Ge-P	=2N1136: 100V	23a	TO-3	AL 102...103, AUY 37, 2N3616, 2N3618
2 N 1137	USA	Ge-P	L.F.S P, 60V, 6A, 60W, hFE>75	23a	TO-3	AL 102...103, AUY 28, 2N3615...18, ++
2 N 1137 A		Ge-P	=2N1137: 90V	23a	TO-3	AL 102...103, AUY 28, 2N3616, 2N3618
2 N 1137 B		Ge-P	=2N1137: 100V	23a	TO-3	AL 102...103, AUY 37, 2N3616, 2N3618
2 N 1138	USA	Ge-P	L.F.S P, 60V, 6A, 60W, hFE>100	23a	TO-3	AL 102...103, AUY 28, 2N3615...18, ++
2 N 1138 A		Ge-P	=2N1138: 90V	23a	TO-3	AL 102...103, AUY 28, 2N3616, 2N3618
2 N 1138 B		Ge-P	=2N1138: 100V	23a	TO-3	AL 102...103, AUY 37, 2N3616, 2N3618
2 N 1139	USA	Si-N	S, 15V, 0,1A, 0,5W(Ta=100°), >100MHz	2a	TO-5	BSV 69, 2N3724, 2SC1072, 2SC1385, ++
2 N 1140	USA	Si-N	S, 40V, 1W(Ta=100°), >35MHz	2a	TO-5	BSV 69, 2N3724, 2SC1072, 2SC1385, ++
2 N 1141(A)	Mot,Sem,Tix	Ge-P	VHF/UHF, 35V, 0,1A, 0,3W, >1200MHz	2a	TO-39	(AFY 18)
2 N 1142(A)	Mot,Sem,Tix	Ge-P	VHF/UHF, 35V, 0,1A, 0,3W, >1000MHz	2a	TO-39	(AFY 18)
2 N 1143(A)	Mot,Sem,Tix	Ge-P	VHF/UHF, 35V, 0,1A, 0,3W, >800MHz	2a	TO-39	(AFY 18)
2 N 1144	USA	Ge-P	L.F, 16V, 0,1A, 0,14W, hfe=55	1a		AC 125...126, AC 151, 2SB54, 2SB56