

BF 462	Si-N	=BF 460: 350V	13m	(MPSU 10)	13m	7
BF 463	Si-P	Vid-L, 250V, 0,5A, 10W, >20MHz	13m	MPSU 60	13m	
BF 464	Si-P	=BF 463: 300V	13m	MPSU 60	13m	
BF 465	Si-P	=BF 463: 350V	13m	(MPSU 60)	13m	7
BF 466	Si-N	NF/S/Vid-L, 200V, 1A, 10W, >100MHz	13m	-		
BF 467	Si-N	=BF 466: 250V	13m	-		
BF 468	Si-N	=BF 466: 300V	13m	-		
BF 469(S)	Si-N	Vid-L, 250V, 0,03A, 2W(Tc=110°),>60MHz	14h	BF 471	14h	
BF 470(S)	Si-P	Vid-L, 250V, 0,03A, 2W(Tc=110°),>60MHz	14h	BF 472	14h	
BF 471(S)	Si-N	=BF 469: 300V	14h	BF 471	14h	
BF 472(S)	Si-P	=BF 470: 300V	14h	BF 472	14h	
BF 479	Si-P	VHF/UHF-V, 2000MHz	24a	BF 979(S)	24e	
BF 479 S	Si-P	=BF 479: 1300MHz	24a	BF 979(S)	24e	
BF 479 T	Si-P	=BF 479: 1850MHz	24a	BF 979(S)	24e	
BF 480	Si-N	UHF-V, 1500MHz	24e	-		
BF 481	Si-N	UHF-V, 1200MHz	24e	-		
BF 483	Si-N	Vid, 300V, 0,05A, 0,83W, >70MHz	7c	BF 487	7c	
BF 484	Si-P	Vid, 250V, 0,1A, 0,83W, >70MHz	7c	BF 421A	7c	
BF 485	Si-N	=BF 483: 350V	7c	BF 487	7c	
BF 486	Si-P	=BF 484: 300V	7c	BF 421A	7c	
BF 487	Si-N	=BF 483: 400V	7c	BF 487	7c	
BF 488	Si-P	=BF 484: 350V	7c	BF 421A	7c	
BF 491(K,L,M)	Si-P	Vid, 200V, 0,5A, 0,625W, >50MHz	7e, 40	BF 421 A	7c	
BF 491 P1	Si-P	=BF 491: 0,2A, 1W	30e	MPSU 60	13m	6
BF 491 P2	Si-P	=BF 491: 0,2A, 1W	30b	-		
BF 492(K,L,M)	Si-P	=BF 491: 250V	7e, 40	BF 421 A	7c	
BF 492 P1	Si-P	=BF 492: 0,2A, 1W	30e	MPSU 60	13m	6
BF 492 P2	Si-P	=BF 492: 0,2A, 1W	30b	2SA1381	14h	6
BF 493(K,L,M)	Si-P	=BF 491: 300V	7e, 40	BF 421 A	7c	
BF 493 P1	Si-P	=BF 493: 0,2A, 1W	30e	MPSU 60	13m	6
BF 493 P2	Si-P	=BF 493: 0,2A, 1W	30b	2SA1381	14h	
BF 493 S	Si-P	=BF 491: 350V	7e(9mm)	-		
BF 494(B)	Si-N	AM/FM, 30V, 30mA, 0,3W, 260MHz	7d	BF 255	7d	
BF 495(C,D)	Si-N	AM/FM, 30V, 30mA, 0,3W, 200MHz	7d	BF 255	7d	
BF 494...495 [Mot]	Si-N	=BF 494...495: 0,1A 0,35W	7e	BF 255	7d	
BF 496	Si-N	VHF-V, 550MHz	7a	BF 198	7d	
BF 497	Si-N	TV-ZF, 1000MHz	8a	BF 199	7d	
BF 500(A)	Si-P	VHF-V/M/O, 400MHz	8a	BF 324	7a	
BF 501	Si-P	VHF-ra, 300MHz	8a	BF 324	7a	
BF 502	Si-N	VHF-M/O, 700MHz	7d	BF 199	7d	
BF 502 S	Si-N	=BF 502: 900MHz	7d	BF 199	7d	
BF 503	Si-N	VHF-M/O, 750MHz	7d	BF 199	7d	
BF 505	Si-N	VHF, >750MHz	7d	2SC2570A	7f	
BF 506	Si-P	VHF-V, 40V, 30mA, 550MHz	7a	BF 324	7a	
BF 506 A	Si-P	=BF 506: 25V, 25mA, 350MHz	7a	BF 324	7a	
BF 507	Si-N	VHF-V/M, >750MHz	7d	2SC2570A	7f	
BF 509(S,T)	Si-P	VHF-V, re, 700...800MHz	7a	(BF 979(S))	24e	4
BF 516	Si-P	VHF/UHF-M/O, 850MHz	5g	-		
BF 517	Si-N	SMD, UHF-A/O, 20V, 25mA, 2GHz	35a	2SC3356	35a	
BF 523	Si-N	TV-ZF, 500MHz	7d	BF 199	7d	
BF 540	Si-P	AM/FM, 130MHz	7d	BF 324	7a	
BF 541	Si-P	AM/FM, 130MHz	7d	BF 324	7a	
BF 542	Si-P	AM/FM, 130MHz	7d	BF 324	7a	
BF 545	N-FET	=BF 245: SMD	35f	-		
BF 547	Si-N	SMD, VHF/UHF-M/O, 30V, 0,03A, 1200MHz	35a	-		
BF 547 W	Si-N	=BF 547:	35a(2mm)	-		