

| | | | | | |
|-----------------|----------|---|-------|-----------|-----|
| 2 N 834 A | Si-N | =2N834: <16/24ns | 2a | - | |
| 2 N 835 | Si-N | S, 25V, 0,2A, 0,3W, <20/35ns | 2a | - | |
| 2 N 869 | Si-P | HF/S, 25V, 0,2A, 0,36W, 300MHz | 2a | (BC 556) | 7a |
| 2 N 869 A | Si-P | =2N869: >400MHz | 2a | (BC 556) | 7a |
| 2 N 870 | Si-N | NF/S, 100V, 0,5W, >50MHz | 2a | BC 639 | 7a |
| 2 N 871 | Si-N | =2N870: >60MHz | 2a | BC 639 | 7a |
| 2 N 910 | Si-N | NF/S, 100V, 1A, 0,5W, >60MHz | 2a | BC 639 | 7c |
| 2 N 911 | Si-N | NF/S, 100V, 1A, 0,5W, >50MHz | 2a | BC 639 | 7c |
| 2 N 912 | Si-N | NF/S, 100V, 1A, 0,5W, >40MHz | 2a | BC 639 | 7c |
| 2 N 914(A) | Si-N | S, 40V, 0,5A, 0,36W, <40/40ns | 2a | - | |
| 2 N 918 | Si-N | VHF/UHF, 30V, 0,05A, 0,2W, >600MHz | 5g | 2SC2570 A | 7f |
| 2 N 929 | Si-N | Uni, ra, 45V, 0,03A, 0,5W, >30MHz | 2a | BC 550 | 7a |
| 2 N 929 A | Si-N | =2N929: 60V | 2a | BC 550 | 7a |
| 2 N 930 | Si-N | Uni, ra, 45V, 0,03A, 0,5W, >30MHz | 2a | BC 550 | 7a |
| 2 N 930 A,B | Si-N | =2N929: 60V | 2a | BC 550 | 7a |
| 2 N 956 | Si-N | NF-Tr, 75V, 0,5W, 300MHz | 2a | BC 639 | 7c |
| 2 N 995(A) | Si-P | Uni, 20V, 0,36W, 300MHz | 2a | BC 556 | 7a |
| 2 N 996 | Si-P | Uni, 15V, 0,2A, 0,36W, >100MHz | 2a | BC 556 | 7a |
| 2 N 1008 | Ge-P | NF/S, 20V, 0,3A, 0,2W | 2a | AC 151 | 2a |
| 2 N 1008 A | Ge-P | =2N1008: 40V | 2a | - | |
| 2 N 1008 B | Ge-P | =2N1008: 60V | 2a | - | |
| 2 N 1021(A) | Ge-P | NF/S-L, 100V, 7A, 150W | 23a | - | |
| 2 N 1022(A) | Ge-P | =2N1021: 120V | 23a | - | |
| 2 N 1073 | Ge-P | NF/S-L, 40V, 10A, 85W | 23a | - | |
| 2 N 1099 | Ge-P | NF/S-L, 80V, 15A, 170W | 38a | - | |
| 2 N 1100 | Ge-P | =2N1099: 100V | 38a | - | |
| 2 N 1189 | Ge-P | NF/S, 45V, 0,5A, 0,2W, 3,5MHz, $\beta > 75$ | 2a | - | |
| 2 N 1190 | Ge-P | NF/S, 45V, 0,5A, 0,2W, 4,5MHz, $\beta > 125$ | 2a | - | |
| 2 N 1191 | Ge-P | NF/S, 40V, 0,2A, 0,2W, 1,5MHz, $\beta > 30$ | 2a | AC 151 | 2a |
| 2 N 1192 | Ge-P | NF/S, 40V, 0,2A, 0,2W, 2MHz, $\beta > 50$ | 2a | AC 151 | 2a |
| 2 N 1193 | Ge-P | NF/S, 40V, 0,2A, 0,2W, 2,5MHz, $\beta > 100$ | 2a | AC 151 | 2a |
| 2 N 1194 | Ge-P | NF/S, 40V, 0,2A, 0,2W, 3MHz, $\beta > 190$ | 2a | AC 151 | 2a |
| 2 N 1613(S) | Si-N | Uni, 75V, 0,5A, 0,8W, >60MHz | 2a | BC 141 | 2a |
| 2 N 1613 A,L | Si-N | =2N1613: 1A, 1W | 2a | BC 141 | 2a |
| 2 N 1613 B | Si-N | =2N1613: 120V, 1A, 1W | 2a | (BC 141) | 2a |
| 2 N 1711(S) | Si-N | Uni, 75V, 0,5A, 0,8W, >70MHz | 2a | BC 141 | 2a |
| 2 N 1711 A,L | Si-N | =2N1711: 1A, 1W | 2a | BC 141 | 2a |
| 2 N 1711 B | Si-N | =2N1711: 120V, 1A, 1W | 2a | (BC 141) | 2a |
| 2 N 1869(A) | 50Hz-Thy | 15V, 1,25A($T_c=100^\circ$), $I_{gt}/I_h < 0,2 / < 5mA$ | 2a | TAG 103 X | 2a |
| 2 N 1870(A) | 50Hz-Thy | =2N1869: 30V | 2a | TAG 103 X | 2a |
| 2 N 1889 | Si-N | NF/S, 100V, 0,5A, 0,8W, >50MHz, $B > 40$ | 2a | BC 141 | 2a |
| 2 N 1890(S) | Si-N | =2N1889: >60MHz, $B > 100$ | 2a | BC 141 | 2a |
| 2 N 1893(L,S) | Si-N | NF/S, 120V, 0,5A, 0,8W, 70MHz | 2a | (BC 141) | 2a |
| 2 N 1893 A | Si-N | =2N1893: 140V, >100MHz | 2a | - | |
| 2 N 1990(S) | Si-N | Nix, 100V, 1A, 0,6W | 2a | BC 141 | 2a |
| 2 N 1990(N,R,W) | Si-N | =2N1990(S): 0,25...0,3W | 2a | BC 639 | 7c |
| 2 N 2009 | 50Hz-Thy | 25V, 1,3A($T_c=80^\circ C$), $I_{gt}/I_h < 0,2 / < 5mA$ | 2a | TAG 103 X | 2a |
| 2 N 2010 | 50Hz-Thy | =2N2009: 50V | 2a | BRX 49 | 7a |
| 2 N 2011 | 50Hz-Thy | =2N2009: 100V | 2a | BRX 49 | 7a |
| 2 N 2012 | 50Hz-Thy | =2N2009: 200V | 2a | BRX 49 | 7a |
| 2 N 2013 | 50Hz-Thy | =2N2009: 300V | 2a | BRX 49 | 7a |
| 2 N 2014 | 50Hz-Thy | =2N2009: 400V | 2a | BRX 49 | 7a |
| 2 N 2060(A,B) | Si-N | Dual, 100V, 0,5A, 0,6W, >60MHz | TO-77 | - | |
| 2 N 2061 | Ge-P | S-L, 20V, 3A, 40W | 23a | AL 102 | 23a |
| 2 N 2061 A | Ge-P | =2N2061: 5A, 90W | 23a | AL 102 | 23a |
| 2 N 2062 | Ge-P | S-L, 20V, 3A, 40W | 23a | AL 102 | 23a |