

TRANSISTOR NUMBER	PM OA LT	PACK- AGE	LEAD INFO	VCB MAX	VCE MAX	VEB MAX	I C MAX	T J MAX	P TOT	F T MIN	C OB MAX	H FE	H FE BIAS	USE	MFR	EUR EQUIV	USA EQUIV	ISS
2N3659	NS	T05	L04	220V	170V		500MA	200C	4WC	50M	6P	20MN	10MA	RME	OBS	BF258	2N4927	2
2N3660	NS	T05	L04	40V	30V		1A5	200C	5WC	25M	275P	25/100	500MA	RHG	OBS	BSS42	2N5321	2
2N3661	NS	T05	L04	60V	50V		1A5	200C	5WC	25M	275P	25/100	500MA	RHG	OBS	BSS42	2N5321	2
2N3662	NS	T098	L21	18V	12V	3V	25MA	125C	200MWF	700M	1P7	20MN	8MA	VLA	GEU	BFX73	2N918	0
2N3663	NS	T098	L21	30V	12V	3V	25MA	125C	200MWF	700M	1P7	20MN	8MA	VLA	GEU	BFX73	2N918	0
2N3664	NS	T039	L04	60V	60V		500MA	200C	800MWF	300M		8/80	50MA	VMS	MOB	BSX59	2N3725	0
2N3665	NS	T039	L04	120V	80V	10V	1A	200C	800MWF	60M	12P	40/120	150MA	AMH	SGI	BSW66	2N1893	0
2N3666	NS	T039	L04	120V	80V	10V	1A	200C	800MWF	60M	12P	100MN	150MA	AMH	SGI	BSW66	2N1893	0
2N3667	NS	T03	L05	50V	50V		15A	200C	117WC	500K		15/60	8A	AHG	OBS	BDX40	2N3772	2
2N3671	PS	T05	L04	60V	50V	5V	600MA	180C	600MWF	200M	9P	75/225	150MA	RMG	SGI	BFX29	2N2905A	0
2N3672	PS	T018	L01	60V	50V	5V	600MA	180C	400MWF	200M	9P	75/225	150MA	RMG	SGI	BSW24	2N2907A	0
2N3673	PS	T046	L01	60V	50V	5V	600MA	200C	350MWF	200M	9P	75/225	150MA	RMG	FCU	BSW24	2N2907A	0
2N3675	NS	T05	L04	90V	55V		3A	200C	8.8WC	1M		12/60	1A	AHG	OBS	BSV64	2N4877	2
2N3676	NS	T05	L04	90V	90V		3A	200C	8.8WC	1M		12/60	1A	AHG	OBS	BSS42	2N5238	2
2N3677	PS	T046	L01	30V	20V		100MA	200C	400MWF	5M	10P	-		ALC	ORY	BCY94	2N2945	2
2N3678	NS	T05	L04	75V	55V	6V	800MA	200C	800MWF	250M	8P	40/120	150MA	RMG	FCU	BSW54	2N2219A	0
2N3681	NS	T072	L06	10V	7V		25MA	200C	200MWF	1000M	0P7	20/220	2MA	ULA	OBS	2N6389	2	
2N3682	NS	T018	L01	40V	15V		200MA	200C	360MWF	600M	4P	40/120	10MA	ULA	OBS	BSX20	2N2369	2
2N3683	NS	T072	L06	12V	9V		25MA	200C	250MWF	1G	2P	-		ULA	FCU	BFY90	2N2857	2
2N3688	NS	T0106	L17	40V	40V		30MA	125C	200MWF	400M	1P6	30MN	4MA	TUG	OBS	BF200	2N918	2
2N3689	NS	T0106	L17	40V	40V		30MA	125C	200MWF	400M	1P6	30MN	4MA	TUG	OBS	BF200	2N918	2
2N3690	NS	T0106	L17	40V	40V		30MA	125C	200MWF	400M	1P6	30MN	4MA	TUG	OBS	BF200	2N918	2
2N3691	NS	T0106	L17	35V	20V	4V	30MA	125C	200MWF	200M	3P5	40/160	10MA	ALG	NAT	BC237	2N5825	0
2N3692	NS	T0106	L17	35V	20V	4V	30MA	125C	200MWF	200M	3P5	100MN	10MA	ALG	NAT	BC237	2N5825	0
2N3693	NS	T0106	L17	45V	45V	4V	30MA	125C	200MWF	200M	6P	40/160	10MA	RLG	SGI	BSW64	2N2222A	0
2N3694	NS	T0106	L17	45V	45V	4V	30MA	125C	200MWF	200M	6P	100MN	10MA	RLG	SGI	BSW64	2N2222A	0
2N3700	NS	T018	L01	140V	80V	7V	1A	200C	500MWF	100M	12P	100MN	150MA	AMH	FCU	BSW66	2N3700	0
2N3701	NS	T018	L01	140V	80V	7V	1A	200C	500MWF	80M	12P	40/120	150MA	AMH	FCU	BSW66	2N3700	0
2N3702	PS	T092	L21	40V	25V	5V	200MA	150C	360MWF	100M	12P	60MN	50MA	ALG	TIB	BC212L	2N5086	0
2N3703	PS	T092	L21	50V	30V	5V	200MA	150C	360MWF	100M	12P	30MN	50MA	ALG	TIB	BC212L	2N5086	0
2N3704	NS	T092	L21	50V	30V	5V	800MA	150C	360MWF	100M	12P	300MN	50MA	AMG	TIB	TIS90	2N3704	0
2N3705	NS	T092	L21	50V	30V	5V	800MA	150C	625MWF	100M	12P	150MN	50MA	AMG	TIB	TIS90	2N3704	0
2N3706	NS	T092	L21	40V	20V	5V	800MA	150C	625MWF	100M	12P	600MN	50MA	AMG	TIB	TIS90	2N3704	0
2N3707	NS	T092	L21	30V	30V	6V	30MA	150C	360MWF	100M	10P	100MN	100UA	ALN	TIB	BC184L	2N5210	2
2N3708	NS	T092	L21	30V	30V	6V	30MA	150C	360MWF	100M	10P	45/660	1MA	ALN	TIB	BC184L	2N5210	0
2N3709	NS	T092	L21	30V	30V	6V	30MA	150C	360MWF	100M	10P	45MN	1MA	ALG	TIB	BC182L	2N5209	0
2N3710	NS	T092	L21	30V	30V	6V	30MA	150C	360MWF	100M	10P	90MN	1MA	ALN	TIB	BC184L	2N5210	0
2N3711	NS	T092	L21	30V	30V	6V	30MA	150C	360MWF	100M	10P	180MN	1MA	ALN	TIB	BC184L	2N5210	0
2N3712	NS	T05	L04	150V	150V	5V	200MA	200C	1WF	40M	9P	30/150	30MA	ALE	MOB	BF337	2N4927	0
2N3712S	NS	T039	L04	150V	150V	5V	200MA	200C	1WF	40M	9P	30/150	30MA	ALE	MOB	BF337	2N3712	2
2N3713	NS	T03	L05	80V	60V	7V	10A	200C	150WC	4M		25/90	1A	RHG	MOB	BDY23	2N3445	0
2N3714	NS	T03	L05	100V	80V	7V	10A	200C	150WC	4M		25/90	1A	RHG	MOB	BDY23	2N3445	2
2N3715	NS	T03	L05	80V	60V	7V	10A	200C	150WC	4M		50/150	1A	RHG	MOB	BDY23	2N3445	2
2N3716	NS	T03	L05	100V	80V	7V	10A	200C	150WC	4M		50/150	1A	RHG	MOB	BDY23	2N3445	0
2N3717	NS	T039	L04	60V			1A	200C	7.5WC	250M	10P	2/100	200MA	RMG	OBS			2
2N3718	PS	T0102	L59	60V			1A	200C	10WC	250M	10P	2/100	200MA	RMG	OBS			2
2N3719	PS	T05	L04	40V	40V	4V	3A	200C	1WF	60M	120P	25/180	1A	AHG	MOB	BSS44	2N3720	2
2N3720	PS	T05	L04	60V	60V	4V	3A	200C	1WF	60M	120P	25/180	1A	AHG	MOB	BSS44	2N3720	2
2N3721	NS	T098	L21	18V	18V	5V	100MA	200C	200MWF	12P	60/660		2MA	ALG	GEU	BC182L	2N3710	0
2N3722	NS	T05	L04	80V	60V	6V	500MA	200C	800MWF	300M	10P	40/150	100MA	RMS	SGI	BSW54	2N2219A	0
2N3723	NS	T05	L04	100V	80V	6V	500MA	200C	800MWF	300M	9P	40/150	100MA	RMS	FCU	BSW54	2N2219A	0
2N3724	NS	T05	L04	50V	30V	6V	500MA	175C	800MWF	300M	12P	60/150	100MA	VMS	SGI	BSX59	2N3444	0
2N3724A	NS	T05	L04	50V	30V	6V	1200MA	200C	1WF	300M	12P	60/150	100MA	VLS	NAT	BSX59	2N3725	0
2N3725	NS	T05	L04	80V	50V	6V	500MA	175C	800MWF	300M	12P	60/150	100MA	VMS	SEU	BSX59	2N3444	0
2N3725A	NS	T05	L04	80V	50V	6V	1200MA	200C	1WF	300M	12P	60/150	100MA	VLS	NAT	BSX59	2N3725	0
2N3730	PG	T03	L05	200V	200V	0V5	3A		10WC	1M		10/200	50MA	AHE	GPD			2
2N3731	PG	T03	L05	320V	320V	2V	10A	90C	5WC			15MN	6A	AHE	GPD			2
2N3732	PG	T03	L05	100V	100V	0V5	3A	90C	3WC	1M		35/500	700MA	AHH	GPD			2
2N3733	NS	T060	L61	65V	40V	4V	3A	200C	23WC	400M	20P	5MN	500MA	UHF	MOB			0
2N3734	NS	T05	L04	50V	30V	5V	1500MA	175C	1WF	300M	9P	30/120	1MA	RLS	SGI	BSW54	2N2219A	0
2N3734A	NS	T05	L04	50V	30V	5V	1500MA	175C	1WF	300M	9P	30/120	1MA	RLS	NAT	BSW54	2N2219A	2
2N3734S	NS	T039	L04	50V	30V	5V	1500MA	175C	1WF	300M	9P	30/120	1MA	RLS	NAT	BSW54	2N2219A	2
2N3735	NS	T05	L04	75V	50V	5V	1500MA	200C	1WF	250M	9P	20/80	1A	VMS	MOB	BSS14	2N3735	0
2N3735S	NS	T039	L04	75V	50V	5V	1A5	200C	1WF	250M	9P	20/80	1A	VMS	MOU	BSS14	2N3735	2
2N3736	NS	T046	L01	50V	30V	5V	1500MA	200C	500MWF	250M	9P	30/120	1A	VMS	MOB	BSX59	2N3725	0
2N3737	NS	T046	L01	75V	50V	5V	1500MA	200C	500MWF	250M	9P	20/80	1A	VMS	MOB	BSX59	2N3725	0
2N3738	NS	T066	L43	250V	225V	6V	3A	175C	20WC	10M	20P	40/200	100MA	RHH	MOT			2
2N3739	NS	T066	L43	325V	300V	6V	3A	175C	20WC	10M		40/200	100MA	RHE	MOT			2
2N3740	PS	T066	L43	60V	60V	7V	10A	200C	25WC	4M	100P	30/100	250MA	RHG	MOB	BDX14	2N3740	2
2N3740A	PS	T066	L43	60V	60V	7V	10A	200C	25WC	4M	100P	30/100	250MA	RHG	MOB	BDX14	2N3740	2
2N3741	PS	T066	L43	80V	80V	7V	10A	200C	25WC	4M	100P	30/100	250MA	RHH	MOB	BDX16	2N3741	2
2N3741A	PS	T066	L43	80V	80V	7V	10A	200C	25WC	4M	100P	30/100	250MA	RHH	MOB	BDX16	2N3741	2
2N3742	NS	T05	L04	300V	300V	7V	50MA	200C	1WF	30M	6P	20/200	30MA	ALE	MOB	BF337	2N4927	0
2N3742S	NS	T039	L04	300V	300V	7V	50MA	200C	1WF	30M	6P	20/200	30MA	ALE	MOB	BF337	2N4927	2
2N3743	PS	T039	L04	300V	300V	5V	50MA	200C	1WF	30M	15P	25/250	30MA	ALE	MOB			0