



National Semiconductor

N-Channel JFETs

NATL SEMICOND DISCRETE LIF D 6501130 0037100 9

General Purpose Amplifiers

Type No.	Case Style	BV _{GSS} BV _{GDO} (V) @ I _g (μA)	I _{GSS} (mA) @ V _{GG} (V)	V _p (V) @ V _{DS} (V)	I _b (mA)	I _{SS} (mA) @ V _{DS} (V)	C _{iss} (mmho) @ V _{DS} (V)	G _{oss} (μmho) @ V _{DS} (V)	C _{iss} (pF) @ V _{DS} (V)	V _{GS} (V)	C _{iss} (pF) @ V _{DS} (V)	V _{GS} (V)	C _{iss} (pF) @ V _{DS} (V)	V _{GS} (V)	(AV) ^{0.5} (Hz)	Process No.	Pkg No.
2N3369	TO-18	40	1	5	30	0.5	2.5	30	30	8	20	0	3	30	0	52	02
2N3370	TO-18	40	1	5	30	0.1	0.6	30	15	8	20	0	3	30	0	52	02
2N3458	TO-18	50	1	0.25	30	3	15	20	35	0	18	0	5	30	0	52	02
2N3459	TO-18	50	1	0.25	30	3.4	20	1000	0.8	4	20	0	5	30	0	52	02
2N3460	TO-18	50	1	0.25	30	1.8	20	1000	0.2	1	20	0	5	30	0	52	02
2N3684	TO-72	50	1	0.1	30	2	5	20	1	2.5	7.5	20	4	20	0	52	25
2N3685	TO-72	50	1	0.1	30	1	3.5	20	1	3	20	0	4	20	0	52	25
2N3686	TO-72	50	1	0.1	30	0.6	2	20	1	0.4	1.2	20	4	20	0	52	25
2N3687	TO-72	50	1	0.1	30	0.3	1.2	20	1	0.1	0.5	20	4	20	0	52	25
2N3821	TO-72	50	1	0.1	30	4	15	0.5	15	1.5	4.5	15	6	15	0	55	25
2N3822	TO-72	50	1	0.1	30	6	15	0.5	2	10	15	0	6	15	0	55	25
2N3867	TO-72	30	1	0.1	20	2	5	20	1	2.5	10	20	5	20	0	55	25
2N3967A	TO-72	30	1	0.1	20	2	5	20	1	2.5	10	20	5	20	0	55	25
2N3968	TO-72	30	1	0.1	20	3	20	1	5	20	2	20	5	20	0	55	25
2N3968A	TO-72	30	1	0.1	20	3	20	1	1	5	20	2	5	20	0	55	25
2N3969	TO-72	30	1	0.1	20	1.7	20	1	0.4	2	20	1.3	5	20	0	55	25
2N3969A	TO-72	30	1	0.1	20	1.7	20	1	0.4	2	20	1.3	5	20	0	55	25
2N4220	TO-72	30	10	0.1	15	4	15	0.1	0.5	3	15	1	4	15	0	55	25
2N4220A	TO-72	30	10	0.1	15	4	15	0.1	0.5	3	15	1	4	15	0	55	25
2N4221	TO-72	30	10	0.1	15	6	15	0.1	2	6	15	2	5	15	0	55	25
2N4221A	TO-72	30	10	0.1	15	6	15	0.1	2	6	15	2	5	15	0	55	25
2N4222	TO-72	30	10	0.1	15	8	15	0.1	5	15	15	2.5	6	15	0	55	25
2N4222A	TO-72	30	10	0.1	15	8	15	0.1	5	15	15	2.5	6	15	0	55	25
2N4338	TO-18	50	1	0.1	30	0.3	1	15	100	0.2	0.6	15	5	15	0	55	25
2N4339	TO-18	50	1	0.1	30	0.6	1.8	15	100	0.5	1.5	15	7	15	0	55	25
2N4340	TO-18	50	1	0.1	30	1	3	15	100	1.2	3.6	15	30	15	0	55	25
2N4341	TO-18	50	1	0.1	30	2	6	15	100	3	9	15	60	15	0	55	25
2N5103	TO-72	25	10	0.1	15	0.5	4	15	1	8	15	2	8	15	0	50	25
2N5104	TO-72	25	1	0.1	15	0.5	4	15	1	2	6	15	5	15	0	50	25

*I_b = 1 mA; I_b = 500 μA; f_{1b} = 40 μA; **I_b = 100 μA; C_{1b} = 250 μA.

T-29-01

JFET Transistors

JFET Transistors

T-29-01

N-Channel JFETs

General Purpose Amplifiers (Continued)

Type No.	Case Style	BV _{GSS} (V) @ I _G (μA)	I _{SSS} (nA) @ V _{GS} (V)	V _p (V) @ V _{GS} (V)	I _D (mA)	I _{SSS} (mA) @ V _{GS} (V)	G _{fs} (mmho) @ V _{GS} (V)	C _{oss} (μmho) @ V _{GS} (V)	C _{iss} (pF) @ V _{GS} (V)	C _{iss} (pF) @ V _{GS} (V)	V _{GS} (V)	C _{iss} (pF) @ V _{GS} (V)	V _{GS} (V)	(NV/Hz) ^{0.5} (Hz)	Process No.	Pkg. No.
2N5105	TO-72	25	0.1	15	0.5	4	15	15	5	15	0	1	15	0	50	25
2N5358	TO-72	40	0.1	20	0.5	3	15	100	1	15	0	2	15	0	55	25
2N5359	TO-72	40	0.1	20	0.8	4	15	100	1.2	15	0	2	15	0	55	25
2N5360	TO-72	40	0.1	20	0.8	4	15	100	1.4	15	0	2	15	0	55	25
2N5361	TO-72	40	0.1	20	1	6	15	100	1.5	15	0	2	15	0	55	25
2N5362	TO-72	40	0.1	20	2	7	15	100	2	15	0	2	15	0	55	25
2N5363	TO-72	40	0.1	20	2.5	8	15	100	2.5	15	0	2	15	0	55	25
2N5364	TO-72	40	0.1	20	2.5	8	15	100	2.7	15	0	2	15	0	55	25
2N5457	TO-92	25	1	15	0.5	6	15	10	2	5	15	0	3	15	55	92
2N5458	TO-92	25	1	15	1	7	15	10	2	9	15	0	3	15	55	92
2N5459	TO-92	25	1	15	2	8	15	10	4	16	15	0	3	15	55	92
2N5556	TO-72	30	0.1	15	0.2	4	15	1	0.5	2.5	15	0	3	15	50	25
2N5557	TO-72	30	0.1	15	0.8	5	15	1	2	5	15	0	3	15	50	25
2N5558	TO-72	30	0.1	15	1.5	6	15	1	4	10	15	0	3	15	50	25
J201	TO-92	40	0.1	20	0.3	1.5	20	10	0.2	1	20	0.5	20		52	92
J202	TO-92	40	0.1	20	0.8	4	20	10	0.9	4.5	20	1	20		52	92
J203	TO-92	40	0.1	20	2	10	20	10	4	20	20	1.5	20		52	92
J210	TO-92	25	0.1	15	1	3	15	1	2	15	15	4	12	15	90	92
J211	TO-92	25	0.1	15	2.5	4.5	15	1	7	20	15	7	12	15	90	92
J212	TO-92	25	0.1	15	4	6	15	1	15	40	15	7	12	15	90	92
MPF103	TO-92	25	1	15	6	15	1	1	1	5	15	0	3	15	55	92
MPF104	TO-92	25	1	15	7	15	1	2	9	15	0	3	15	0	55	92
MPF105	TO-92	25	1	15	8	15	1	4	16	15	0	3	15	0	55	92
MPF109	TO-92	25	10	1	0.2	8	15	10	0.5	24	15	0	3	15	55	92
MPF110	TO-92	20	10	100	0.5	10	10	1	0.5	20	10	0	3	15	50	92
MPF111	TO-92	20	10	100	0.5	10	10	1000	0.5	20	10	0	3	15	50	92
MPF112	TO-92	25	10	100	0.5	10	10	1000	1	25	10	0	3	15	55	92
PN3684	TO-92	50	0.1	30	2	5	20	1	2.5	7.5	20	2	20	0	52	92
PN3685	TO-92	50	0.1	30	1	3.5	20	1	1	3	20	1.5	2.5	20	52	92
PN3686	TO-92	50	0.1	30	0.6	2	20	1	0.4	1.2	20	1	2	20	52	92

N-Channel JFETs

General Purpose Amplifiers (Continued)

Type No.	Case Style	BV _{GSS} *BV _{GDO} (V) @ I _G (μA)	I _{SS} (nA) @ V _{DS} (V)	V _P (V) @ V _{DS} (V)	I _D (nA)	I _{BSS} (mA) @ V _{DS} (V)	G _{fs} (mmho) @ V _{DS} (V)	G _{oss} (μmho) @ V _{DS} (V)	C _{iss} (pF) @ V _{DS} (V)	C _{iss} (pF) @ V _{DS} (V)	V _{GS} (V)	V _{GS} (V)	($\frac{BV}{fT}$) ^{0.5} @ Freq. (Hz)	Process No.	Pkg. No.
PN3687	TO-92	50	0.1	30	0.3	1.2	20	1	0.5	1.5	20	0	150	52	92
PN4220	TO-92	30	0.1	15	4	15	1	4	15	15	0	0	20	55	92
PN4221	TO-92	30	0.1	15	6	15	2	5	15	0	0	0	20	55	92
PN4222	TO-92	30	0.1	15	8	15	2.5	6	15	0	0	0	20	55	92
PN4302	TO-92	30	1	10	4	20	1	20	0	3	20	0	100	52	92
PN4303	TO-92	30	1	10	6	20	2	20	0	6	20	0	100	52	92
PN4304	TO-92	30	1	10	10	20	1	20	0	6	20	0	125	52	92
PN4338	TO-92	50	0.1	30	0.3	1	15	100	0.2	0.6	15	0	20	52	92
PN4389	TO-92	50	0.1	30	0.6	1.8	15	100	0.5	1.5	15	0	20	52	92
PN5163	TO-92	25	1	10	0.4	8	15	1000	1	40	15	0	50	50	92
TIS58	TO-92	25	1	4	0.5	5	15	20	2.5	8	15	2 mA	20	50	94
TIS59	TO-92	25	1	4	1	9	15	20	6	25	15	2 mA	20	50	94

T-29-01

JFET Transistors

5