

2 N 6169		50Hz-Thy	=2N6167: 400V	54b	=TO-48			2N6173, MCR 65-6
2 N 6170		50Hz-Thy	=2N6167: 600V	54b	=TO-48			2N6174, MCR 65-8
2 N 6171	Mot	50Hz-Thy	=2N3870	54b	=TO-48			MCR 65-3
2 N 6172		50Hz-Thy	=2N3871	54b	=TO-48			MCR 65-4
2 N 6173		50Hz-Thy	=2N3872	54b	=TO-48			MCR 65-6
2 N 6174		50Hz-Thy	=2N3873	54b	=TO-48			MCR 65-8
2 N 6175	Rca	Si-N	LF,Vid, P, 300/250V, 1A, 20W, >21MHz	14m	=TO-126			(BD 410, BUJ 63, 2SC3051, 2SC3425,++) <sup>5</sup>
2 N 6176	Rca	Si-N	=2N6175: 350/300V	14m	=TO-126			(BD 410, BUJ 63, 2SC3051, 2SC3425,++) <sup>5</sup>
2 N 6177	Rca	Si-N	=2N6175: 450/350V	14m	=TO-126			(BD 410, BUJ 63, 2SC3051, 2SC3425,++) <sup>5</sup>
2 N 6178	Rca	Si-N	P, 100/75V, 2A, 25W, >50MHz, <80/800ns	(2N6180) 14m	=TO-126	(BD 139) <sup>5</sup>	14h	(BD 139, BD 230, BD 379, BD 529,++) <sup>4</sup>
2 N 6179		Si-N	=2N6178: 75/50V	(2N6181) 14m	=TO-126	(BD 139) <sup>5</sup>	14h	(BD 139, BD 230, BD 377, BD 527,++) <sup>4</sup>
2 N 6180	Rca	Si-P	P, 100/75V, 2A, 25W, >50MHz, <80/800ns	(2N6178) 14m	=TO-126	(BD 139) <sup>5</sup>	14h	(BD 140, BD 231, BD 380, BD 530,++) <sup>4</sup>
2 N 6181		Si-P	=2N6182: 75/50V	(2N6179) 14m	=TO-126	(BD 140) <sup>5</sup>	14h	(BD 140, BD 231, BD 378, BD 528,++) <sup>4</sup>
2 N 6182	Sca,Ssi,Stc Tra	Si-P	S P, 80/80V, 10A, 60W, >30MHz, <200/2200ns hFE=30...120	49m (2N5477)	TO-59			(2N5290...91) <sup>6</sup>
2 N 6183		Si-P	=2N6182: hFE=60...240	(2N5478) 49m	TO-59			(2N5290...91) <sup>6</sup>
2 N 6184		Si-P	=2N6182: 100/100V	(2N5479) 49m	TO-59			(2N5290...91) <sup>6</sup>
2 N 6185		Si-P	=2N6182: 100/100V, hFE=60...240	(2N5480) 49m	TO-59			(2N5290...91) <sup>6</sup>
2 N 6186	USA,Mot	Si-P	=2N6182: Iso	(2N5346) 49a	TO-59			(2N5290...91) <sup>6</sup>
2 N 6187		Si-P	=2N6183: Iso	(2N5347) 49a	TO-59			(2N5290...91) <sup>6</sup>
2 N 6188		Si-P	=2N6184: Iso	(2N5348) 49a	TO-59			(2N5290...91) <sup>6</sup>
2 N 6189		Si-P	=2N6185: Iso	(2N5349) 49a	TO-59			(2N5290...91) <sup>6</sup>
2 N 6190	Mot,Sca,Ssi Sol,Stc	Si-P	S, 80/80V, 5A, 10W(Tc=100°), >30MHz, <200/2200ns hFE=30...120	2a (2N5336)	TO-39			BFT 35...37, BUY 90
2 N 6191		Si-P	=2N6190: hFE=60...240	(2N5337) 2a	TO-39			BFT 35...37, BUY 90
2 N 6192		Si-P	=2N6190: 100/100V	(2N5338) 2a	TO-39			BFT 36...37, BUY 90
2 N 6193		Si-P	=2N6190: 100/100V, hFE=60...120	(2N5339) 2a	TO-39			BFT 36...37, BUY 90
2 N 6194	Trw	Si-N	HF P, 50V, 5W	62a				-
2 N 6195	Trw	Si-N	HF P, 50V, 10W	62a				-
2 N 6196	Trw	Si-N	HF P, 50V, 20W	62a				-
2 N 6197	Ctr	Si-N	HF P, 60/35V, 1A, 10W	55r	SOT-120			-
2 N 6198	Ctr	Si-N	HF P, 60/35V, 2.5A, 25W	55r	SOT-120			-
2 N 6199	Ctr	Si-N	HF P, 60/35V, 5A, 50W	55r	SOT-120			-
2 N 6200	Ctr	Si-N	HF P, 60/35V, 8.5A, 85W	55r	SOT-120			-
2 N 6201	Ctr	Si-N	HF P, 60/35V, 12A, 140W	55r	SOT-147			-
2 N 6202	Ctr	Si-N	HF P, 60/33V, 0.5A, 10W	55r	SOT-120			-
2 N 6203	Ctr	Si-N	HF P, 60/33V, 1A, 20W	55r	SOT-120			-
2 N 6204	Ctr	Si-N	HF P, 60/33V, 2A, 40W	55r	SOT-120			-
2 N 6205	Ctr	Si-N	HF P, 60/33V, 4A, 80W	55r	SOT-120			-
2 N 6206	Ctr	Si-N	HF P, 50/30V, 0.5A, 10W	55r	SOT-122			-
2 N 6207	Ctr	Si-N	HF P, 50/30V, 1A, 20W	55r	SOT-122			-
2 N 6208	Ctr	Si-N	HF P, 50/30V, 2A, 40W	55r	SOT-122			-
2 N 6211	Mot,Rca,Stc	Si-P	S P, 275/225V, 2/5A, 35W, >20MHz, -/3,1µs	(2N3583) 22a	TO-66			BUX 66A...C, 2SA1009(A), 2SA1236, 2SA1397
2 N 6212		Si-P	=2N6211: 350/300V	(2N3584) 22a	TO-66			BUX 66B...C, 2SA1009(A), 2SA1236, 2SA1397
2 N 6213		Si-P	=2N6211: 400/350V	(2N3585) 22a	TO-66			BUX 66C, 2SA1009A, 2SA1236, 2SA1397
2 N 6214		Si-P	=2N6211: 450/400V	(2N3585) 22a	TO-66			2N6422...23
2 N 6215	Sol,Ssi,Stc	Si-N	S P, 100/80V, 50A, 125W(Tc=100°), >20MHz, <1/1,25µs	49m	TO-63			2N6060, 2N6278...81
2 N 6216	Ker,Stc	Si-N	S P, 200/150V, 10A, 71W(Tc=100°), >20MHz, <0,8/1µs	23a	TO-3			BUX 17(A...C), BUX 42...43, BUY 18, ++
2 N 6217		Si-N	=2N6216: 180/80V	23a	TO-3			BUX 17(A...C), BUX 42...43, BUY 18, ++
2 N 6218	Gen,Mic,Sem	Si-N	S,Vid, 300/300V, 0,05A, 0,5W, >50MHz, <0,5/5µs	7a	SOT-30			BF 299, BF 420, BF 483, 2SC3468, ++
2 N 6219		Si-N	=2N6218: 250/250V	7a	SOT-30			BF 298...299, BF 420, BF 483, 2SC3468, ++
2 N 6220		Si-N	=2N6218: 200/200V	7a	SOT-30			BF 298...299, BF 422, BF 483, 2SC3468, ++
2 N 6221		Si-N	=2N6218: 150/150V	7a	SOT-30			BF 297...299, BF 422, BF 483, 2SC3468, ++
2 N 6222	Gen,Sem,Spr	Si-N	LF, 60/60V, 0,1A, 0,36, hFE=75...200	(2N6223) 7a	SOT-30			BC 174, BC 182, BC 190, BC 546, ++
2 N 6223	Gen,Sem,Spr	Si-P	LF, 60/60V, 0,1A, 0,36W, hFE=75...200	(2N6222) 7a	SOT-30			BC 212, BC 256, BC 266, BC 556, ++
2 N 6224		Si-N	=2N6222: hFE=150...300	(2N6225) 7a	SOT-30			BC 174, BC 182, BC 190, BC 546, ++
2 N 6225		Si-P	=2N6223: hFE=150...300	(2N6224) 7a	SOT-30			BC 212, BC 256, BC 266, BC 556, ++
2 N 6226	USA,Mot	Si-P	LFS P, 100/100V, 6/10A, 150W, >1MHz	(2N5758) 23a	TO-3			BD 246C, BDV 96, BDX 96, 2N6229...31, ++
2 N 6227		Si-P	=2N6226: 120/120V	(2N5759) 23a	TO-3			BD 246D, 2N6230...31, 2SA1116...17, ++
2 N 6228		Si-P	=2N6226: 140/140V	(2N5760) 23a	TO-3			BD 246D, 2N6231, 2SA1116...17, 2SB555, ++
2 N 6229	USA,Mot	Si-P	LFS P, 100/100V, 10/15A, 150W, >1MHz	(2N5632) 23a	TO-3	BD 318	23a	BD 318, 2N6029...31, 2SA1116...17, ++
2 N 6230		Si-P	=2N6229: 120/120V	(2N5633) 23a	TO-3	MJ 15016	23a	MJ 15016, 2N6030...31, 2SA1116...17, ++
2 N 6231		Si-P	=2N6229: 140/140V	(2N5634) 23a	TO-3	MJ 15016	23a	MJ 15016, 2N6031, 2SA1116...17, 2SB555, ++
2 N 6232	Sca,Stc,Uni	Si-N	P, 140/100V, 10A, 15W(Tc=25°), >30MHz, <250/1200nd	2a	TO-5			BUY 82
2 N 6232-4		Si-N	=2N6232:	2a	TO-5 <sup>o</sup>			(BUY 82)
2 N 6233	Mot,Stc,Uni	Si-N	S P, 250/225V, 5/10A, 50W, >20MHz, -/4µs	22a	TO-66			BUT 56(A), BUX 63, 2SC2907, 2SC3035, ++
2 N 6234		Si-N	=2N6233: 300/275V	22a	TO-66			BUT 56(A), BUX 63, 2SC2907, 2SC3035, ++
2 N 6235		Si-N	=2N6233: 350/325V	22a	TO-66			BUT 56(A), BUX 63, 2SC2907, 2SC3035, ++
2 N 6236	Mot,Tag	50Hz-Thy	30V, 2,6A(Tc=90°), Igt/Ih<0,2/<5mA	14e	TO-126	TIC 106 M <sup>4</sup>	17e	MCR106-1, (C108Y, TAG108Y, S2060V,++) <sup>4</sup>
2 N 6237		50Hz-Thy	=2N6236: 50V	14e	TO-126	TIC 106 M <sup>4</sup>	17e	MCR106-2, (C108F, TAG108F, S2060F,++) <sup>4</sup>
2 N 6238		50Hz-Thy	=2N6236: 100V	14e	TO-126	TIC 106 M <sup>4</sup>	17e	MCR106-3, (C108A, TAG108A, S2060A,++) <sup>4</sup>
2 N 6239		50Hz-Thy	=2N6236: 200V	14e	TO-126	TIC 106 M <sup>4</sup>	17e	MCR106-4, (C108B, TAG108B, S2060B,++) <sup>4</sup>
2 N 6240		50Hz-Thy	=2N6236: 400V	14e	TO-126	TIC 106 M <sup>4</sup>	17e	MCR106-6, (C108D, TAG108D, S2060D,++) <sup>4</sup>
2 N 6241		50Hz-Thy	=2N6236: 600V	14e	TO-126	TIC 106 M <sup>4</sup>	17e	MCR106-8, (C108M, TAG108M, S2060M,++) <sup>4</sup>
2 N 6246	USA,Rca,Tix	Si-P	LFS P, 70/50V, 15A, 125W, >6MHz	(2N6471) 23a	TO-3	BD 318	23a	BD 318, BD 546B, MJ 2955, 2N6029...31, ++
2 N 6247		Si-P	=2N6246: 90/80V	(2N6472) 23a	TO-3	BD 318	23a	BD 318, BD 546C, MJ 2955, 2N6029...31, ++
2 N 6248		Si-P	=2N6246: 110/100V	23a	TO-3	BD 318	23a	BD 318, BD 546D, MJ 2955, 2N6030...31, ++
2 N 6249	USA,Mot,Rca Tho,Tix,Tos	Si-N	S P, 300/200V, 10/30A, 175W, 8MHz, -/2,3µs	23a	TO-3	(S 2530 A)	23a	BUX 17A...C, BUJ 24...25, BUW 72, ++
2 N 6250		Si-N	=2N6249: 375/275V	23a	TO-3	(S 2530 A)	23a	BUX 17B,C, BUW 24...25, BUW 34, BUW 72, ++
2 N 6251		Si-N	=2N6249: 450/350V	23a	TO-3	(S 2530 A)	23a	BUX 17C, BUW 24...25, BUW 34, BUW 72, ++
2 N 6253	USA,Rca,Tix	Si-N	LFS P, 55/45V, 15A, 115W, >0,8MHz	23a	TO-3			BD 315, BD 545A, 2N3055, 2N5881...82, ++
2 N 6254	USA,Rca,Tix	Si-N	LFS P, 100/80V, 15A, 150W, >0,8MHz	23a	TO-3			BD 317, BD 545C, 2N3772, 2N5629...31, ++
2 N 6255	Ker,Mot,Whs	Si-N	VHF Drv,Out, 36/18V, 1A, PQ=3W(175MHz)	2a	TO-39			BFQ 43, BFS 22, BFW 46, 2N3924
2 N 6256	Mot	Si-N	UHF Drv,Out, 36/18V, 0,4A, PQ=0,5W(470MHz)	51r	SOT-122D			BLU 98, MRF 627...628
2 N 6257	USA,Mot,Rca	Si-N	LFS P, 50/40V, 20/30A, 150W, >0,8MHz	23a	TO-3			BD 364, BDX 40...41, 2N3771...72, ++
2 N 6258	USA,Mot,Rca	Si-N	LFS P, 100/80V, 30/30A, 250W, >0,8MHz	23a	TO-3			BDY 29, MJ 802, 2SD797
2 N 6259	USA,Mot,Rca	Si-N	LFS P, 170/150V, 16/30A, 250W, >0,2MHz	23a	TO-3			BDW 14, BDY 56, 2SC2607...08, 2SD753, ++
2 N 6260	USA,Rca	Si-N	LFS P, 50/40V, 3A, 29W, >0,8MHz	22a	TO-66			BD 241, BD 535, BD 935, 2N4231...33, ++
2 N 6261	USA,Rca	Si-N	LFS P, 90/80V, 4A, 50W, >0,8MHz	22a	TO-66			BD 243B, BD 539C, BD 953, 2N3054, ++
2 N 6262	USA,Rca,Tix	Si-N	LFS P, 170/150V, 10/15A, 150W, >0,8MHz	23a	TO-3			BD 745F, BDY 54, 2SC2607...08, 2SD753, ++
2 N 6263	USA,Rca	Si-N	LFS P, 140/120V, 3/4A, 20W, >0,2MHz	22a	TO-66			BD 241D, BD 243D, 2N3441, 2SD608, ++
2 N 6264		Si-N	LFS P, 170/150V, 3/4A, 50W, >0,2MHz	22a	TO-66			BD 241E, BD 243E, 2SD386(A)