

2 N 2172	USA	Ge-P	LFS, 20V, 0,4A, 0,2W, >5MHz	2a	TO-5				AC 128, AC 152...153, ASY 77, 2N1189...90
2 N 2173	Spr	Ge-P	LFS, 25V, 0,75A, 0,24W	2a	TO-39				AC 128, AC 153
2 N 2174	Nsc	Si-P	LFS, 45V, 0,4W, 1MHz						BC 212, BC 257, BC 307, BC 557, ++
2 N 2175	USA	Si-P	Uni. sym, 6/6/6V, 0,05A, 0,1W, >10MHz	2a	TO-5				(BC 213, BC 258, BC 308, BC 558,++)
2 N 2176	USA	Si-P	Uni. sym, 6/6/6V, 0,05A, 0,1W, >10MHz	2a	TO-18				(BC 213, BC 258, BC 308, BC 558,++)
2 N 2177	USA	Si-P	Uni. sym, 6/6/6V, 0,05A, 0,1W, >8MHz	2a	TO-5				(BC 213, BC 258, BC 308, BC 558,++)
2 N 2178	USA	Si-P	Uni. sym, 6/6/6V, 0,05A, 0,1W, >8MHz	2a	TO-18				(BC 213, BC 258, BC 308, BC 558,++)
2 N 2180	Phc	Ge-P	HF/S, 15/6/15V, 0,05A, 0,05W, >60MHz	37d	TO-24				-
2 N 2181	Phc,Ray	Si-P	Chopper, 25/25/25V, 0,05A, 0,15W	2a	TO-1				2N2946
2 N 2182	Phc,Ray	Si-P	=2x 2N2181 Matched Pair	2a	TO-1				2x 2N2946
2 N 2183	Phc,Ray	Si-P	Chopper, 15/10/15V, 0,05A, 0,15W	2a	TO-1				2N2946
2 N 2184	Phc,Ray	Si-P	=2x 2N2183 Matched Pair	2a	TO-1				2x 2N2946
2 N 2185	Sem,Tdy	Si-P	Chopper, 30/30/30V, 0,05A, 0,15W	2a	TO-18				2N2946
2 N 2186	Sem,Tdy	Si-P	=2x 2N2185 Matched Pair	2a	TO-18				2x 2N2946
2 N 2187	Sem,Tdy	Si-P	=2x 2N2185 Matched Pair	2a	TO-18				2x 2N2946
2 N 2188	USA,Tix	Ge-P	HF, 40V, 0,03A, 0,125W, >60MHz	2a	TO-58				AF 124...125, AF 200
2 N 2189	USA,Tix	Ge-P	=2N2188: >102MHz	2a	TO-58				AF 106, AF 109R, AF 306
2 N 2190	USA,Tix	Ge-P	=2N2188: 60V	2a	TO-58				(AF 124...125, AF 200)
2 N 2191	USA,Tix	Ge-P	=2N2188: 60V, >102MHz	2a	TO-58				(AF 106, AF 109R, AF 306)
2 N 2192(A,B)	USA,EUR	Si-N	LFS, 60V, 1A, 0,8W, >50MHz	2a	TO-5	BC 141	2a		BC 140...141, BSW 27...28, 2N3252...53, ++
2 N 2193(A,AS,B)	USA,EUR	Si-N	LFS, 80V, 1A, 0,8W, >50MHz	2a	TO-5	BC 141	2a		BC 140...141, BSW 39, 2N3444
2 N 2194(A,B)	USA,EUR	Si-N	LFS, 60V, 1A, 0,8W, >50MHz	2a	TO-5	BC 141	2a		BC 140...141, BSW 27...28, 2N3252...53, ++
2 N 2195(A,B)	USA,EUR	Si-N	LFS, 45V, 1A, 0,6W, >50MHz	2a	TO-5	BC 141	2a		BC 140...141, BSW 27...28, 2N3252...53, ++
2 N 2196	USA,Tho	Si-N	LFS P, 80V, 1A, 15W, hFE=30...90	43m	=TO-37				(BD 139, BD 230, BD 387, BD 829,++) <sup>4</sup>
2 N 2197	USA,Tho	Si-N	=2N2196: hFE=75...200	43m	=TO-37				(BD 139, BD 230, BD 387, BD 829,++) <sup>4</sup>
2 N 2198	Cen,Etc	Si-N	LF, 80V, 0,2A, 0,6W, >4MHz	2a	TO-5				BC 140...141, BC 300...302, 2N3053, ++
2 N 2199	USA	Ge-P	HF, 15V, 0,1A, 0,075W, >120MHz	2a	TO-9				AFY 18, 2N3323...25
2 N 2200	USA	Ge-P	HF, 15V, 0,1A, 0,075W, >120MHz	2a	TO-9				AFY 18, 2N3323...25
2 N 2201	USA	Si-N	LFS, 120V, 1A, >10MHz	43m	=TO-37				(BD 524, 2SC2690, 2SC3421, 2SD1381...82) <sup>4</sup>
2 N 2202	USA	Si-N	=2N2201:	2a	=TO-5				(BD 524, 2SC2690, 2SC3421, 2SD1381...82) <sup>4</sup>
2 N 2203	USA	Si-N	=2N2201:	5g	=TO-12				(BD 524, 2SC2690, 2SC3421, 2SD1381...82) <sup>4</sup>
2 N 2204	USA	Si-N	=2N2201:						(BD 524, 2SC2690, 2SC3421, 2SD1381...82) <sup>4</sup>
2 N 2205	USA,Sgs	Si-N	S, 25V, 0,2A, 0,3W, 35/60ns, hFE>20	2a	TO-18				BSS 11...12, BSX 19...20, 2N2368...69(A),++
2 N 2206	USA,Mot	Si-N	=2N2205: hFE=40...120	2a	TO-46				BSS 11...12, BSX 19...20, 2N2368...69(A),++
2 N 2207	USA,Phi	Ge-P	HF, 70V, 0,05A, 0,26W, >140MHz	1g	TO-7				(AF 118)
2 N 2208	USA	Ge-P	HF, 30V, 10mA, 0,12W	4e	TO-44				AF 124...126, AF 200
2 N 2209	Cen,Stc	Ge-P	LFS, 30V, 0,1A, 0,15W, >6MHz	2a	TO-5				ASY 26, ASY 76...77
2 N 2210	USA	Ge-P	LFS P, 100V, 15A, 70W	38a	TO-36				2N2493
2 N 2211	Cen,Sty	Ge-P	LFS P, 80V, 5A, 90W	23a	TO-3				AL 102...103, AUY 28, 2N1546...48, ++
2 N 2212	USA,Mot	Ge-P	S P, 120V, 10A, 102W	23a	TO-3				AL 100, AUY 38, 2N2290, 2N2293, 2N2527
2 N 2213	Gen	UJT-P	40/60V, 0,45W, Rbb<9,1kΩ						-
2 N 2214	Trw	Si-N	S, 25V, 0,2A, 0,25W, 200MHz	24b	TO-50				BC 238, BC 548, BSW 41, 2N706A, 2N708,++
2 N 2216	old	Si-P	LFS, 150V, 0,25A, 0,8W, 40MHz	2a	TO-5				2N3636...37, 2N5415, 2SA712
2 N 2217	USA,Mic,Tix	Si-N	Uni, 60/30V, 0,8A, 0,8W, >250MHz, hFE=20...60, <35/285ns	2a	TO-5	(BC 141)	2a		BSW 51...54, BSX 59...61, 2N3444, ++
2 N 2217 A		Si-N	=2N2217: 75/40V	2a	TO-5	(BC 141)	2a		BSW 51...54, BSX 59...61, 2N3444, ++
2 N 2218(A)	USA,EUR,Mic	Si-N	=2N2217: hFE=40...120	2N2904	2a	TO-5	(BC 141)	2a	BSW 51...54, BSX 59...61, 2N3444, ++
2 N 2219(A)	USA,EUR,Mic	Si-N	=2N2217: hFE=100...300	2N2905	2a	TO-5	(BC 141)	2a	BSW 51...54, BSX 59...61, 2N3444, ++
2 N 2220(A)	USA,Mic,Tix	Si-N	=2N2217: 0,5W	2a	TO-18	(BC 639)	7c		BSS 40...41, BSW 61...64, 2N4014, ++
2 N 2221(A)	USA,EUR,Mic	Si-N	=2N2218: 0,5W	2N2906	2a	TO-18	(BC 639)	7c	BSS 40...41, BSW 61...64, 2N4014, ++
2 N 2222(A)	USA,EUR,Mic	Si-N	=2N2219: 0,5W	2N2907	2a	TO-18	(BC 639)	7c	BSS 40...41, BSW 61...64, 2N4014, ++
2 N 2223	USA,Fer,Gen	Si-N	Dual, 100/60V, 0,5A, 0,6W, >50MHz, ΔUbe<15mV		TO-77	(CBE-EBC-)			BFX 70...72, 2N2060
2 N 2223 A	Mot,Sgs,Tix								
2 N 2224	USA,Mot	Si-N	=2N2223: ΔUbe<5mV		TO-77	(CBE-EBC-)			BFX 70...72, 2N2060
2 N 2224	USA,Mot	Si-N	S, 65V, 0,5A, 0,8W, >250MHz	2a	TO-5	BC 141	2a		BC 140...141, BC 300...302, 2N2218...19A,++
2 N 2225	Cen,Stc	Ge-P	S, 15V, 0,4A, 0,2W, <100/200ns	2a	TO-5				-
2 N 2226	USA,Whs	Si-N	S P, 50V, 10A, 150W, hFE=100...500		TO-82				-
2 N 2227	USA,Whs	Si-N	=2N2226: 100V		TO-82				-
2 N 2228	USA,Whs	Si-N	=2N2226: 150V		TO-82				-
2 N 2229	USA,Whs	Si-N	=2N2226: 200V		TO-82				-
2 N 2230	USA,Whs	Si-N	S P, 50V, 10A, 150W, hFE>350		TO-82				-
2 N 2231	USA,Whs	Si-N	=2N2230: 100V		TO-82				-
2 N 2232	USA,Whs	Si-N	=2N2230: 150V		TO-82				-
2 N 2233	USA,Whs	Si-N	=2N2230: 200V		TO-82				-
2 N 2234	Itt,Sty	Si-N	LFS P, 40V, 0,5A, 10W(Tc=50°), >50MHz	23a	TO-3				-
2 N 2235	Itt,Sty	Si-N	=2N2234: >100MHz	23a	TO-3				-
2 N 2236	USA	Si-N	LFS, 40V, 0,5A, 0,6W, >50MHz	2a	TO-5				BC 140...141, BC 300...302, 2N2218...19, ++
2 N 2237	USA	Si-N	=2N2236: >100MHz	2a	TO-5				BC 140...141, BC 300...302, 2N2218...19, ++
2 N 2238	Cen	Ge-P	HF, 30V, 0,05A, 0,3W, >400MHz	2a	TO-5				AF 139, AF 239(S), 2N3283...86
2 N 2239	Sca,Ssi	Si-N	LF Drv,Out, 60V, 0,5A, 2,5MHz	43m	TO-37				(BD 137, BD 167, BD 517, BD 827,++) <sup>4</sup>
2 N 2240	USA	Si-N	LFS, 25V, 0,5A, 0,6W, >50MHz, hFE=40...120	2a	TO-5				BC 140...141, BC 300...302, 2N3053, ++
2 N 2241	USA	Si-N	=2N2240: hFE=100...300	2a	TO-5				BC 140...141, BC 300...302, 2N3053, ++
2 N 2242	USA,Fch,Mot	Si-N	S, 40V, 0,225A, 0,36W, <30/50ns	2a	TO-18				BSS 10...11, BSX 19...20, 2N2368...69(A),++
2 N 2243(A)	USA,Mic,Tix	Si-N	LFS, 120V, 1A, 0,8W, >50MHz	2a	TO-39				BC 300, 2N1893(A), 2N2102, 2N2405, ++
2 N 2244	Nsc,Sty	Si-N	Uni, 20V, 0,1A, 0,5W, >60MHz, hFE=5...15	2a	TO-18				BC 168, BC 183, BC 238, BC 548, ++
2 N 2245	Nsc,Sty	Si-N	=2N2244: hFE=10...30	2a	TO-18				BC 168, BC 183, BC 238, BC 548, ++
2 N 2246	Nsc,Sty	Si-N	=2N2244: hFE=20...60	2a	TO-18				BC 168, BC 183, BC 238, BC 548, ++
2 N 2247	Nsc,Sty	Si-N	Uni, 45V, 0,1A, 0,5W, >60MHz, hFE=5...15	2a	TO-18				BC 167, BC 182, BC 237, BC 547, ++
2 N 2248	Nsc,Sty	Si-N	=2N2247: hFE=10...30	2a	TO-18				BC 167, BC 182, BC 237, BC 547, ++
2 N 2249	Nsc,Sty	Si-N	=2N2247: hFE=20...60	2a	TO-18				BC 167, BC 182, BC 237, BC 547, ++
2 N 2250	Nsc,Sty	Si-N	Uni, 25V, 0,1A, 0,5W, >60MHz, hFE=5...15	2a	TO-18				BC 168, BC 183, BC 238, BC 548, ++
2 N 2251	Nsc,Sty	Si-N	=2N2250: hFE=10...30	2a	TO-18				BC 168, BC 183, BC 238, BC 548, ++
2 N 2252	Nsc,Sty	Si-N	=2N2250: hFE=20...60	2a	TO-18				BC 168, BC 183, BC 238, BC 548, ++
2 N 2253	Nsc,Sty	Si-N	Uni, 50V, 0,1A, 0,5W, >60MHz, hFE=5...15	2a	TO-18				BC 167, BC 182, BC 237, BC 547, ++
2 N 2254	Nsc,Sty	Si-N	=2N2253: hFE=10...30	2a	TO-18				BC 167, BC 182, BC 237, BC 547, ++
2 N 2255	Nsc,Sty	Si-N	=2N2253: hFE=20...60	2a	TO-18				BC 167, BC 182, BC 237, BC 547, ++
2 N 2256	USA,Mot	Si-N	SS, 7V, 0,1A, 0,3W, <77ns, hFE>20	2a	TO-18				-
2 N 2257	USA,Mot	Si-N	=2N2256: hFE>40	2a	TO-18				-
2 N 2258	USA,Mot	Ge-P	SS, 7V, 0,1A, 0,15W, <77ns, hFE>20	2a	TO-18				-
2 N 2259	USA,Mot	Ge-P	=2N2258: hFE>40	2a	TO-18				-
2 N 2260	GTO-Thy		30V, 0,2A, Igt<0,25mA						-
2 N 2261	GTO-Thy		=2N2260: Igt<0,5mA						-
2 N 2262	GTO-Thy		=2N2260: Igt<5mA						-