

2 N 5726		50Hz-Thy	=2N5721: 0.39A(Tc=90°)	2a	TO-5			(2N2326A) ⁶
2 N 5727		50Hz-Thy	=2N5722: 0.39A(Tc=90°)	2a	TO-5			(2N2328A) ⁶
2 N 5728		50Hz-Thy	=2N5723: 0.39A(Tc=90°)	2a	TO-5			(2N2329A) ⁶
2 N 5729	Sol,Ssi,Stc	Si-N	S P, 100/80V, 5A, 11.7W(Tc=25°), >30MHz, <0.2/3,5µs	2a	TO-5			2N4895...97, 2N5338...39, BUX 34, BUY 80
2 N 5730		Si-N	=2N5729: 10A, 45W	49a	TO-59			(2N5288...89) ⁶
2 N 5731	Sol,Ssi,Stc	Si-N	S P, 100/80V, 20A, 75W, >30MHz, <0.3/3,6µs	49a	TO-61			-
2 N 5732		Si-N	=2N5731: 20A, 87.5W	23a	TO-3			(BDX 40, BDY 57, 2N3772) ⁸
2 N 5733	Sol,Ssi,Stc	Si-N	S P, 100/80V, 30A, 150W, >30MHz, <0.7/4µs	49a	TO-63			-
2 N 5734		Si-N	=2N5733: 125W	23a	TO-3			(BDY 29, MJ 802, 2SD797) ⁸
2 N 5735	Amp	Si-N	Min, 60/30V, 0.3A, 0.36W, >200MHz, hFE=40...120		TO-122			-
2 N 5736		Si-N	=2N5735: hFE=100...300		TO-122			-
2 N 5737	USA	Si-P	LFS P, 60/60V, 10A, 50W(Tc=100°), >10MHz	23a	TO-3			BD 312, BD 546A, BDW 22A, 2N5875...76, ++
2 N 5738		Si-P	=2N5737: 100/100V	23a	TO-3			BD 318, BD 546C, BDW 22C, 2N6229...31, ++
2 N 5739		Si-P	=2N5737: 20W(Tc=100°)	22a	TO-66			BD 708, BD 744A, BD 808, BDT 82, ++
2 N 5740		Si-P	=2N5737: 100/100V, 20W(Tc=100°)	22a	TO-66			BD 712, BD 744C, BDT 86, ++
2 N 5741	USA	Si-P	LFS P, 60/60V, 20A, 65W(Tc=100°), >10MHz	23a	TO-3			BD 250A, BD 367, BD 746A, 2N5883...84, ++
2 N 5742		Si-P	=2N5741: 100/100V	23a	TO-3			BD 250C, BD 746C, MJ 4502
2 N 5743		Si-P	=2N5741: 25W(Tc=100°)	22a	TO-66			-
2 N 5744		Si-P	=2N5741: 100/100V, 25W(Tc=100°)	22a	TO-66			-
2 N 5745	USA Mot,Sgs	Si-P	LFS P, 80/80V, 20/50A, 200W, >2MHz, <1/3µs	23a	TO-3			BD 369,MJ 4502, 2N5884
2 N 5754	Rca,Tag	Triac	=T 2303A	2m	TO-5			·T 2303A
2 N 5755		Triac	=T 2303B	2m	TO-5			·T 2303B
2 N 5756		Triac	=T 2303D	2m	TO-5			·T 2303D
2 N 5757		Triac	=T 2303M	2m	TO-5			·T 2303M
2 N 5758	USA Mot,Tix	Si-N	LFS P, 100/100V, 6/10A, 150W, >1MHz	[2N6226]	23a	TO-3		BD 245C, BDV 95, BDX 95, 2N5632...33, ++
2 N 5759		Si-N	=2N5758: 120/120V	[2N6227]	23a	TO-3		BD 245D, 2N4348, 2N5634, 2SC2607...08, ++
2 N 5760		Si-N	=2N5758: 140/140V	[2N6228]	23a	TO-3		BD 245D, 2N4348, 2N5634, 2SC2607...08, ++
2 N 5761	Nip	Si-N	UHF, 20/15V, 0.03A, 0.25W, >3.7GHz	51s				BFQ 60, BFQ 71, 2SC1119, 2SC1336, ++
2 N 5762	Nip	Si-N	UHF, 20/15V, 0.04A, 0.3W, >3.3GHz	51s				BFQ 60, BFQ 71, 2SC1119, 2SC1336, ++
2 N 5763	Mot	Si-P	S, RadH, 65/60V, 0.6A, 0.4W, <50/250ns	2a	TO-18			-
2 N 5764	Trw	Si-N	HF Drv,Out, 55/25V, 0.75A, 10W	55r				-
2 N 5765	Trw	Si-N	HF P, 55/25V, 1.5A, 19W	55r				-
2 N 5766	Trw	Si-N	HF Drv,Out, 55/25V, 0.2A, 5W	55r				-
2 N 5767	Trw	Si-N	HF Drv,Out, 55/25V, 0.35A, 10W	55r				-
2 N 5768	Trw	Si-N	HF Drv,Out, 55/25V, 0.7A, 20W	55r				-
2 N 5769	USA Mic,Nsc	Si-N	S, 40/15V, 0.2A, 0.625W, >500MHz, <12/18ns	7e	TO-92			BSS 10...11, BSX 19...20, 2N2368...69(A), ++
2 N 5770	USA,Nsc	Si-N	UHF, 30/15V, 0.05A, 0.7W, >900MHz	7e	TO-92	2SC2570 A	7f	BF 377...378, BF 689, BF 763, 2N2857, ++
2 N 5771	USA Mot,Nsc	Si-P	S, 15/15V, 0.05A, 0.625W, >850MHz, <15/20ns	7e	TO-92			BSX 62...64, 2N4238...39, 2SC2214, ++
2 N 5772	USA,Min,Nsc	Si-N	S, 40/15V, 0.2A, 0.625W, >350MHz, <25/35ns	7e	TO-92			BSS 10...11, BSX 19...20, 2N2368...69(A), ++
2 N 5773	Trw	Si-N	HF Drv,Out, 65/35V, 0.5A, 5W	55r	TO-117			-
2 N 5774	Trw	Si-N	HF P, 65/35V, 1.5A, 18W	55r	TO-129			-
2 N 5775	Trw	Si-N	HF P, 65/35V, 3A, 40W	60c				-
2 N 5776	Trw	Si-N	HF P, 65/35V, 6A, 70W	60c				-
2 N 5777...5780		Opto						
2 N 5781	USA,Rca	Si-P	LFS, 80/65V, 3.5A, 1W, >8MHz, <500/2500ns	[2N5784]	2a	TO-5		2N4236, 2N6303
2 N 5782		Si-P	=2N5781: 65/50V	[2N5785]	2a	TO-5		2N3720, 2N3868, 2N4235...36, 2N6303
2 N 5783		Si-P	=2N5781: 45/40V	[2N5786]	2a	TO-5		2N3720, 2N3868, 2N4235...36, 2N6303
2 N 5784	USA,Rca	Si-N	LFS, 80/65V, 3.5A, 1W, >1MHz, <5/15µs	2a	TO-5			BSX 63...64, 2N4238...39, 2SC2214, ++
2 N 5785		Si-N	=2N5784: 65/50V	2a	TO-5			BSX 62...64, 2N4238...39, 2SC2214, ++
2 N 5786		Si-N	=2N5784: 45/40V	2a	TO-5			BSX 62...64, 2N4237...39, 2SC2214, ++
2 N 5787	Fch,Mot	50Hz-Thy	30V, 0.24A, Igt/Ih<0.35/<10mA	8a	TO-106	(TAG 103 X)	2a	(2N2323, 2N6332, TAG 615-100, TIC 44,)+4
2 N 5788		50Hz-Thy	=2N5787: 60V	8a	TO-106	(BRX 49)	7a	(2N2324, 2N6334, TAG 615-100, TIC 46,)+4
2 N 5789		50Hz-Thy	=2N5787: 100V	8a	TO-106	(BRX 49)	7a	(2N2324, 2N6334, TAG 615-100, TIC 46,)+4
2 N 5790		50Hz-Thy	=2N5787: 200V	8a	TO-106	(BRX 49)	7a	(2N2326, 2N6335, TAG 615-200, TIC 47,)+4
2 N 5791		50Hz-Thy	=2N5787: 300V	8a	TO-106	(BRX 49)	7a	(2N2328, 2N6336, TAG 615-300, TAG 06C,)+4
2 N 5792		50Hz-Thy	=2N5787: 400V	8a	TO-106	(BRX 49)	7a	(2N2329, 2N6337, TAG 615-400, TAG 06D,)+4
2 N 5793	Mot,Ray,Sca	Si-N	Dual, S, 75/40V, 0.6A, 0.6W, >250MHz, <45/310ns hFE=40...120	TO-99	(CBE-EBC-)			2N3409...11, 2N3728...29
2 N 5794		Si-N	=2N5793: hFE=100...300	TO-77	(CBE-EBC-)			2N3409...11, 2N3728...29
2 N 5795	Mot,Ray,Sca	Si-P	Dual, S, 60/60V, 0.6A, 0.6W, >200MHz, <47/140ns hFE=40...120	TO-77	(CBE-EBC-)			BFX 11, 2N4015...16
2 N 5796		Si-P	=2N5795: hFE=100...300	TO-77	(CBE-EBC-)			BFX 11, 2N4015...16
2 N 5797	Mot	P-FET	LF, sym, 40V, Idss>0.02mA, Up<4V	7c	TO-92			2N2606
2 N 5798	Mot	P-FET	LF, sym, 40V, Idss>0.08mA, Up<6V	7c	TO-92			-
2 N 5799	Mot	P-FET	LF, sym, 40V, Idss>0.25mA, Up<8V	7c	TO-92			-
2 N 5800	Mot	P-FET	LF, sym, 40V, Idss>0.7mA, Up<9V	7c	TO-92			-
2 N 5801	Mot	N-FET	Uni, In, 40V, Idss>2mA, Up<4V	2b	TO-18			2N5360, 2N5246, 2SK107
2 N 5802	Mot	N-FET	Uni, In, 40V, Idss>10mA, Up<6V	2b	TO-18			BF 256C, BF 348, BFT 10, 2N5397, 2N5486
2 N 5803	Mot	N-FET	Uni, In, 40V, Idss>30mA, Up<8V	2b	TO-18			BFT 10C, 2SK125
2 N 5804	USA,Rca	Si-N	S P, 300/225, 5/15A, 110W, >15MHz, <0.5/5,5µs	23a	TO-3			BUW 71, BUX 16A...C, BUX 18(A...C), ++
2 N 5805		Si-N	=2N5804: 375/300V	23a	TO-3			BUW 71, BUX 16B...C, BUX 18B...C, ++
2 N 5806	Rca	Triac	200V, 25A=(Tc=80°), Igt/Ih<150/<75mA	21l	=TO-48			BTX 94/200
2 N 5807		Triac	=2N5806: 400V	21l	=TO-48			BTX 94/400
2 N 5808		Triac	=2N5806: 500V	21l	=TO-48			BTX 94/500
2 N 5809		Triac	=2N5806: 600V	21l	=TO-48			BTX 94/600
2 N 5810	Gen,Mic,Sem	Si-N	LF Drv, 35/25V, 0.75/1A, 0.5W, >100MHz, hFE=60...200	7a	SOT-30			BC 337...338, BC 635, BC 637, BC 639, ++
2 N 5811	Gen,Mic,Sem	Si-P	LF Drv, 35/25V, 0.75/1A, 0.5W, >100MHz, hFE=60...200	[2N5811]	7a	SOT-30		BC 327...328, BC 636, BC 638, BC 640, ++
2 N 5812		Si-N	=2N5810: >135MHz, hFE=150...500	[2N5810]				
2 N 5813		Si-P	=2N5811: >135MHz, hFE=150...500	[2N5812]	7a	SOT-30		BC 337...338, BC 635, BC 637, BC 639, ++
2 N 5814		Si-N	=2N5810: 50/40V	[2N5815]	7a	SOT-30		BC 337, BC 635, BC 637, BC 639, ++
2 N 5815		Si-P	=2N5811: 50/40V	[2N5814]	7a	SOT-30		BC 327, BC 636, BC 638, BC 640, ++
2 N 5816		Si-N	=2N5810: 50/40V, >120MHz, hFE=100...200	[2N5817]	7a	SOT-30		BC 337, BC 635, BC 637, BC 639, ++
2 N 5817		Si-P	=2N5811: 50/40V, >120MHz, hFE=100...200	[2N5816]	7a	SOT-30		BC 327, BC 636, BC 638, BC 640, ++
2 N 5818		Si-N	=2N5810: 50/40V, >135MHz, hFE=150...300	[2N5819]	7a	SOT-30		BC 337, BC 635, BC 637, BC 639, ++
2 N 5819		Si-P	=2N5811: 50/40V, >135MHz, hFE=150...300	[2N5818]	7a	SOT-30		BC 327, BC 636, BC 638, BC 640, ++
2 N 5820		Si-N	=2N5810: 70/60V	[2N5821]	7a	SOT-30		BC 639, 2SD667, 2SD1226, 2SD1768, ++
2 N 5821		Si-P	=2N5811: 70/60V	[2N5820]	7a	SOT-30		BC 640, 2B647, 2SB910, 2SB1041, ++
2 N 5822		Si-N	=2N5810: 70/60V, >120MHz, hFE=100...200	[2N5823]	7a	SOT-30		BC 639, 2SD667, 2SD1226, 2SD1768, ++
2 N 5823		Si-P	=2N5811: 70/60V, >120MHz, hFE=100...200	[2N5822]	7a	SOT-30		BC 640, 2B647, 2SB910, 2SB1041, ++
2 N 5824	USA,Gen,Mic	Si-N	Uni, 50/40V, 0.1A, 0.36W, >90MHz, hFE=60...120	7a	SOT-30			BC 167, BC 182, BC 237, BC 547, ++
2 N 5825		Si-N	=2N5824: hFE=100...200	7a	SOT-30			BC 167, BC 182, BC 237, BC 547, ++