

TYPE NO	CONSTRUCTION	PACKAGE & PINOUT	V <sub>DS</sub>	I <sub>D</sub>	T <sub>J</sub>	P <sub>TOT</sub>	V <sub>GS(OFF)</sub> OR V <sub>GS(TH)</sub>	I <sub>SS</sub> OR I <sub>D(OFF)</sub>	C <sub>IS</sub>	R <sub>DS(ON)</sub>	C <sub>ISS</sub>	C <sub>RSS</sub>	USE	MNF	SUBSTITUTE	
			MAX	MAX	MAX		MAX	MAX		MAX	MAX	MAX				MAX
2N5361CHP	NJD	CHIP	40V	18mA	200C		1.6/5V	2.5/5mA	1.5/4.5mS			6P0	2P0	RLG	SLX	
2N5362	NJD	TO72	Bk	40V	18mA	175C		2/7V	2/5mS			6P0	2P0	ALN	SLX	BFW11
2N5362CHP	NJD	CHIP	-	40V	18mA	200C		2/7V	2/5.5mS			6P0	2P0	RLG	SLX	
2N5363	NJD	TO72	Bk	40V	18mA	175C		2.5/8V	7/14mA			6P0	2P0	ALN	SLX	BC264D
2N5363CHP	NJD	CHIP	-	40V	18mA	200C		2.5/8V	7/14mA			6P0	2P0	RLG	SLX	2N4303
2N5364	NJD	TO72	Bk	40V	18mA	175C		2.5/8V	9/18mA			6P0	2P0	ALN	SLX	BFW10
2N5364CHP	NJD	CHIP	-	40V	18mA	200C		2.5/8V	9/18mA			6P0	2P0	RLG	SLX	2N5245
2N5391	NJD	TO18	E	70V	2mA	200C	300mWF	0.5/2V	1.5mAmx	1.5/4.5mS		18P	5P0	ALN	TEL	BF800
2N5392	NJD	TO18	E	70V	3mA	200C	300mWF	0.5/2.5V	1/3mA	2/6mS		18P	5P0	ALN	TEL	BF808
2N5393	NJD	TO18	E	70V	5mA	200C	300mWF	1/3V	2.5/5mA	3/6.5mS		18P	5P0	ALN	TEL	BFW56
2N5394	NJD	TO18	E	70V	6mA	200C	300mWF	1/4V	4/6mA	4/7.5mS		18P	5P0	ALN	TEL	BF810
2N5395	NJD	TO18	E	70V	8mA	200C	300mWF	1.5/4V	5.5/8mA	4.5/7.5mS		18P	5P0	ALN	TEL	BF805
2N5396	NJD	TO18	E	70V	-	200C	300mWF	2/5V	7.5/10mA	4.5/7.5mS		18P	5P0	ALN	TEL	BF805
2N5397	NJD	TO72	Ek	25V	30mA	200C	300mWF	1/6V	10/30mA	6/10mS		5P0	1P2	TUG	INS	BF256C
2N5397/D	NJD	CHIP	-	25V	30mA	200C	300mWF	1/6V	10/30mA	6/10mS		5P0	1P2	TUG	INS	BF256C
2N5397/W	NJD	SLICE	-	25V	30mA	200C	300mWF	1/6V	10/30mA	6/10mS		5P0	1P2	TUG	INS	BF256C
2N5397CHP	NJD	CHIP	-	25V	40mA	200C		1/6V	10/30mA	6/10mS		5P0	1P2	ULG	SLX	
2N5397T092	NJD	TO92	D	25V	30mA	125C	300mWF	1/6V	10/30mA	6/10mS		5P0	1P2	TUG	INS	BF256C
2N5398	NJD	TO72	Ek	25V	40mA	200C	300mWF	1/6V	5/40mA	5.5/10mS		5P5	1P3	TUG	INS	BF256C
2N5398/D	NJD	CHIP	-	25V	40mA	-	300mWF	1/6V	5/40mA	5.5/10mS		5P5	1P3	TUG	INS	BF256B
2N5398/W	NJD	SLICE	-	25V	40mA	200C	300mWF	1/6V	5/40mA	5.5/10mS		5P5	1P3	TUG	INS	BF256B
2N5398T092	NJD	TO92	D	25V	40mA	125C	300mWF	1/6V	5/40mA	5.5/10mS		5P5	1P3	TUG	SLX	BF256B
2N5432	NJD	TO18	E	25V	400mA	200C	300mWF	4/10V	150mAmn		5R0	30P	15P	RMS	SLX	
2N5432/D	NJD	CHIP	-	25V	400mA	200C	300mWF	4/10V	150mAmn		5R0	30P	15P	RMS	INS	
2N5432/W	NJD	SLICE	-	25V	400mA	200C	300mWF	4/10V	150mAmn		5R0	30P	15P	RMS	INS	
2N5432CHP	NJD	CHIP	-	25V	500mA	200C		4/10V	150mAmn		5R0	30P	15P	RMS	SLX	
2N5432T092	NJD	TO92	D	25V	400mA	125C	300mWF	4/10V	150mAmn		5R0	30P	15P	RMS	INS	
2N5433	NJD	TO18	E	25V	400mA	200C	300mWF	3/9V	100mAmn		7R0	30P	15P	RMS	SLX	
2N5433/D	NJD	CHIP	-	25V	400mA	200C	300mWF	3/9V	100mAmn		7R0	30P	15P	RMS	INS	
2N5433/W	NJD	SLICE	-	25V	400mA	200C	300mWF	3/9V	100mAmn		7R0	30P	15P	RMS	INS	
2N5433CHP	NJD	CHIP	-	25V	500mA	200C		3/9V	100mAmn		7R0	30P	15P	RMS	SLX	
2N5433T092	NJD	TO92	D	25V	400mA	125C	300mWF	3/9V	100mAmn		7R0	30P	15P	RMS	INS	
2N5434	NJD	TO18	E	25V	400mA	200C	300mWF	1/4V	30mAmn		10R	30P	15P	RMS	SLX	
2N5434/D	NJD	CHIP	-	25V	400mA	200C	300mWF	1/4V	30mAmn		10R	30P	15P	RMS	INS	
2N5434/W	NJD	SLICE	-	25V	400mA	200C	300mWF	1/4V	30mAmn		10R	30P	15P	RMS	INS	
2N5434CHP	NJD	CHIP	-	25V	500mA	200C		1/4V	30mAmn		10R	30P	15P	RMS	SLX	
2N5434T092	NJD	TO92	D	25V	400mA	125C	300mWF	1/4V	30mAmn		10R	30P	15P	RMS	INS	
2N5452	NJD	TO71	EnE	50V	5mA	150C	500mWF	1/4.5V	0.5/5mA	1/3mS		4P0	1P2	DUA	SLX	BF010
2N5452X2	NJD	TO71	EnE	50V	5mA	150C	500mWF	1/4.5V	0.5/5mA	1/3mS		4P0	1P2	DUA	INS	BF010
2N5453	NJD	TO71	EnE	50V	5mA	150C	500mWF	1/4.5V	0.5/5mA	1/3mS		4P0	1P2	DUA	SLX	BF010
2N5453X2	NJD	TO71	EnE	50V	5mA	150C	500mWF	1/4.5V	0.5/5mA	1/3mS		4P0	1P2	DUA	INS	BF010
2N5454	NJD	TO71	EnE	50V	5mA	150C	500mWF	1/4.5V	0.5/5mA	1/3mS		4P0	1P2	DUA	INS	BF010
2N5454X2	NJD	TO71	EnE	50V	5mA	150C	500mWF	1/4.5V	0.5/5mA	1/3mS		4P0	1P2	DUA	INS	BF010
2N5457	NJD	TO92	C	25V	16mA	135C	310mWF	0.5/6V	1/5mA	1/5mS		7P0	3P0	ALG	SLX	BFW12
2N5458	NJD	TO92	C	25V	16mA	135C	310mWF	1/7V	2/9mA	1.5/5.5mS		7P0	3P0	ALG	SLX	BFW61
2N5459	NJD	TO92	C	25V	16mA	135C	310mWF	2/8V	4/16mA	2/6mS		7P0	3P0	ALG	SLX	BC264C
2N5460	PJD	TO92	D	40V	16mA	135C	310mWF	0.75/6V	1/5mA	1/4mS		7P0	2P0	ALN	INS	BF320A
2N5460/D	PJD	CHIP	-	40V	16mA	135C	310mWF	0.75/6V	1/5mA	1/4mS		7P0	2P0	ALN	INS	BF320A
2N5460/W	PJD	SLICE	-	40V	16mA	135C	310mWF	0.75/6V	1/5mA	1/4mS		7P0	2P0	ALN	INS	BF320A
2N5461	P.D	TO92	D	40V	16mA	135C	310mWF	1/7.5V	2/9mA	1.5/5mS		7P0	2P0	ALN	INS	BF320B
2N5461/D	PJD	CHIP	-	40V	16mA	135C	310mWF	1/7.5V	2/9mA	1.5/5mS		7P0	2P0	ALN	INS	BF320B
2N5461/W	PJD	SLICE	-	40V	16mA	135C	310mWF	1/7.5V	2/9mA	1.5/5mS		7P0	2P0	ALN	INS	BF320B
2N5462	PJD	TO92	D	40V	16mA	135C	310mWF	1.8/9V	4/16mA	2/6mS		7P0	2P0	ALN	INS	BF320B
2N5462/D	PJD	CHIP	-	40V	16mA	135C	310mWF	1.8/9V	4/16mA	2/6mS		7P0	2P0	ALN	INS	BF320B
2N5462/W	PJD	SLICE	-	40V	16mA	135C	310mWF	1.8/9V	4/16mA	2/6mS		7P0	2P0	ALN	INS	BF320B
2N5463	PJD	TO92	D	60V	16mA	135C	310mWF	0.75/6V	1/5mA	1/4mS		7P0	2P0	ALN	INS	BF320A
2N5463/D	PJD	CHIP	-	60V	16mA	135C	310mWF	0.75/6V	1/5mA	1/4mS		7P0	2P0	ALN	INS	BF320A
2N5463/W	PJD	SLICE	-	60V	16mA	135C	310mWF	0.75/6V	1/5mA	1/4mS		7P0	2P0	ALN	INS	BF320A
2N5464	PJD	TO92	D	60V	16mA	135C	310mWF	1/7.5V	2/9mA	1.5/5mS		7P0	2P0	ALN	INS	BF320B
2N5464/D	PJD	CHIP	-	60V	16mA	135C	310mWF	1/7.5V	2/9mA	1.5/5mS		7P0	2P0	ALN	INS	BF320B
2N5464/W	PJD	SLICE	-	60V	16mA	135C	310mWF	1/7.5V	2/9mA	1.5/5mS		7P0	2P0	ALN	INS	BF320B
2N5465	PJD	TO92	D	60V	16mA	135C	310mWF	1.8/9V	4/16mA	2/6mS		7P0	2P0	ALN	INS	BF320B
2N5465/D	PJD	CHIP	-	60V	16mA	135C	310mWF	1.8/9V	4/16mA	2/6mS		7P0	2P0	ALN	INS	BF320B
2N5465/W	PJD	SLICE	-	60V	16mA	135C	310mWF	1.8/9V	4/16mA	2/6mS		7P0	2P0	ALN	INS	BF320B
2N5471	PJD	TO72	Fk	40V	2mA	175C	300mWF	0.5/4V	60µAmx	60/180µS		5P0	1P0	ALG	MOT	
2N5472	PJD	TO72	Fk	40V	2mA	175C	300mWF	0.7/4V	120µAmx	80/220µS		5P0	1P0	ALG	MOT	2N2606
2N5473	PJD	TO72	Fk	40V	2mA	175C	300mWF	0.9/6V	100/250µA	120/300µS		5P0	1P0	ALG	MOT	2N2606
2N5474	PJD	TO72	Fk	40V	2mA	175C	300mWF	1.2/7V	200/500µA	160/400µS		5P0	1P0	ALG	MOT	2N2606
2N5475	PJD	TO72	Fk	40V	2mA	175C	300mWF	1.5/8V	0.4/1mA	200/500µS		5P0	1P0	ALG	MOT	2N2843
2N5476	PJD	TO72	Fk	40V	2mA	175C	300mWF	2/9V	0.8/2mA	260/650µS		5P0	1P0	ALG	MOT	2N2844
2N5484	NJD	TO92	C	25V	5mA	150C	310mWF	0.3/3V	1/5mA	2.5mS		5P0	1P2	FVG	SLX	BF256A
2N5485	NJD	TO92	C	25V	30mA	150C	310mWF	0.5/4V	4/10mA	3.5/7mS		5P0	1P0	TUG	SLX	BF256B
2N5486	NJD	TO92	C	25V	30mA	150C	310mWF	2/6V	8/20mA	4/8mS		5P0	1P0	TUG	SLX	BF256C
2N5505	PJD	TO71	EnE	30V	7mA	150C	250mWF	4Vmx	7mA	1/3.5mS		16P	-	DUA	TEL	2N5247
2N5505X2	PJD	TO71	EnE	30V	7mA	150C	250mWF	4Vmx	7mA	1/3.5mS		16P	-	DUA	TEL	2N5510