

Transistor Type No.	N P S	G /	Manufacturer	Lead Ident	Out-line	Maximum (V)			Maximum		Max. T.(°C)	Frequency Resp.(MHz)	Leakage		Gain	
						V _{CB}	V _{CE'}	V _{EB}	I _C	Power			I _{CS0 @ V_{CS}}	h _{FE} @ I _C		
2N3429	N	S	WHE	560	560A	50	25.0	7.500A	150.000W	175J	.250G		20	5.000A		
2N3430	N	S	WHE	560	560A	100	25.0	7.500A	150.000W	175J	.250G		20	5.000A		
2N3431	N	S	WHE	560	560A	150	25.0	7.500A	150.000W	175J	.250G		20	5.000A		
2N3432	N	S	WHE	560	560A	200	25.0	7.500A	150.000W	175J	.250G		20	5.000A		
2N3433	N	S	WHE	560	560A	250	25.0	7.500A	150.000W	175J	.250G		20	5.000A		
2N3439	N	S	RCA	211	TO 5	450	350	7.0	1.000A	1.000W	200J	8.000G	200A	300V	80	.020A
2N3440	N	S	RCA	211	TO 5	300	250	7.0	1.000A	1.000W	200J	8.000G	500A	200V	80	.020A
2N3441	N	S	STC RCA	605	TO 66	160	140	7.0	3.000A	25.000W	200J	150.000G	5MA	140V	40	.500A
2N3442	N	S	RCA	605	TO 3	160	140	7.0	10.000A	117.000W	200J	AUD	1MA	140V	38	2.000A
2N3444	N	S	TI I FSC ITT	211	TO 5	80	50	5.0	1.000A	1.000W	200J	150.000G	500NA	60V	34	.500A
2N3445	N	S	MOT	605	TO 3	80	60	6.0	7.500A	115.000W	200J	10.000G	1000A	60V	40	3.000A
2N3446	N	S	MOT	605	TO 3	100	80	10.0	7.500A	115.000W	200J	10.000G	1000A	80V	40	3.000A
2N3447	N	S	MOT	605	TO 3	80	60	6.0	7.500A	115.000W	200J	10.000G	1000A	60V	75	5.000A
2N3448	N	S	MOT	605	TO 3	100	80	10.0	7.500A	115.000W	200J	10.000G	1000A	80V	75	5.000A
2N3467	N	S	RAY MOT FSC	211	TO 5	40	40	5.0	1.000A	1.000W	200J	175.000G	100NA	30V	70	.500A
2N3468	N	S	RAY MOT FSC	211	TO 5	50	50	5.0	1.000A	1.000W	200J	150.000G	100NA	30V	40	.500A
2N3469	N	S	SDL	211	TO 5	35	25	8.0		4.000W	200J	70.000G	100NA	35V	200	1.000A
2N3470	N	S	WHE	561	561F	50	50	15.0	10.000A	150.000W	150J	.500G	200UA	50V	200	
2N3471	N	S	WHE	561	561F	100	100	15.0	10.000A	150.000W	150J	.500G	200UA	100V	200	
2N3472	N	S	WHF	561	561F	150	150	15.0	10.000A	150.000W	150J	.500G	200UA	150V	200	
2N3473	N	S	WHE	561	561F	200	200	15.0	10.000A	150.000W	150J	.500G	200UA	200V	200	
2N3474	N	S	WHE	561	561F	50	50	15.0	10.000A	150.000W	150J	.500G	200UA	50V	500	
2N3475	N	S	WHE	561	561F	100	100	15.0	10.000A	150.000W	150J	.500G	200UA	100V	500	
2N3476	N	S	WHE	561	561F	150	150	15.0	10.000A	150.000W	150J	.500G	200UA	150V	500	
2N3477	N	S	WHE	561	561F	200	200	15.0	10.000A	150.000W	150J	.500G	200UA	200V	500	
2N3478	N	S	RCA	193	193A	30	15	2.0		.200W	200J	900.000G	20NA	1V	90	.002A
2N3485	P	S	FSC TII MOT GEC	211	TO 46	60	40	5.0	.600A	.360W	200J	200.000G	20NA	50V	70	.150A
2N3485A	P	S	FSC TII MOT GEC	211	TO 46	60	60	5.0	.600A	.360W	200J	200.000G	10NA	50V	70	.150A
2N3486	P	S	FSC TII MOT GEC	211	TO 46	60	40	5.0	.600A	.360W	200J	200.000G	20NA	50V	160	.150A
2N3486A	P	S	FSC TII MOT GEC	211	TO 46	60	60	5.0	.600A	.360W	200J	200.000G	10NA	50V	160	.150A
2N3493	N	S	MOT	217	TO 72	12	8	5.0		.150W	200J	400.000G	5NA	6V	70	.001A
2N3494	P	S	MOT TII	210	TO 5	80	80	4.5	.100A	.600W	200J	200.000G	100NA	50V	80	.010A
2N3495	P	S	MOT TII	210	TO 5	120	120	4.5	.100A	.600W	200J	150.000G	100NA	90V	80	.010A
2N3496	P	S	MOT TII	210	TO 18	80	80	4.5	.100A	.400W	200J	200.000G	100NA	50V	80	.010A
2N3497	P	S	MOT TII	210	TO 18	120	120	4.5	.100A	.400W	200J	150.000G	100NA	90V	80	.010A
2N3498	N	S	MOT TRW	210	TO 5	100	100	6.0	.500A	1.000W	200J	150.000G	50NA	50V	70	.150A
2N3499	N	S	MOT TRW	210	TO 5	100	100	6.0	.500A	1.000W	200J	150.000G	50NA	50V	180	.150A
2N3500	N	S	MOT	210	TO 5	150	150	6.0	.300A	1.000W	200J	150.000G	50NA	75V	70	.150A
2N3501	N	S	MOT	210	TO 5	150	150	6.0	.300A	1.000W	200J	150.000G	50NA	75V	180	.150A
2N3502	P	S	FSC TII GEC	211	TO 5	45	45	5.0	.600A	.700W	200J	200.000G	10NA	30V	150	.150A
2N3503	P	S	FSC TII GEC	211	TO 5	60	60	5.0	.600A	.700W	200J	200.000G	10NA	50V	150	.150A
2N3504	P	S	FSC TII GEC	211	TO 18	45	45	5.0	.600A	.400W	200J	200.000G	10NA	30V	150	.150A
2N3505	P	S	FSC TII GEC	211	TO 18	60	60	5.0	.600A	.400W	200J	200.000G	10NA	50V	150	.150A