

NPN General Purpose Transistors by Ascending V_{ce0} (Continued)

| Part Type | V_{ce0} (V) Min | V_{cbo} (V) Min | H_{fe} | | I_c/V_{ce} (mA/V) | Ft (MHz) Min | Package |
|-----------|----------------------|----------------------|----------|-----|------------------------|-----------------|---------|
| | | | Min | Max | | | |
| PN3566 | 30 | 40 | 150 | 600 | 10/10 | 700 | TO-92 |
| PN3641 | 30 | 60 | 40 | 120 | 150/10 | 250 | TO-92 |
| PN3643 | 30 | 60 | 100 | 300 | 150/10 | 250 | TO-92 |
| PN4141 | 30 | 60 | 40 | 120 | 150/10 | 250 | TO-92 |
| PN4142 | 30 | 60 | 100 | 300 | 150/10 | 250 | TO-92 |
| PN5449 | 30 | 50 | 100 | 300 | 50/2.0 | 100 | TO-92 |
| TN2219 | 30 | 60 | 100 | 300 | 150/10 | 50 | TO-237 |
| 2N1613 | 32 | 75 | 40 | 120 | 150/10 | 60 | TO-39 |
| BCW60A | 32 | 32 | 120 | 200 | 2.0/5.0 | 125 | TO-236 |
| BCW65A | 32 | 60 | 100 | 250 | 100/1.0 | 100 | TO-236 |
| MPS6573 | 35 | | 100 | 500 | 10/5.0 | 300 | TO-92 |
| MPS6574 | 35 | | 100 | 300 | 1/5.0 | 300 | TO-92 |
| 2N2218A | 40 | 75 | 40 | 120 | 150/10 | 250 | TO-39 |
| 2N2219A | 40 | 75 | 100 | 300 | 150/10 | 300 | TO-39 |
| 2N2221A | 40 | 75 | 40 | 120 | 150/10 | 250 | TO-18 |
| 2N2222A | 40 | 74 | 100 | 300 | 150/10 | 300 | TO-18 |
| 2N3109 | 40 | 80 | 100 | 300 | 150/1.0 | 70 | TO-39 |
| 2N3903 | 40 | 60 | 50 | 150 | 10/1.0 | 250 | TO-92 |
| 2N3904 | 40 | 60 | 100 | 300 | 10/1.0 | 200 | TO-92 |
| 2N3946 | 40 | 60 | 59 | 150 | 10/1.0 | 250 | TO-18 |
| 2N4400 | 40 | 60 | 50 | 150 | 150/1.0 | 200 | TO-92 |
| 2N4401 | 40 | 60 | 100 | 300 | 150/1.0 | 250 | TO-92 |
| 2N4424 | 40 | 40 | 180 | 540 | 2/4.5 | | TO-92 |
| 2N4944 | 40 | 80 | 40 | 120 | 150/1.0 | 900 | TO-92 |
| 2N4946 | 40 | 80 | 100 | 300 | 150/1.0 | 900 | TO-92 |
| 2N697 | 40 | 60 | 40 | 120 | 150/10 | 50 | TO-39 |
| BSR14 | 40 | 75 | 100 | 300 | 150/10 | 300 | TO-236 |
| BSR17 | 40 | 60 | 50 | 150 | 10/1.0 | 250 | TO-236 |
| BSS79B | 40 | 75 | 40 | 120 | 150/10 | 250 | TO-236 |
| BSS79C | 40 | 75 | 100 | 300 | 150/10 | 250 | TO-236 |
| MMBT2218A | 40 | 75 | 40 | 120 | 150/10 | 250 | TO-236 |
| MMBT2219A | 40 | 75 | 100 | 300 | 150/10 | 300 | TO-236 |
| MMBT2221A | 40 | 75 | 40 | 120 | 150/10 | 250 | TO-236 |
| MMBT2222A | 40 | 75 | 100 | 300 | 150/10 | 300 | TO-236 |
| MMBT3569 | 40 | 80 | 100 | 300 | 150/10 | 60 | TO-236 |
| MMBT3903 | 40 | 60 | 50 | 150 | 10/0.1 | 250 | TO-236 |
| MMBT3904 | 40 | 60 | 100 | 300 | 10/0.1 | 300 | TO-236 |
| MMBT3926 | 40 | 60 | 59 | 150 | 10/0.1 | 250 | TO-236 |
| MMBT4400 | 40 | 60 | 50 | 150 | 150/1.0 | 200 | TO-236 |
| MMBT4401 | 40 | 60 | 100 | 300 | 150/1.0 | 250 | TO-236 |
| MMBT420 | 40 | | 40 | 400 | 5/10 | 125 | TO-236 |
| MPS3903 | 40 | 60 | 20 | | 0.1/1.0 | 200 | TO-92 |
| MPS6514 | 40 | | 150 | 300 | 2/10 | | TO-92 |
| MPS6530 | 40 | 60 | 40 | 120 | 100/1.0 | | TO-92 |
| MPS6531 | 40 | 60 | 90 | 270 | 100/1.0 | | TO-92 |
| MPSA10 | 40 | | 40 | 400 | 5/10 | 50 | TO-92 |
| MPSA20 | 40 | | 40 | 400 | 5/10 | 125 | TO-92 |
| PN2218A | 40 | 75 | 40 | 120 | 150/10 | 250 | TO-92 |
| PN2219A | 40 | 75 | 100 | 300 | 150/10 | 300 | TO-92 |
| PN2221A | 40 | 75 | 40 | 120 | 150/10 | 250 | TO-92 |
| PN2222A | 40 | 45 | 100 | 300 | 150/10 | 300 | TO-92 |
| PN222A | 40 | 75 | 100 | 300 | 150/10 | 300 | TO-92 |
| PN3567 | 40 | 80 | 40 | 120 | 30/1.0 | 900 | TO-92 |
| PN3569 | 40 | 80 | 100 | 300 | 150/1.0 | 900 | TO-92 |