

TRANSISTOR NUMBER	PM OA LT	PACK-AGE	LEAD INFO	VCB MAX	VCE MAX	VEB MAX	I C MAX	T J MAX	P TOT	F T MIN	C OB MAX	H FE	H FE BIAS	USE	MFR	EUR EQUIV	USA EQUIV	ISS
BC315	PS	X10	L20	45V	35V	5V	100MA	150C	300MWF	200M	10P	100MN	2MA	ALN	TIB	BC309	2N6003	0
BC315A	PS	X10	L20	45V	35V	5V	100MA	150C	300MWF	200M	10P	125MN	2MA	ALN	TIB	BC309	2N6003	2
BC315B	PS	X10	L20	45V	35V	5V	100MA	150C	300MWF	200M	10P	200MN	2MA	ALN	TIB	BC309	2N6003	2
BC317	NS	T092	L14	50V	45V	6V	150MA	135C	310MWF	100M	4P	110MN	2MA	ALG	MOU	BC167	2N5209	0
BC317A	NS	T092	L14	50V	45V	6V	150MA	135C	310MWF	100M	4P	110MN	2MA	ALG	MOU	BC167	2N5209	0
BC317B	NS	T092	L14	50V	45V	6V	150MA	135C	310MWF	100M	4P	200MN	2MA	ALG	MOU	BC167	2N5209	0
BC318	NS	T092	L14	40V	30V	5V	150MA	135C	310MWF	100M	4P	110MN	2MA	ALG	MOU	BC167	2N5209	0
BC318A	NS	T092	L14	40V	30V	5V	150MA	135C	310MWF	100M	4P	110MN	2MA	ALG	MOU	BC167	2N5209	0
BC318B	NS	T092	L14	40V	30V	5V	150MA	135C	310MWF	100M	4P	200MN	2MA	ALG	MOU	BC167	2N5209	0
BC318C	NS	T092	L14	40V	30V	5V	150MA	135C	310MWF	100M	4P	400MN	2MA	ALG	MOU	BC169	2N5210	0
BC319	NS	T092	L14	30V	20V	5V	150MA	135C	310MWF	100M	4P	200MN	2MA	ALN	MOU	BC169	2N5210	0
BC319B	NS	T092	L14	30V	20V	5V	150MA	135C	310MWF	100M	4P	200MN	2MA	ALN	MOU	BC169	2N5210	0
BC319C	NS	T092	L14	30V	25V	5V	150MA	135C	310MWF	100M	4P	400MN	2MA	ALN	MOU	BC169	2N5210	0
BC320	PS	T092	L14	50V	45V	6V	150MA	135C	310MWF	100M	4P	110MN	2MA	ALG	MOU	BC320	2N5086	0
BC320A	PS	T092	L14	50V	45V	6V	150MA	135C	310MWF	100M	4P	110MN	2MA	ALG	MOU	BC320	2N5086	0
BC320B	PS	T092	L14	50V	45V	6V	150MA	135C	310MWF	100M	4P	200MN	2MA	ALG	MOU	BC320	2N5086	0
BC321	PS	T092	L14	40V	30V	5V	150MA	135C	310MWF	100M	4P	110MN	2MA	ALG	MOU	BC320	2N5086	0
BC321A	PS	T092	L14	40V	30V	5V	150MA	135C	310MWF	100M	4P	110MN	2MA	ALG	MOU	BC320	2N5086	0
BC321B	PS	T092	L14	40V	30V	5V	150MA	135C	310MWF	100M	4P	200MN	2MA	ALG	MOU	BC320	2N5086	0
BC321C	PS	T092	L14	45V	30V	5V	150MA	135C	310MWF	100M	4P	400MN	2MA	ALN	MOU	BC352B	2N5086	2
BC322	PS	T092	L14	30V	20V	5V	150MA	135C	310MWF	100M	4P	110MN	2MA	ALN	MOU	BC322	2N5087	0
BC322B	PS	T092	L14	30V	20V	5V	150MA	135C	310MWF	100M	4P	200MN	2MA	ALN	MOU	BC322	2N5087	0
BC322C	PS	T092	L14	30V	20V	5V	150MA	135C	310MWF	100M	4P	400MN	2MA	ALN	MOU	BC322	2N5087	0
BC323	NS	T039	L04	100V	60V	5V	5A	200C	800MWF	50M	80P	50MN	500MA	AMG	SGI	BFY50	2N2297	0
BC324	NS	T039	L04	85V	55V	5V	1A	200C	800MWF	50M	40P	20MN	500MA	AMG	SGI	BFY50	2N2297	0
BC325	PS	T018	L01	60V	60V	6V	50MA	200C	360MWF	100M	9P	40MN	10UA	ALA	TIB	BCY71	2N3965	2
BC326	PS	T018	L01	60V	60V	6V	50MA	200C	360MWF	100M	9P	100MN	10UA	ALA	TIB	BCY71	2N3965	2
BC327	PS	X10	L20	50V	45V	5V	800MA	150C	500MWF	60M	18P	63MN	100MA	AMG	SID	BC327	2N5819	0
BC327AP	PS	T092	L74	50V	45V	5V	800MA	150C	500MWF	60M	18P	100MN	100MA	AMG	FEB	BC32716	2N5819	2
BC327BP	PS	T092	L74	50V	45V	5V	800MA	150C	500MWF	60M	18P	160MN	100MA	AMG	FEB	BC32725	2N5819	2
BC327CP	PS	T092	L74	50V	45V	5V	800MA	150C	500MWF	60M	18P	250MN	100MA	AMG	FEB	BC32740	2N5819	2
BC327/01	PS	X09	L10	45V	45V	6V	500MA	125C	400MWF	50M	15P	100MN	100MA	AMG	OBS	BSY59	2N6014	2
BC327/10	PS	T092	L74	50V	45V	5V	1A	150C	500MWF	50M	24P	67/150	100MA	AMG	SID	BC327	2N6014	2
BC327/16	PS	X10	L20	50V	45V	5V	800MA	150C	500MWF	60M	18P	100MN	100MA	AMG	SID	BC327	2N5819	2
BC327/25	PS	X10	L20	50V	45V	5V	800MA	150C	500MWF	60M	18P	160MN	100MA	AMG	SID	BC327	2N5819	2
BC327/40	PS	X10	L20	50V	45V	5V	800MA	150C	500MWF	60M	18P	250MN	100MA	AMG	SID	BC327	2N5819	0
BC328	PS	X10	L20	30V	25V	5V	800MA	150C	500MWF	60M	18P	63MN	100MA	AMG	SID	BC327	2N5819	0
BC328AP	PS	T092	L74	30V	25V	5V	800MA	150C	500MWF	60M	18P	100MN	100MA	AMG	FEB	BC32816	2N5819	2
BC328BP	PS	T092	L74	30V	25V	5V	800MA	150C	500MWF	60M	18P	160MN	100MA	AMG	FEB	BC32825	2N5819	2
BC328CP	PS	T092	L74	30V	25V	5V	800MA	150C	500MWF	60M	18P	250MN	100MA	AMG	FEB	BC32840	2N5819	2
BC328/01	PS	X09	L10	25V	25V	5V	500MA	125C	400MWF	50M	15P	100MN	100MA	AMG	OBS	BSY59	2N6014	2
BC328/10	PS	T092	L74	30V	25V	5V	1A	150C	500MWF	50M	24P	67/150	100MA	AMG	SID	BC327	2N6014	2
BC328/16	PS	X10	L20	30V	25V	5V	800MA	150C	500MWF	60M	18P	100MN	100MA	AMG	SID	BC327	2N5819	0
BC328/25	PS	X10	L20	30V	25V	5V	800MA	150C	500MWF	60M	18P	160MN	100MA	AMG	SID	BC327	2N5819	0
BC328/40	PS	X10	L20	30V	25V	5V	800MA	150C	500MWF	60M	18P	250MN	100MA	AMG	SID	BC327	2N5819	0
BC329	NS	T092	L74	60V	60V	6V	30MA	150C	250MWF	100M	6P	240MN	2MA	ALN	TIW	BC239	2N5827	1
BC329B	NS	X10	L20	60V	60V	6V	30MA	150C	250MWF	100M	6P	220MN	2MA	ALN	TIW	BC239	2N5827	0
BC329C	NS	X10	L20	60V	60V	6V	30MA	150C	250MWF	100M	3P	220MN	2MA	ALN	TIW	BC239	2N5827	0
BC330	NS	T092	L74	60V	60V	6V	30MA	150C	250MWF	100M	6P	220MN	2MA	ALN	TIW	BC239	2N5827	1
BC330B	NS	X10	L20	45V	45V	6V	30MA	150C	250MWF	100M	3P	220MN	2MA	ALN	TIW	BC239	2N5827	0
BC330C	NS	X10	L20	45V	45V	6V	30MA	150C	220MWF	100M	3P	220FG	2MA	ALN	TIW	BC239	2N5827	0
BC331	NS	T092	L74	60V	60V	6V	30MA	150C	250MWF	100M	3P	125MN	2MA	ALN	TIW	BC239	2N5827	1
BC331A	NS	X10	L20	60V	60V	6V	30MA	150C	250MWF	100M	3P	100MN	2MA	ALG	TIW	BC237	2N5825	0
BC331B	NS	X10	L20	60V	60V	6V	30MA	150C	250MWF	100M	3P	100MN	2MA	ALG	TIW	BC237	2N5825	0
BC331C	NS	X10	L20	60V	60V	6V	30MA	150C	250MWF	100M	3P	100MN	2MA	ALG	TIW	BC237	2N5825	0
BC332	NS	T092	L74	45V	45V	6V	30MA	150C	250MWF	100M	3P	100MN	2MA	ALN	TIW	BC239	2N5827	1
BC332A	NS	X10	L20	45V	45V	6V	30MA	150C	250MWF	100M	3P	100MN	2MA	ALG	TIW	BC237	2N2825	0
BC332B	NS	X10	L20	45V	45V	6V	30MA	150C	250MWF	100M	3P	100MW	2MA	ALG	TIW	BC237	2N2825	0
BC332C	NS	X10	L20	45V	45V	6V	30MA	150C	250MWF	100M	3P	100MN	2MA	ALG	TIW	BC237	2N5825	0
BC333	NS	T092	L14	25V	25V	5V	50MA	135C	310MWF	50M	4P	100MN	100UA	ALG	MOB	BC320	2N5086	0
BC334	PS	T092	L14	25V	25V	5V	50MA	135C	310MWF	50M	4P	100MN	100UA	ALG	MOB	BC320	2N5286	0
BC335	NS	T092	L14	25V	25V	5V	50MA	135C	310MWF	50M	4P	100MN	100UA	ALN	MOB	BC322	2N5087	0
BC336	PS	T092	L14	25V	25V	5V	50MA	135C	310MWF	50M	4P	100MN	100UA	ALN	MOB	BC322	2N5087	0
BC337	NS	X10	L20	50V	45V	5V	800MA	150C	360MWF	60M	20P	100MN	100MA	AMG	SID	BC337	2N5818	0
BC337AP	NS	T092	L74	50V	45V	5V	800MA	150C	360MWF	60M	20P	100MN	100MA	AMG	FEB	BC33716	2N6016	2
BC337BP	NS	T092	L74	50V	45V	5V	800MA	150C	360MWF	60M	20P	160MN	100MA	AMG	FEB	BC33725	2N6016	2
BC337CP	NS	T092	L74	50V	45V	5V	800MA	150C	360MWF	60M	20P	250MN	100MA	AMG	FEB	BC33740	2N6016	2
BC337/01	NS	X09	L10	45V	45V	6V	500MA	150C	400MWF	50M	20P	100MN	100MA	AMG	OBS	BFW87	2N6220	2
BC337/10	NS	T092	L74	50V	45V	5V	1A	150C	500MWF	50M	24P	67/150	100MA	AMG	SID	BC487B	2N6220	2
BC337/16	NS	X10	L20	50V	45V	5V	800MA	150C	360MWF	60M	20P	100MN	100MA	AMG	SID	BC337	2N5818	0
BC337/25	NS	X10	L20	50V	45V	5V	800MA	150C	360MWF	60M	20P	160MN	100MA	AMG	SID	BC337	2N5818	0
BC337/40	NS	X10	L20	50V	45V	5V	800MA	150C	360MWF	60M	20P	250MN	100MA	AMG	SID	BC337	2N5818	0
BC338	NS	X10	L20	30V	20V	5V	800MA	150C	360MWF	60M	20P	100MN	100MA	AMG	SID	BC337	2N5818	0
BC338AP	NS	T092	L74	30V	20V	5V	800MA	150C	360MWF	60M	20P	100MN	100MA	AMG	FEB	BC33740	2N6016	2
BC338BP	NS	T092	L74	30V	20V	5V	800MA	150C	360MWF	60M	20P	160MN	100MA	AMG	FEB	BC33740	2N6016	2